

JVC

PARTS LIST

CD RECEIVER

KD-A815J
KD-R816UH

KD-R810J
KD-R811E

KD-R816U
KD-R811EY

■ PRECAUTIONS ON SCHEMATIC DIAGRAMS

- Due to the improvement in performance, some part numbers shown in the circuit diagrams may not agree with those indicated in the Parts List.
- The parts numbers, values and rated voltage etc. in the Schematic Diagrams are for reference only.
- Since the circuit diagrams are standard ones, the circuits and circuit constants may be subject to change for improvement without any notice.

■ PRECAUTIONS ON PARTS LIST

- The parts identified by the $\triangle$ symbol are critical for safety. Whenever replacing these parts, be sure to use specified ones to secure the safety.
- The parts not indicated in this Parts List and those which are filled with lines --- in the Parts No. columns will not be supplied.
- P.W. BOARD Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied.
- When ordering chips, screws etc., place bulk orders (unit of tens) whenever possible to improve shipping efficiency.
- There are cases where the actual implemented parts in the sets and the service parts are different. When ordering parts, make sure to refer to the Parts List.

■ PRECAUTIONS ON SERVICE


Certain parts of the power circuits and the GNDs differ according to the models. Care must be taken for the following points as the differences are indicated separately in the LIVE GND () and the ISOLATED (NEUTRAL) GND ()

1. Do not touch the LIVE GND, or do not touch the LIVE GND and the ISOLATED (NEUTRAL) GND at the same time. It may cause an electric shock.
Before pulling out the chassis or other parts, make sure to pull out the power cord from the wall outlet first.
2. Do not short circuit between the LIVE GND and ISOLATED (NEUTRAL) GND, or never measure the LIVE GND and ISOLATED (NEUTRAL) GND at the same time using measuring instruments (oscilloscope, etc.). It may blow fuses or damage other parts.

■ DEVIATION TOLERANCE RANGE

DEVIATION TOLERANCE RANGE									
F	G	J	K	M	N	R	H	Z	P
± 1%	± 2%	± 5%	±10%	±20%	±30%	+30% -10%	+50% -10%	+80% -20%	+100% -0%

Exploded view of general assembly



The parts without symbol number are not service.

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
------	------------	-----------	------------	-------------	-----	-------


General assembly <M1MM>

1		GE10253-003A	TOP CHASSIS		1	A,B
1		GE10253-004A	TOP CHASSIS		1	C,D,E,F
2		GE33234-002A	HEAT SINK		1	
3		GE20232-005A	BOTTOM COVER		1	A,C,D,E,F
3		GE20232-004A	BOTTOM COVER		1	B
4		GE32830-004A	INSULATOR		1	
5		GE40395-002A	SIDE PANEL		1	
6		QYSDST2604ZA	TAP SCREW	M2.6 x 4mm	3	
7		GE40377-002A	SCREW		3	
8		GE40377-003A	SPECIAL SCREW		2	
9		QYSDST2610ZA	TAP SCREW	M2.6 x 10mm	1	
10		QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	1	
11		QYSDSF2606ZA	TAP SCREW	M2.6 x 6mm	1	
12		QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	1	
13		GE40377-002A	SCREW		2	
14		QYSDST2608ZA	TAP SCREW	M2.6 x 8mm	1	
15		QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	1	
16		QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	1	A,B
16		QYSDST2604ZA	TAP SCREW	M2.6 x 4mm	1	C,D,E,F
17		GE10242-012A	FRONT CHASSIS		1	
18		GE33792-001A	LOCK LEVER		1	
19		GE40368-002A	TORSION SPRING		1	
20		GE32810-001A	RELEASE LEVER		1	
21		GE30999-004A	COMP.SPRING		1	
22		GE40432-001A	BLIND		1	
23		QLD0639-001	LCD MODULE		1	
24		GE33886-004A	FRT PANEL ASSY		1	A
24		GE33886-005A	FRT PANEL ASSY		1	B,C,D,E,F
25		GE33885-022A	FINDER ASSY		1	A
25		GE33885-016A	FINDER ASSY		1	B
25		GE33885-017A	FINDER ASSY		1	C,D
25		GE33885-023A	FINDER ASSY		1	E,F
26		GE40463-001A	JVC BADGE		1	
27		GE33800-002A	EJECT BUTTON		1	
28		GE33801-002A	SOURCE BUTTON		1	
29		GE33802-004A	NAVI BUTTON		1	
30		GE33803-001A	DISP BUTTON		1	
31		GE40495-001A	MENU BTN ASSY		1	
32		GE33805-003A	BUTTON RIM		1	A
32		GE33805-001A	BUTTON RIM		1	B,C,D,E,F
33		GE33806-005A	PHONE BACK BTN		1	A
33		GE33806-007A	PHONE BACK BTN		1	B,C,D
33		GE33806-006A	PHONE BACK BTN		1	E,F
34		GE33807-001A	RIM LENS		1	
35		GE33808-003A	RIM COVER		1	A
35		GE33808-001A	RIM COVER		1	B,C,D,E,F
36		GE33809-002A	LIGHT GUIDE		1	
37		GE33810-001A	RUBBER BASE		1	
38		GE33881-002A	DETACH BUTTON		1	
39		GE30999-009A	COMP.SPRING		1	
40		GE33704-006A	VOLUME KNOB		1	A
40		GE33704-001A	VOLUME KNOB		1	B,C,D,E,F
41		GE40127-006A	KNOB SPRING		1	
42		GE10273-003A	REAR COVER		1	
43		VKZ4777-010	MINI SCREW		4	
44		GE33816-001A	LCD LENS		1	
45		GE33817-001A	LENS CASE		1	
46		GE33818-001A	LCD CASE		1	
47		GE40483-001A	LIGHTING SHEET		1	
48		GE40484-001A	LIGHTING SHEET		1	
49		GE40431-003A	REMOTE SHEET		1	
50		GE33917-001A	NAME PLATE		1	A
50		GE33920-001A	NAME PLATE		1	B
50		GE33923-001A	NAME PLATE		1	C,D
50		GE33926-002A	NAME PLATE		1	E,F
51		GE40442-001A	FCC RULE LABEL		1	A,B
52		QAM1077-001	USB CABLE		1	
53		QAM1002-001	CAR CABLE		1	
54		GE40354-001A	IC BRACKET		1	
55		GE40308-001A	REG IC BRACKET		1	
△ 56		QMFZ064-150-J1	FUSE	15A	1	

CD mechanism assembly

Block No.MBMM

FLM-CD5-1D



The parts without symbol number are not service.

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
FLM-CD5-1D CD mechanism <MBMM>						
	1	LV11256-001A	MECHA FRAME		1	A,B,C,D,E,F
	2	LV36800-002A	LINK ARM		1	A,B,C,D,E,F
	3	LV44658-001A	LINK SPRING		1	A,B,C,D,E,F
	4	LV22300-002A	SLIDE CAM (L)		1	A,B,C,D,E,F
	5	LV22298-002A	SLIDE CAM(R)		1	A,B,C,D,E,F
	6	LV36802-001A	LOAD RACK		1	A,B,C,D,E,F
	7	LV44552-001A	RETURN SPRING		1	A,B,C,D,E,F
	8	LV36803-002A	F LOCK LEVER		1	A,B,C,D,E,F
	9	LV36804-002A	CAM COVER		1	A,B,C,D,E,F
	10	VKZ4539-054	MINI SCREW		1	A,B,C,D,E,F
	11	QAR0373-002	MOTOR		1	A,B,C,D,E,F
	12	QYSPSPT2025MA	SCREW	M2 x 2.5mm	2	A,B,C,D,E,F
	13	LV36903-003A	L M BASE ASSY		1	A,B,C,D,E,F
	14	VKZ4539-054	MINI SCREW		2	A,B,C,D,E,F
	15	LV36806-001A	L WORM GEAR		1	A,B,C,D,E,F
	16	LV36805-002A	M WHEEL GEAR		1	A,B,C,D,E,F
	17	LV36807-001A	A WHEEL GEAR		1	A,B,C,D,E,F
	18	LV36808-001A	R ACT GEAR(1)		1	A,B,C,D,E,F
	19	LV36809-001A	LOAD ACT GEAR		1	A,B,C,D,E,F
	20	LV36810-001A	LOADING GEAR		1	A,B,C,D,E,F
	21	QYWDL1230250	SLIT WASHER	3mm/1.2mm x 0.25mm	1	A,B,C,D,E,F
	23	CM-FLMCD1D	SPINDLE MOTOR ASSY		1	A,B,C,D,E,F
	27	QAL1226-001	PICK UP		1	A,B,C,D,E,F
	28	LV44555-001A	MAIN SHAFT		1	A,B,C,D,E,F
	29	LV36799-001A	RACK PLATE		1	A,B,C,D,E,F
	30	LV45227-001A	RACK SPRING		1	A,B,C,D,E,F
	31	QYSPSGT1745ZA	TAP SCREW	M1.7 x 4.5mm	1	A,B,C,D,E,F
	32	LV36813-201A	SUB GUIDE CAP		1	A,B,C,D,E,F
	33	QAR0144-003	MOTOR	2.0V DC	1	A,B,C,D,E,F
	34	QYSPSPT2025MA	SCREW	M2 x 2.5mm	2	A,B,C,D,E,F
	35	LV22296-001A	F MOTOR HOLDER		1	A,B,C,D,E,F
	36	VKZ4539-054	MINI SCREW		2	A,B,C,D,E,F
	37	LV36814-001A	F WORM GEAR		1	A,B,C,D,E,F
	38	LV36815-002A	F WHEEL GEAR		1	A,B,C,D,E,F
	39	LV36816-001A	TRIGGER ARM		1	A,B,C,D,E,F
	41	LV37326-003A	CLAMPER ASSY		1	A,B,C,D,E,F
	42	LV44557-002A	CLAMPER SPRING		1	A,B,C,D,E,F
	43	LV44558-001A	SUS SPRING		4	A,B,C,D,E,F
	44	LV36820-001A	WIRE HOLDER		1	A,B,C,D,E,F
	45	LV36904-001A	DAMPER		2	A,B,C,D,E,F
	46	LV37061-001A	DAMPER		1	A,B,C,D,E,F
	47	LV11260-003A	TOP COVER		1	A,B,C,D,E,F
	48	VKZ4539-054	MINI SCREW		4	A,B,C,D,E,F
	49	LV11264-003A	DISC PLATE		1	A,B,C,D,E,F
	50	LV44586-001A	SPECIAL SCREW		1	A,B,C,D,E,F
	51	LV36801-002A	GEAR HOLDER		1	A,B,C,D,E,F
	52	VKZ4539-054	MINI SCREW		1	A,B,C,D,E,F
	53	LV36821-201A	R ACT GEAR(2)		1	A,B,C,D,E,F
	54	LV36822-201A	R ACT GEAR(3)		1	A,B,C,D,E,F
	55	LV36823-201A	ROLLER GEAR		1	A,B,C,D,E,F
	56	LV44559-003A	ROLLER SHAFT		1	A,B,C,D,E,F
	57	LV22744-001A	R HOLDER ASSY 2		1	A,B,C,D,E,F
	58	LV44560-001A	ROLLER		2	A,B,C,D,E,F
	59	LV44590-001A	WASHER		1	A,B,C,D,E,F
	60	LV45268-001A	ROLLER COLLAR 2		1	A,B,C,D,E,F
	61	LV44562-002A	ROLLER SPRING		2	A,B,C,D,E,F
	62	QAL0817-003	FPC		1	A,B,C,D,E,F
	63	VKZ4539-054	MINI SCREW		3	A,B,C,D,E,F
	64	VKZ4539-054	MINI SCREW		1	A,B,C,D,E,F
	66	LV45269-001A	R HOLDER ROD		1	A,B,C,D,E,F
	67	LV45270-001A	WASHER 2		1	A,B,C,D,E,F
	70	WJS0085-001A-E	E-FL/RB WIRE		1	A,B,C,D,E,F
	71	LV34916-002A	WIRE CLAMP		1	A,B,C,D,E,F
Electrical parts list Main board <01>						
△	IC1	TEF6606T/V5-X	IC		1	
	IC71	LC72725KV-X	IC		1	E,F
	IC181	NJW1222V-X	IC		1	
	IC201	NJM4565E-X	IC		1	
	IC271	NJM2160BV-X	IC		1	A,C,D
△	IC301	TDA7851A	IC		1	
	IC361	NJM2792V-X	IC		1	A,C,D
△	IC501	LA6565-X	IC		1	
	IC521	MN6627553PA	IC		1	
	IC581	NJM4580E-X	IC		1	
△	IC701	JES185C	IC(MCU)		1	A,B,C,D
△	IC701	JES186B	IC(MCU)		1	E,F
	IC771	R1EX24016ASAA-X	IC		1	E,F
	IC801	74AHCT126PW-X	IC		1	A,B
△	IC901	R2S25400DS-E	IC		1	
	IC902	XC6213B332NG-X	IC		1	
	IC921	NJM2855DL1-33-X	IC		1	
	IC931	TPS54140DGQ-X	IC		1	
	IC941	TPS54140DGQ-X	IC		1	
	Q251	KTD1304-X	TRANSISTOR		1	
	Q301	RT1N141C-X	DIGI TRANSISTOR		1	A
	Q301 or	UN2211-X	TRANSISTOR		1	A
	Q322	IMX9-W	PAIR TRANSISTOR		1	
	Q332	IMX9-W	PAIR TRANSISTOR		1	
	Q501	2SB1424/R/-W	TRANSISTOR		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
		Q502	2SA2188/F-X	TRANSISTOR	1	
		Q701	2SA812A/5-6/-X	TRANSISTOR	1	
	or	Q701	ISA1530AC1/QR/X	TRANSISTOR	1	
		Q702	2SC1623A/5-6/-X	TRANSISTOR	1	
	or	Q702	2SC3928A/QR/-X	TRANSISTOR	1	
		Q703	RT1N141C-X	DIGI TRANSISTOR	1	
	or	Q703	UN2211-X	TRANSISTOR	1	
		Q704	RT1P141C-X	DIGI TRANSISTOR	1	
	or	Q704	UN2111-X	TRANSISTOR	1	
		Q781	RT1P141C-X	DIGI TRANSISTOR	1	
	or	Q781	UN2111-X	TRANSISTOR	1	
		Q782	2SC1623A/5-6/-X	TRANSISTOR	1	
	or	Q782	2SC3928A/QR/-X	TRANSISTOR	1	
		Q784	RT1P141C-X	DIGI TRANSISTOR	1	
	or	Q784	UN2111-X	TRANSISTOR	1	
		Q785	RT1P141C-X	DIGI TRANSISTOR	1	
	or	Q785	UN2111-X	TRANSISTOR	1	
		Q851	2SB1132/QR/-W	TRANSISTOR	1	C,D
		Q852	RT1N141C-X	DIGI TRANSISTOR	1	C,D
	or	Q852	UN2211-X	TRANSISTOR	1	C,D
		Q881	RT1N141C-X	DIGI TRANSISTOR	1	
	or	Q881	UN2211-X	TRANSISTOR	1	
		Q976	RT1N141C-X	DIGI TRANSISTOR	1	
	or	Q976	UN2211-X	TRANSISTOR	1	
		Q977	2SA812A/5-6/-X	TRANSISTOR	1	
	or	Q977	ISA1530AC1/QR/X	TRANSISTOR	1	
		D321	BAW56-TP-X	SI DIODE	1	
	or	D321	MC2836-X	DIODE	1	
		D331	BAW56-TP-X	SI DIODE	1	
	or	D331	MC2836-X	DIODE	1	
		D477	NAF0029-001X	DIODE	1	V
		D478	NAF0029-001X	DIODE	1	V
		D501	GS1J-LTP-X	DIODE	1	
		D502	GS1J-LTP-X	DIODE	1	
		D708	RKZ6.2B2KG-X	Z DIODE	1	
	or	D708	MA8062/M/-X	Z DIODE	1	
		D709	RKZ6.2B2KG-X	Z DIODE	1	
	or	D709	MA8062/M/-X	Z DIODE	1	
		D710	RKZ6.2B2KG-X	Z DIODE	1	
	or	D710	MA8062/M/-X	Z DIODE	1	
		D711	RKZ6.2B2KG-X	Z DIODE	1	
	or	D711	MA8062/M/-X	Z DIODE	1	
		D712	RKZ6.2B2KG-X	Z DIODE	1	
	or	D712	MA8062/M/-X	Z DIODE	1	
		D713	RKZ6.2B2KG-X	Z DIODE	1	
	or	D713	MA8062/M/-X	Z DIODE	1	
		D714	RKZ6.2B2KG-X	Z DIODE	1	A,C,D,E,F
	or	D714	MA8062/M/-X	Z DIODE	1	A,C,D,E,F
		D716	RKZ5.6B2KG-X	Z DIODE	1	
	or	D716	MA8056/M/-X	Z DIODE	1	
		D717	MC2838-X	DIODE	1	
	or	D717	MA152WK-X	SI DIODE	1	
		D721	MC2838-X	DIODE	1	
	or	D721	MA152WK-X	SI DIODE	1	
		D722	BAW56-TP-X	SI DIODE	1	
	or	D722	MC2836-X	DIODE	1	
		D781	HSU119-X	SI DIODE	1	
	or	D781	MA111-X	SI DIODE	1	
		D784	RKZ11B2KG-X	Z DIODE	1	
	or	D784	MA8110/M/-X	Z DIODE	1	
		D785	HSU119-X	SI DIODE	1	
	or	D785	MA111-X	SI DIODE	1	
		D786	HSU119-X	SI DIODE	1	
	or	D786	MA111-X	SI DIODE	1	
		D787	HSU119-X	SI DIODE	1	
	or	D787	MA111-X	SI DIODE	1	
		D788	HSU119-X	SI DIODE	1	
	or	D788	MA111-X	SI DIODE	1	
		D789	1SS380-X	SI DIODE	1	
		D851	MBRX130-TP-X	SB DIODE	1	C,D
	or	D851	MA22D23-X	SB DIODE	1	C,D
		D852	MBRX130-TP-X	SB DIODE	1	C,D
	or	D852	MA22D23-X	SB DIODE	1	C,D
△		D901	1N5401-BPC04	SI DIODE	1	
△	or	D901	1N5401-04	SI DIODE	1	
		D902	HSU119-X	SI DIODE	1	
	or	D902	MA111-X	SI DIODE	1	
		D931	RB055L-40-X	SB DIODE	1	
		D941	RB055L-40-X	SB DIODE	1	
		D971	MBRX130-TP-X	SB DIODE	1	
	or	D971	MA22D23-X	SB DIODE	1	
		D972	MBRX130-TP-X	SB DIODE	1	
	or	D972	MA22D23-X	SB DIODE	1	
		C1	NDC31HJ-102X	C CAPACITOR	1	1000pF 50V J
		C2	NDC31HJ-7R0X	C CAPACITOR	1	7pF 50V J
		C3	NDC31HJ-102X	C CAPACITOR	1	1000pF 50V J
		C4	NCB31AK-224X	C CAPACITOR	1	0.22uF 10V K
		C5	NDC31HJ-150X	C CAPACITOR	1	15pF 50V J
		C6	NDC31HJ-220X	C CAPACITOR	1	22pF 50V J
		C10	NCB31AK-105X	C CAPACITOR	1	1uF 10V K
		C11	NCBA1CK-103W	C CAPACITOR	1	0.01uF 16V K
		C12	NCBA1CK-103W	C CAPACITOR	1	0.01uF 16V K

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C13	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C14	NCB31AK-224X	C CAPACITOR	0.22uF 10V K	1	
	C15	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C16	NCBA1CK-103W	C CAPACITOR	0.01uF 16V K	1	
	C17	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C18	NCBA1CK-103W	C CAPACITOR	0.01uF 16V K	1	
	C19	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C22	NDCA1HJ-120W	C CAPACITOR	12pF 50V J	1	
	C23	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C24	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C25	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C26	QEKJ1CM-107Z	E CAPACITOR	100uF 16V M	1	
	C33	NDC31HJ-5R6X	C CAPACITOR	5.6pF 50V J	1	
	C71	NDCA1HJ-561W	C CAPACITOR	560pF 50V J	1	E,F
	C72	NDCA1HJ-331W	C CAPACITOR	330pF 50V J	1	E,F
	C73	QEKJ1HM-225Z	E CAPACITOR	2.2uF 50V M	1	E,F
	C74	NDCA1HJ-270W	C CAPACITOR	27pF 50V J	1	E,F
	C75	NDCA1HJ-270W	C CAPACITOR	27pF 50V J	1	E,F
	C76	NCBA1CK-103W	C CAPACITOR	0.01uF 16V K	1	E,F
	C77	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	E,F
	C78	NCBA1CK-103W	C CAPACITOR	0.01uF 16V K	1	E,F
	C161	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C162	QTE1H64-225Z	E CAPACITOR	2.2uF 50V	1	
	C163	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	A,B
	C164	NCBA1HK-332W	C CAPACITOR	3300pF 50V K	1	
	C165	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C166	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C167	NCB31AK-474X	C CAPACITOR	0.47uF 10V K	1	
	C168	NCB31AK-224X	C CAPACITOR	0.22uF 10V K	1	
	C169	QTE1C57-476Z	E CAPACITOR	47uF 16V	1	
	C171	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C172	QTE1H64-225Z	E CAPACITOR	2.2uF 50V	1	
	C173	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	A,B
	C174	NCBA1HK-332W	C CAPACITOR	3300pF 50V K	1	
	C175	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C179	QTE1A57-107Z	E CAPACITOR	100uF 10V	1	
	C180	NCB31HK-472X	C CAPACITOR	4700pF 50V K	1	
	C181	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C182	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C191	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C192	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C193	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C231	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C232	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C233	NDCA1HJ-331W	C CAPACITOR	330pF 50V J	1	
	C234	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C236	QEKJ1CM-226Z	E CAPACITOR	22uF 16V M	1	
	C238	NDCA1HJ-331W	C CAPACITOR	330pF 50V J	1	
	C239	NCBA1AK-333W	C CAPACITOR	0.033uF 10V K	1	
	C240	NCB31HK-273X	C CAPACITOR	0.027uF 50V K	1	
	C241	NCB31HK-273X	C CAPACITOR	0.027uF 50V K	1	
	C242	NDCA1HJ-220W	C CAPACITOR	22pF 50V J	1	
	C243	NCBA1AK-333W	C CAPACITOR	0.033uF 10V K	1	
	C244	QEKJ1CM-226Z	E CAPACITOR	22uF 16V M	1	
	C245	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C246	NDC31HJ-151X	C CAPACITOR	150pF 50V J	1	
	C271	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	A,C,D
	C272	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	A,C,D
	C273	QEKJ1CM-107Z	E CAPACITOR	100uF 16V M	1	A,C,D
	C274	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	A,C,D
	C275	NCB31HK-152X	C CAPACITOR	1500pF 50V K	1	A,C,D
	C276	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C301	QFV91HJ-474Z	MF CAPACITOR	0.47uF 50V J	1	
	C302	QFV91HJ-474Z	MF CAPACITOR	0.47uF 50V J	1	
	C303	NDC31HJ-560X	C CAPACITOR	56pF 50V J	1	
	C304	NDC31HJ-560X	C CAPACITOR	56pF 50V J	1	
	C305	NDCA1HJ-820W	C CAPACITOR	82pF 50V J	1	
	C306	QTE1H57-475Z	E CAPACITOR	4.7uF 50V	1	
	C307	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C308	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C310	NDC31HJ-820X	C CAPACITOR	82pF 50V J	1	
	C311	QFV91HJ-474Z	MF CAPACITOR	0.47uF 50V J	1	
	C312	QFV91HJ-474Z	MF CAPACITOR	0.47uF 50V J	1	
	C313	NDC31HJ-560X	C CAPACITOR	56pF 50V J	1	
	C314	NDC31HJ-560X	C CAPACITOR	56pF 50V J	1	
	C315	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C316	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C317	QTE1C57-476Z	E CAPACITOR	47uF 16V	1	
	C318	QTE1H57-475Z	E CAPACITOR	4.7uF 50V	1	
	C319	NCB31EK-223X	C CAPACITOR	0.022uF 25V K	1	
	C320	NCB31EK-223X	C CAPACITOR	0.022uF 25V K	1	
	C361	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	A,C,D
	C362	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	A,C,D
	C365	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C366	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C367	QEKJ1AM-227Z	E CAPACITOR	220uF 10V M	1	A,C,D
	C368	QEKJ1AM-227Z	E CAPACITOR	220uF 10V M	1	A,C,D
	C369	QEKJ1CM-226Z	E CAPACITOR	22uF 16V M	1	A,C,D
	C370	NCBA1HK-152W	C CAPACITOR	1500pF 50V K	1	A,C,D
	C371	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	A,C,D

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C372	NCBA1HK-152W	C CAPACITOR	1500pF 50V K	1	A,C,D
	C381	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	A,C,D
	C382	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	A,C,D
	C385	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C386	QEKJ1HM-475Z	E CAPACITOR	4.7uF 50V M	1	
	C387	QEKJ1CM-107Z	E CAPACITOR	100uF 16V M	1	A,C,D
	C388	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	A,C,D
	C477	NDCA1HJ-220W	C CAPACITOR	22pF 50V J	1	
	C478	NDCA1HJ-220W	C CAPACITOR	22pF 50V J	1	
	C493	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C501	NCBA1HK-222W	C CAPACITOR	2200pF 50V K	1	
	C503	NCB31HK-562X	C CAPACITOR	5600pF 50V K	1	
	C505	NCBA1HK-222W	C CAPACITOR	2200pF 50V K	1	
	C507	NCB31EK-682X	C CAPACITOR	6800pF 25V K	1	
	C509	NDC31HJ-680X	C CAPACITOR	68pF 50V J	1	
	C511	QEKJ1AM-107Z	E CAPACITOR	100uF 10V M	1	
	C512	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C513	QEKJ1CM-476Z	E CAPACITOR	47uF 16V M	1	
	C515	QEKJ0JM-107Z	E CAPACITOR	100uF 6.3V M	1	
	C516	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C517	NCB31HK-102X	C CAPACITOR	1000pF 50V K	1	
	C520	NCBA1CK-153W	C CAPACITOR	0.015uF 16V K	1	
	C521	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C522	NCBA1HK-102W	C CAPACITOR	1000pF 50V K	1	
	C523	NCB31CK-823X	C CAPACITOR	0.082uF 16V K	1	
	C525	NCBA1HK-102W	C CAPACITOR	1000pF 50V K	1	
	C526	NCB31AK-334X	C CAPACITOR	0.33uF 10V K	1	
	C527	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C528	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C530	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C531	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C532	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C533	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C534	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C535	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C538	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C541	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C542	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C543	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C544	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C545	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	
	C546	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C547	NCB31AK-154X	C CAPACITOR	0.15uF 10V K	1	
	C549	NCB31HK-272X	C CAPACITOR	2700pF 50V K	1	
	C550	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	
	C551	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C552	NCBA1CK-223W	C CAPACITOR	0.022uF 16V K	1	
	C553	NCBA1HK-332W	C CAPACITOR	3300pF 50V K	1	
	C554	NCB31AK-334X	C CAPACITOR	0.33uF 10V K	1	
	C555	NCJ21CK-475X-R	C CAPACITOR	4.7uF 16V K	1	
	C556	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C557	NDC31HJ-681X	C CAPACITOR	680pF 50V J	1	
	C558	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	
	C559	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	
	C560	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C561	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C562	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C583	NDCA1HJ-821W	C CAPACITOR	820pF 50V J	1	
	C584	NDCA1HJ-821W	C CAPACITOR	820pF 50V J	1	
	C585	QTE1H57-475Z	E CAPACITOR	4.7uF 50V	1	
	C586	QTE1H57-475Z	E CAPACITOR	4.7uF 50V	1	
	C587	NDCA1HJ-151W	C CAPACITOR	150pF 50V J	1	
	C588	NDCA1HJ-151W	C CAPACITOR	150pF 50V J	1	
	C590	QTE0J57-476Z	E CAPACITOR	47uF 6.3V	1	
	C591	QTE1A57-107Z	E CAPACITOR	100uF 10V	1	
	C592	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C701	NDCA1HJ-220W	C CAPACITOR	22pF 50V J	1	
	C702	NDCA1HJ-270W	C CAPACITOR	27pF 50V J	1	
	C705	NDC31HJ-220X	C CAPACITOR	22pF 50V J	1	
	C706	NDC31HJ-220X	C CAPACITOR	22pF 50V J	1	
	C709	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	1	
	C710	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	1	
	C711	NDC31HJ-470X	C CAPACITOR	47pF 50V J	1	
	C712	NDC31HJ-220X	C CAPACITOR	22pF 50V J	1	
	C713	NDC31HJ-470X	C CAPACITOR	47pF 50V J	1	
	C714	NDC31HJ-101X	C CAPACITOR	100pF 50V J	1	A,C,D,E,F
	C715	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C716	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C717	NCBA1CK-473W	C CAPACITOR	0.047uF 16V K	1	
	C718	NCBA1CK-103W	C CAPACITOR	0.01uF 16V K	1	
	C720	NCB31CK-473X	C CAPACITOR	0.047uF 16V K	1	
	C721	NCB31CK-473X	C CAPACITOR	0.047uF 16V K	1	
	C722	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C723	QEKJ0JM-337Z	E CAPACITOR	330uF 6.3V M	1	
	C724	NDC31HJ-101X	C CAPACITOR	100pF 50V J	1	
	C725	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C726	NDC31HJ-470X	C CAPACITOR	47pF 50V J	1	
	C727	NCBA1CK-473W	C CAPACITOR	0.047uF 16V K	1	
	C730	NDC31HJ-102X	C CAPACITOR	1000pF 50V J	1	
	C731	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C732	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C733	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C771	NCBA1AK-473W	C CAPACITOR	0.047uF 10V K	1	E,F
	C781	QEKJ0JM-107Z	E CAPACITOR	100uF 6.3V M	1	
	C784	QEKJ1CM-107Z	E CAPACITOR	100uF 16V M	1	
	C785	QEKJ0JM-476Z	E CAPACITOR	47uF 6.3V M	1	
	C786	NCBA1AK-104W	C CAPACITOR	0.1uF 10V K	1	
	C801	NCBA1CK-473W	C CAPACITOR	0.047uF 16V K	1	A,B
	C851	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	C,D
	C852	NCB31CK-224X	C CAPACITOR	0.22uF 16V K	1	C,D
	C881	QEKJ1CM-226Z	E CAPACITOR	22uF 16V M	1	
	C901	QE20870-278	E CAPACITOR	2700uF	1	
	C903	QEKJ1CM-476Z	E CAPACITOR	47uF 16V M	1	
	C904	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C905	QEKJ1CM-476Z	E CAPACITOR	47uF 16V M	1	
	C906	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C907	QEKJ1CM-107Z	E CAPACITOR	100uF 16V M	1	
	C908	QERF1AM-227Z	E CAPACITOR	220uF 10V M	1	
	C909	QERF0JM-337Z	E CAPACITOR	330uF 6.3V M	1	
	C910	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C911	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	1	
	C912	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C913	QEKJ1CM-106Z	E CAPACITOR	10uF 16V M	1	
	C915	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	1	
	C916	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C917	QEKJ0JM-337Z	E CAPACITOR	330uF 6.3V M	1	
	C918	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C921	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C922	QEKJ0JM-107Z	E CAPACITOR	100uF 6.3V M	1	
	C923	NCB31AK-105X	C CAPACITOR	1uF 10V K	1	
	C925	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	1	
	C926	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	1	
	C928	QEKJ1EM-476Z	E CAPACITOR	47uF 25V M	1	
	C929	QEKJ1EM-476Z	E CAPACITOR	47uF 25V M	1	
	C930	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C931	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C932	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C933	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C934	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C935	NCB31HK-272X	C CAPACITOR	2700pF 50V K	1	
	C936	NDC31HJ-5R6X	C CAPACITOR	5.6pF 50V J	1	
	C937	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C938	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C939	NDCA1HJ-100W	C CAPACITOR	10pF 50V J	1	
	C940	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C941	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C942	NCJ11EK-106X-A	C CAPACITOR	10uF 25V K	1	
	C943	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C944	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C945	NCB31HK-272X	C CAPACITOR	2700pF 50V K	1	
	C946	NDC31HJ-5R6X	C CAPACITOR	5.6pF 50V J	1	
	C947	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C948	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C949	NDCA1HJ-100W	C CAPACITOR	10pF 50V J	1	
	C952	NCB10JK-106X-A	C CAPACITOR	10uF 6.3V K	1	
	C953	NDC31HJ-101X	C CAPACITOR	100pF 50V J	1	
	C971	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	1	
	R1	NRSA63J-474X	MG RESISTOR	470kΩ 1/16W J	1	
	R2	NRSA63J-474X	MG RESISTOR	470kΩ 1/16W J	1	
	R3	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R4	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5	NRSA02J-470X	MG RESISTOR	47Ω 1/10W J	1	
	R6	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	
	R7	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	
	R8	NRSA02J-470X	MG RESISTOR	47Ω 1/10W J	1	
	R11	NRS181J-4R7X	MG RESISTOR	4.7Ω 1/8W J	1	
	R14	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R15	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R71	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	E,F
	R72	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	E,F
	R73	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	E,F
	R74	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	1	E,F
	R166	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R167	NRSA63J-471X	MG RESISTOR	470Ω 1/16W J	1	
	R176	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R184	NRSA6AJ-123W	MG RESISTOR	12kΩ 1/16W J	1	
	R189	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R194	NRSA6AJ-123W	MG RESISTOR	12kΩ 1/16W J	1	
	R195	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R202	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R230	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R231	NRSA6AJ-122W	MG RESISTOR	1.2kΩ 1/16W J	1	
	R232	NRSA6AJ-122W	MG RESISTOR	1.2kΩ 1/16W J	1	
	R233	NRSA6AJ-124W	MG RESISTOR	120kΩ 1/16W J	1	
	R234	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	
	R235	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R237	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R238	NRSA6AJ-124W	MG RESISTOR	120kΩ 1/16W J	1	
	R239	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R240	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R241	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R242	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R243	NRSA02J-100X	MG RESISTOR	10Ω 1/10W J	1	
	R271	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D
	R272	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	1	A,C,D
	R273	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	B,E,F
	R274	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	
	R275	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R276	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R277	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R278	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R301	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R302	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R304	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R309	NRSA02J-100X	MG RESISTOR	10Ω 1/10W J	1	
	R310	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R311	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R312	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R313	NRSA6AJ-271W	MG RESISTOR	270Ω 1/16W J	1	A
	R314	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	A
	R321	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R322	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R323	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R331	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R332	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R333	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R341	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R342	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R343	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R351	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R352	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R353	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R361	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	A,C,D
	R362	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D
	R363	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R365	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	A,C,D
	R366	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D
	R367	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R371	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	B,E,F
	R372	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	B,E,F
	R373	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	B,E,F
	R374	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	B,E,F
	R377	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R378	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R381	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	A,C,D
	R382	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D
	R383	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R385	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	A,C,D
	R386	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D
	R387	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R477	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R478	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R502	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	1	
	R503	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	
	R504	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R505	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R507	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R508	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R509	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R510	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R511	NRSA6AJ-562W	MG RESISTOR	5.6kΩ 1/16W J	1	
	R512	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R513	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R514	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R515	NRSA6AJ-562W	MG RESISTOR	5.6kΩ 1/16W J	1	
	R516	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R517	NRSA6AJ-682W	MG RESISTOR	6.8kΩ 1/16W J	1	
	R518	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R519	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R520	NRS125J-100X	MG RESISTOR	10Ω 1/2W J	1	
	R521	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R522	NRSA6AJ-512W	MG RESISTOR	5.1kΩ 1/16W J	1	
	R523	NRSA6AJ-333W	MG RESISTOR	33kΩ 1/16W J	1	
	R524	NRSA6AJ-683W	MG RESISTOR	68kΩ 1/16W J	1	
	R525	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	1	
	R528	NRSA63J-220X	MG RESISTOR	22Ω 1/16W J	1	
	R529	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R531	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R532	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R533	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R534	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R535	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R536	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R537	NRSA02J-100X	MG RESISTOR	10Ω 1/10W J	1	
	R538	NRSA02J-100X	MG RESISTOR	10Ω 1/10W J	1	
	R539	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R540	NRSA6AJ-821W	MG RESISTOR	820Ω 1/16W J	1	
	R541	NRSA6AJ-272W	MG RESISTOR	2.7kΩ 1/16W J	1	
	R542	NRSA6AJ-823W	MG RESISTOR	82kΩ 1/16W J	1	
	R544	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R546	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R547	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R548	NRSA6AJ-221W	MG RESISTOR	220Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R549	NRSA6AJ-105W	MG RESISTOR	1MΩ 1/16W J	1	
	R550	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R551	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R552	NRSA6AJ-220W	MG RESISTOR	22Ω 1/16W J	1	
	R553	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R554	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R583	NRSA6AJ-243W	MG RESISTOR	24kΩ 1/16W J	1	
	R584	NRSA6AJ-243W	MG RESISTOR	24kΩ 1/16W J	1	
	R585	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R586	NRSA6AJ-822W	MG RESISTOR	8.2kΩ 1/16W J	1	
	R587	NRSA6AJ-273W	MG RESISTOR	27kΩ 1/16W J	1	
	R588	NRSA6AJ-273W	MG RESISTOR	27kΩ 1/16W J	1	
	R591	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R592	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R593	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R594	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R601	NRS125J-100X	MG RESISTOR	10Ω 1/2W J	1	
	R603	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R701	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R702	NRSA6AJ-106W	MG RESISTOR	10MΩ 1/16W J	1	
	R703	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R705	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R707	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R709	NRSA6AJ-151W	MG RESISTOR	150Ω 1/16W J	1	
	R710	NRSA6AJ-151W	MG RESISTOR	150Ω 1/16W J	1	
	R711	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R712	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	
	R713	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R714	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R715	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R719	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R721	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R722	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R723	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R724	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	C,D
	R725	NRSA6AJ-393W	MG RESISTOR	39kΩ 1/16W J	1	
	R726	NRSA6AJ-562W	MG RESISTOR	5.6kΩ 1/16W J	1	
	R727	NRSA6AJ-682W	MG RESISTOR	6.8kΩ 1/16W J	1	
	R728	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R729	NRSA6AJ-393W	MG RESISTOR	39kΩ 1/16W J	1	
	R730	NRSA6AJ-153W	MG RESISTOR	15kΩ 1/16W J	1	
	R731	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R732	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R733	NRSA6AJ-122W	MG RESISTOR	1.2kΩ 1/16W J	1	
	R734	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R735	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	
	R736	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	
	R741	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R743	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R745	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R748	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R749	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	A,C,D,E,F
	R750	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	A,B
	R751	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R752	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R753	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R754	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R755	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R756	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R758	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	E,F
	R759	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	A,B
	R761	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	
	R762	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	A,B
	R763	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	A,B
	R764	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	A,B
	R765	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	A,B
	R767	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R771	NRSA6AJ-271W	MG RESISTOR	270Ω 1/16W J	1	E,F
	R772	NRSA6AJ-271W	MG RESISTOR	270Ω 1/16W J	1	E,F
	R781	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R782	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R783	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R784	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R786	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	1	
	R790	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	A,C,D,E,F
	R791	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	A,C,D,E,F
	R792	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R793	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R796	NRSA6AJ-123W	MG RESISTOR	12kΩ 1/16W J	1	
	R797	NRSA6AJ-104W	MG RESISTOR	100kΩ 1/16W J	1	
	R798	NRSA6AJ-474W	MG RESISTOR	470kΩ 1/16W J	1	
	R801	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	A,B
	R803	NRSA6AJ-682W	MG RESISTOR	6.8kΩ 1/16W J	1	A,B
	R804	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	A,B
	R805	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	A,B
	R806	NRSA6AJ-104W	MG RESISTOR	100kΩ 1/16W J	1	A,B
	R807	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	A,B
	R808	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	A,B
	R809	NRSA6AJ-682W	MG RESISTOR	6.8kΩ 1/16W J	1	A,B
	R810	NRSA6AJ-104W	MG RESISTOR	100kΩ 1/16W J	1	A,B

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R811	NRSA6AJ-104W	MG RESISTOR	100kΩ 1/16W J	1	A,B
	R812	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	A,B
	R814	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	A,B
	R851	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	C,D
	R852	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	C,D
	R853	QRE142J-102X	C RESISTOR	1kΩ 1/4W J	1	C,D
	R881	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R882	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R901	QRE142J-102X	C RESISTOR	1kΩ 1/4W J	1	
	R902	NRSA02J-912X	MG RESISTOR	9.1kΩ 1/10W J	1	
	R903	NRSA02J-472X	MG RESISTOR	4.7kΩ 1/10W J	1	
	R921	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R922	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R923	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R924	NRS125J-390X	MG RESISTOR	39Ω 1/2W J	1	
	R925	NRS125J-390X	MG RESISTOR	39Ω 1/2W J	1	
	R930	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R931	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	
	R932	NRSA63J-394X	MG RESISTOR	390kΩ 1/16W J	1	
	R933	NRSA6AJ-681W	MG RESISTOR	680Ω 1/16W J	1	
	R935	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R936	NRSA6AD-153W	MG RESISTOR	15kΩ 1/16W D	1	
	R937	NRSA6AD-823W	MG RESISTOR	82kΩ 1/16W D	1	
	R940	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R941	NRSA6AJ-392W	MG RESISTOR	3.9kΩ 1/16W J	1	
	R942	NRSA63J-394X	MG RESISTOR	390kΩ 1/16W J	1	
	R943	NRSA6AJ-681W	MG RESISTOR	680Ω 1/16W J	1	
	R945	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R946	NRSA6AD-153W	MG RESISTOR	15kΩ 1/16W D	1	
	R947	NRSA6AD-823W	MG RESISTOR	82kΩ 1/16W D	1	
	R951	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R952	NRSA6AJ-103W	MG RESISTOR	10kΩ 1/16W J	1	
	R971	NRS181J-332X	MG RESISTOR	3.3kΩ 1/8W J	1	
	R976	NRSA02J-513X	MG RESISTOR	51kΩ 1/10W J	1	
	R977	NRSA02J-153X	MG RESISTOR	15kΩ 1/10W J	1	
	RA521	NRZ0034-330W	NET RESISTOR	33Ω 1/32W J x4	1	
	RA522	NRZ0034-330W	NET RESISTOR	33Ω 1/32W J x4	1	
	L1	NQL093K-R47X	P COIL	0.47uH K	1	
	L2	NQL093K-1R8X	P COIL	1.8uH K	1	
	L3	NQL093K-R22X	P COIL	0.22uH K	1	
	L4	QQR1872-001	RF COIL		1	
	L5	QQL244J-561Z	COIL	560uH J	1	
	L6	QQL244J-561Z	COIL	560uH J	1	
	L7	QQL244K-4R7Z	COIL	4.7uH K	1	
	L8	QQL244K-4R7Z	COIL	4.7uH K	1	
	L9	NQL093K-R47X	P COIL	0.47uH K	1	
	L472	NQR0536-001X	CHOKO COIL		1	
	L521	NQL093K-1R8X	P COIL	1.8uH K	1	
	L701	QQL244K-4R7Z	COIL	4.7uH K	1	
	L702	QQL244K-4R7Z	COIL	4.7uH K	1	
	L703	QQL244J-470Z	COIL	47uH J	1	
	L901	QQR1809-001	CHOKO COIL		1	
	L931	NQLC8CM-220X	COIL	22uH M	1	
	L941	NQLC8CM-220X	COIL	22uH M	1	
	CN202	QGA2001C1-02	CONNECTOR	W-B (1-2)	1	
	CN472	QGA2001C1-05	CONNECTOR	W-B (1-5)	1	
	CN501	QGB2027MD-26	CONNECTOR	B-B (1-26)	1	
	CN701	QGZ1101J1-20	CONNECTOR	(1-20)	1	
	CN702	QNS0283-001	3.5 JACK		1	A,C,D,E,F
	CN901	QNZ0607-001	CAR CONNECTOR		1	
	J1	QNB0190-001	ANT TERMINAL		1	
	J1 or	QNB0348-001	ANT TERMINAL		1	
	J321	QNN0839-001	PIN JACK		1	A
	J321	QNN0837-001	PIN JACK		1	B,C,D,E,F
	J801	QNZ0095-001	CONNECTOR		1	A,B
	K581	NQR0022-005X	FERRITE BEADS		1	
	K703	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	K704	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	K705	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	PP2	QZW0010-001	STYLE PIN		1	
	PP4	QZW0010-001	STYLE PIN		1	
	PP6	QZW0010-001	STYLE PIN		1	
	S703	QSW0648-001Z	TACT SWITCH		1	
	X11	QAX0952-001Z	CRYSTAL		1	
	X71	QAX0954-001Z	CRYSTAL		1	E,F
	X521	QAX0714-001Z	C RESONATOR	16.000MHz	1	
	X701	QAX0916-001Z	CRYSTAL		1	
	X702	QAX0953-001	CRYSTAL		1	
Switch board <02>						
	IC601	PCA9624PW-X	IC		1	
	IC602	S-80824CNNB-G-W	IC		1	
	IC602 or	IC-PST3424U-X	IC		1	
	IC661	JES187E	IC(MCU)		1	
	IC681	KSM-2003TN2M	IR DETECT UNIT		1	
	Q601	2SA812A/5-6/-X	TRANSISTOR		1	
	Q601 or	ISA1530AC1/QR/X	TRANSISTOR		1	
	Q602	2SA812A/5-6/-X	TRANSISTOR		1	
	Q602 or	ISA1530AC1/QR/X	TRANSISTOR		1	
	Q603	2SC1623A/5-6/-X	TRANSISTOR		1	
	Q603 or	2SC3928A/QR/-X	TRANSISTOR		1	
	D601	NSSM065T-X	LED		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D602	NSSM065T-X	LED		1	
	D604	LHQ974/LM/-X	LED		1	
	D605	LHQ974/LM/-X	LED		1	
	D608	NSSM065T-X	LED		1	
	D618	RKZ5.6B2KG-X	Z DIODE		1	
	D618	or MA8056/M/-X	Z DIODE		1	
	D624	HSU119-X	SI DIODE		1	
	D624	or MA111-X	SI DIODE		1	
	D625	RKZ5.1B2KG-X	Z DIODE		1	
	D625	or MA8051/M/-X	Z DIODE		1	
	D626	RKZ5.1B2KG-X	Z DIODE		1	
	D626	or MA8051/M/-X	Z DIODE		1	
	D630	MC2838-X	DIODE		1	
	D630	or MA152WK-X	SI DIODE		1	
	C601	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C604	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C605	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C606	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C607	NCB20JK-106X	C CAPACITOR	10uF 6.3V K	1	
	C611	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C612	NCB31CK-105X	C CAPACITOR	1uF 16V K	1	
	C614	NBE21CM-106X	TA E CAPACITOR	10uF 16V M	1	
	C624	NBE20JM-106X	TA E CAPACITOR	10uF 6.3V M	1	
	C630	NCB31EK-473X	C CAPACITOR	0.047uF 25V K	1	
	C631	NCB20JK-475X	C CAPACITOR	4.7uF 6.3V K	1	
	C632	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C644	NCB31CK-105X	C CAPACITOR	1uF 16V K	1	
	C649	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C651	NCB20JK-475X	C CAPACITOR	4.7uF 6.3V K	1	
	C653	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C654	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C655	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C656	NCB11EM-105X	C CAPACITOR	1uF 25V M	1	
	C657	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C658	NCB11EM-105X	C CAPACITOR	1uF 25V M	1	
	C659	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C660	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C661	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C662	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C663	NCJ31CK-105X-A	C CAPACITOR	1uF 16V K	1	
	C664	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C682	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	1	
	C688	NCJ11EK-106X-R	C CAPACITOR	10uF 25V	1	
	R601	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R602	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	1	
	R603	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	1	
	R604	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	1	
	R605	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	1	
	R606	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R607	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	
	R608	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	
	R609	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	1	
	R610	NRSA63J-680X	MG RESISTOR	680Ω 1/16W J	1	
	R611	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R612	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	1	
	R613	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R614	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R615	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	1	
	R616	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R617	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R618	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	1	
	R619	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	1	
	R620	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	1	
	R621	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	1	
	R622	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	1	
	R624	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R625	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R626	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R627	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R628	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R629	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R632	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R633	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R634	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	
	R635	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	1	
	R637	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R643	NRS181J-331X	MG RESISTOR	330Ω 1/8W J	1	
	R647	NRS181J-821X	MG RESISTOR	820Ω 1/8W J	1	
	R648	NRS181J-471X	MG RESISTOR	470Ω 1/8W J	1	
	R649	NRS181J-471X	MG RESISTOR	470Ω 1/8W J	1	
	R653	NRS181J-751X	MG RESISTOR	750Ω 1/8W J	1	
	R654	NRS181J-471X	MG RESISTOR	470Ω 1/8W J	1	
	R655	NRS181J-471X	MG RESISTOR	470Ω 1/8W J	1	
	R659	NRSA63J-471X	MG RESISTOR	470Ω 1/16W J	1	
	R661	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R662	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R663	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	1	
	R664	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	1	
	R665	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J	1	
	R667	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R668	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	1	
	R669	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	1	
	R670	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	1	
	R671	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J	1	
	R673	NRS181J-4R7X	MG RESISTOR	4.7Ω 1/8W J	1	
	R681	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	1	
	R682	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R686	NRSA63J-471X	MG RESISTOR	470Ω 1/16W J	1	
	R690	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	1	
	R692	NRSA63J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	R694	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	
	R695	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	1	
	R696	NRSA63J-474X	MG RESISTOR	470kΩ 1/16W J	1	
	R697	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R698	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	RA601	NRZ0065-472X	MG RESISTOR	4.7kΩ	1	
	RA602	NRZ0065-472X	MG RESISTOR	4.7kΩ	1	
	RA603	NRZ0065-472X	MG RESISTOR	4.7kΩ	1	
	RA604	NRZ0065-331X	NET RESISTOR	330Ω	1	
	RA605	NRZ0065-331X	NET RESISTOR	330Ω	1	
	L601	NQL79GM-470X	COIL	47uH M	1	
	L602	NQR0536-001X	CHOKO COIL		1	
	L604	NQR0022-005X	FERRITE BEADS		1	
	L670	NQR0007-002X	FERRITE BEADS		1	
	L671	NQR0007-002X	FERRITE BEADS		1	
	L672	NQR0007-002X	FERRITE BEADS		1	
	CJ601	QGZ1101K1-20	CONNECTOR	(1-20)	1	
	CN602	QGF0522F3-33W	CONNECTOR	FFC/FPC (1-33)	1	
	CN603	QNZ1006-001	USB CONNECTOR		1	
	EN601	QSW1231-002	ROTARY ENCODER		1	
	J601	QNS0280-001	3.5 JACK		1	
	S601	NSW0326-001X	TACT SWITCH		1	
	S602	NSW0326-001X	TACT SWITCH		1	
	S603	NSW0326-001X	TACT SWITCH		1	
	S604	NSW0326-001X	TACT SWITCH		1	
	S605	NSW0326-001X	TACT SWITCH		1	
	S607	NSW0326-001X	TACT SWITCH		1	
	S608	NSW0326-001X	TACT SWITCH		1	
	S609	NSW0326-001X	TACT SWITCH		1	
	S610	NSW0326-001X	TACT SWITCH		1	
	S611	NSW0326-001X	TACT SWITCH		1	
	S612	NSW0326-001X	TACT SWITCH		1	
	X601	NAX0752-001X	C RESONATOR		1	
Module board <03>						
	IC401	TCC8600	IC		1	
	IC402	R1EX24256ASAS-X	IC		1	
	IC441	JVM481J	PROGRAMMED IC		1	
	IC442	M12L1281687TG2T	IC(DIGITAL)		1	
	IC471	74LVC1G3157GW-X	IC		1	
	IC481	MFI341S2162-X	IC		1	
	IC491	NJM2878F4-18-X	IC		1	
	IC601	PCM1780-X	IC		1	
	Q401	RT1N441C-X	TRANSISTOR		1	
	Q401 or	UN2213-X	DIGI TRANSISTOR		1	
	D601	RKZ5.1B2KG-X	Z DIODE		1	
	D601 or	MA8051M/M-X	Z DIODE		1	
	C401	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C402	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C403	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C404	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C405	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C406	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C407	NDC31HJ-270X	C CAPACITOR	27pF 50V J	1	
	C408	NDC31HJ-330X	C CAPACITOR	33pF 50V J	1	
	C409	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C410	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C414	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C415	NCBA1HK-122W	C CAPACITOR	1200pF 50V K	1	
	C416	NCJ30JM-106X-A	C CAPACITOR	10uF 6.3V M	1	
	C417	NDCA1HJ-331W	C CAPACITOR	330pF 50V J	1	
	C418	NCB31AK-154X	C CAPACITOR	0.15uF 10V K	1	
	C419	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C420	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C421	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C422	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C423	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C424	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C425	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C426	NDCA1HJ-200W	C CAPACITOR	20pF 50V J	1	
	C430	NQR0450-001X	EMI FILTER	0.022uF 50V M	1	
	C441	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C442	NBE20JM-226X	TA E CAPACITOR	22uF 6.3V M	1	
	C443	NBE20JM-226X	TA E CAPACITOR	22uF 6.3V M	1	
	C444	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C445	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C446	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C447	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C448	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C449	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C450	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C451	NDCA1HJ-221W	C CAPACITOR	220pF 50V J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C452	NDCA1HJ-221W	C CAPACITOR	220pF 50V J	1	
	C453	NDCA1HJ-221W	C CAPACITOR	220pF 50V J	1	
	C471	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C481	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C482	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C491	NBE41AM-476X	TA E CAPACITOR	47uF 10V M	1	
	C492	NCB20JK-106X	C CAPACITOR	10uF 6.3V K	1	
	C493	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	1	
	C494	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C495	NBE20JM-226X	TA E CAPACITOR	22uF 6.3V M	1	
	C497	NDC31HJ-331X	C CAPACITOR	330pF 50V J	1	
	C601	NBE41AM-476X	TA E CAPACITOR	47uF 10V M	1	
	C602	NCBA1CK-123W	C CAPACITOR	0.012uF 16V K	1	
	C603	NCBA1CK-104W	C CAPACITOR	0.1uF 16V K	1	
	C604	NBE41AM-476X	TA E CAPACITOR	47uF 10V M	1	
	C605	NDCA1HJ-101W	C CAPACITOR	100pF 50V J	1	
	C606	NDCA1HJ-101W	C CAPACITOR	100pF 50V J	1	
	R401	NRSA6AJ-470W	MG RESISTOR	47Ω 1/16W J	1	
	R402	NRSA6AJ-470W	MG RESISTOR	47Ω 1/16W J	1	
	R403	NRSA6AJ-470W	MG RESISTOR	47Ω 1/16W J	1	
	R404	NRSA6AJ-151W	MG RESISTOR	150Ω 1/16W J	1	
	R405	NRSA6AJ-105W	MG RESISTOR	1MΩ 1/16W J	1	
	R406	NQR0022-005X	FERRITE BEADS		1	
	R407	NQR0286-007X	FERRITE BEADS		1	
	R408	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R409	NRSA6AJ-223W	MG RESISTOR	22kΩ 1/16W J	1	
	R410	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R411	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R412	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R413	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R414	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R415	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R416	NRSA6AJ-271W	MG RESISTOR	270Ω 1/16W J	1	
	R417	NRSA6AJ-271W	MG RESISTOR	270Ω 1/16W J	1	
	R418	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R419	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R420	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R421	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R422	NRSA6AJ-222W	MG RESISTOR	2.2kΩ 1/16W J	1	
	R424	NQR0286-007X	FERRITE BEADS		1	
	R425	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R426	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R427	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R428	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	1	
	R429	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R430	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	
	R431	NRSA6AJ-101W	MG RESISTOR	100Ω 1/16W J	1	
	R432	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R433	NRSA6AJ-102W	MG RESISTOR	1kΩ 1/16W J	1	
	R434	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R435	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	1	
	R441	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R443	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R444	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R446	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	1	
	R447	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R448	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R449	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R450	NRSA6AJ-472W	MG RESISTOR	4.7kΩ 1/16W J	1	
	R451	NQR0286-007X	FERRITE BEADS		1	
	R452	NQR0286-007X	FERRITE BEADS		1	
	R453	NQR0286-007X	FERRITE BEADS		1	
	R454	NQR0286-007X	FERRITE BEADS		1	
	R455	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R456	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R457	NRSA6AJ-330W	MG RESISTOR	33Ω 1/16W J	1	
	R458	NRSA6AJ-0R0W	MG RESISTOR	0Ω 1/16W J	1	
	R481	NRSA6AJ-473W	MG RESISTOR	47kΩ 1/16W J	1	
	R521	NQR0286-007X	FERRITE BEADS		1	
	R601	NQR0286-007X	FERRITE BEADS		1	
	R602	NQR0286-007X	FERRITE BEADS		1	
	R603	NQR0286-007X	FERRITE BEADS		1	
	R604	NRSA6AJ-220W	MG RESISTOR	22Ω 1/16W J	1	
	R605	NRSA6AJ-220W	MG RESISTOR	22Ω 1/16W J	1	
	R606	NRSA6AJ-220W	MG RESISTOR	22Ω 1/16W J	1	
	R607	NRSA63J-220X	MG RESISTOR	22Ω 1/16W J	1	
	R608	NRS181J-181X	MG RESISTOR	180Ω 1/8W J	1	
	R609	NRS181J-181X	MG RESISTOR	180Ω 1/8W J	1	
	L401	NQL093K-R12X	P COIL	0.12uH K	1	
	L402	NQL093K-R12X	P COIL	0.12uH K	1	
	L403	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	1	
	L404	NQR0022-005X	FERRITE BEADS		1	
	L405	NQR0022-005X	FERRITE BEADS		1	
	L406	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	1	
	L407	NQR0022-005X	FERRITE BEADS		1	
	L409	NQR0536-001X	CHOKE COIL		1	
	L410	NQR0536-001X	CHOKE COIL		1	
	L491	NQL79GM-4R7X	COIL	4.7uH M	1	
	L601	NQL79GM-470X	COIL	47uH M	1	
	CN441	QGG2011M1-18X	CONNECTOR	(1-18)	1	
	CN442	QGG2011M1-18X	CONNECTOR	(1-18)	1	
	CN444	QGG2504M5-02	CONNECTOR	(1-2)	1	


MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	K441	NQR0502-001X	FERRITE BEADS		1	
	K442	NQR0286-007X	FERRITE BEADS		1	
	K443	NQR0286-007X	FERRITE BEADS		1	
	K444	NQR0286-007X	FERRITE BEADS		1	
	K445	NQR0286-007X	FERRITE BEADS		1	
	K446	NQR0286-007X	FERRITE BEADS		1	
	K447	NQR0286-007X	FERRITE BEADS		1	
	K448	NQR0286-007X	FERRITE BEADS		1	
	K449	NQR0286-007X	FERRITE BEADS		1	
	K450	NQR0286-007X	FERRITE BEADS		1	
	K451	NQR0022-005X	FERRITE BEADS		1	
	X401	NAX0975-001X	CRYSTAL		1	
FLM-CD5-1D Mecha control board <04>						
	Q101	2SC3928A/R/-X	TRANSISTOR		1	A,B,C,D,E,F
	Q101 or	2SD601A/R/-X	TRANSISTOR		1	A,B,C,D,E,F
	Q201	2SC3928A/R/-X	TRANSISTOR		1	A,B,C,D,E,F
	Q201 or	2SD601A/R/-X	TRANSISTOR		1	A,B,C,D,E,F
	Q301	PS1191RB22/BC/X	PHOTO TRANSISTOR		1	A,B,C,D,E,F
	Q302	PS1191RB22/BC/X	PHOTO TRANSISTOR		1	A,B,C,D,E,F
	D101	AN1105W21/AB/-X	IR LED		1	A,B,C,D,E,F
	D201	AN1105W21/AB/-X	IR LED		1	A,B,C,D,E,F
	R101	NRSA02J-391X	MG RESISTOR	390Ω 1/10W J	1	A,B,C,D,E,F
	R102	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	1	A,B,C,D,E,F
	R103	NRSA63J-184X	MG RESISTOR	180kΩ 1/16W J	1	A,B,C,D,E,F
	R104	NRSA63J-184X	MG RESISTOR	180kΩ 1/16W J	1	A,B,C,D,E,F
	R105	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	1	A,B,C,D,E,F
	R201	NRSA02J-391X	MG RESISTOR	390Ω 1/10W J	1	A,B,C,D,E,F
	R202	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	1	A,B,C,D,E,F
	R203	NRSA63J-184X	MG RESISTOR	180kΩ 1/16W J	1	A,B,C,D,E,F
	R204	NRSA63J-184X	MG RESISTOR	180kΩ 1/16W J	1	A,B,C,D,E,F
	R205	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	1	A,B,C,D,E,F
	CN101	QGB2027LA-26X	CONNECTOR	B-B (1-26)	1	A,B,C,D,E,F
	CN102	QGF0522F3-15W	CONNECTOR	FFC/FPC (1-15)	1	A,B,C,D,E,F
	SW1	NSW0291-001X	DETECT SWITCH		1	A,B,C,D,E,F

Packing materials and accessories

Block No.M3MM

No additional / supplemental order of WARRANTY CARDS are available.



The parts without symbol number are not service.

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KD-A815J	A	KD-R810J	B	KD-R816U	C	KD-R816UH	D
KD-R811E	E	KD-R811EY	F				

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
Packing and accessories <M3MM>						
A1		GET0651-001A	INST BOOK	ENG SPA FRE	1	A,B
A3		GET0651-002A	INSTALL MANUAL	ENG SPA FRE	1	A,B
A4		-----	WARRANTY CARD	BT-52008-1	1	A,B
A5		-----	WARRANTY CARD	BT-51029-3	1	A
A5		-----	WARRANTY CARD	BT-51018-6	1	B
A6		BT-51044-1	REGIST CARD		1	A,B
A7		GET0652-001A	INST BOOK	ENG THA	1	C,D
A7		GET0653-003A	INST BOOK	ENG FRE	1	E
A7		GET0653-007A	INST BOOK	CZE HUN	1	F
A8		GET0652-006A	INSTALL MANUAL	ENG THA	1	C,D
A8		GET0653-008A	INSTALL MANUAL	GER	1	E,F
A9		GET0653-009A	INSTALL MANUAL	DUT SPA ITA POR	1	E
A9		GET0653-013A	INSTALL MANUAL	POL RUS GRE	1	F
A10		GET0653-010A	INSTALL MANUAL	ENG FRE	1	E
A10		GET0653-014A	INSTALL MANUAL	CZE HUN	1	F
A11		-----	WARRANTY CARD	BT-54042-1	1	E,F
A12		GET0617-001B	ADAPTER SHEET		1	
A13		QAU0526-001	RF MODULE		1	
A14		GET0652-002A	INST BOOK	KOR CHI(TAIWAN) ARA PER	1	C
A14		GET0653-001A	INST BOOK	GER	1	E,F
A15		GET0652-003A	INST BOOK	RUS	1	C
A15		GET0653-002A	INST BOOK	DUT SPA ITA POR	1	E
A15		GET0653-006A	INST BOOK	POL RUS GRE	1	F
A16		GET0652-007A	INSTALL MANUAL	KOR CHI(TAIWAN) ARA PER	1	C
A17		GET0652-008A	INSTALL MANUAL	RUS	1	C
A18		RM-RK50C1	REMOCON UNIT		1	A,B,E,F
A18		RM-RK50M	REMOCON UNIT		1	C,D
A19		QAM1143-001	CAR CABLE		1	A,B
A19		QAM1146-001	CAR CABLE		1	C,D
A19		QAM1149-002	CAR CABLE		1	E,F
A20		QAN0096-001	MICROPHONE		1	
A21		GE32320-001A	HARD CASE ASSY		1	
A22		GE40481-001A	HOOK		2	
A23		GE20267-001A	MOUNTING SLEEVE		1	
A24		GE20235-014A	TRIM PLATE		1	A,B,C,D
A24		GE20204-020A	TRIM PLATE		1	E,F
P1		GE33918-001A	CARTON		1	A
P1		GE33921-001A	CARTON		1	B
P1		GE33924-001A	CARTON		1	C,D
P1		GE33927-001A	CARTON		1	E,F
P2		GE10271-001A	CUSHION		1	A,B,C,D
P2		GE10270-001A	CUSHION		1	E,F
P3		QPC03004315PB	POLY BAG	30cm x 43cm	1	
P4		QPC01002515	POLY BAG	10cm x 25cm	1	A,B
P5		FSPG4002-001	POLY BAG		2	A,B,C,E,F
P5		FSPG4002-001	POLY BAG		1	D
P6		QPC01002515	POLY BAG	10cm x 25cm	1	A,B,C,D,E
P7		QPA01003003	POLY BAG	10cm x 30cm	1	