

This exploded view diagram illustrates the components of the HP Z840 G2 chassis, arranged in the order they should be installed. The components are labeled as follows:

- DC1**: Power supply unit.
- DC2**: Power supply unit.
- RC1**: Remote control.
- 351**: Front bezel.
- 352**: Front bezel.
- 353**: Chassis frame.
- 354 x2**: Two screws for the front bezel.
- 355 x6**: Six screws for the front bezel.
- 356 x6**: Six screws for the front bezel.
- 357**: Cable for the front bezel.
- 358**: Cable for the front bezel.
- 501-802**: Front bezel.



Parts with the exploded numbers larger than 700 are not supplied.  
created date:2019-10-23

| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
|----------|------|------------|------|------------|------|----------|------|
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |


| Safe | Symbol No. | Parts No. | Parts Name | Description | QTY | Local |
|------|------------|-----------|------------|-------------|-----|-------|
|------|------------|-----------|------------|-------------|-----|-------|

# EXPLODED VIEW (UNIT) <M1MM>

|   |      |               |                 |                 |    |                |
|---|------|---------------|-----------------|-----------------|----|----------------|
| △ | DC1  | E3A-0324-00   | DC CORD         |                 | 1  | K2,M1,K1,K3,K0 |
| △ | DC2  | E3A-0455-00   | DC CORD         |                 | 1  | E1             |
|   | MAB1 | CB-XJ1296K02N | MAIN PWB        | XJ1-296K-02     | 1  | K2             |
|   | MAB1 | CB-XJ1296E01N | MAIN PWB        | XJ1-296E-01     | 1  | E1             |
|   | MAB1 | CB-XJ1296M01N | MAIN PWB        | XJ1-296M-01     | 1  | M1             |
|   | MAB1 | CB-XJ1296K01N | MAIN PWB        | XJ1-296K-01     | 1  | K1             |
|   | MAB1 | CB-XJ1296K03N | MAIN PWB        | XJ1-296K-03     | 1  | K3             |
|   | MAB1 | CB-XJ1296K00N | MAIN PWB        | XJ1-296K-00     | 1  | K0             |
|   | DME1 | XJJ-070W-00   | CD MECHANISM    |                 | 1  |                |
| △ | F901 | FZB10BT-100   | BLADE FUSE      | 32V             | 1  |                |
|   | FC1  | E3G-0158-00   | FFC WIRE        |                 | 1  |                |
|   | LCD1 | B3H-0128-00   | LCD             |                 | 1  |                |
|   | PA1  | A6D-0158-07   | PANEL ASSY      |                 | 1  | K2,K3          |
|   | PA1  | A6D-0158-00   | PANEL ASSY      |                 | 1  | E1             |
|   | PA1  | A6D-0158-01   | PANEL ASSY      |                 | 1  | M1             |
|   | PA1  | A6D-0158-08   | PANEL ASSY      |                 | 1  | K1             |
|   | PA1  | A6D-0158-02   | PANEL ASSY      |                 | 1  | K0             |
|   | RC1  | A7A-0019-00   | REMOTE CTL(IR)  |                 | 1  | M1,K1          |
|   | A    | LV41200-004A  | SPECIAL SCREW   |                 | 3  |                |
|   | B    | QYSDST2604ZA  | TAP SCREW       | M2.6 x 4.0mm    | 2  |                |
|   | E    | QYSDST2606ZA  | TAP SCREW       | M2.6 x 6.0mm    | 1  |                |
|   | F    | QYSDST2608ZA  | TAP SCREW       | M2.6 x 8.0mm    | 1  |                |
|   | G    | QYSDST2610ZA  | TAP SCREW       | M2.6 x 10.0mm   | 2  |                |
|   | H    | QYSDSF2608ZA  | TAP SCREW       | M2.6 x 8.0mm    | 1  |                |
|   | J    | QYSPSG3008ZA  | TAP SCREW       | M3.0 x 8.0mm    | 1  |                |
|   | K    | QYSDST2606ZA  | TAP SCREW       | M2.6 x 6.0mm    | 1  | K2,K0          |
|   | L    | QYSDST2606ZA  | TAP SCREW       | M2.6 x 6.0mm    | 1  | M1,K1          |
|   | P    | QYSDSF2006ZA  | TAP SCREW       | M2.0 x 6.0mm    | 10 |                |
|   | Q    | QYSDST2004ZA  | TAP SCREW       | M2.0 x 4.0mm    | 2  |                |
|   | 215  | E3A-0699-00   | CORD W.CON.     |                 | 1  | M1,K1          |
|   | 251  | B1A-0109-04   | FRONT GLASS     |                 | 1  | K2             |
|   | 251  | B1A-0109-07   | FRONT GLASS     |                 | 1  | E1             |
|   | 251  | B1A-0109-09   | FRONT GLASS     |                 | 1  | M1             |
|   | 251  | B1A-0109-03   | FRONT GLASS     |                 | 1  | K1             |
|   | 251  | B1A-0109-05   | FRONT GLASS     |                 | 1  | K3             |
|   | 251  | B1A-0109-02   | FRONT GLASS     |                 | 1  | K0             |
|   | 252  | K2K-0496-00   | KEY TOP         |                 | 1  |                |
|   | 253  | K2K-0497-01   | KNOB            |                 | 1  |                |
|   | 254  | GE40127-005A  | KNOB SPRING     |                 | 1  |                |
|   | 255  | B1K-0153-00   | LIGHTING BOARD  |                 | 1  |                |
|   | 256  | B1K-0154-00   | LIGHTING BOARD  |                 | 1  |                |
|   | 257  | B1K-0155-01   | LIGHTING BOARD  |                 | 1  |                |
|   | 258  | K2E-0121-00   | PUSH KNOB       |                 | 1  |                |
|   | 259  | K2E-0122-00   | PUSH KNOB       |                 | 1  |                |
|   | 260  | E2K-0096-00   | CONDUCT RUBBER  |                 | 2  |                |
|   | 351  | GE20366-001A  | TRIM PLATE      |                 | 1  | K2,E1,K1,K3,K0 |
|   | 352  | B9H-0018-00   | ESCUTCHEON      |                 | 1  | M1,K1,K0       |
|   | 353  | LV22876-001A  | SLEEVE ASSY     |                 | 1  | K2,E1,K1,K3,K0 |
|   | 354  | LV45516-001A  | LEVER           |                 | 2  | K2,E1,K1,K3,K0 |
|   | 355  | QYSDSP5008ZA  | SCREW           | M5.0 x 8.0mm    | 6  | K2,M1,K1,K3,K0 |
|   | 356  | QYSSSP5008ZA  | SCREW           | M5.0 x 8.0mm    | 6  | K2,M1,K1,K3,K0 |
|   | 357  | T9B-0073-00   | MICROPHONE      |                 | 1  |                |
|   | 358  | E3A-0701-00   | CORD W.CON.     |                 | 1  | M1,K1          |
|   | 501  | B5A-3152-00   | INST.MANUAL     |                 | 1  | M1             |
|   | 702  | -----         | SWITCH PWB      | NO SERVICE PART | 1  | K2,M1,K1,K3,K0 |
|   | 702  | -----         | SWITCH PWB      | NO SERVICE PART | 1  | E1             |
|   | 711  | -----         | TOP COVER       | NO SERVICE PART | 1  |                |
|   | 712  | -----         | BOTTOM PLATE    | NO SERVICE PART | 1  |                |
|   | 713  | -----         | HEAT SINK       | NO SERVICE PART | 1  |                |
|   | 714  | -----         | COOL SHEET      | NO SERVICE PART | 1  |                |
|   | 761  | -----         | PANEL           | NO SERVICE PART | 1  | K2,E1,K1,K3    |
|   | 761  | -----         | PANEL           | NO SERVICE PART | 1  | M1             |
|   | 761  | -----         | PANEL           | NO SERVICE PART | 1  | K0             |
|   | 762  | -----         | KNOB ASSY       | NO SERVICE PART | 1  |                |
|   | 763  | -----         | KNOB ASSY       | NO SERVICE PART | 1  | K2,K3,K0       |
|   | 763  | -----         | KNOB ASSY       | NO SERVICE PART | 1  | E1             |
|   | 763  | -----         | KNOB ASSY       | NO SERVICE PART | 1  | M1,K1          |
|   | 764  | -----         | PUSH KNOB       | NO SERVICE PART | 1  |                |
|   | 765  | -----         | PUSH KNOB       | NO SERVICE PART | 1  |                |
|   | 766  | -----         | PUSH KNOB       | NO SERVICE PART | 1  |                |
|   | 767  | -----         | PUSH KNOB       | NO SERVICE PART | 1  |                |
|   | 768  | -----         | PUSH KNOB       | NO SERVICE PART | 1  |                |
|   | 769  | -----         | COVER           | NO SERVICE PART | 1  |                |
|   | 780  | -----         | LIGHTING BOARD  | NO SERVICE PART | 1  |                |
|   | 781  | -----         | LIGHTING BOARD  | NO SERVICE PART | 1  |                |
|   | 782  | -----         | BLIND PLATE     | NO SERVICE PART | 1  |                |
|   | 783  | -----         | LCD CASE        | NO SERVICE PART | 1  |                |
|   | 784  | -----         | OPTI.DIFFUSER   | NO SERVICE PART | 1  |                |
|   | 785  | -----         | LIGHTING BOARD  | NO SERVICE PART | 1  |                |
|   | 786  | -----         | REF.SHEET       | NO SERVICE PART | 1  |                |
|   | 802  | -----         | SUB-INST.MANUAL | NO SERVICE PART | 1  | K2,K1,K3,K0    |
|   | 802  | -----         | SUB-INST.MANUAL | NO SERVICE PART | 1  | E1             |

## Block No.MBMM

● W01-2067-08



| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
|----------|------|------------|------|------------|------|----------|------|
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No. | Parts Name | Description | QTY | Local |
|------|------------|-----------|------------|-------------|-----|-------|
|------|------------|-----------|------------|-------------|-----|-------|

EXPLODED VIEW (CD MECHANISM: XJJ-070W-00) <MBMM>

|      |               |                 |                 |   |
|------|---------------|-----------------|-----------------|---|
| DM1  | CM-FC2-MD     | MD CHASSIS ASSY |                 | 1 |
| DM2  | CM-FC2-M      | LOAD MOTOR ASSY |                 | 1 |
| DPU1 | T2F-0002-00   | CD OPT PICKUP   |                 | 1 |
| FPC1 | QAL1465-001   | FPC             |                 | 1 |
| A    | LV45568-001A  | MINI SCREW      |                 | 2 |
| B    | QYSPSGT1745ZA | TAP SCREW       | M1.7 x 4.5mm    | 1 |
| C    | QYSPSPT2025MA | SCREW           | M2.0 x 2.5mm    | 2 |
| D    | VKZ4539-054   | MINI SCREW      |                 | 4 |
| E    | LV45818-001A  | G.HOLDER SCREW  |                 | 5 |
| F    | LV45815-001A  | M. SHAFT SCREW  |                 | 1 |
| G    | LV45816-001A  | ROLLER WASHER   |                 | 2 |
| 1    | LV11877-003A  | OUTER CHASSIS   |                 | 1 |
| 2    | LV11878-006A  | LOWER CHASSIS   |                 | 1 |
| 3    | LV3A174-002A  | DISC ARM L      |                 | 1 |
| 4    | LV3A175-001A  | DISC ARM R      |                 | 1 |
| 5    | LV23057-001A  | SLIDER R        |                 | 1 |
| 6    | LV3A178-001A  | TRIGGER SLIDER  |                 | 1 |
| 7    | LV23058-001A  | SLIDER L        |                 | 1 |
| 8    | LV3A179-002A  | TRIGGER ARM     |                 | 1 |
| 9    | LV3A173-001A  | JOINT LEVER     |                 | 1 |
| 10   | LV23055-003A  | ROLLER LEVER    |                 | 1 |
| 12   | LV3A181-002A  | TRANSFER ARM    |                 | 1 |
| 13   | LV45797-002A  | SL LOCK CAM     |                 | 1 |
| 14   | LV3A182-003A  | SL LOCK ARM     |                 | 1 |
| 15   | LV3A183-001A  | PICK LOCK ARM   |                 | 1 |
| 18   | LV3A187-002A  | HELICAL GEAR 1  |                 | 1 |
| 19   | LV3A188-001A  | TRANSFER GEAR   |                 | 1 |
| 20   | LV3A189-001A  | LOAD GEAR H     |                 | 1 |
| 21   | LV3A190-001A  | DRIVE GEAR      |                 | 1 |
| 22   | LV3A191-001A  | JOINT GEAR      |                 | 1 |
| 23   | LV3A192-001A  | WORM GEAR 2     |                 | 1 |
| 24   | LV3A193-001A  | HELICAL GEAR 2  |                 | 1 |
| 25   | LV3A194-001A  | LOAD GEAR V     |                 | 1 |
| 26   | LV3A195-001A  | PICK GEAR 1     |                 | 1 |
| 27   | LV3A196-001A  | PICK GEAR 2     |                 | 1 |
| 28   | LV3A197-001A  | RACK GEAR       |                 | 1 |
| 32   | LV45796-001A  | R.RETAINER L    |                 | 1 |
| 33   | D3K-0002-00   | DAMPER          |                 | 2 |
| 38   | LV45809-001A  | FLOAT SPRING(F) |                 | 2 |
| 39   | LV45810-001A  | TRIGGER SPRING  |                 | 1 |
| 40   | LV45811-001A  | LOAD SPRING     |                 | 1 |
| 41   | LV45812-001A  | ROLLER SPRING   |                 | 1 |
| 42   | LV45813-002A  | CLAMP SPRING    |                 | 1 |
| 43   | LV45814-001A  | PICK SPRING     |                 | 1 |
| 44   | LV36813-302A  | SUB GUIDE CAP   |                 | 1 |
| 46   | D2B-0037-00   | SHAFT           |                 | 1 |
| 49   | LV11881-002A  | GEAR HOLDER     |                 | 1 |
| 50   | LV11880-004A  | DISC GUIDE      |                 | 1 |
| 54   | CM-FC2-R      | ROLLER ASSY     |                 | 1 |
| 55   | D1A-0100-00   | ARM             |                 | 1 |
| 56   | G0A-0138-00   | EXTEN.SPRING    |                 | 1 |
| 57   | D3K-0003-00   | DAMPER          |                 | 1 |
| 58   | LV45835-001A  | FLOAT SPRING(R) |                 | 2 |
| 60   | LV3A271-002A  | CL BASE ASSY    |                 | 1 |
| 811  | -----         | CLAMP ARM       | NO SERVICE PART | 1 |
| 816  | -----         | ROLLER GEAR     | NO SERVICE PART | 1 |
| 817  | -----         | WORM GEAR 1     | NO SERVICE PART | 1 |
| 829  | -----         | ROLLER          | NO SERVICE PART | 2 |
| 830  | -----         | ROLLER SHAFT    | NO SERVICE PART | 1 |
| 831  | -----         | R.RETAINER R    | NO SERVICE PART | 1 |
| 834  | -----         | SIN TWIST WIRE  | NO SERVICE PART | 1 |
| 835  | -----         | SIN TWIST WIRE  | NO SERVICE PART | 1 |
| 836  | -----         | SIN TWIST WIRE  | NO SERVICE PART | 2 |
| 845  | -----         | HC TURN TABLE   | NO SERVICE PART | 1 |
| 847  | -----         | CLAMPER         | NO SERVICE PART | 1 |
| 848  | -----         | WIRE HOLDER     | NO SERVICE PART | 1 |
| 851  | -----         | MD CHASSIS ASSY | NO SERVICE PART | 1 |
| 852  | -----         | SPINDLE MOTOR   | NO SERVICE PART | 1 |
| 853  | -----         | CD MECHA PWB    | NO SERVICE PART | 1 |
| 859  | -----         | MOTOR           | NO SERVICE PART | 1 |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe                              | Symbol No. | Parts No.     | Parts Name      | Description  | QTY | Local |
|-----------------------------------|------------|---------------|-----------------|--------------|-----|-------|
| MAIN PWB ASSY (XJ1-296x-0x) <XJ1> |            |               |                 |              |     |       |
|                                   | IC161      | BD37069FV-M   | ANALOG IC       |              | 1   |       |
|                                   | IC162      | NJM111100F1   | ANALOG IC       |              | 1   |       |
|                                   | IC164      | NJM111100F1   | ANALOG IC       |              | 1   | M1    |
|                                   | IC165      | NJW4190R-A    | ANALOG IC       |              | 1   | K0    |
|                                   | IC220      | NJM8065V      | ANALOG IC       |              | 1   |       |
|                                   | IC301      | JCV8034       | ANALOG IC       |              | 1   |       |
|                                   | IC411      | MFI343S00177  | MCU IC          |              | 1   |       |
|                                   | IC470      | TC7SH08FUJC   | MOS IC          |              | 1   | K2,K0 |
|                                   | IC540      | MP9943AGQ     | ANALOG IC       |              | 1   |       |
|                                   | IC601      | TEF6657HNV101 | ANALOG IC       |              | 1   |       |
|                                   | IC701      | STA1080       | MPU IC          | BGA          | 1   |       |
|                                   | IC702      | TC7SH08FUJC   | MOS IC          |              | 1   |       |
|                                   | IC821      | W3F-0485-00   | ROM IC          |              | 1   |       |
|                                   | IC822      | W25Q16JVSIM   | ROM IC          |              | 1   |       |
|                                   | IC831      | IC-PST8428U   | MOS IC          |              | 1   |       |
|                                   | IC841      | IC-PST8428U   | MOS IC          |              | 1   |       |
|                                   | IC890      | TPS25221DBV   | MOS IC          |              | 1   |       |
|                                   | IC901      | BD49105RFS-M  | ANALOG IC       |              | 1   |       |
|                                   | IC1901     | M12L2511A6BIS | DRAM IC         |              | 1   |       |
|                                   | Q220       | LSCR523UBFS8  | TRANSISTOR      |              | 1   |       |
|                                   | Q240       | IMX9          | DUAL TRANSISTOR |              | 1   |       |
|                                   | Q270       | LTA024EEBFS8  | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q271       | LSAR523UBFS8  | TRANSISTOR      |              | 1   |       |
|                                   | Q272       | LTC024EEBFS8  | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q273       | LTA024EEBFS8  | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q274       | LTC024EEBFS8  | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q300       | IMX9          | DUAL TRANSISTOR |              | 1   |       |
|                                   | Q310       | IMX9          | DUAL TRANSISTOR |              | 1   |       |
|                                   | Q470       | LTC014EEBFS8  | DIGI TRANSISTOR |              | 1   | K2,K0 |
|                                   | Q471       | LTC043TEBFS8  | DIGI TRANSISTOR |              | 1   | K2,K0 |
|                                   | Q500       | LTC043EUBFS8  | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q780       | RE1C002ZP     | FET             |              | 1   | M1,K1 |
|                                   | Q781       | RE1C002ZP     | FET             |              | 1   | M1,K1 |
|                                   | Q782       | KRC407E-P     | DIGI TRANSISTOR |              | 1   | M1,K1 |
|                                   | Q903       | KRC407E-P     | DIGI TRANSISTOR |              | 1   |       |
|                                   | Q904       | RE1C002ZP     | FET             |              | 1   |       |
|                                   | Q920       | KRA307E-P     | TRANSISTOR      |              | 1   |       |
|                                   | D220       | UDZV6.8B      | ZENER DIODE     |              | 1   |       |
|                                   | D221       | UDZV6.8B      | ZENER DIODE     |              | 1   |       |
|                                   | D222       | UDZV5.6B      | ZENER DIODE     |              | 1   |       |
|                                   | D271       | BAW56-TP      | DIODE ARRAY     |              | 1   |       |
|                                   | D273       | 1SS355-HF     | DIODE           |              | 1   |       |
|                                   | D370       | BAW56-TP      | DIODE ARRAY     |              | 1   |       |
|                                   | D390       | SM5818PL      | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D391       | MBR0530       | DIODE           |              | 1   |       |
|                                   | D400       | RB521SM-30    | DIODE           |              | 1   |       |
|                                   | D401       | UDZV5.1B      | ZENER DIODE     |              | 1   |       |
|                                   | D471       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D472       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D473       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D474       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D475       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D476       | RSB6.8SM      | ZENER DIODE     |              | 1   | K2,K0 |
|                                   | D540       | SMD24PL       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D783       | DAN202UM      | DIODE           |              | 1   | M1,K1 |
|                                   | D902       | SK34A-L       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D903       | SK34A-L       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D904       | GS1J-LTP      | DIODE           |              | 1   |       |
|                                   | D905       | GS1J-LTP      | DIODE           |              | 1   |       |
|                                   | D906       | SK34A-L       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D907       | SK34A-L       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D908       | SK34A-L       | SCHOTTKY DIODE  |              | 1   |       |
|                                   | D991       | GN3XB         | DIODE           |              | 1   |       |
|                                   | C101       | CK73JXR1H332K | C CAPACITOR     | 3300pF 50V K | 1   |       |
|                                   | C102       | CK73JXR1H332K | C CAPACITOR     | 3300pF 50V K | 1   |       |
|                                   | C103       | CK73GXR1C475K | C CAPACITOR     | 4.7uF 16V K  | 1   |       |
|                                   | C104       | CK73FXR1C106K | C CAPACITOR     | 10uF 16V K   | 1   |       |
|                                   | C105       | CK73GXR1C475K | C CAPACITOR     | 4.7uF 16V K  | 1   |       |
|                                   | C106       | CK73HXR1A105K | C CAPACITOR     | 1uF 10V K    | 1   |       |
|                                   | C161       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C162       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C163       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C164       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C165       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C166       | CE32BJ1V4R7M  | E CAPACITOR     | 4.7uF 35V M  | 1   |       |
|                                   | C167       | CK73GXR1C475K | C CAPACITOR     | 4.7uF 16V K  | 1   |       |
|                                   | C168       | CK73GXR1C475K | C CAPACITOR     | 4.7uF 16V K  | 1   |       |
|                                   | C169       | CE32BY1C470M  | E CAPACITOR     | 47uF 16V M   | 1   |       |
|                                   | C170       | CE32CL1C100M  | E CAPACITOR     | 10uF 16V M   | 1   |       |
|                                   | C171       | CE32CL1E330M  | E CAPACITOR     | 33uF 25V M   | 1   | M1    |
|                                   | C171       | CE32BM1E470M  | E CAPACITOR     | 47uF 25V M   | 1   | K0    |
|                                   | C175       | CK73JXR1H103K | C CAPACITOR     | 0.01uF 50V K | 1   |       |
|                                   | C177       | CK73GXR1A106K | C CAPACITOR     | 10uF 10V K   | 1   |       |
|                                   | C181       | CK73FXR1C106K | C CAPACITOR     | 10uF 16V K   | 1   | K0    |
|                                   | C183       | CK73GXR1C105K | C CAPACITOR     | 1uF 16V K    | 1   | K0    |
|                                   | C187       | CK73HXR1C105K | C CAPACITOR     | 1uF 16V K    | 1   | K0    |
|                                   | C188       | CK73GXR1E105K | C CAPACITOR     | 1uF 25V K    | 1   | K0    |
|                                   | C189       | CK73HXR1H104K | C CAPACITOR     | 0.1uF 50V K  | 1   | M1    |
|                                   | C190       | CK73JXR1H103K | C CAPACITOR     | 0.01uF 50V K | 1   | M1    |
|                                   | C191       | CC73JCH1H101J | C CAPACITOR     | 100pF 50V J  | 1   | M1    |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.     | Parts Name  | Description    | QTY | Local                            |
|------|------------|---------------|-------------|----------------|-----|----------------------------------|
|      | C192       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   | M1                               |
|      | C221       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C222       | CK73JXR0J333K | C CAPACITOR | 0.033uF 6.3V K | 1   |                                  |
|      | C223       | CK73JXR0J333K | C CAPACITOR | 0.033uF 6.3V K | 1   |                                  |
|      | C224       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C225       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C226       | CC73JCH1H220J | C CAPACITOR | 22pF 50V J     | 1   |                                  |
|      | C227       | CC73JCH1H151J | C CAPACITOR | 150pF 50V J    | 1   |                                  |
|      | C228       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C229       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C230       | CK73GXR1A105K | C CAPACITOR | 1uF 10V K      | 1   | E1                               |
|      | C231       | CC73JCH1H151J | C CAPACITOR | 150pF 50V J    | 1   |                                  |
|      | C234       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C235       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C236       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C252       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C262       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C273       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C304       | CE32CL1E330M  | E CAPACITOR | 33uF 25V M     | 1   |                                  |
|      | C311       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C312       | CK73GXR1C105K | C CAPACITOR | 1uF 16V K      | 1   |                                  |
|      | C316       | CK73GXR1C224K | C CAPACITOR | 0.22uF 16V K   | 1   |                                  |
|      | C317       | CK73GXR1C224K | C CAPACITOR | 0.22uF 16V K   | 1   |                                  |
|      | C318       | CK73GXR1C224K | C CAPACITOR | 0.22uF 16V K   | 1   |                                  |
|      | C319       | CK73GXR1C224K | C CAPACITOR | 0.22uF 16V K   | 1   |                                  |
|      | C322       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C324       | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K    | 1   |                                  |
|      | C332       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C342       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C352       | CK73EXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   | K2,M1,K1,K3,K0<br>K2,M1,K1,K3,K0 |
|      | C370       | CK73HXR1H104K | C CAPACITOR | 0.1uF 50V K    | 1   | K2,K0<br>K2,K0<br>K2,K0          |
|      | C391       | CK73HXR1C105K | C CAPACITOR | 1uF 16V K      | 1   |                                  |
|      | C410       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |                                  |
|      | C411       | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K   | 1   |                                  |
|      | C472       | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K    | 1   |                                  |
|      | C473       | CK73FXR1C106K | C CAPACITOR | 10uF 16V K     | 1   |                                  |
|      | C474       | CK73GXR1C225K | C CAPACITOR | 2.2uF 16V K    | 1   |                                  |
|      | C475       | CK73GXR1C225K | C CAPACITOR | 2.2uF 16V K    | 1   |                                  |
|      | C540       | CE32CC1A151M  | E CAPACITOR | 150uF 10V M    | 1   |                                  |
|      | C542       | CK73JXR1C224K | C CAPACITOR | 0.22uF 16V K   | 1   |                                  |
|      | C543       | CK73HXR1C105K | C CAPACITOR | 1uF 16V K      | 1   |                                  |
|      | C544       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |                                  |
|      | C545       | CK73FXR1C106K | C CAPACITOR | 10uF 16V K     | 1   |                                  |
|      | C547       | CK73HXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |                                  |
|      | C548       | CK73HXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |                                  |
|      | C549       | CK73HXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |                                  |
|      | C550       | CC73JCH1H150J | C CAPACITOR | 15pF 50V J     | 1   |                                  |
|      | C601       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |                                  |
|      | C602       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |                                  |
|      | C603       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |                                  |
|      | C604       | CK73GBB1H152K | C CAPACITOR | 1500pF 50V K   | 1   | K2,K0<br>K2,K0<br>K2,K0          |
|      | C605       | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K   | 1   |                                  |
|      | C606       | CC73JCH1H090D | C CAPACITOR | 9pF 50V D      | 1   |                                  |
|      | C607       | CC73JCH1H010C | C CAPACITOR | 1pF 50V C      | 1   |                                  |
|      | C608       | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K   | 1   |                                  |
|      | C609       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |                                  |
|      | C610       | CC73JCH1H120J | C CAPACITOR | 12pF 50V J     | 1   |                                  |
|      | C611       | CC73JCH1H010C | C CAPACITOR | 1pF 50V C      | 1   |                                  |
|      | C612       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |                                  |
|      | C614       | CC73JCH1H220J | C CAPACITOR | 22pF 50V J     | 1   |                                  |
|      | C615       | CC73JCH1H330J | C CAPACITOR | 33pF 50V J     | 1   |                                  |
|      | C616       | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K   | 1   |                                  |
|      | C617       | CK73JXR0J474K | C CAPACITOR | 0.47uF 6.3V K  | 1   |                                  |
|      | C618       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |                                  |
|      | C619       | CK73GXR1H104K | C CAPACITOR | 0.1uF 50V K    | 1   |                                  |
|      | C620       | CK73GXR1E105K | C CAPACITOR | 1uF 25V K      | 1   |                                  |
|      | C621       | CK73GXR1E105K | C CAPACITOR | 1uF 25V K      | 1   |                                  |
|      | C624       | CK73GXR1C225K | C CAPACITOR | 2.2uF 16V K    | 1   |                                  |
|      | C680       | CK73GXR0J225K | C CAPACITOR | 2.2uF 6.3V K   | 1   |                                  |
|      | C701       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |                                  |
|      | C702       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   | K2,K0<br>K2,K0<br>K2,K0          |
|      | C703       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |                                  |
|      | C704       | CC73JCH1H180J | C CAPACITOR | 18pF 50V J     | 1   |                                  |
|      | C705       | CC73JCH1H180J | C CAPACITOR | 18pF 50V J     | 1   |                                  |
|      | C706       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |                                  |
|      | C707       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |                                  |
|      | C708       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |                                  |
|      | C710       | CK73JXR1H222K | C CAPACITOR | 2200pF 50V K   | 1   |                                  |
|      | C711       | CC73JCH1H100D | C CAPACITOR | 10pF 50V D     | 1   |                                  |
|      | C713       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C714       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |                                  |
|      | C715       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |                                  |
|      | C716       | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K   | 1   |                                  |
|      | C717       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |                                  |
|      | C718       | CC73JCH1H470J | C CAPACITOR | 47pF 50V J     | 1   |                                  |
|      | C719       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |
|      | C720       | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |                                  |
|      | C721       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |                                  |
|      | C722       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |                                  |
|      | C723       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |                                  |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.     | Parts Name  | Description    | QTY | Local |
|------|------------|---------------|-------------|----------------|-----|-------|
|      | C724       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |       |
|      | C725       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C726       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |       |
|      | C727       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C728       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |       |
|      | C729       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C730       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |       |
|      | C731       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C733       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C735       | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K   | 1   |       |
|      | C736       | CC73JCH1H070D | C CAPACITOR | 7pF 50V D      | 1   |       |
|      | C737       | CC73JCH1H080D | C CAPACITOR | 8pF 50V D      | 1   |       |
|      | C738       | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K   | 1   |       |
|      | C740       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |       |
|      | C741       | CC73JCH1H100D | C CAPACITOR | 10pF 50V D     | 1   |       |
|      | C742       | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |       |
|      | C745       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C746       | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |       |
|      | C750       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C756       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C760       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C780       | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K   | 1   | M1,K1 |
|      | C781       | CK73GBB1H102K | C CAPACITOR | 1000pF 50V K   | 1   | M1,K1 |
|      | C782       | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   | M1,K1 |
|      | C820       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C821       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C824       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C830       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C831       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C832       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C841       | CK73HXR1A334K | C CAPACITOR | 0.33uF 10V K   | 1   |       |
|      | C842       | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C843       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C890       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C891       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C902       | CC73JCH1E391J | C CAPACITOR | 390pF 25V J    | 1   |       |
|      | C903       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C904       | CC73JCH1E271J | C CAPACITOR | 270pF 25V J    | 1   |       |
|      | C905       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C906       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C907       | CE32CC1A151M  | E CAPACITOR | 150uF 10V M    | 1   |       |
|      | C911       | CK73GXR1E105K | C CAPACITOR | 1uF 25V K      | 1   |       |
|      | C912       | CK73EXR1E106K | C CAPACITOR | 10uF 25V K     | 1   |       |
|      | C913       | CK73EXR1E106K | C CAPACITOR | 10uF 25V K     | 1   |       |
|      | C914       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C915       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C916       | CE32BY1C221M  | E CAPACITOR | 220uF 16V M    | 1   |       |
|      | C917       | CK73GXR1E105K | C CAPACITOR | 1uF 25V K      | 1   |       |
|      | C918       | CC73JCH1E391J | C CAPACITOR | 390pF 25V J    | 1   |       |
|      | C935       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C943       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C944       | CE32CC1A151M  | E CAPACITOR | 150uF 10V M    | 1   |       |
|      | C945       | CC73JCH1E561J | C CAPACITOR | 560pF 25V J    | 1   |       |
|      | C946       | CK73GXR1E105K | C CAPACITOR | 1uF 25V K      | 1   |       |
|      | C947       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C948       | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C949       | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K   | 1   |       |
|      | C950       | CK73GXR1C475K | C CAPACITOR | 4.7uF 16V K    | 1   |       |
|      | C952       | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C954       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C960       | CK73HXR1C105K | C CAPACITOR | 1uF 16V K      | 1   |       |
|      | C992       | CD04ET1C222M1 | E CAPACITOR | 2200uF 16V M   | 1   |       |
|      | C993       | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C994       | CD04EU1C222M1 | E CAPACITOR | 2200uF 16V M   | 1   |       |
|      | C1020      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1301      | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C1305      | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C1306      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1600      | CK73JXR0J153K | C CAPACITOR | 0.015uF 6.3V K | 1   |       |
|      | C1602      | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C1603      | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C1902      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1903      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C1904      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1905      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1906      | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C1907      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1908      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1909      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C1910      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K    | 1   |       |
|      | C2002      | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K    | 1   |       |
|      | C2008      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |       |
|      | C2010      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K    | 1   |       |
|      | C2025      | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C2027      | CK73GXR1A106K | C CAPACITOR | 10uF 10V K     | 1   |       |
|      | C2037      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K   | 1   |       |
|      | C2040      | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C2041      | CC73JCH1H101J | C CAPACITOR | 100pF 50V J    | 1   |       |
|      | C2048      | CK73HXR0J474K | C CAPACITOR | 0.47uF 6.3V K  | 1   |       |
|      | C2050      | CK73HXR1A105K | C CAPACITOR | 1uF 10V K      | 1   |       |
|      | C2051      | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |
|      | C2052      | CK73JXR0J224K | C CAPACITOR | 0.22uF 6.3V K  | 1   |       |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.     | Parts Name  | Description   | QTY | Local          |
|------|------------|---------------|-------------|---------------|-----|----------------|
|      | C2084      | CK73HXR1H104K | C CAPACITOR | 0.1uF 50V K   | 1   |                |
|      | C2117      | CC73JCH1H101J | C CAPACITOR | 100pF 50V J   | 1   |                |
|      | C9003      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   | K2,K0          |
|      | C9015      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9020      | CK73JXR1A104K | C CAPACITOR | 0.1uF 10V K   | 1   | E1             |
|      | C9021      | CC73JCH1H101J | C CAPACITOR | 100pF 50V J   | 1   |                |
|      | C9022      | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K  | 1   |                |
|      | C9023      | CK73GXR1H104K | C CAPACITOR | 0.1uF 50V K   | 1   | E1             |
|      | C9025      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9026      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9027      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9028      | CK73JXR0J104K | C CAPACITOR | 0.1uF 6.3V K  | 1   | E1             |
|      | C9030      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9037      | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K  | 1   |                |
|      | C9038      | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K   | 1   |                |
|      | C9039      | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K   | 1   |                |
|      | C9040      | CK73JXR1H222K | C CAPACITOR | 2200pF 50V K  | 1   | E1             |
|      | C9045      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9049      | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K  | 1   |                |
|      | C9050      | CK73JXR1H472K | C CAPACITOR | 4700pF 50V K  | 1   |                |
|      | C9053      | CK73JXR1H102K | C CAPACITOR | 1000pF 50V K  | 1   |                |
|      | C9054      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9062      | CK73JXR1H222K | C CAPACITOR | 2200pF 50V K  | 1   | E1             |
|      | C9064      | CK73JXR1H222K | C CAPACITOR | 2200pF 50V K  | 1   | E1             |
|      | C9067      | CK73JXR1H222K | C CAPACITOR | 2200pF 50V K  | 1   | E1             |
|      | C9085      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9086      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9087      | CK73JXR1H103K | C CAPACITOR | 0.01uF 50V K  | 1   |                |
|      | C9101      | CK73JXR1E104K | C CAPACITOR | 0.1uF 25V K   | 1   |                |
|      | C9103      | CC73JCH1H220J | C CAPACITOR | 22pF 50V J    | 1   |                |
|      | C9117      | CK73GXR1A106K | C CAPACITOR | 10uF 10V K    | 1   |                |
|      | C9118      | CK73GXR1A106K | C CAPACITOR | 10uF 10V K    | 1   |                |
|      | C9120      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9130      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9131      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9132      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9201      | CC73JCH1H050C | C CAPACITOR | 5pF 50V C     | 1   |                |
|      | C9202      | CC73JCH1H050C | C CAPACITOR | 5pF 50V C     | 1   |                |
|      | C9203      | CC73JCH1H050C | C CAPACITOR | 5pF 50V C     | 1   |                |
|      | C9204      | CC73JCH1H070D | C CAPACITOR | 7pF 50V D     | 1   |                |
|      | C9205      | CC73JCH1H070D | C CAPACITOR | 7pF 50V D     | 1   |                |
|      | C9518      | CK73JXR1H471K | C CAPACITOR | 470pF 50V K   | 1   |                |
|      | C9527      | CK73EXR1E106K | C CAPACITOR | 10uF 25V K    | 1   |                |
|      | R100       | RK73HB1J471J  | MG RESISTOR | 470Ω 1/16W J  | 1   |                |
|      | R101       | RK73HB1J000J  | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R103       | RK73HB1J473J  | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R104       | RK73HB1J473J  | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R118       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R119       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R120       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R145       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R146       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R147       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R148       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R149       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R150       | RK73HB1J680J  | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R160       | RK73HB1J000J  | MG RESISTOR | 0Ω 1/16W J    | 1   | M1             |
|      | R161       | RK73HB1J000J  | MG RESISTOR | 0Ω 1/16W J    | 1   | M1,K0          |
|      | R162       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R165       | RK73HH1J152D  | MG RESISTOR | 1.5kΩ 1/16W D | 1   |                |
|      | R166       | RK73HH1J822D  | MG RESISTOR | 8.2kΩ 1/16W D | 1   |                |
|      | R173       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R175       | RK73GB2A000J  | MG RESISTOR | 0Ω 1/10W J    | 1   | K2,E1,K1,K3,K0 |
|      | R176       | RK73GB2A000J  | MG RESISTOR | 0Ω 1/10W J    | 1   | K0             |
|      | R177       | RK73HB1J562J  | MG RESISTOR | 5.6kΩ 1/16W J | 1   | K0             |
|      | R178       | RK73HB1J752J  | MG RESISTOR | 7.5kΩ 1/16W J | 1   | K0             |
|      | R179       | RK73HH1J102D  | MG RESISTOR | 1kΩ 1/16W D   | 1   | K0             |
|      | R180       | RK73HH1J153D  | MG RESISTOR | 15kΩ 1/16W D  | 1   | K0             |
|      | R181       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   | K0             |
|      | R182       | RK73HH1J752D  | MG RESISTOR | 7.5kΩ 1/16W D | 1   | M1             |
|      | R183       | RK73HH1J132D  | MG RESISTOR | 1.3kΩ 1/16W D | 1   | M1             |
|      | R188       | RK73GB2A000J  | MG RESISTOR | 0Ω 1/10W J    | 1   | K2,E1,M1,K1,K3 |
|      | R220       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R221       | RK73HB1J101J  | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R222       | RK73HB1J000J  | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R223       | RK73HB1J822J  | MG RESISTOR | 8.2kΩ 1/16W J | 1   |                |
|      | R224       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R225       | RK73HB1J333J  | MG RESISTOR | 33kΩ 1/16W J  | 1   |                |
|      | R226       | RK73HB1J122J  | MG RESISTOR | 1.2kΩ 1/16W J | 1   |                |
|      | R227       | RK73HB1J124J  | MG RESISTOR | 120kΩ 1/16W J | 1   |                |
|      | R229       | RK73HB1J122J  | MG RESISTOR | 1.2kΩ 1/16W J | 1   |                |
|      | R230       | RK73HB1J124J  | MG RESISTOR | 120kΩ 1/16W J | 1   |                |
|      | R231       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R232       | RK73GB2A103J  | MG RESISTOR | 10kΩ 1/10W J  | 1   |                |
|      | R233       | RK73HB1J681J  | MG RESISTOR | 680Ω 1/16W J  | 1   |                |
|      | R234       | RK73HB1J222J  | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R235       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R236       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R237       | RK73HB1J471J  | MG RESISTOR | 470Ω 1/16W J  | 1   |                |
|      | R238       | RK73HB1J103J  | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.    | Parts Name  | Description   | QTY | Local          |
|------|------------|--------------|-------------|---------------|-----|----------------|
|      | R250       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   |                |
|      | R251       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   |                |
|      | R252       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   |                |
|      | R253       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   | K2,M1,K1,K3,K0 |
|      | R254       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R260       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   | E1             |
|      | R261       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | E1             |
|      | R262       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   | E1             |
|      | R264       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   | E1             |
|      | R270       | RK73GB2A104J | MG RESISTOR | 100kΩ 1/10W J | 1   |                |
|      | R271       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   |                |
|      | R272       | RK73HB1J303J | MG RESISTOR | 30kΩ 1/16W J  | 1   |                |
|      | R273       | RK73GB2A223J | MG RESISTOR | 22kΩ 1/10W J  | 1   |                |
|      | R274       | RK73HB1J332J | MG RESISTOR | 3.3kΩ 1/16W J | 1   |                |
|      | R302       | RK73HB1J432J | MG RESISTOR | 4.3kΩ 1/16W J | 1   |                |
|      | R303       | RK73EB2E160J | MG RESISTOR | 16Ω 1/4W J    | 1   |                |
|      | R304       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R305       | RK73EB2E1R0J | MG RESISTOR | 1.0Ω 1/4W J   | 1   |                |
|      | R316       | RK73HB1J680J | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R317       | RK73HB1J680J | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R318       | RK73HB1J680J | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R319       | RK73HB1J680J | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R320       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   |                |
|      | R321       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   |                |
|      | R322       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R323       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   |                |
|      | R330       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   |                |
|      | R331       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   |                |
|      | R332       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R333       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   |                |
|      | R340       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R341       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R342       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   | K2,M1,K1,K3,K0 |
|      | R343       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R350       | RK73HB1J181J | MG RESISTOR | 180Ω 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R351       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R352       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   | K2,M1,K1,K3,K0 |
|      | R353       | RK73HB1J331J | MG RESISTOR | 330Ω 1/16W J  | 1   | K2,M1,K1,K3,K0 |
|      | R370       | RK73GB2A683J | MG RESISTOR | 68kΩ 1/10W J  | 1   |                |
|      | R371       | RK73GB2A123J | MG RESISTOR | 12kΩ 1/10W J  | 1   |                |
|      | R372       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R373       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R390       | RK73EB2E472J | MG RESISTOR | 4.7kΩ 1/4W J  | 1   |                |
|      | R400       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R410       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R411       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R413       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R414       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R468       | RK73GB2A100J | MG RESISTOR | 10Ω 1/10W J   | 1   | K2,K0          |
|      | R469       | RK73GB2A4R7J | MG RESISTOR | 4.7Ω 1/10W J  | 1   | K2,K0          |
|      | R470       | RK73GB2A100J | MG RESISTOR | 10Ω 1/10W J   | 1   | K2,K0          |
|      | R471       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   | K2,K0          |
|      | R472       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   | K2,K0          |
|      | R473       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   | K2,K0          |
|      | R474       | RK73FB2B221J | MG RESISTOR | 220Ω 1/8W J   | 1   | K2,K0          |
|      | R475       | RK73HB1J100J | MG RESISTOR | 10Ω 1/16W J   | 1   | K2,K0          |
|      | R476       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | K2,K0          |
|      | R477       | RK73HB1J104J | MG RESISTOR | 100kΩ 1/16W J | 1   | K2,K0          |
|      | R541       | RK73HB1J512J | MG RESISTOR | 5.1kΩ 1/16W J | 1   |                |
|      | R542       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R543       | RK73EB2E200J | MG RESISTOR | 20Ω 1/4W J    | 1   |                |
|      | R544       | RK73HB1J393J | MG RESISTOR | 39kΩ 1/16W J  | 1   |                |
|      | R545       | RK73HH1J183D | MG RESISTOR | 18kΩ 1/16W D  | 1   |                |
|      | R546       | RK73HH1J393D | MG RESISTOR | 39kΩ 1/16W D  | 1   |                |
|      | R548       | RK73HH1J683D | MG RESISTOR | 68kΩ 1/16W D  | 1   |                |
|      | R549       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R600       | RK73GB2A102J | MG RESISTOR | 1kΩ 1/10W J   | 1   |                |
|      | R602       | RK73GB2A820J | MG RESISTOR | 82Ω 1/10W J   | 1   |                |
|      | R603       | RK73HB1J105J | MG RESISTOR | 1MΩ 1/16W J   | 1   |                |
|      | R604       | RK73HB1J105J | MG RESISTOR | 1MΩ 1/16W J   | 1   |                |
|      | R605       | RK73HB1J4R7J | MG RESISTOR | 4.7Ω 1/16W J  | 1   |                |
|      | R606       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R607       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R682       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R683       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R684       | RK73HB1J392J | MG RESISTOR | 3.9kΩ 1/16W J | 1   |                |
|      | R685       | RK73HB1J392J | MG RESISTOR | 3.9kΩ 1/16W J | 1   |                |
|      | R702       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R703       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R704       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R705       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R706       | RK73HB1J332J | MG RESISTOR | 3.3kΩ 1/16W J | 1   |                |
|      | R707       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R709       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R710       | RK73HB1J682J | MG RESISTOR | 6.8kΩ 1/16W J | 1   |                |
|      | R711       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R712       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R715       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R718       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R721       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R722       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R723       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.    | Parts Name  | Description   | QTY | Local          |
|------|------------|--------------|-------------|---------------|-----|----------------|
|      | R725       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R730       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R731       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R733       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R734       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R735       | RK73HB1J273J | MG RESISTOR | 27kΩ 1/16W J  | 1   |                |
|      | R737       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R738       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R739       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R740       | RK73HB1J472J | MG RESISTOR | 4.7kΩ 1/16W J | 1   |                |
|      | R741       | RK73GB2A473J | MG RESISTOR | 47kΩ 1/10W J  | 1   |                |
|      | R742       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R743       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R744       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R746       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R748       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R750       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R753       | RK73HB1J273J | MG RESISTOR | 27kΩ 1/16W J  | 1   |                |
|      | R755       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R756       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R760       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R761       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R762       | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |                |
|      | R763       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R766       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R768       | RK73HB1J393J | MG RESISTOR | 39kΩ 1/16W J  | 1   | E1             |
|      | R768       | RK73HB1J333J | MG RESISTOR | 33kΩ 1/16W J  | 1   | M1             |
|      | R769       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   | K2,K1,K3,K0    |
|      | R769       | RK73HB1J822J | MG RESISTOR | 8.2kΩ 1/16W J | 1   | E1             |
|      | R769       | RK73HB1J153J | MG RESISTOR | 15kΩ 1/16W J  | 1   | M1             |
|      | R770       | RK73HB1J153J | MG RESISTOR | 15kΩ 1/16W J  | 1   | K2             |
|      | R770       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | K1             |
|      | R770       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   | K3             |
|      | R770       | RK73HB1J273J | MG RESISTOR | 27kΩ 1/16W J  | 1   | K0             |
|      | R771       | RK73HB1J333J | MG RESISTOR | 33kΩ 1/16W J  | 1   | K2             |
|      | R771       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   | E1,M1          |
|      | R771       | RK73HB1J273J | MG RESISTOR | 27kΩ 1/16W J  | 1   | K1             |
|      | R771       | RK73HB1J223J | MG RESISTOR | 22kΩ 1/16W J  | 1   | K0             |
|      | R772       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R775       | RK73HB1J152J | MG RESISTOR | 1.5kΩ 1/16W J | 1   | M1,K1          |
|      | R776       | RK73HB1J152J | MG RESISTOR | 1.5kΩ 1/16W J | 1   | M1,K1          |
|      | R777       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R778       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R779       | RK73HB1J470J | MG RESISTOR | 47Ω 1/16W J   | 1   | M1,K1          |
|      | R781       | RK73HB1J470J | MG RESISTOR | 47Ω 1/16W J   | 1   | M1,K1          |
|      | R782       | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |                |
|      | R783       | RK73HH1J472D | MG RESISTOR | 4.7kΩ 1/16W D | 1   | M1,K1          |
|      | R784       | RK73HH1J472D | MG RESISTOR | 4.7kΩ 1/16W D | 1   | M1,K1          |
|      | R785       | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |                |
|      | R786       | RK73GB2A681J | MG RESISTOR | 680Ω 1/10W J  | 1   | M1,K1          |
|      | R788       | RK73HH1J823D | MG RESISTOR | 82kΩ 1/16W D  | 1   |                |
|      | R789       | RK73HH1J393D | MG RESISTOR | 39kΩ 1/16W D  | 1   |                |
|      | R790       | RK73HB1J4R7J | MG RESISTOR | 4.7Ω 1/16W J  | 1   |                |
|      | R791       | RK73GB2A681J | MG RESISTOR | 680Ω 1/10W J  | 1   | M1,K1          |
|      | R792       | RK73HB1J4R7J | MG RESISTOR | 4.7Ω 1/16W J  | 1   |                |
|      | R793       | RK73HB1J273J | MG RESISTOR | 27kΩ 1/16W J  | 1   |                |
|      | R794       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R795       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R796       | RK73HH1J302D | MG RESISTOR | 3kΩ 1/16W D   | 1   |                |
|      | R797       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R798       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R799       | RK73HB1J105J | MG RESISTOR | 1MΩ 1/16W J   | 1   |                |
|      | R800       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R801       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R802       | RK73GB2A473J | MG RESISTOR | 47kΩ 1/10W J  | 1   | E1             |
|      | R803       | RK73HB1J225J | MG RESISTOR | 2.2MΩ 1/16W J | 1   | K2,M1,K1,K3,K0 |
|      | R804       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R805       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R806       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R808       | RK73HB1J680J | MG RESISTOR | 68Ω 1/16W J   | 1   |                |
|      | R809       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |                |
|      | R811       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R813       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |                |
|      | R814       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R815       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R819       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R820       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R823       | RK73HB1J470J | MG RESISTOR | 47Ω 1/16W J   | 1   |                |
|      | R824       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |                |
|      | R827       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R828       | RK73HB1J103J | MG RESISTOR | 10kΩ 1/16W J  | 1   |                |
|      | R829       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R831       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |                |
|      | R832       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |                |
|      | R833       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R834       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R835       | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |                |
|      | R836       | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |                |
|      | R837       | RK73HB1J511J | MG RESISTOR | 510Ω 1/16W J  | 1   | M1,K1          |
|      | R838       | RK73HB1J511J | MG RESISTOR | 510Ω 1/16W J  | 1   | M1,K1          |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.    | Parts Name  | Description   | QTY | Local       |
|------|------------|--------------|-------------|---------------|-----|-------------|
|      | R839       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   | M1,K1       |
|      | R840       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   | M1,K1       |
|      | R841       | RK73HB1J104J | MG RESISTOR | 100kΩ 1/16W J | 1   | M1,K1       |
|      | R842       | RK73HB1J104J | MG RESISTOR | 100kΩ 1/16W J | 1   | M1,K1       |
|      | R843       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   | M1,K1       |
|      | R844       | RK73HB1J332J | MG RESISTOR | 3.3kΩ 1/16W J | 1   |             |
|      | R845       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |             |
|      | R846       | RK73HB1J473J | MG RESISTOR | 47kΩ 1/16W J  | 1   |             |
|      | R870       | RK73HB1J562J | MG RESISTOR | 5.6kΩ 1/16W J | 1   |             |
|      | R889       | RK73HB1J332J | MG RESISTOR | 3.3kΩ 1/16W J | 1   |             |
|      | R891       | RK73HH1J243D | MG RESISTOR | 24kΩ 1/16W D  | 1   |             |
|      | R893       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |             |
|      | R903       | RK73HH1J394D | MG RESISTOR | 390kΩ 1/16W D | 1   | K2,E1,K1,K3 |
|      | R903       | RK73HH1J474D | MG RESISTOR | 470kΩ 1/16W D | 1   | M1          |
|      | R903       | RK73HH1J334D | MG RESISTOR | 330kΩ 1/16W D | 1   | K0          |
|      | R904       | RK73HH1J103D | MG RESISTOR | 10kΩ 1/16W D  | 1   | K2,E1,K1,K3 |
|      | R904       | RK73HH1J563D | MG RESISTOR | 56kΩ 1/16W D  | 1   | M1          |
|      | R904       | RK73HH1J473D | MG RESISTOR | 47kΩ 1/16W D  | 1   | K0          |
|      | R905       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |             |
|      | R908       | RK73HH1J154D | MG RESISTOR | 150kΩ 1/16W D | 1   |             |
|      | R909       | RK73HH1J473D | MG RESISTOR | 47kΩ 1/16W D  | 1   |             |
|      | R910       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |             |
|      | R911       | RK73HB1J683J | MG RESISTOR | 68kΩ 1/16W J  | 1   |             |
|      | R912       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |             |
|      | R913       | RK73HB1J101J | MG RESISTOR | 100Ω 1/16W J  | 1   |             |
|      | R917       | RK73HH1J393D | MG RESISTOR | 39kΩ 1/16W D  | 1   |             |
|      | R920       | RK73HH1J124D | MG RESISTOR | 120kΩ 1/16W D | 1   |             |
|      | R921       | RK73HH1J153D | MG RESISTOR | 15kΩ 1/16W D  | 1   |             |
|      | R922       | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |             |
|      | R923       | RK73HH1J564D | MG RESISTOR | 560kΩ 1/16W D | 1   |             |
|      | R924       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R925       | RK73HH1J184D | MG RESISTOR | 180kΩ 1/16W D | 1   |             |
|      | R927       | RK73GB2A103J | MG RESISTOR | 10kΩ 1/10W J  | 1   |             |
|      | R928       | RK73GB2A101J | MG RESISTOR | 100Ω 1/10W J  | 1   |             |
|      | R929       | RK73GB2A101J | MG RESISTOR | 100Ω 1/10W J  | 1   |             |
|      | R933       | RK73HH1J684D | MG RESISTOR | 680kΩ 1/16W D | 1   |             |
|      | R934       | RK73HH1J563D | MG RESISTOR | 56kΩ 1/16W D  | 1   |             |
|      | R939       | RK73HH1J433D | MG RESISTOR | 43kΩ 1/16W D  | 1   |             |
|      | R940       | RK73HH1J123D | MG RESISTOR | 12kΩ 1/16W D  | 1   |             |
|      | R941       | RK73HH1J393D | MG RESISTOR | 39kΩ 1/16W D  | 1   |             |
|      | R946       | RK73HB1J222J | MG RESISTOR | 2.2kΩ 1/16W J | 1   |             |
|      | R949       | RK73GB2A000J | MG RESISTOR | 0Ω 1/10W J    | 1   |             |
|      | R950       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R951       | RK73HB1J471J | MG RESISTOR | 470Ω 1/16W J  | 1   |             |
|      | R952       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R954       | RK73GB2A222J | MG RESISTOR | 2.2kΩ 1/10W J | 1   |             |
|      | R955       | RK73EB2E184J | MG RESISTOR | 180kΩ 1/4W J  | 1   |             |
|      | R961       | RK73HB1J153J | MG RESISTOR | 15kΩ 1/16W J  | 1   |             |
|      | R980       | RK73EB2E682J | MG RESISTOR | 6.8kΩ 1/4W J  | 1   |             |
|      | R981       | RK73EB2E682J | MG RESISTOR | 6.8kΩ 1/4W J  | 1   |             |
|      | R982       | RK73EB2E473J | MG RESISTOR | 47kΩ 1/4W J   | 1   |             |
|      | R984       | RK73EB2E473J | MG RESISTOR | 47kΩ 1/4W J   | 1   |             |
|      | R993       | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R1070      | RK73HB1J102J | MG RESISTOR | 1kΩ 1/16W J   | 1   |             |
|      | R1300      | RK73HB1J562J | MG RESISTOR | 5.6kΩ 1/16W J | 1   |             |
|      | R1302      | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |             |
|      | R1303      | RK73HB1J220J | MG RESISTOR | 22Ω 1/16W J   | 1   |             |
|      | R1900      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1901      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1902      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1903      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1904      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1905      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1906      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1907      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1908      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1909      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1910      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1911      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1912      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1913      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1914      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1915      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1920      | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R1921      | RK73HB1J470J | MG RESISTOR | 47Ω 1/16W J   | 1   |             |
|      | R1922      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1923      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1924      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1925      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1926      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1927      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1928      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1929      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1930      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1931      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1932      | RK73HB1J000J | MG RESISTOR | 0Ω 1/16W J    | 1   |             |
|      | R1933      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1934      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1935      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1936      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1937      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |
|      | R1938      | RK73HB1J330J | MG RESISTOR | 33Ω 1/16W J   | 1   |             |

| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
|----------|------|------------|------|------------|------|----------|------|
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.     | Parts Name      | Description   | QTY | Local          |
|------|------------|---------------|-----------------|---------------|-----|----------------|
|      | R1939      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R1940      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R1941      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R1942      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R1943      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R1944      | RK73HB1J330J  | MG RESISTOR     | 33Ω 1/16W J   | 1   |                |
|      | R2002      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2003      | RK73HB1J220J  | MG RESISTOR     | 22Ω 1/16W J   | 1   |                |
|      | R2004      | RK73HB1J220J  | MG RESISTOR     | 22Ω 1/16W J   | 1   |                |
|      | R2006      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2007      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   | K2,K0          |
|      | R2008      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2010      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2011      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2012      | RK73HB1J220J  | MG RESISTOR     | 22Ω 1/16W J   | 1   |                |
|      | R2013      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2014      | RK73HB1J103J  | MG RESISTOR     | 10kΩ 1/16W J  | 1   |                |
|      | R2016      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2017      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2018      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2019      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2021      | RK73HB1J220J  | MG RESISTOR     | 22Ω 1/16W J   | 1   |                |
|      | R2023      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2026      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R2029      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R2033      | RK73HB1J222J  | MG RESISTOR     | 2.2kΩ 1/16W J | 1   |                |
|      | R2034      | RK73HB1J222J  | MG RESISTOR     | 2.2kΩ 1/16W J | 1   |                |
|      | R7571      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R7581      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R7641      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R7651      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R9001      | RK73HB1J000J  | MG RESISTOR     | 0Ω 1/16W J    | 1   |                |
|      | R9006      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R9011      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R9019      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R9029      | RK73HB1J272J  | MG RESISTOR     | 2.7kΩ 1/16W J | 1   |                |
|      | R9030      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R9031      | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |                |
|      | R9201      | RK73HH1J100D  | MG RESISTOR     | 10Ω 1/16W D   | 1   |                |
|      | R9710      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R9711      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R9712      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | R9713      | RK73HB1J472J  | MG RESISTOR     | 4.7kΩ 1/16W J | 1   |                |
|      | L165       | LR73Z0AD100M  | CHIP INDUCTOR   |               | 1   | K0             |
|      | L411       | LR73Z0AD4R7M  | CHIP INDUCTOR   |               | 1   |                |
|      | L540       | LK73Z0CA4R7M  | M.CHIP INDUCTOR |               | 1   |                |
|      | L541       | LR79Z0JM100M  | CHIP INDUCTOR   |               | 1   |                |
|      | L600       | LR73Z0AD1R0M  | CHIP INDUCTOR   |               | 1   |                |
|      | L601       | LK73G0BE4R7K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L602       | LK73H0BUR47K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L603       | LK73H0BUR10K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L604       | LK73H0BU1R0K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L605       | LK73H0BUR22K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L606       | LK73H0BUR12K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L607       | LK73H0BUR15K  | M.CHIP INDUCTOR |               | 1   |                |
|      | L691       | LR73Z0AD1R0M  | CHIP INDUCTOR   |               | 1   |                |
|      | L701       | LR73Z0AD4R7M  | CHIP INDUCTOR   |               | 1   |                |
|      | L702       | LB73H0AY-004  | CHIP FERRITE    |               | 1   |                |
|      | L706       | LB73H0AY-004  | CHIP FERRITE    |               | 1   | K2,K0          |
|      | L707       | LB73H0AY-004  | CHIP FERRITE    |               | 1   | K2,K0          |
|      | L708       | LB73H0CT-002  | CHIP FERRITE    |               | 1   |                |
|      | L709       | LB73H0AY-004  | CHIP FERRITE    |               | 1   |                |
|      | L821       | LB73G0ED-002  | CHIP FERRITE    |               | 1   |                |
|      | L830       | LB73G0ED-002  | CHIP FERRITE    |               | 1   |                |
|      | L901       | LR79Z0JM330M  | CHIP INDUCTOR   |               | 1   |                |
|      | L902       | LR79Z0JM330M  | CHIP INDUCTOR   |               | 1   |                |
|      | L903       | LK73Z0CA4R7M  | M.CHIP INDUCTOR |               | 1   |                |
|      | L990       | L3D-0043-00   | CHOKE COIL      |               | 1   |                |
|      | L2006      | RK73HH1J470D  | MG RESISTOR     |               | 1   |                |
|      | L9002      | RK73GB2A000J  | MG RESISTOR     |               | 1   |                |
|      | A1303      | W0C-0414-00   | CIRCUIT MODULE  |               | 1   |                |
|      | CN702      | EA710AQ-1503A | W TO B CONNE    |               | 1   | M1,K1          |
|      | CN703      | EB750AA-1020C | B TO B CONNE    |               | 1   |                |
|      | CN990      | E5J-0139-00   | R.RECEPTACLE    |               | 1   |                |
|      | CN3000     | EC720AE-1026B | FFC FPC CONNE   |               | 1   |                |
|      | E2         | J1B-0034-00   | WIRE CLAMPER    |               | 1   | M1,K1          |
|      | F321       | F53-0513-08   | PATTERN FUSE    | 4A            | 1   |                |
|      | F322       | F53-0513-08   | PATTERN FUSE    | 4A            | 1   |                |
|      | F540       | FZA10BH-2R5   | FUSE (CC)       |               | 1   |                |
|      | J220       | E1B-0013-00   | 3.5D PHONE JACK |               | 1   |                |
|      | J321       | E6D-0016-10   | PIN JACK        |               | 1   | K2,M1,K1,K3,K0 |
|      | J321       | E6D-0015-10   | PIN JACK        |               | 1   | E1             |
|      | J470       | E5G-0029-00   | CYL.RECEPTACLE  |               | 1   | K2,K0          |
|      | J600       | E6J-0017-00   | JACK OTHERS     |               | 1   |                |
|      | K2005      | LR73Z0AD4R7M  | CHIP INDUCTOR   |               | 1   |                |
|      | VA360      | SDV1005E18//0 | VARIATOR        |               | 1   |                |
|      | VA390      | SDV1005E18//0 | VARIATOR        |               | 1   |                |
|      | VA602      | F0K-0265-00   | SURGE ABSORBER  |               | 1   |                |
|      | VA701      | F0K-0282-00   | SURGE ABSORBER  |               | 1   |                |
|      | VA702      | F0K-0282-00   | SURGE ABSORBER  |               | 1   |                |

△

| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
|----------|------|------------|------|------------|------|----------|------|
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe                                | Symbol No. | Parts No.     | Parts Name      | Description  | QTY | Local          |
|-------------------------------------|------------|---------------|-----------------|--------------|-----|----------------|
|                                     | VA703      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA704      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA705      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA706      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA707      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA709      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA710      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA711      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA714      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA715      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA716      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA717      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA780      | F0K-0282-00   | SURGE ABSORBER  |              | 1   | M1,K1          |
|                                     | VA781      | F0K-0282-00   | SURGE ABSORBER  |              | 1   | M1,K1          |
|                                     | VA905      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA906      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | VA907      | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | X600       | L7J-0014-00   | QUARTZ CRYSTAL  |              | 1   |                |
|                                     | X701       | L7J-0138-00   | QUARTZ CRYSTAL  |              | 1   |                |
|                                     | X702       | L7J-0123-00   | QUARTZ CRYSTAL  |              | 1   |                |
| SWITCH PWB ASSY (XJ6-155x-0x) <XJ6> |            |               |                 |              |     |                |
|                                     | IC1        | BU97520AKV-M  | MOS IC          |              | 1   |                |
|                                     | IC2        | BU97520AKV-M  | MOS IC          |              | 1   |                |
|                                     | IC90       | SIRD630B6T    | IR DETECT UNIT  |              | 1   | K2,M1,K1,K3,K0 |
|                                     | Q1         | KTC4075P/Y/   | TRANSISTOR      |              | 1   |                |
|                                     | Q50        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q51        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q52        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q53        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q54        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q55        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q56        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q57        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q58        | KTC4075EP/Y/  | TRANSISTOR      |              | 1   |                |
|                                     | Q90        | KRA302E-P     | DIGI TRANSISTOR |              | 1   | K2,M1,K1,K3,K0 |
|                                     | Q91        | KRC402E-P     | DIGI TRANSISTOR |              | 1   | K2,M1,K1,K3,K0 |
|                                     | D1         | UDZV5.6B      | ZENER DIODE     |              | 1   |                |
|                                     | D2         | SM5818PL      | SCHOTTKY DIODE  |              | 1   |                |
|                                     | D20        | QSMH-C199     | LED             |              | 1   |                |
|                                     | D40        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D41        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D42        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D43        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D44        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D45        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D70        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D71        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D72        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D73        | LRTBGVTG-U//0 | LED             |              | 1   |                |
|                                     | D82        | F0K-0282-00   | SURGE ABSORBER  |              | 1   |                |
|                                     | C1         | CK73GXR1A475K | C CAPACITOR     | 4.7uF 10V K  | 1   |                |
|                                     | C2         | CK73GXR1A475K | C CAPACITOR     | 4.7uF 10V K  | 1   |                |
|                                     | C5         | CK73GXR1C105K | C CAPACITOR     | 1uF 16V K    | 1   |                |
|                                     | C6         | CK73EXR1E106K | C CAPACITOR     | 10uF 25V K   | 1   |                |
|                                     | C7         | CK73EXR1E106K | C CAPACITOR     | 10uF 25V K   | 1   |                |
|                                     | C8         | CK73EXR1E106K | C CAPACITOR     | 10uF 25V K   | 1   |                |
|                                     | C60        | CK73JXR1H102K | C CAPACITOR     | 1000pF 50V K | 1   |                |
|                                     | C61        | CK73JXR1H102K | C CAPACITOR     | 1000pF 50V K | 1   |                |
|                                     | C82        | CK73EXR1E106K | C CAPACITOR     | 10uF 25V K   | 1   |                |
|                                     | C83        | CK73JXR1H471K | C CAPACITOR     | 470pF 50V K  | 1   |                |
|                                     | C84        | CK73JXR1H472K | C CAPACITOR     | 4700pF 50V K | 1   |                |
|                                     | C85        | CK73JXR1H471K | C CAPACITOR     | 470pF 50V K  | 1   |                |
|                                     | C86        | CK73JXR1H472K | C CAPACITOR     | 4700pF 50V K | 1   |                |
|                                     | C91        | CK73GXR1A105K | C CAPACITOR     | 1uF 10V K    | 1   | K2,M1,K1,K3,K0 |
|                                     | C820       | CC73HCH1H221J | C CAPACITOR     | 220pF 50V J  | 1   |                |
|                                     | C830       | CK73JXR1C104K | C CAPACITOR     | 0.1uF 16V K  | 1   |                |
|                                     | C840       | CK73HXR1C104K | C CAPACITOR     | 0.1uF 16V K  | 1   |                |
|                                     | C850       | CK73JXR1C104K | C CAPACITOR     | 0.1uF 16V K  | 1   |                |
|                                     | R1         | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R3         | RK73GB2A471J  | MG RESISTOR     | 470Ω 1/10W J | 1   |                |
|                                     | R5         | RK73EB2E331J  | MG RESISTOR     | 330Ω 1/4W J  | 1   |                |
|                                     | R6         | RK73EB2E102J  | MG RESISTOR     | 1kΩ 1/4W J   | 1   |                |
|                                     | R10        | RK73FB2B152J  | MG RESISTOR     | 1.5kΩ 1/8W J | 1   |                |
|                                     | R11        | RK73HB1J121J  | MG RESISTOR     | 120Ω 1/16W J | 1   |                |
|                                     | R20        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R21        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R22        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R23        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R24        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R25        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R26        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R27        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R30        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R31        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R32        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R33        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R35        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R36        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R37        | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J | 1   |                |
|                                     | R38        | RK73FB2B271J  | MG RESISTOR     | 270Ω 1/8W J  | 1   |                |
|                                     | R39        | RK73FB2B331J  | MG RESISTOR     | 330Ω 1/8W J  | 1   |                |

| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
|----------|------|------------|------|------------|------|----------|------|
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe                                  | Symbol No. | Parts No.     | Parts Name      | Description   | QTY | Local |
|---------------------------------------|------------|---------------|-----------------|---------------|-----|-------|
| R41                                   |            | RK73FB2B681J  | MG RESISTOR     | 680Ω 1/8W J   | 1   |       |
| R42                                   |            | RK73FB2B271J  | MG RESISTOR     | 270Ω 1/8W J   | 1   |       |
| R43                                   |            | RK73FB2B331J  | MG RESISTOR     | 330Ω 1/8W J   | 1   |       |
| R45                                   |            | RK73FB2B681J  | MG RESISTOR     | 680Ω 1/8W J   | 1   |       |
| R46                                   |            | RK73FB2B271J  | MG RESISTOR     | 270Ω 1/8W J   | 1   |       |
| R47                                   |            | RK73FB2B331J  | MG RESISTOR     | 330Ω 1/8W J   | 1   |       |
| R49                                   |            | RK73FB2B681J  | MG RESISTOR     | 680Ω 1/8W J   | 1   |       |
| R50                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R51                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R52                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R53                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R54                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R55                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R56                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R57                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R58                                   |            | RK73HB1J682J  | MG RESISTOR     | 6.8kΩ 1/16W J | 1   |       |
| R60                                   |            | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |       |
| R61                                   |            | RK73HB1J101J  | MG RESISTOR     | 100Ω 1/16W J  | 1   |       |
| R62                                   |            | RK73HB1J4R7J  | MG RESISTOR     | 4.7Ω 1/16W J  | 1   |       |
| R71                                   |            | RK73FB2B681J  | MG RESISTOR     | 680Ω 1/8W J   | 1   |       |
| R72                                   |            | RK73FB2B271J  | MG RESISTOR     | 270Ω 1/8W J   | 1   |       |
| R73                                   |            | RK73FB2B331J  | MG RESISTOR     | 330Ω 1/8W J   | 1   |       |
| R75                                   |            | RK73FB2B681J  | MG RESISTOR     | 680Ω 1/8W J   | 1   |       |
| R76                                   |            | RK73FB2B271J  | MG RESISTOR     | 270Ω 1/8W J   | 1   |       |
| R77                                   |            | RK73FB2B331J  | MG RESISTOR     | 330Ω 1/8W J   | 1   |       |
| R80                                   |            | RK73EB2E221J  | MG RESISTOR     | 220Ω 1/4W J   | 1   |       |
| R1001                                 |            | RK73GB2A000J  | MG RESISTOR     | 0Ω 1/10W J    | 1   |       |
| L2                                    |            | LR73Z0AD100M  | CHIP INDUCTOR   |               | 1   |       |
| CN1                                   |            | EB760AA-1020A | B TO B CONNE    |               | 1   |       |
| FL80                                  |            | L7K-0038-00   | FILTER          |               | 1   |       |
| J60                                   |            | E1B-0037-00   | 3.5D PHONE JACK |               | 1   |       |
| J80                                   |            | E5J-0069-00   | USB TERMINAL    |               | 1   |       |
| S1                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S2                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S3                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S4                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S5                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S6                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S7                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S8                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S9                                    |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S11                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S12                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S13                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S14                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S15                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S16                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S18                                   |            | S7A-0001-00   | TACTILE PUSH SW |               | 1   |       |
| S20                                   |            | T9K-0007-00   | ROTARY ENCODER  |               | 1   |       |
| CD MECHA PWB ASSY (XJD-018W-00) <XJD> |            |               |                 |               |     |       |
| IC1                                   |            | MN6627553APA  | ANALOG IC       |               | 1   |       |
| IC2                                   |            | BD8266EFV-M   | ANALOG IC       |               | 1   |       |
| Q1                                    |            | 2SB1197K/QR/  | TRANSISTOR      |               | 1   |       |
| C1                                    |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C3                                    |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C4                                    |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C7                                    |            | CK73HXR1A334K | C CAPACITOR     | 0.33uF 10V K  | 1   |       |
| C8                                    |            | CC73JCH1E102J | C CAPACITOR     | 1000pF 25V J  | 1   |       |
| C9                                    |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C10                                   |            | CC73JCH1E102J | C CAPACITOR     | 1000pF 25V J  | 1   |       |
| C11                                   |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C12                                   |            | CK73JXR1A153K | C CAPACITOR     | 0.015uF 10V K | 1   |       |
| C13                                   |            | CC73JCH1E681J | C CAPACITOR     | 680pF 25V J   | 1   |       |
| C14                                   |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C15                                   |            | CK73GXR0J475K | C CAPACITOR     | 4.7uF 6.3V K  | 1   |       |
| C16                                   |            | CK73HXR0J105K | C CAPACITOR     | 1uF 6.3V K    | 1   |       |
| C17                                   |            | CK73HXR1A334K | C CAPACITOR     | 0.33uF 10V K  | 1   |       |
| C18                                   |            | CK73JXR1H332K | C CAPACITOR     | 3300pF 50V K  | 1   |       |
| C19                                   |            | CK73JXR1E223K | C CAPACITOR     | 0.022uF 25V K | 1   |       |
| C20                                   |            | CK73GXR1A106K | C CAPACITOR     | 10uF 10V K    | 1   |       |
| C21                                   |            | CK73HXR1A334K | C CAPACITOR     | 0.33uF 10V K  | 1   |       |
| C26                                   |            | CK73GXR1A106K | C CAPACITOR     | 10uF 10V K    | 1   |       |
| C27                                   |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C28                                   |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C50                                   |            | CK73JXR1H682K | C CAPACITOR     | 6800pF 50V K  | 1   |       |
| C51                                   |            | CK73JXR1H682K | C CAPACITOR     | 6800pF 50V K  | 1   |       |
| C52                                   |            | CK73JXR1H103K | C CAPACITOR     | 0.01uF 50V K  | 1   |       |
| C53                                   |            | CK73JXR1H103K | C CAPACITOR     | 0.01uF 50V K  | 1   |       |
| C55                                   |            | CK73HXR1A154K | C CAPACITOR     | 0.15uF 10V K  | 1   |       |
| C60                                   |            | CC73JCH1E102J | C CAPACITOR     | 1000pF 25V J  | 1   |       |
| C61                                   |            | CC73JCH1E102J | C CAPACITOR     | 1000pF 25V J  | 1   |       |
| C62                                   |            | CK73GXR1A106K | C CAPACITOR     | 10uF 10V K    | 1   |       |
| C82                                   |            | CC73JCH1E681J | C CAPACITOR     | 680pF 25V J   | 1   |       |
| C83                                   |            | CC73JCH1H120J | C CAPACITOR     | 12pF 50V J    | 1   |       |
| C84                                   |            | CC73JCH1H120J | C CAPACITOR     | 12pF 50V J    | 1   |       |
| C85                                   |            | CK73JXR1A104K | C CAPACITOR     | 0.1uF 10V K   | 1   |       |
| C244                                  |            | CK73HXR1A154K | C CAPACITOR     | 0.15uF 10V K  | 1   |       |
| R3                                    |            | RK73HB1J821J  | MG RESISTOR     | 820Ω 1/16W J  | 1   |       |
| R4                                    |            | RK73HB1J105J  | MG RESISTOR     | 1MΩ 1/16W J   | 1   |       |
| R7                                    |            | RK73HB1J272J  | MG RESISTOR     | 2.7kΩ 1/16W J | 1   |       |
| R8                                    |            | RK73HB1J821J  | MG RESISTOR     | 820Ω 1/16W J  | 1   |       |

|          |      |            |      |            |      |          |      |
|----------|------|------------|------|------------|------|----------|------|
| MODEL    | MARK | MODEL      | MARK | MODEL      | MARK | MODEL    | MARK |
| DPX504BT | K2   | DPX-5200BT | E1   | DPX-5200BT | M1   | DPX524BT | K1   |
| DPX560BT | K3   | DPX594BT   | K0   |            |      |          |      |

| Safe | Symbol No. | Parts No.     | Parts Name     | Description   | QTY | Local |
|------|------------|---------------|----------------|---------------|-----|-------|
| R9   |            | RK73HB1J823J  | MG RESISTOR    | 82kΩ 1/16W J  | 1   |       |
| R10  |            | RK73FB2B4R7J  | MG RESISTOR    | 4.7Ω 1/8W J   | 1   |       |
| R11  |            | RK73HB1J822J  | MG RESISTOR    | 8.2kΩ 1/16W J | 1   |       |
| R12  |            | RK73HB1J105J  | MG RESISTOR    | 1MΩ 1/16W J   | 1   |       |
| R17  |            | RK73HB1J123J  | MG RESISTOR    | 12kΩ 1/16W J  | 1   |       |
| R18  |            | RK73HB1J822J  | MG RESISTOR    | 8.2kΩ 1/16W J | 1   |       |
| R20  |            | RK73HB1J103J  | MG RESISTOR    | 10kΩ 1/16W J  | 1   |       |
| R21  |            | RK73HB1J822J  | MG RESISTOR    | 8.2kΩ 1/16W J | 1   |       |
| R23  |            | RK73HB1J183J  | MG RESISTOR    | 18kΩ 1/16W J  | 1   |       |
| R24  |            | RK73HB1J272J  | MG RESISTOR    | 2.7kΩ 1/16W J | 1   |       |
| R26  |            | RK73HB1J223J  | MG RESISTOR    | 22kΩ 1/16W J  | 1   |       |
| R28  |            | RK73HB1J114J  | MG RESISTOR    | 110kΩ 1/16W J | 1   |       |
| R31  |            | RK73HB1J821J  | MG RESISTOR    | 820Ω 1/16W J  | 1   |       |
| R32  |            | RK73HB1J821J  | MG RESISTOR    | 820Ω 1/16W J  | 1   |       |
| R33  |            | RK73HB1J131J  | MG RESISTOR    | 130Ω 1/16W J  | 1   |       |
| R37  |            | RK73HB1J103J  | MG RESISTOR    | 10kΩ 1/16W J  | 1   |       |
| R44  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R47  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R48  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R49  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R50  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R51  |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| R52  |            | RK73HB1J562J  | MG RESISTOR    | 5.6kΩ 1/16W J | 1   |       |
| R53  |            | RK73HB1J562J  | MG RESISTOR    | 5.6kΩ 1/16W J | 1   |       |
| R54  |            | RK73HB1J562J  | MG RESISTOR    | 5.6kΩ 1/16W J | 1   |       |
| R305 |            | RK73HB1J101J  | MG RESISTOR    | 100Ω 1/16W J  | 1   |       |
| L1   |            | LB73G0EA-002  | CHIP FERRITE   |               | 1   |       |
| L2   |            | LB73H0AY-004  | CHIP FERRITE   |               | 1   |       |
| L3   |            | LB73H0AY-004  | CHIP FERRITE   |               | 1   |       |
| CN1  |            | EC720AE-1026B | FFC FPC CONNE  |               | 1   |       |
| CN2  |            | EC720AK-0515A | FFC FPC CONNE  |               | 1   |       |
| S1   |            | S6J-0001-00   | PUSH SWITCH    |               | 1   |       |
| S2   |            | S6J-0001-00   | PUSH SWITCH    |               | 1   |       |
| S3   |            | S6J-0002-00   | PUSH SWITCH    |               | 1   |       |
| X1   |            | L7J-0005-00   | QUARTZ CRYSTAL |               | 1   |       |