



(PF3679AA-VA)

# EXPLODED VIEW / PARTS LIST

## Parts list

NO.	PART NO.	DESCRIPTION	Q'TY	NO.	PART NO.	DESCRIPTION	Q'TY
1	-----	*Unsuded number	-	10-5	074-1302-28	OUTLET SOCKET(28P)	1
1-1	940-8790-90	ES-ASSY(CV641UL)(for PF3692AA)	1	10-6	074-4105-00	OUTLET SOCKET(USB)	1
	940-8862-60	ES-ASSY(CV682UL)(for PF3692AB)	1	10-7	074-2248-40	OUTLET SOCKET(40P)	1
	940-8862-67	ES-ASSY(CV693UL)(for PF3692AC)	1	10-8	074-2248-30	OUTLET SOCKET(30P)	1
	940-8790-91	ES-ASSY(CV741CL)(for PF3695AA)	1	10-9	074-2249-04	OUTLET SOCKET(4P)	1
	940-8862-55	ES-ASSY(CV752CL)(for PF3695AB)	1	10-10	074-2248-60	OUTLET SOCKET(60P)	1
	940-8862-68	ES-ASSY(CV793CL)(for PF3695AC)	1	10-11	060-8162-90	BLUETOOTH MODULE	1
1-2	013-9745-00	TOUCH PANEL	1	10-12	074-8023-51	OUTLET SOCKET(SD)	1
1-3	379-0491-02	TFT	1	10-13	331-5533-03	PRESSED PART(BRKT-L)	1
1-4	335-9939-02	MOLDED PART(GUIDE ILLUMI L)	1	10-14	331-5534-01	PRESSED PART(BRKT-R)	1
1-5	335-9938-02	MOLDED PART(GUIDE ILLUMI R)	1	10-15	331-5586-01	PRESSED PART(BRKT-F)	1
1-6	346-0314-11	LEATHER PART	1	10-16	778-3006-00	TAP-SCREW(Φ3x6)	2
1-7	335-9937-00	MOLDED PART(DISC GUIDE)	1	10-17	714-2606-8B	MACHINE SCREW	1
1-8	331-3038-50	EARTH PLATE	1	10-18	076-0569-02	PLUG(2P)	1
1-9	331-5532-03	PRESSED PART(LCD HOLDER)	1	11	816-3135-55	FLAT WIRE(L58 W16.6)	1
1-10	947-0863-02	KNOB ASSY	2	12	816-3105-55	FLAT WIRE(L58 W41.6)	1
1-11	-----	*Unsuded number	-	13	816-3167-57	FLAT WIRE(L198)	1
1-11-1	-----	SW PWB(428200-039)	1	14	854-4667-52	EXTENSION LEAD	1
1-11-2	016-0018-37	VR W/SHAFT	2	15	-----	SETPLATE(for PF3692AA)(113658-276)	1
1-11-3	001-7141-90	DIODE(RED)	13		-----	SETPLATE(for PF3692AB)(153357-276)	1
1-11-4	013-6202-52	TACT SWITCH(SKPMBJE010)	1		-----	SETPLATE(for PF3692AC)(153367-276)	1
1-11-5	013-6201-53	TACT SWITCH(SKPMAPE010)	4		-----	SETPLATE(for PF3695AA)(113661-276)	1
1-11-6	074-2248-30	OUTLET SOCKET(30P)	1		-----	SETPLATE(for PF3695AB)(153352-276)	1
1-11-7	074-2240-60	OUTLET SOCKET(10P)	1		-----	SETPLATE(for PF3695AC)(153368-276)	1
1-11-8	001-7109-92	DIODE(RED)	2	16	714-2614-8B	MACHINE SCREW	2
1-12	716-0878-50	SPECIAL SCREW(M2.6x5)	5	17	714-2606-8B	MACHINE SCREW	6
1-13	716-0778-52	SPECIAL SCREW(M2x8)	8	18	716-0878-50	SPECIAL SCREW	13
1-14	347-9767-00	INSULATOR	1	19	714-2604-8B	MACHINE SCREW	14
2	-----	*Unsuded number	-	20	778-3006-51	TAP SCREW	4
2-1	-----	MAIN PWB(461100-039)	1	21	-----	*Unsuded number	-
2-2	076-6021-60	PLUG(10P)	1	21-1	-----	SD CARD(002310-065)	1
2-3	074-2248-80	OUTLET SOCKET(80P)	1	22	347-9373-00	PAPER PART(TAPE)	1
2-4	074-1261-00	OUTLET SOCKET(16P)	1	23	020-3066-00	DC-MOTOR	1
2-5	051-2077-00	IC(TB2959HQ)	1	24	732-2614-1B	SEMS SCREW	2
2-6	092-2260-00	ANT-RECEPT(RADIO)	1	25	-----	LABEL(SAT)(for PF3692AA)	1
2-7	092-2259-00	ANT-RECEPT(XM)	1		-----	LABEL(SAT)(for PF3692AB/C)	1
2-8	-----	XM TUNER PACK(US)(for PF3692A)	1		-----	LABEL(SAT)(for PF3695AA)	1
	-----	XM TUNER PACK(CA)(for PF3695A)	1		-----	LABEL(SAT)(for PF3695AB/C)	1
2-9	331-5535-04	BRKT-C	1	26	-----	LABEL(HD RADIO)	1
2-10	778-3006-00	TAP-SCREW	2	27	-----	LABEL(VR64)(for PF3692AA)	1
3	311-2084-11	LOWER CASE	1		-----	LABEL(VR68)(for PF3692AB)	1
4	310-2026-12	UPPER CASE	1		-----	LABEL(VR69)(for PF3692AC)	1
5	309-2002-01	FRONT PLATE	1		-----	LABEL(VR74)(for PF3695AA)	1
6	313-2194-02	HEAT SINK	1		-----	LABEL(VR75)(for PF3695AB)	1
7	331-5531-01	PRESSED PART(MECH BRKT)	1		-----	LABEL(VR79)(for PF3695AC)	1
8	929-5400-81	CD-MECH-MODULE	1	28	347-9381-00	PROTECT-SHEET	1
9	347-9449-02	PROTECTOR	1	29	-----	LABEL(XM SAT)	1
10	-----	*Unsuded number	-	30	345-6717-00	GASKET	1
10-1	-----	NAVI PWB(448000-039)	1	31	347-9492-00	PAPER PART(CUSHION SHEET)	4
10-2	076-6030-60	PLUG(10P)	1	32	-----	*Not mounted(LABEL)	-
10-3	074-2248-80	OUTLET SOCKET(80P)	1	33	-----	*Not mounted(BSMI LABEL)	-
10-4	076-6023-07	PLUG(7P)	1				

# ELECTRICAL PARTS LIST

## MAIN PWB(B1) section

\* Neither the part numbers of parts on which software is written, nor part numbers of parts for which replacement is prohibited in the production process are listed in the parts list.

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
ANT100	092-2260-00	ANT-RECEPT(3P)	C248	046-4732-78	0.047uF K B	C429	043-5600-90	0.10uF
ANT900	092-2259-00	ANT-RECEPT(1P)	C250	046-1042-78	0.1uF K B	C430	043-5600-90	0.10uF
C100	166-1201-50	12pF CH	C251	042-4033-90	6.3V 220uF	C431	168-1042-38	50V 0.1uF K
C102	046-1022-58	50V 1000pF	C252	045-1007-50	10 +/-0.5pF CH	C501	046-1042-78	0.1uF K B
C103	046-1022-58	50V 1000pF	C253	045-1007-50	10 +/-0.5pF CH	C502	165-1073-35	16V 100uF
C104	045-3901-50	39pFJ CH	C254	168-1052-78	16V 1uF K	C505	168-1052-78	16V 1uF K
C105	045-1211-50	120pFJ CH	C255	046-1042-78	0.1uF K B	C506	168-1052-78	16V 1uF K
C106	045-1501-50	15pFJ CH	C256	043-0552-90	6.3V 47uF M	C545	046-6822-58	6800pF K B
C107	045-2211-50	220pFJ CH	C257	046-1042-78	0.1uF K B	C546	046-1042-78	0.1uF K B
C108	046-3922-58	3900pF K B	C258	046-1042-78	0.1uF K B	C547	046-6822-58	6800pF K B
C109	046-1022-58	50V 1000pF	C259	046-1042-78	0.1uF K B	C548	046-1042-78	0.1uF K B
C110	046-1032-78	0.01uF K B	C260	046-1042-78	0.1uF K B	C549	043-0562-90	10V 0.22uF
C111	046-1032-78	0.01uF K B	C261	046-4712-58	470pF K B	C550	043-0602-90	10uF
C112	045-5096-50	5pF +/-0.25pF CH	C262	178-2255-79	2.2uF	C551	043-0562-90	10V 0.22uF
C113	046-3322-58	3300pF K B	C263	178-2255-79	2.2uF	C552	168-1052-78	16V 1uF K
C114	046-2232-78	0.022uF K B	C264	166-2201-50	22pF CH	C553	046-1042-78	0.1uF K B
C115	046-1022-58	50V 1000pF	C265	166-2201-50	22pF CH	C555	046-2222-58	2200pF K B
C116	046-2232-78	0.022uF K B	C269	045-4701-50	47pF CH	C558	046-2222-58	2200pF K B
C117	046-2232-78	0.022uF K B	C270	045-4701-50	47pF CH	C560	046-1042-78	0.1uF K B
C118	046-2232-78	0.022uF K B	C271	045-4701-50	47pF CH	C561	043-7402-90	16V 22uF
C119	046-2232-78	0.022uF K B	C272	045-4701-50	47pF CH	C562	043-7402-90	16V 22uF
C120	043-0562-90	10V 0.22uF	C275	046-1042-78	0.1uF K B	C567	043-7402-90	16V 22uF
C121	046-2232-78	0.022uF K B	C276	046-1042-78	0.1uF K B	C568	043-7402-90	16V 22uF
C122	043-0563-90	16V 47uF	C279	178-2255-79	2.2uF	C573	043-7402-90	16V 22uF
C124	045-2201-50	22pFJ CH	C280	178-2255-79	2.2uF	C574	042-4015-91	25V 470uF
C128	045-2201-50	22pFJ CH	C281	166-2201-50	22pF CH	C575	043-7503-90	4.7uF
C131	045-4796-50	4.7pFJ CH	C282	166-2201-50	22pF CH	C576	043-7503-90	4.7uF
C132	046-1042-78	0.1uF K B	C283	043-6401-90	16V 10uF	C577	043-7503-90	4.7uF
C164	033-0000-05	1/16W 0 ohm	C300	166-2711-50	270pF CH	C579	043-0554-90	25V 10uF
C165	033-0000-05	1/16W 0 ohm	C301	166-2711-50	270pF CH	C901	046-1022-58	50V 1000pF
C177	046-1022-58	50V 1000pF	C302	178-2732-78	0.027uF	C902	046-1022-58	50V 1000pF
C203	168-4752-98	4.7uF K	C303	178-2732-78	0.027uF	C903	046-1022-58	50V 1000pF
C204	168-4752-98	4.7uF K	C304	178-2732-78	0.027uF	C905	043-5703-90	50V 0.001uF
C205	046-1042-78	0.1uF K B	C305	178-2732-78	0.027uF	C906	043-7701-90	2.2uF
C206	046-1042-78	0.1uF K B	C306	166-5611-50	560pF CH	C907	042-4025-90	16V 47uF
C207	046-1042-78	0.1uF K B	C307	166-5611-50	560pF CH	C909	046-1042-78	0.1uF K B
C208	046-1042-78	0.1uF K B	C308	166-2201-50	22pF CH	C910	046-1042-78	0.1uF K B
C209	046-1042-78	0.1uF K B	C309	166-2201-50	22pF CH	C911	046-1022-58	50V 1000pF
C210	045-8097-50	8pF +/-0.5pF CH	C310	166-2201-50	22pF CH	C912	046-1022-58	50V 1000pF
C211	045-1007-50	10 +/-0.5pF CH	C311	166-2201-50	22pF CH	C916	045-1011-50	100pFJ CH
C212	046-1042-78	0.1uF K B	C312	166-5611-50	560pF CH	C917	045-1801-50	18pFJ CH
C214	168-4752-98	4.7uF K	C313	166-5611-50	560pF CH	C918	045-1801-50	18pFJ CH
C216	046-1042-78	0.1uF K B	C314	166-2711-50	270pF CH	C923	043-4306-90	1uF
C217	168-4752-98	4.7uF K	C315	166-2711-50	270pF CH	C924	168-1052-78	16V 1uF K
C218	046-1042-78	0.1uF K B	C316	168-2242-58	0.22uF K	C927	046-1022-58	50V 1000pF
C219	046-1042-78	0.1uF K B	C317	168-2242-58	0.22uF K	C928	046-1022-58	50V 1000pF
C220	046-1042-78	0.1uF K B	C318	168-2242-58	0.22uF K	D100	001-9013-90	BA891
C221	043-0559-90	6.3V 22uF	C321	042-4007-90	50V 10uF M	D101	001-9013-90	BA891
C222	168-1052-78	16V 1uF K	C322	168-1052-78	16V 1uF K	D400	001-2412-90	RR264M-400
C223	046-1042-78	0.1uF K B	C323	043-0574-90	25V 1.0uF	D401	001-2403-90	M1F60
C224	046-1042-78	0.1uF K B	C328	042-0630-50	16V 100uF	D402	001-2403-90	M1F60
C225	046-1042-78	0.1uF K B	C329	168-1042-78	16V 0.1uF K	D503	001-2403-90	M1F60
C226	046-1042-78	0.1uF K B	C330	ADZ0292	6.3V 220uF	D504	001-2403-90	M1F60
C227	046-1042-78	0.1uF K B	C331	168-2242-58	0.22uF K	D505	001-2633-90	1SS388-TPL3,F
C228	046-1042-78	0.1uF K B	C332	168-1052-78	16V 1uF K	D506	001-2633-90	1SS388-TPL3,F
C229	046-1042-78	0.1uF K B	C334	168-2242-58	0.22uF K	FE900	-----	XM TUNER PACK (US)(for PF3692A)
C230	046-3322-58	3300pF K B	C335	046-1042-78	0.1uF K B		-----	XM TUNER PACK (CA)(for PF3695A)
C231	046-1022-58	50V 1000pF	C336	046-1042-78	0.1uF K B	IC101	-----	TEF7000 (Tuner)
C232	042-4015-90	16V 470uF	C400	165-1053-65	50V 1uF			(Thermal pad) (402590-051)
C233	046-3322-58	3300pF K B	C402	168-2222-55	2200pF K	IC200	-----	SAF7741HV/ N127ZK (DSP)
C234	046-1022-58	50V 1000pF	C403	168-2222-55	2200pF K			(Exposed die pad) (674713-051)
C235	046-1042-78	0.1uF K B	C404	168-2222-55	2200pF K	IC301	051-2077-00	TB2959HQ
C236	046-1022-58	50V 1000pF	C405	168-2222-55	2200pF K	IC302	051-3034-90	NJM4558V
C237	046-1022-58	50V 1000pF	C406	168-2222-55	2200pF K	IC303	051-3034-90	NJM4558V
C239	046-1042-78	0.1uF K B	C407	168-2222-55	2200pF K			
C241	046-6812-58	680pF K B	C408	168-2222-55	2200pF K			
C242	046-6812-58	680pF K B	C409	168-2222-55	2200pF K			
C243	046-6812-58	680pF K B	C424	042-4441-10	25V 4700uF			
C244	046-6812-58	680pF K B	C426	168-1032-55	0.01uF K			
C245	046-1042-78	0.1uF K B	C427	165-1063-35	16V 10uF			
C247	165-2263-15	6.3V 22uF	C428	043-5600-90	0.10uF			

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
IC401	051-5418-08	S-80827CNMC-B8M-T2	Q507	192-4081-00	2SC4081	R317	119-3331-15	1/10W 33k ohm
IC402	051-5418-08	S-80827CNMC-B8M-T2	Q508	125-2027-91	DTC114EUA	R322	116-8211-15	1/4W 820 ohm
IC500	-----	BD00C0AWFP (Voltage regulator) (Thermal pad) (358290-051)	Q509	125-2027-91	DTC114EUA	R323	116-1021-15	1/4W 1k ohm
IC502	051-3639-90	AP3405DS	Q510	125-8044-90	SH8K15GZETB	R364	119-2221-15	1/10W 2.2k ohm
IC503	051-3767-90	BD00GC0EEFJ-ME2	Q511	125-8044-90	SH8K15GZETB	R400	116-4721-15	1/4W 4.7k ohm
IC900	-----	NJM2386ADL3-05-TE1 (Thermal pad) (337490-051)	Q513	190-2071-00	2SA2071	R401	116-5621-15	1/4W 5.6k ohm
IC901	051-3764-90	BD00HA5EEFJ-ME2	R101	033-1811-15	1/16W 180 ohm J	R418	116-4721-15	1/4W 4.7k ohm
J680	074-2248-80	SOCKET(80P)	R102	033-3311-15	1/16W 330 ohm J	R420	116-1831-15	1/4W 18k ohm
L100	010-2198-62	0.27uH	R103	033-4741-15	1/16W 470k ohm J	R421	119-1031-15	1/10W 10k ohm
L101	010-3406-56	3.3uH J	R104	033-1201-15	1/16W 12 ohm	R422	116-1121-15	1/4W 1.1k ohm
L102	010-3406-46	0.47uH J	R105	033-5601-15	1/16W 56 ohm J	R423	119-2721-15	1/10W 2.7k ohm
L103	010-3439-51	1.8uH	R108	033-2231-15	1/16W 22k ohm J	R425	119-5621-15	1/10W 5.6k ohm
L104	010-3406-42	0.22uH	R109	033-3921-15	1/16W 3.9k ohm J	R426	119-1021-15	1/10W 1k ohm
L105	010-3104-54	600 ohm/100MHz	R110	033-0000-05	1/16W 0 ohm	R430	032-0221-09	1/16W 33k ohm F
L106	010-2290-52	330uH	R111	033-0000-05	1/16W 0 ohm	R431	032-0221-09	1/16W 33k ohm F
L107	010-2290-52	330uH	R113	033-4741-15	1/16W 470k ohm J	R432	032-0221-09	1/16W 33k ohm F
L200	010-3105-62	1k ohm/100MHz	R114	033-1051-15	1/16W 1M ohm J	R433	033-0000-05	1/16W 0 ohm
L201	010-3104-54	600 ohm/100MHz	R115	033-1051-15	1/16W 1M ohm J	R434	032-0221-65	1/16W 68k ohm F
L202	010-3104-54	600 ohm/100MHz	R148	033-0000-05	1/16W 0 ohm	R435	033-0000-05	1/16W 0 ohm
L203	010-3104-54	600 ohm/100MHz	R149	033-0000-05	1/16W 0 ohm	R436	032-0221-09	1/16W 33k ohm F
L204	010-3104-54	600 ohm/100MHz	R151	033-1811-15	1/16W 180 ohm J	R437	032-0221-53	1/16W 18k ohm F
L205	010-3104-54	600 ohm/100MHz	R152	033-1811-15	1/16W 180 ohm J	R439	116-3321-15	1/4W 3.3k ohm
L206	010-3104-54	600 ohm/100MHz	R175	033-0000-05	1/16W 0 ohm	R441	116-4721-15	1/4W 4.7k ohm
L207	010-3104-54	600 ohm/100MHz	R176	033-0000-05	1/16W 0 ohm	R442	033-1031-15	1/16W 10k ohm J
L208	119-1001-15	1/10W 10 ohm	R200	033-1031-15	1/16W 10k ohm J	R535	032-0225-98	1/16W 18k ohm
L209	010-3104-54	600 ohm/100MHz	R201	033-1011-15	1/16W 100 ohm J	R536	032-0225-00	1/16W 150k ohm
L210	010-3104-54	600 ohm/100MHz	R202	119-2201-15	1/10W 22 ohm	R537	032-0225-67	1/16W 16k ohm 0.5%
L211	010-3104-54	600 ohm/100MHz	R203	033-1021-15	1/16W 1k ohm J	R538	032-0225-98	1/16W 18k ohm
L212	010-3104-54	600 ohm/100MHz	R204	033-1011-15	1/16W 100 ohm J	R539	033-1041-15	1/16W 100k ohm J
L213	010-3104-54	600 ohm/100MHz	R205	033-1031-15	1/16W 10k ohm J	R540	032-0221-09	1/16W 33k ohm F
L214	010-3104-54	600 ohm/100MHz	R206	033-1031-15	1/16W 10k ohm J	R541	032-0221-83	1/16W 3.3k ohm F
L215	010-3104-54	600 ohm/100MHz	R207	033-1021-15	1/16W 1k ohm J	R542	032-0221-83	1/16W 3.3k ohm F
L216	010-3104-54	600 ohm/100MHz	R208	033-1021-15	1/16W 1k ohm J	R543	032-0221-09	1/16W 33k ohm F
L217	010-3104-54	600 ohm/100MHz	R209	033-1021-15	1/16W 1k ohm J	R544	033-1041-15	1/16W 100k ohm J
L218	010-3104-54	600 ohm/100MHz	R210	033-1021-15	1/16W 1k ohm J	R549	116-4791-15	1/4W 4.7 ohm
L219	010-3104-54	600 ohm/100MHz	R218	032-0140-89	1/10W 47k ohm F	R552	116-4791-15	1/4W 4.7 ohm
L220	010-3104-54	600 ohm/100MHz	R219	032-0140-89	1/10W 47k ohm F	R553	032-0217-55	1/3W 0.016 ohm
L221	010-3104-54	600 ohm/100MHz	R220	033-1011-15	1/16W 100 ohm J	R554	032-0225-60	1/16W 22k ohm +/- 0.5%
L222	010-3105-62	1k ohm/100MHz	R221	033-1011-15	1/16W 100 ohm J	R555	032-0225-81	1/16W 4.7k ohm 0.5%
L223	010-3105-62	1k ohm/100MHz	R224	032-0140-89	1/10W 47k ohm F	R556	032-0225-68	1/16W 5.6k ohm +/- 0.5%
L224	010-3103-55	120 ohm/100MHz	R225	032-0140-89	1/10W 47k ohm F	R558	032-0224-50	1/2W 0.008 ohm F
L225	010-3103-55	120 ohm/100MHz	R226	032-0210-53	1/10W 15k ohm 1%	R560	032-0221-83	1/16W 3.3k ohm F
L226	010-3103-55	120 ohm/100MHz	R227	032-0210-53	1/10W 15k ohm 1%	R561	032-0221-34	1/16W 51k ohm F
L227	010-3103-55	120 ohm/100MHz	R231	033-0000-05	1/16W 0 ohm	R562	032-0221-11	1/16W 5.6k ohm F
L301	010-3104-54	600 ohm/100MHz	R234	033-0000-05	1/16W 0 ohm	R564	033-2711-15	1/16W 270 ohm J
L302	010-3104-54	600 ohm/100MHz	R235	033-0000-05	1/16W 0 ohm	R565	033-2021-15	1/16W 2k ohm
L402	010-2285-82	390 ohm/100MHz	R241	033-1011-15	1/16W 100 ohm J	R566	033-2021-15	1/16W 2k ohm
L403	010-8064-00	144uH	R243	033-1011-15	1/16W 100 ohm J	R567	033-2711-15	1/16W 270 ohm J
L404	010-2285-82	390 ohm/100MHz	R245	119-2201-15	1/10W 22 ohm	R572	033-1031-15	1/16W 10k ohm J
L501	010-3531-52	4.7uH	R246	033-1011-15	1/16W 100 ohm J	R576	119-3321-15	1/10W 3.3k ohm
L502	010-3531-52	4.7uH	R247	033-1011-15	1/16W 100 ohm J	R577	117-1031-15	1/8W 10k ohm
L503	010-3414-92	2.2uH	R248	033-1011-15	1/16W 100 ohm J	R578	116-2221-15	1/4W 2.2k ohm
L504	010-2285-82	390 ohm/100MHz	R249	033-1011-15	1/16W 100 ohm J	R579	116-2221-15	1/4W 2.2k ohm
L601	010-3104-50	30 ohm/100MHz	R250	033-1011-15	1/16W 100 ohm J	R581	119-4731-15	1/10W 47k ohm
L602	010-3104-50	30 ohm/100MHz	R251	032-0210-53	1/10W 15k ohm 1%	R582	032-0221-50	1/16W 43k ohm F
L603	010-3104-50	30 ohm/100MHz	R252	032-0210-53	1/10W 15k ohm 1%	R583	032-0210-06	1/10W 8.2k ohm F
L902	010-3104-53	220 ohm/100MHz	R253	119-3311-15	1/10W 330 ohm	R584	033-0000-05	1/16W 0 ohm
L904	010-3104-53	220 ohm/100MHz	R254	033-0000-05	1/16W 0 ohm	R585	032-0221-07	1/16W 56k ohm F
P400	074-1261-00	OUTLET SOCKET	R255	033-0000-05	1/16W 0 ohm	R587	032-0221-11	1/16W 5.6k ohm F
P610	076-6021-60	10P	R300	119-1031-15	1/10W 10k ohm	R588	032-0221-11	1/16W 5.6k ohm F
Q200	125-7007-90	Si5441BDC-TI-E3	R301	119-1031-15	1/10W 10k ohm	R616	119-0000-05	1/10W 0 ohm JW
Q404	190-2071-00	2SA2071	R302	119-1031-15	1/10W 10k ohm	R617	119-0000-05	1/10W 0 ohm JW
Q405	192-4081-00	2SC4081	R303	119-1031-15	1/10W 10k ohm	R618	119-0000-05	1/10W 0 ohm JW
Q406	192-4081-00	2SC4081	R304	119-1031-15	1/10W 10k ohm	R619	033-0000-05	1/16W 0 ohm
Q407	190-1586-00	2SA1586 O.Y.G	R305	119-1031-15	1/10W 10k ohm	R620	033-0000-05	1/16W 0 ohm
			R306	119-4741-15	1/10W 470k ohm	R621	033-0000-05	1/16W 0 ohm
			R307	119-4741-15	1/10W 470k ohm	R905	032-0162-50	1/10W 0.51 ohm
			R308	119-4741-15	1/10W 470k ohm	R910	033-3311-15	1/16W 330 ohm J
			R309	119-4741-15	1/10W 470k ohm	R913	033-1021-15	1/16W 1k ohm J
			R310	119-1031-15	1/10W 10k ohm	R915	033-1021-15	1/16W 1k ohm J
			R311	119-1031-15	1/10W 10k ohm	R918	033-1021-15	1/16W 1k ohm J
			R312	119-2221-15	1/10W 2.2k ohm			
			R313	119-2221-15	1/10W 2.2k ohm			
			R314	119-2221-15	1/10W 2.2k ohm			
			R316	032-0140-50	1/10W 10k ohm F			

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
R921	033-1021-15	1/16W 1k ohm J	R933	033-0000-05	1/16W 0 ohm	ZD100	060-8107-50	SURGE
R923	033-0000-05	1/16W 0 ohm	R934	119-0000-05	1/10W 0 ohm JW			PROTECTOR
R924	033-3301-15	1/16W 33 ohm J	R935	119-0000-05	1/10W 0 ohm JW	ZD400	-----	SM5S22A-HE3/2D
R925	033-3301-15	1/16W 33 ohm J	RN200	050-0140-51	1/32W 22 ohm x4J			(Thermal pad)
R926	033-1011-15	1/16W 100 ohm J	T100	010-4100-50	0.215uH			(491290-001)
R930	033-0000-05	1/16W 0 ohm	TH501	002-0335-50	SMD1812P050	ZD401	001-4301-28	HZU5.1B1
R931	032-0221-50	1/16W 43k ohm F			TF/30	PWB	039-4611-00	PWB(WITHOUT
R932	032-0210-06	1/10W 8.2k ohm F	X200	061-3589-80	FA-238 41.6MHz			COMPONENTS)

SW PWB(B2) section

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
D1300	001-7141-90	VFHR1111C-4BY2A-TR RED	D1319	001-7141-90	VFHR1111C-4BY2A-TR RED	R110	119-0000-05	1/10W 0 ohm JW
D1301	001-7141-90	VFHR1111C-4BY2A-TR RED	D1320	001-7141-90	VFHR1111C-4BY2A-TR RED	R111	119-0000-05	1/10W 0 ohm JW
D1302	001-7141-90	VFHR1111C-4BY2A-TR RED	D1321	001-7141-90	VFHR1111C-4BY2A-TR RED	R112	119-0000-05	1/10W 0 ohm JW
D1303	001-7141-90	VFHR1111C-4BY2A-TR RED	D1322	001-7141-90	VFHR1111C-4BY2A-TR RED	R113	119-0000-05	1/10W 0 ohm JW
D1304	001-7141-90	VFHR1111C-4BY2A-TR RED	J101	074-2248-30	30P	R114	032-0210-75	1/10W 820 ohm F
D1305	001-7141-90	VFHR1111C-4BY2A-TR RED	J102	074-2240-60	10P	R115	032-0210-51	1/10W 750 ohm F
D1306	001-7141-90	VFHR1111C-4BY2A-TR RED	R100	032-0210-55	1/10W 2.2k ohm F	R116	032-0210-75	1/10W 820 ohm F
D1307	001-7141-90	VFHR1111C-4BY2A-TR RED	R101	032-0210-55	1/10W 2.2k ohm F	R117	032-0210-51	1/10W 750 ohm F
D1316	001-7109-92	SML-311UTT86 RED	R102	032-0210-55	1/10W 2.2k ohm F	R118	032-0221-55	1/16W 1.5k ohm F
D1317	001-7109-92	SML-311UTT86 RED	R103	032-0210-55	1/10W 2.2k ohm F	R119	032-0210-51	1/10W 750 ohm F
D1318	001-7141-90	VFHR1111C-	R104	032-0221-55	1/16W 1.5k ohm F	SW100	016-0018-37	VR W/SHAFT
			R105	032-0210-75	1/10W 820 ohm F	SW101	016-0018-37	VR W/SHAFT
			R106	032-0210-75	1/10W 820 ohm F	SW102	013-6201-53	SKPMAPE010
			R107	032-0210-75	1/10W 820 ohm F	SW103	013-6201-53	SKPMAPE010
			R108	032-0210-75	1/10W 820 ohm F	SW104	013-6201-53	SKPMAPE010
			R109	032-0210-75	1/10W 820 ohm F	SW105	013-6201-53	SKPMAPE010
						SW106	013-6202-52	SKPMBJE010
						PWB	039-4282-00	PWB(WITHOUT COMPONENTS)

## NAVI PWB(B3) section

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
C1002	168-1032-55	0.01uF K	C125	046-1022-58	50V 1000pF	C1512	046-6832-78	0.068uF K B
C1004	178-1062-88	10uF	C1250	043-6404-90	16V 10uF	C1513	046-4732-78	0.047uF K B
C1008	046-1032-78	0.01uF K B	C126	046-1042-78	0.1uF K B	C1514	043-0574-90	25V 1.0uF
C1015	046-1042-78	0.1uF K B	C1265	046-1042-78	0.1uF K B	C1515	043-7702-90	1.0uF
C1016	046-1042-78	0.1uF K B	C1266	168-1052-78	16V 1uF K	C1516	043-0566-90	50V 2.2uF K
C1017	043-6404-90	16V 10uF	C1268	AAZ0264	16V 1uF	C1517	168-1042-38	50V 0.1uF K
C1018	043-7200-90	6.3V 47uF	C127	046-1042-78	0.1uF K B	C1518	168-6832-78	0.068uF K
C1020	046-1042-78	0.1uF K B	C1272	046-1042-78	0.1uF K B	C1519	043-7702-90	1.0uF
C1021	046-1042-78	0.1uF K B	C1273	168-1052-78	16V 1uF K	C152	046-1042-78	0.1uF K B
C1022	046-1042-78	0.1uF K B	C1275	168-1052-78	16V 1uF K	C1521	043-6404-90	16V 10uF
C1023	046-1042-78	0.1uF K B	C1276	168-1052-78	16V 1uF K	C1523	166-3311-50	330pF CH
C103	046-1042-78	0.1uF K B	C128	046-1042-78	0.1uF K B	C1524	043-6404-90	16V 10uF
C104	043-0577-90	6.3V 1.0uF	C129	046-1042-78	0.1uF K B	C1525	043-6404-90	16V 10uF
C106	046-1022-58	50V 1000pF	C130	046-1042-78	0.1uF K B	C1526	168-6832-78	0.068uF K
C109	046-1042-78	0.1uF K B	C131	046-1042-78	0.1uF K B	C1527	168-6832-78	0.068uF K
C110	046-1042-78	0.1uF K B	C1313	046-1022-58	50V 1000pF	C1528	043-6404-90	16V 10uF
C111	046-1042-78	0.1uF K B	C1314	043-0554-90	25V 10uF	C153	046-1042-78	0.1uF K B
C1118	166-6097-50	6pF +/-0.5pF CH	C1315	046-1022-58	50V 1000pF	C1538	043-0566-90	50V 2.2uF K
C112	046-1042-78	0.1uF K B	C1316	043-0554-90	25V 10uF	C154	046-1042-78	0.1uF K B
C1121	166-6097-50	6pF +/-0.5pF CH	C1317	168-1052-78	16V 1uF K	C1601	046-1022-58	50V 1000pF
C1123	046-3322-58	3300pF K B	C1318	043-0554-90	25V 10uF	C1602	046-1022-58	50V 1000pF
C1124	046-3322-58	3300pF K B	C1319	046-1022-58	50V 1000pF	C1603	046-1022-58	50V 1000pF
C1125	046-3322-58	3300pF K B	C132	046-1042-78	0.1uF K B	C1604	046-1022-58	50V 1000pF
C1126	046-1042-78	0.1uF K B	C1320	043-0554-90	25V 10uF	C1606	046-1022-58	50V 1000pF
C113	046-1042-78	0.1uF K B	C1321	043-0554-90	25V 10uF	C1608	046-1022-58	50V 1000pF
C1135	045-1011-50	100pFJ CH	C1322	046-1022-58	50V 1000pF	C1610	046-1022-58	50V 1000pF
C1136	045-1007-50	10 +/-0.5pF CH	C1323	045-2201-50	22pFJ CH	C1612	046-1022-58	50V 1000pF
C1137	045-1007-50	10 +/-0.5pF CH	C1325	168-1042-38	50V 0.1uF K	C1613	168-1052-78	16V 1uF K
C114	046-1022-58	50V 1000pF	C1327	043-6400-90	16V 4.7uF K	C1614	046-1042-78	0.1uF K B
C1140	043-6404-90	16V 10uF	C1328	168-1052-78	16V 1uF K	C1615	168-1052-78	16V 1uF K
C1141	046-1022-58	50V 1000pF	C1329	168-1052-78	16V 1uF K	C1616	178-1062-88	10uF
C1143	168-1042-38	50V 0.1uF K	C133	046-1042-78	0.1uF K B	C1619	168-1022-55	1000pF K
C1144	168-3342-58	0.33uF K	C1330	168-1042-38	50V 0.1uF K	C201	046-1022-58	50V 1000pF
C1145	168-1042-38	50V 0.1uF K	C134	046-1042-78	0.1uF K B	C202	046-1042-78	0.1uF K B
C1146	168-1042-38	50V 0.1uF K	C135	046-1042-78	0.1uF K B	C203	046-1042-78	0.1uF K B
C1147	046-1022-58	50V 1000pF	C136	046-1042-78	0.1uF K B	C204	045-1201-50	12pFJ CH
C1148	046-1022-58	50V 1000pF	C137	046-1042-78	0.1uF K B	C205	045-1201-50	12pFJ CH
C1149	168-1042-38	50V 0.1uF K	C138	046-1022-58	50V 1000pF	C206	045-6097-50	6pF +/-0.5pF CH
C115	046-1042-78	0.1uF K B	C139	046-1022-58	50V 1000pF	C207	045-6097-50	6pF +/-0.5pF CH
C1150	168-1042-38	50V 0.1uF K	C140	046-1042-78	0.1uF K B	C219	046-1042-78	0.1uF K B
C1153	046-1042-78	0.1uF K B	C1404	043-7700-90	50V 4.7uF	C220	046-1022-58	50V 1000pF
C116	046-1022-58	50V 1000pF	C1405	ADZ0265	35V 47uF	C221	046-1042-78	0.1uF K B
C1161	168-1042-38	50V 0.1uF K	C1406	043-7700-90	50V 4.7uF	C222	046-1022-58	50V 1000pF
C1165	043-6404-90	16V 10uF	C141	046-1042-78	0.1uF K B	C223	046-1042-78	0.1uF K B
C1166	046-3322-58	3300pF K B	C142	046-1042-78	0.1uF K B	C224	046-1022-58	50V 1000pF
C1167	043-7402-90	16V 22uF	C1429	043-7700-90	50V 4.7uF	C226	045-1501-50	15pFJ CH
C117	046-1042-78	0.1uF K B	C143	046-1042-78	0.1uF K B	C228	046-1042-78	0.1uF K B
C118	046-1042-78	0.1uF K B	C1430	168-1042-38	50V 0.1uF K	C233	043-0587-90	50V 18pF
C119	046-1042-78	0.1uF K B	C1431	168-1832-55	0.018uF K	C301	046-1032-78	0.01uF K B
C120	046-1042-78	0.1uF K B	C1432	043-0605-90	10V 2.2uF	C302	043-6200-90	6.3V 10uF
C1201	043-5600-90	0.10uF	C1434	168-1042-38	50V 0.1uF K	C303	043-6200-90	6.3V 10uF
C1202	043-7402-90	16V 22uF	C1435	046-1022-58	50V 1000pF	C304	043-0577-90	6.3V 1.0uF
C1203	043-0559-90	6.3V 22uF	C1436	045-1011-50	100pFJ CH	C305	043-0577-90	6.3V 1.0uF
C1204	043-7402-90	16V 22uF	C1437	045-1011-50	100pFJ CH	C306	046-1042-78	0.1uF K B
C1205	046-1042-78	0.1uF K B	C1438	168-1032-55	0.01uF K	C308	046-1042-78	0.1uF K B
C1206	046-1042-78	0.1uF K B	C1439	046-1022-58	50V 1000pF	C309	046-1042-78	0.1uF K B
C1209	046-1042-78	0.1uF K B	C144	046-1042-78	0.1uF K B	C311	046-1042-78	0.1uF K B
C121	046-1042-78	0.1uF K B	C1440	043-7700-90	50V 4.7uF	C312	046-1042-78	0.1uF K B
C1210	178-1062-88	10uF	C1441	ADZ0265	35V 47uF	C313	046-1042-78	0.1uF K B
C1211	043-7402-90	16V 22uF	C1442	168-1042-38	50V 0.1uF K	C314	046-1042-78	0.1uF K B
C1213	168-1052-78	16V 1uF K	C145	046-1042-78	0.1uF K B	C315	046-1042-78	0.1uF K B
C1215	043-0566-90	50V 2.2uF K	C146	046-1042-78	0.1uF K B	C317	046-1042-78	0.1uF K B
C1216	043-0566-90	50V 2.2uF K	C147	046-1022-58	50V 1000pF	C318	046-1042-78	0.1uF K B
C1218	043-0559-90	6.3V 22uF	C148	046-1042-78	0.1uF K B	C320	046-1042-78	0.1uF K B
C1219	043-0559-90	6.3V 22uF	C149	046-1022-58	50V 1000pF	C323	046-1042-78	0.1uF K B
C122	046-1042-78	0.1uF K B	C150	046-1042-78	0.1uF K B	C324	046-1042-78	0.1uF K B
C1223	043-0559-90	6.3V 22uF	C1501	ADZ0265	35V 47uF	C326	046-1042-78	0.1uF K B
C1226	043-6404-90	16V 10uF	C1502	168-1042-38	50V 0.1uF K	C327	046-1042-78	0.1uF K B
C123	046-1042-78	0.1uF K B	C1506	045-1011-50	100pFJ CH	C328	046-1042-78	0.1uF K B
C124	046-1022-58	50V 1000pF	C1507	043-0570-90	16V 2.2uF K	C329	046-1042-78	0.1uF K B
C1244	046-3332-78	0.033uF K B	C1508	043-0574-90	25V 1.0uF	C330	046-1042-78	0.1uF K B
C1245	046-1045-59	0.1uF Z F	C151	046-1042-78	0.1uF K B	C331	046-1042-78	0.1uF K B
C1249	168-1052-78	16V 1uF K	C1511	046-2232-78	0.022uF K B	C332	046-1042-78	0.1uF K B

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
C333	046-1042-78	0.1uF K B	C621	046-1042-78	0.1uF K B	FL1304	010-3303-50	BK20104M601-T
C334	046-1042-78	0.1uF K B	C622	043-7402-90	16V 22uF	FL1305	010-3303-50	BK20104M601-T
C335	046-1042-78	0.1uF K B	C623	046-1042-78	0.1uF K B	FL1306	010-3303-50	BK20104M601-T
C336	046-1042-78	0.1uF K B	C627	043-6400-90	16V 4.7uF K	FL1307	010-3303-50	BK20104M601-T
C337	046-1042-78	0.1uF K B	C628	043-6200-90	6.3V 10uF	IC1003	CUZ0502	TC7WH123FKF
C338	043-0577-90	6.3V 1.0uF	C629	046-1042-78	0.1uF K B	IC1004	051-5408-08	S-80921CNMC-G8RT2G
C339	043-0577-90	6.3V 1.0uF	C630	046-1042-78	0.1uF K B	IC1005	051-7222-60	MC74VHC1G08 DFT2G
C340	043-0577-90	6.3V 1.0uF	C632	168-1052-78	16V 1uF K	IC1007	051-7222-60	MC74VHC1G08 DFT2G
C341	046-1042-78	0.1uF K B	C633	168-1052-78	16V 1uF K	IC1008	051-7202-90	MC74VHC1G32 DFT2G
C342	046-1042-78	0.1uF K B	C701	045-8097-50	8pF +/-0.5pF CH	IC1009	051-7222-60	MC74VHC1G08 DFT2G
C343	046-1042-78	0.1uF K B	C702	045-8097-50	8pF +/-0.5pF CH	IC101	-----	DRA624AIZKKQ1 (App DSP) (BGA type) (676300-051)
C344	046-1042-78	0.1uF K B	C703	046-1032-78	0.01uF K B	IC1010	051-7281-60	MC74VHC1G14 DFT2G
C345	046-1042-78	0.1uF K B	C705	042-4033-90	6.3V 220uF	IC102	-----	K4B2G1646Q-BPH9 (DDR3 SDRAM) (FBGA) (933903-051)
C346	046-1042-78	0.1uF K B	C706	046-1042-78	0.1uF K B	IC102	-----	MT41K128M16JT-125E-IT:K (Thermal pad type) (933920-051)
C347	046-1042-78	0.1uF K B	C707	046-1042-78	0.1uF K B	IC103	-----	K4B2G1646Q-BPH9 (DDR3 SDRAM) (FBGA) (933903-051)
C348	046-1042-78	0.1uF K B	C708	046-1042-78	0.1uF K B	IC103	-----	MT41K128M16JT-125E-IT:K (Thermal pad type) (933920-051)
C349	046-1042-78	0.1uF K B	C709	046-1042-78	0.1uF K B	IC104	-----	MX29GL640EBTI-70G (FLASH MICOM) (Software should be written on production) (982690-051)
C350	046-1042-78	0.1uF K B	C710	168-4752-98	4.7uF K	IC1104	051-7563-90	NLV27WZ16DFT2G
C351	046-1042-78	0.1uF K B	C711	046-1042-78	0.1uF K B	IC1106	051-3776-90	NJM2815GM1-51A
C352	046-1042-78	0.1uF K B	C715	178-1232-78	0.012uF	IC1201	-----	SC183CULTRT (Regulator) (Exposed pad) (358800-051)
C353	046-1042-78	0.1uF K B	C716	046-1042-78	0.1uF K B	IC1203	-----	BD3572FP (Thermal pad) (358790-051)
C354	046-1042-78	0.1uF K B	C801	178-1062-88	10uF	IC1210	051-3328-90	S-1323B18NB-N8D-TF
C355	046-1042-78	0.1uF K B	C802	046-2232-78	0.022uF K B	IC1211	051-3519-90	NJU7771F05-TE2
C356	046-1042-78	0.1uF K B	C806	046-1042-78	0.1uF K B	IC1212	-----	SC183CULTRT (Regulator) (Exposed pad) (358800-051)
C357	046-1042-78	0.1uF K B	C807	043-0548-50	10V 2.2uF	IC1213	051-3519-90	NJU7771F05-TE2
C358	046-1042-78	0.1uF K B	C808	046-1022-58	50V 1000pF	IC1214	-----	BD00IA5EEFJ-ME2 (LDO REG) (Exposed Pad) (376390-051)
C359	046-1042-78	0.1uF K B	C809	178-1062-88	10uF	IC1301	051-6761-80	S-8412AAAW7I-TCBB30
C360	046-1042-78	0.1uF K B	C810	046-2222-58	2200pF K B	IC1401	-----	BD81A04EFV-M (Thermal pad) (611390-051)
C361	046-1042-78	0.1uF K B	C811	046-6822-58	6800pF K B	IC1501	-----	OZ528ILN-B1-0-TR (Thermal pad) (394090-051)
C362	046-1042-78	0.1uF K B	C812	046-1042-78	0.1uF K B			
C363	046-1042-78	0.1uF K B	C814	046-1042-78	0.1uF K B			
C364	046-1042-78	0.1uF K B	C815	178-1062-88	10uF			
C365	046-1042-78	0.1uF K B	C816	046-1042-78	0.1uF K B			
C366	046-1042-78	0.1uF K B	C817	046-3332-78	0.033uF K B			
C367	046-1042-78	0.1uF K B	C818	046-1042-78	0.1uF K B			
C368	046-1042-78	0.1uF K B	C819	178-1062-88	10uF			
C369	046-1042-78	0.1uF K B	C820	043-0605-90	10V 2.2uF			
C370	046-1042-78	0.1uF K B	C821	043-0577-90	6.3V 1.0uF			
C371	046-1042-78	0.1uF K B	C822	046-1042-78	0.1uF K B			
C372	178-1062-88	10uF	C823	178-1062-88	10uF			
C373	046-1042-78	0.1uF K B	C830	045-2201-50	22pFJ CH			
C374	043-7201-90	6.3V 100uF	C833	178-1062-88	10uF			
C375	046-1042-78	0.1uF K B	C902	046-1042-78	0.1uF K B			
C376	046-1032-78	0.01uF K B	C903	168-1042-38	50V 0.1uF K			
C377	046-1022-58	50V 1000pF	C912	168-1042-38	50V 0.1uF K			
C378	046-1022-58	50V 1000pF	CN1601	074-2249-04	SOCKET(4P)			
C379	046-1042-78	0.1uF K B	D1	001-2640-90	D1FJ4			
C380	046-1042-78	0.1uF K B	D1002	001-1304-90	DAN202U			
C381	046-1042-78	0.1uF K B	D1003	001-1325-90	1SS387			
C382	046-1042-78	0.1uF K B	D1103	001-4910-91	DF5A5.6F			
C383	046-1042-78	0.1uF K B	D1104	001-4910-91	DF5A5.6F			
C384	046-1042-78	0.1uF K B	D1109	001-2630-90	1SS420-TPL3,F			
C385	046-1032-78	0.01uF K B	D1111	001-2412-90	RR264M-400			
C386	046-1042-78	0.1uF K B	D1112	001-0580-90	1SS352			
C387	043-0577-90	6.3V 1.0uF	D1114	001-2412-90	RR264M-400			
C388	046-1032-78	0.01uF K B	D1116	001-2630-90	1SS420-TPL3,F			
C389	046-1032-78	0.01uF K B	D1117	001-2651-90	RSX101M-30TR			
C390	046-1032-78	0.01uF K B	D1501	001-2630-90	1SS420-TPL3,F			
C413	046-1042-78	0.1uF K B	D1502	001-2630-90	1SS420-TPL3,F			
C501	046-1032-78	0.01uF K B	D1503	001-2640-90	D1FJ4			
C502	178-1062-88	10uF	D1504	001-2620-90	RB060L-40			
C503	046-1032-78	0.01uF K B	D1505	001-2640-90	D1FJ4			
C505	046-3332-78	0.033uF K B	D2	001-2640-90	D1FJ4			
C506	046-1032-78	0.01uF K B	D702	001-2630-90	1SS420-TPL3,F			
C507	046-1042-78	0.1uF K B	D904	001-2630-90	1SS420-TPL3,F			
C508	046-1042-78	0.1uF K B	D905	001-2630-90	1SS420-TPL3,F			
C509	043-6200-90	6.3V 10uF	D906	001-2630-90	1SS420-TPL3,F			
C510	046-1032-78	0.01uF K B	D907	001-2630-90	1SS420-TPL3,F			
C511	046-1042-78	0.1uF K B	D908	001-2630-90	1SS420-TPL3,F			
C514	043-6200-90	6.3V 10uF	D909	001-2630-90	1SS420-TPL3,F			
C516	045-1007-50	10 +/-0.5pF CH	D911	001-4910-91	DF5A5.6F			
C517	045-1007-50	10 +/-0.5pF CH	D912	001-4910-91	DF5A5.6F			
C518	046-1032-78	0.01uF K B	FL1301	BMZ0251	BK20104L121-T			
C520	045-5096-50	5pF +/-0.25pF CH	FL1302	010-3303-50	BK20104M601-T			
C620	046-1042-78	0.1uF K B	FL1303	010-3303-50	BK20104M601-T			

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
IC1601	051-6112-90	BU21024FV-ME2	L607	010-3104-50	30 ohm/100MHz	R111	033-3301-15	1/16W 33 ohm J
IC201	051-5460-90	R3132Q30EA8-TR-F	L701	010-2279-50	4.7uH	R1114	119-1021-15	1/10W 1k ohm
IC202	051-6934-90	MFI341S2313	L802	010-3127-91	220 ohm/100MHz	R1115	119-1021-15	1/10W 1k ohm
IC206	051-5460-90	R3132Q30EA8-TR-F	L804	BMZ0211	BLM18PG121SN 1D	R112	033-3301-15	1/16W 33 ohm J
IC501	-----	AK8859VN-L (Video-Decoder) (Thermal pad) (647790-051)	L902	010-3104-50	30 ohm/100MHz	R1121	119-1021-15	1/10W 1k ohm
IC603	051-3579-90	S1112B15MCL 6ATFG	NF1103	060-3117-51	CKD510JB1E223 ST	R1122	119-1031-15	1/10W 10k ohm
IC604	051-3766-90	BD00HC5EEFJ-ME2	NF1104	060-3117-51	CKD510JB1E223 ST	R1124	033-1011-15	1/16W 100 ohm J
IC701	051-5449-90	BU4229G	NF1601	010-3303-90	120 ohm/100MHz x4	R1125	033-1031-15	1/16W 10k ohm J
IC702	-----	uPD70F3333 GC(A)-UEU-AX (MICOM) (Software should be written on production) (032920-052)	P1103	076-6023-07	7P	R1126	033-1031-15	1/16W 10k ohm J
IC801	051-3067-90	NJM14558V	P1104	074-1302-28	28P	R1142	033-2221-15	1/16W 2.2k ohm J
IC803	060-8162-90	BT MODULE (UGXZD-105A)	P1201	076-6030-60	10P	R1143	033-0000-05	1/16W 0 ohm
IC804	051-6533-90	AK7756VF	P1203	076-0569-02	2P	R1145	116-1021-15	1/4W 1k ohm
IC901	051-7222-60	MCT74VHC1G08 DFT2G	Q1001	125-0035-91	DTA114EUBTL	R1146	116-1021-15	1/4W 1k ohm
J1001	074-8023-51	SOCKET(SD)	Q1003	125-2046-91	DTC114EUBTL	R1147	116-1021-15	1/4W 1k ohm
J1101	074-4105-00	SOCKET(4P)	Q1004	125-0035-91	DTA114EUBTL	R1148	033-2221-15	1/16W 2.2k ohm J
J1301	074-2248-60	SOCKET60P	Q1006	125-2046-91	DTC114EUBTL	R1149	033-1031-15	1/16W 10k ohm J
J601	074-2248-40	SOCKET(40P)	Q1010	191-1197-50	2SB1197K Q,R	R115	033-3301-15	1/16W 33 ohm J
J901	074-2248-80	SOCKET80P	Q1011	125-2046-91	DTC114EUBTL	R1150	033-1031-15	1/16W 10k ohm J
J902	074-2248-30	SOCKET30P	Q1106	190-1576-60	2SA1576UBTL	R1151	033-1021-15	1/16W 1k ohm J
L1002	BMZ0211	BLM18PG121 SN1D	Q1107	125-2046-91	DTC114EUBTL	R1152	033-2221-15	1/16W 2.2k ohm J
L1101	BEZ0122	DLP11SN900HL2L	Q1109	190-1576-60	2SA1576UBTL	R1153	033-1021-15	1/16W 1k ohm J
L1105	010-3442-50	LBM2016T3R3J	Q1110	192-4081-00	2SC4081	R1154	033-5621-15	1/16W 5.6k ohm J
L1201	010-3104-50	30 ohm/100MHz	Q1111	192-4081-00	2SC4081	R1155	033-1031-15	1/16W 10k ohm J
L1202	010-3104-50	30 ohm/100MHz	Q1205	125-2046-91	DTC114EUBTL	R1156	033-3931-15	1/16W 39k ohm J
L1203	010-3104-50	30 ohm/100MHz	Q1206	125-7011-90	RSR025P03TL	R1157	119-3921-15	1/10W 3.9k ohm
L1204	010-3104-50	30 ohm/100MHz	Q1408	125-8032-90	RVQ040N05 TR	R1158	116-1011-15	1/4W 100 ohm
L1205	010-3104-50	30 ohm/100MHz	Q1409	192-4081-00	2SC4081	R1159	033-1021-15	1/16W 1k ohm J
L1206	010-3548-50	2.2uH	Q1410	192-4081-00	2SC4081	R116	033-1031-15	1/16W 10k ohm J
L1210	010-3548-50	2.2uH	Q1411	125-2046-91	DTC114EUBTL	R1160	033-2221-15	1/16W 2.2k ohm J
L1301	BMZ0211	BLM18PG121 SN1D	Q1502	CA11433	2SA1576AT106R	R1161	033-0000-05	1/16W 0 ohm
L1303	010-3126-52	470ohm	Q1505	CA11433	2SA1576AT106R	R1166	033-3321-15	1/16W 3.3k ohm J
L1401	BAZ0381	56uH	Q1507	CA11433	2SA1576AT106R	R1167	033-6821-15	1/16W 6.8k ohm J
L1402	010-3523-50	CDRH5D28 RHPNP-220MC	Q1508	192-4081-00	2SC4081	R1168	033-4711-15	1/16W 470 ohm J
L1503	010-3502-90	10uH	Q1513	125-2046-91	DTC114EUBTL	R1172	116-1011-15	1/4W 100 ohm
L1505	010-3502-90	10uH	Q1514	125-2046-92	DTC124EUBTL	R1177	033-1021-15	1/16W 1k ohm J
L1506	010-3502-90	10uH	Q601	191-1197-50	2SB1197K Q,R	R1188	032-0221-74	1/16W 10k ohm 1%
L1601	010-3127-91	220 ohm/100MHz	Q602	191-1197-50	2SB1197K Q,R	R1211	032-0221-04	1/16W 10 ohm F
L200	010-3126-52	470ohm	Q603	125-2046-91	DTC114EUBTL	R1220	032-0221-30	1/16W 150k ohm F
L301	BMZ0211	BLM18PG121SN 1D	Q604	125-2046-91	DTC114EUBTL	R1221	032-0221-10	1/16W 15k ohm F
L302	BMZ0211	BLM18PG121SN 1D	Q701	125-2046-91	DTC114EUBTL	R1222	032-0221-06	1/16W 100k ohm F
L303	BMZ0211	BLM18PG121SN 1D	Q901	192-4081-00	2SC4081	R1232	032-0221-74	1/16W 10k ohm 1%
L304	BMZ0211	BLM18PG121SN 1D	Q902	192-4081-00	2SC4081	R1233	032-0221-63	1/16W 12k ohm F
L305	BMZ0211	BLM18PG121SN 1D	R1007	033-3301-15	1/16W 33 ohm J	R1234	032-0221-96	1/16W 820 ohm 1%
L501	BMZ0211	BLM18PG121SN 1D	R1008	033-3301-15	1/16W 33 ohm J	R124	033-1001-15	1/16W 10 ohm J
L502	010-3417-90	10uH	R1009	033-3301-15	1/16W 33 ohm J	R125	033-1001-15	1/16W 10 ohm J
L503	BMZ0211	BLM18PG121SN 1D	R101	033-0000-05	1/16W 0 ohm	R126	032-0221-90	1/16W 240 ohm 1%
L504	010-3125-90	120 ohm/100MHz	R1010	033-3301-15	1/16W 33 ohm J	R127	032-0221-90	1/16W 240 ohm 1%
L604	010-3104-50	30 ohm/100MHz	R1011	033-3301-15	1/16W 33 ohm J	R128	032-0221-98	1/16W 120 ohm 1%
L605	010-3104-50	30 ohm/100MHz	R1012	033-1011-15	1/16W 100 ohm J	R129	032-0221-99	1/16W 100 ohm 1%
L606	010-3104-50	30 ohm/100MHz	R1014	033-4731-15	1/16W 47k ohm J	R1292	119-2731-15	1/10W 27k ohm
			R102	033-0000-05	1/16W 0 ohm	R1294	119-1231-15	1/10W 12k ohm
			R103	033-0000-05	1/16W 0 ohm	R1298	033-1001-15	1/16W 10 ohm J
			R1032	032-0221-75	1/16W 47k ohm F	R130	032-0221-99	1/16W 100 ohm 1%
			R1033	033-4731-15	1/16W 47k ohm J	R131	032-0221-99	1/16W 100 ohm 1%
			R1036	033-1031-15	1/16W 10k ohm J	R132	032-0221-99	1/16W 100 ohm 1%
			R1037	033-1041-15	1/16W 100k ohm J	R133	032-0221-99	1/16W 100 ohm 1%
			R1038	033-4721-15	1/16W 4.7k ohm J	R1334	119-1031-15	1/10W 10k ohm
			R1039	033-1031-15	1/16W 10k ohm J	R1335	033-3301-15	1/16W 33 ohm J
			R104	032-0225-53	1/16W 49.9 ohm	R1337	119-1031-15	1/10W 10k ohm
			R1040	033-4731-15	1/16W 47k ohm J	R134	032-0221-99	1/16W 100 ohm 1%
			R1041	033-4731-15	1/16W 47k ohm J	R1340	119-1031-15	1/10W 10k ohm
			R1042	033-4731-15	1/16W 47k ohm J	R1342	119-1031-15	1/10W 10k ohm
			R1043	033-1011-15	1/16W 100 ohm J	R1343	119-1031-15	1/10W 10k ohm
			R1045	033-4731-15	1/16W 47k ohm J	R1344	119-1031-15	1/10W 10k ohm
			R105	033-3301-15	1/16W 33 ohm J	R135	032-0221-99	1/16W 100 ohm 1%
			R1050	033-1031-15	1/16W 10k ohm J	R136	032-0221-99	1/16W 100 ohm 1%
			R1051	033-5611-15	1/16W 560 ohm J	R1365	033-1011-15	1/16W 100 ohm J
			R1053	033-2221-15	1/16W 2.2k ohm J	R1366	032-0221-91	1/16W 18 ohm F
			R106	033-1031-15	1/16W 10k ohm J	R1370	119-4301-15	1/10W 43 ohm
			R109	033-3301-15	1/16W 33 ohm J	R1374	032-0221-91	1/16W 18 ohm F
			R110	033-3301-15	1/16W 33 ohm J	R1375	119-1611-15	1/10W 160 ohm
						R138	033-1031-15	1/16W 10k ohm J
						R1380	119-4301-15	1/10W 43 ohm
						R1381	119-1611-15	1/10W 160 ohm
						R1383	032-0221-15	1/16W 56 ohm

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
R1384	032-0221-17	1/16W 180 ohm	R1610	AQZ0462	1/16W 330k ohm	R294	033-3301-15	1/16W 33 ohm J
R1385	032-0221-17	1/16W 180 ohm	R1611	AQZ0462	1/16W 330k ohm	R295	033-0000-05	1/16W 0 ohm
R1386	032-0221-15	1/16W 56 ohm	R1612	AQZ0462	1/16W 330k ohm	R296	033-1031-15	1/16W 10k ohm J
R1387	032-0221-03	1/16W 22 ohm 1%	R1621	033-4721-15	1/16W 4.7k ohm J	R297	033-1031-15	1/16W 10k ohm J
R140	033-3301-15	1/16W 33 ohm J	R1622	033-3301-15	1/16W 33 ohm J	R304	032-0221-99	1/16W 100 ohm 1%
R141	033-3301-15	1/16W 33 ohm J	R201	033-3301-15	1/16W 33 ohm J	R305	032-0221-99	1/16W 100 ohm 1%
R142	033-3301-15	1/16W 33 ohm J	R202	033-3301-15	1/16W 33 ohm J	R307	033-0000-05	1/16W 0 ohm
R143	033-0000-05	1/16W 0 ohm	R203	033-4721-15	1/16W 4.7k ohm J	R401	033-1021-15	1/16W 1k ohm J
R1454	032-0246-50	0.75W 0.2 ohm	R204	033-3301-15	1/16W 33 ohm J	R402	033-1021-15	1/16W 1k ohm J
R1455	032-0246-50	0.75W 0.2 ohm	R205	033-3301-15	1/16W 33 ohm J	R408	033-1031-15	1/16W 10k ohm J
R1457	033-2231-15	1/16W 22k ohm J	R206	033-3301-15	1/16W 33 ohm J	R411	033-1031-15	1/16W 10k ohm J
R1459	119-4791-15	1/10W 4.7 ohm	R207	033-3301-15	1/16W 33 ohm J	R412	033-1031-15	1/16W 10k ohm J
R1460	033-2231-15	1/16W 22k ohm J	R208	033-3301-15	1/16W 33 ohm J	R413	033-1031-15	1/16W 10k ohm J
R1461	033-2231-15	1/16W 22k ohm J	R209	033-3301-15	1/16W 33 ohm J	R417	033-1031-15	1/16W 10k ohm J
R1462	033-2231-15	1/16W 22k ohm J	R210	032-0221-95	1/16W 2.7k ohm F	R422	033-1031-15	1/16W 10k ohm J
R1463	032-0221-56	1/16W 22k ohm F	R211	033-3301-15	1/16W 33 ohm J	R424	033-1031-15	1/16W 10k ohm J
R1464	032-0210-88	1/10W 5.1k ohm F	R212	033-0000-05	1/16W 0 ohm	R425	033-1031-15	1/16W 10k ohm J
R1466	032-0221-59	1/16W 220 ohm F	R213	033-3301-15	1/16W 33 ohm J	R428	033-1031-15	1/16W 10k ohm J
R1467	032-0221-75	1/16W 47k ohm F	R214	033-3301-15	1/16W 33 ohm J	R430	033-1031-15	1/16W 10k ohm J
R1468	032-0221-59	1/16W 220 ohm F	R215	033-3301-15	1/16W 33 ohm J	R501	033-8201-15	1/16W 82 ohm J
R1469	033-5121-15	1/16W 5.1k ohm	R216	033-3301-15	1/16W 33 ohm J	R504	032-0221-88	1/16W 30 ohm F
R1470	033-2231-15	1/16W 22k ohm J	R217	033-3301-15	1/16W 33 ohm J	R505	033-4701-15	1/16W 47 ohm J
R1471	032-0221-10	1/16W 15k ohm F	R218	032-0221-01	1/16W 47 ohm F	R506	032-0221-72	1/16W 470 ohm F
R1472	032-0221-74	1/16W 10k ohm 1%	R219	033-0000-05	1/16W 0 ohm	R507	032-0221-61	1/16W 6.8k ohm F
R1473	032-0221-56	1/16W 22k ohm F	R220	033-0000-05	1/16W 0 ohm	R627	033-4731-15	1/16W 47k ohm J
R1474	032-0221-56	1/16W 22k ohm F	R222	033-0000-05	1/16W 0 ohm	R628	033-3911-15	1/16W 390 ohm J
R1476	032-0221-06	1/16W 100k ohm F	R224	033-3301-15	1/16W 33 ohm J	R633	033-1041-15	1/16W 100k ohm J
R1477	032-0221-56	1/16W 22k ohm F	R225	033-3301-15	1/16W 33 ohm J	R634	033-1031-15	1/16W 10k ohm J
R1478	119-0000-05	1/10W 0 ohm JW	R227	033-1031-15	1/16W 10k ohm J	R635	033-1031-15	1/16W 10k ohm J
R1481	119-0000-05	1/10W 0 ohm JW	R229	033-3301-15	1/16W 33 ohm J	R636	033-5611-15	1/16W 560 ohm J
R1482	119-0000-05	1/10W 0 ohm JW	R230	033-3301-15	1/16W 33 ohm J	R637	033-5611-15	1/16W 560 ohm J
R1483	033-2231-15	1/16W 22k ohm J	R231	033-3301-15	1/16W 33 ohm J	R638	033-1041-15	1/16W 100k ohm J
R1484	033-2231-15	1/16W 22k ohm J	R232	033-0000-05	1/16W 0 ohm	R640	032-0221-51	1/16W 4.7k ohm F
R1485	033-2231-15	1/16W 22k ohm J	R236	033-1031-15	1/16W 10k ohm J	R641	032-0221-56	1/16W 22k ohm F
R1487	032-0221-61	1/16W 6.8k ohm F	R237	033-1031-15	1/16W 10k ohm J	R642	032-0221-83	1/16W 3.3k ohm F
R1488	032-0221-95	1/16W 2.7k ohm F	R238	033-1031-15	1/16W 10k ohm J	R651	033-0000-05	1/16W 0 ohm
R1501	033-4721-15	1/16W 4.7k ohm J	R239	033-0000-05	1/16W 0 ohm	R701	032-0221-61	1/16W 6.8k ohm F
R1504	119-2711-15	1/10W 270 ohm	R240	033-0000-05	1/16W 0 ohm	R702	033-4731-15	1/16W 47k ohm J
R1505	033-4721-15	1/16W 4.7k ohm J	R241	033-3301-15	1/16W 33 ohm J	R703	033-1041-15	1/16W 100k ohm J
R1506	033-1031-15	1/16W 10k ohm J	R242	033-1031-15	1/16W 10k ohm J	R704	033-1041-15	1/16W 100k ohm J
R1509	033-1031-15	1/16W 10k ohm J	R244	033-0000-05	1/16W 0 ohm	R705	033-4731-15	1/16W 47k ohm J
R1510	032-0221-59	1/16W 220 ohm F	R245	033-0000-05	1/16W 0 ohm	R706	033-1041-15	1/16W 100k ohm J
R1512	032-0221-59	1/16W 220 ohm F	R246	033-0000-05	1/16W 0 ohm	R707	033-1041-15	1/16W 100k ohm J
R1514	032-0221-83	1/16W 3.3k ohm F	R247	033-3301-15	1/16W 33 ohm J	R708	033-1041-15	1/16W 100k ohm J
R1516	032-0210-02	1/10W 56k ohm 1%	R250	033-0000-05	1/16W 0 ohm	R709	033-1021-15	1/16W 1k ohm J
R1519	032-0210-58	1/10W 12k ohm F	R252	033-3301-15	1/16W 33 ohm J	R710	033-4731-15	1/16W 47k ohm J
R1520	032-0210-17	1/10W 6.8k ohm F	R254	033-3301-15	1/16W 33 ohm J	R711	033-1011-15	1/16W 100 ohm J
R1521	033-0000-05	1/16W 0 ohm	R255	033-1031-15	1/16W 10k ohm J	R712	033-1011-15	1/16W 100 ohm J
R1522	032-0210-88	1/10W 5.1k ohm F	R256	033-4721-15	1/16W 4.7k ohm J	R713	033-1011-15	1/16W 100 ohm J
R1523	032-0210-58	1/10W 12k ohm F	R257	033-4721-15	1/16W 4.7k ohm J	R714	033-1011-15	1/16W 100 ohm J
R1524	032-0210-59	1/10W 5.6k ohm F	R258	033-3321-15	1/16W 3.3k ohm J	R715	033-1011-15	1/16W 100 ohm J
R1525	032-0210-72	1/10W 1.8k ohm 1%	R259	033-3321-15	1/16W 3.3k ohm J	R716	033-1011-15	1/16W 100 ohm J
R1527	032-0210-40	1/10W 1.3k ohm F	R260	033-0000-05	1/16W 0 ohm	R717	033-4731-15	1/16W 47k ohm J
R1528	032-0210-88	1/10W 5.1k ohm F	R261	033-0000-05	1/16W 0 ohm	R718	033-1031-15	1/16W 10k ohm J
R1529	032-0210-88	1/10W 5.1k ohm F	R262	032-0221-32	1/16W 220k ohm F	R720	032-0221-74	1/16W 10k ohm 1%
R1531	032-0210-57	1/10W 4.7k ohm F	R263	033-4721-15	1/16W 4.7k ohm J	R721	032-0221-74	1/16W 10k ohm 1%
R1533	032-0210-95	1/10W 2k ohm F	R264	033-4721-15	1/16W 4.7k ohm J	R722	033-0000-05	1/16W 0 ohm
R1536	032-0210-16	1/10W 1.2k ohm F	R265	033-4721-15	1/16W 4.7k ohm J	R723	033-0000-05	1/16W 0 ohm
R1540	033-3321-15	1/16W 3.3k ohm J	R267	033-0000-05	1/16W 0 ohm	R724	033-3331-15	1/16W 33k ohm J
R1543	033-2231-15	1/16W 22k ohm J	R269	033-0000-05	1/16W 0 ohm	R725	033-3331-15	1/16W 33k ohm J
R1546	033-2231-15	1/16W 22k ohm J	R272	033-3301-15	1/16W 33 ohm J	R726	033-0000-05	1/16W 0 ohm
R1547	033-2231-15	1/16W 22k ohm J	R273	033-0000-05	1/16W 0 ohm	R727	033-0000-05	1/16W 0 ohm
R1548	033-2231-15	1/16W 22k ohm J	R276	033-0000-05	1/16W 0 ohm	R728	119-3331-15	1/10W 33k ohm
R1550	033-2231-15	1/16W 22k ohm J	R277	033-0000-05	1/16W 0 ohm	R729	033-4731-15	1/16W 47k ohm J
R1557	033-3331-15	1/16W 33k ohm J	R278	033-0000-05	1/16W 0 ohm	R730	033-0000-05	1/16W 0 ohm
R1558	033-2231-15	1/16W 22k ohm J	R279	033-0000-05	1/16W 0 ohm	R731	033-1011-15	1/16W 100 ohm J
R1564	117-1021-15	1/8W 1k ohm	R282	033-0000-05	1/16W 0 ohm	R732	033-1041-15	1/16W 100k ohm J
R1569	117-0000-05	1/8W 0 ohm JW	R283	033-0000-05	1/16W 0 ohm	R733	033-1041-15	1/16W 100k ohm J
R1578	033-1031-15	1/16W 10k ohm J	R286	033-1031-15	1/16W 10k ohm J	R734	033-1041-15	1/16W 100k ohm J
R1582	116-0000-05	1/4W 0 ohm JW	R287	033-1041-15	1/16W 100k ohm J	R735	033-1041-15	1/16W 100k ohm J
R1603	032-0221-03	1/16W 22 ohm 1%	R288	033-1031-15	1/16W 10k ohm J	R736	033-1021-15	1/16W 1k ohm J
R1605	032-0221-03	1/16W 22 ohm 1%	R289	033-1031-15	1/16W 10k ohm J	R737	033-1021-15	1/16W 1k ohm J
R1607	032-0221-03	1/16W 22 ohm 1%	R290	033-1031-15	1/16W 10k ohm J	R738	033-1041-15	1/16W 100k ohm J
R1608	032-0221-03	1/16W 22 ohm 1%	R291	033-0000-05	1/16W 0 ohm	R739	033-4721-15	1/16W 4.7k ohm J
R1609	AQZ0462	1/16W 330k ohm	R292	033-3301-15	1/16W 33 ohm J	R740	033-4731-15	1/16W 47k ohm J

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
R741	033-4731-15	1/16W 47k ohm J	R943	033-3301-15	1/16W 33 ohm J	RN217	050-0156-78	1/16W 1k ohm x4
R742	033-1011-15	1/16W 100 ohm J	R949	033-3301-15	1/16W 33 ohm J	RN403	050-0156-57	1/16W 10k ohm x4
R743	033-1041-15	1/16W 100k ohm J	R951	033-1031-15	1/16W 10k ohm J	RN404	050-0156-57	1/16W 10k ohm x4
R745	033-1041-15	1/16W 100k ohm J	R954	033-1011-15	1/16W 100 ohm J	RN501	050-0156-59	1/16W 33 ohm x4
R747	033-4731-15	1/16W 47k ohm J	R955	033-1011-15	1/16W 100 ohm J	RN502	050-0156-59	1/16W 33 ohm x4
R748	032-0210-26	1/10W 82 ohm F	R956	033-1011-15	1/16W 100 ohm J	RN702	050-0156-63	1/16W 47k ohm x4
R749	032-0210-26	1/10W 82 ohm F	R957	033-1031-15	1/16W 10k ohm J	RN703	050-0156-64	1/16W 100k ohm x4
R750	032-0210-00	1/10W 330 ohm F	R958	033-1031-15	1/16W 10k ohm J	RN901	050-0156-59	1/16W 33 ohm x4
R751	032-0210-00	1/10W 330 ohm F	R960	116-2221-15	1/4W 2.2k ohm	RN918	050-0156-59	1/16W 33 ohm x4
R752	033-4731-15	1/16W 47k ohm J	R961	033-4731-15	1/16W 47k ohm J	RN919	050-0156-59	1/16W 33 ohm x4
R753	033-0000-05	1/16W 0 ohm	R962	033-0000-05	1/16W 0 ohm	RN922	050-0156-52	1/16W 100 ohm x4
R755	033-0000-05	1/16W 0 ohm	RN1002	050-0156-63	1/16W 47k ohm x4	RN923	050-0156-52	1/16W 100 ohm x4
R756	033-4731-15	1/16W 47k ohm J	RN101	050-0156-53	1/16W 0 ohm x4	RN924	050-0156-57	1/16W 10k ohm x4
R763	033-1041-15	1/16W 100k ohm J	RN102	050-0156-53	1/16W 0 ohm x4	RN925	050-0156-57	1/16W 10k ohm x4
R764	033-1041-15	1/16W 100k ohm J	RN103	050-0156-53	1/16W 0 ohm x4	SUP1101	001-4323-90	RCLAMP0502A
R765	033-4731-15	1/16W 47k ohm J	RN104	050-0156-53	1/16W 0 ohm x4	TH1100	002-0335-50	SMD1812P050
R801	033-1041-15	1/16W 100k ohm J	RN105	050-0156-53	1/16W 0 ohm x4			TF/30
R802	032-0221-08	1/16W 1k ohm F	RN106	050-0156-53	1/16W 0 ohm x4	TH1202	002-0335-51	SMD1812P150
R803	032-0221-79	1/16W 1.2k ohm F	RN107	050-0156-59	1/16W 33 ohm x4			TF/24
R804	032-0221-33	1/16W 20k ohm F	RN108	050-0156-59	1/16W 33 ohm x4	TH701	002-0315-00	TN10-3U153JT
R805	033-1031-15	1/16W 10k ohm J	RN109	050-0156-59	1/16W 33 ohm x4	VR1108	001-9213-50	EZJZ1V270EA
R806	033-1031-15	1/16W 10k ohm J	RN110	050-0156-59	1/16W 33 ohm x4	VR1109	001-9213-50	EZJZ1V270EA
R807	032-0221-51	1/16W 4.7k ohm F	RN112	050-0156-59	1/16W 33 ohm x4	VR1110	001-9213-50	EZJZ1V270EA
R808	033-0000-05	1/16W 0 ohm	RN113	050-0156-59	1/16W 33 ohm x4	VR1111	001-9213-50	EZJZ1V270EA
R809	033-1031-15	1/16W 10k ohm J	RN114	050-0156-59	1/16W 33 ohm x4	VR1112	001-9213-50	EZJZ1V270EA
R811	033-0000-05	1/16W 0 ohm	RN115	050-0156-59	1/16W 33 ohm x4	VR1113	001-9213-50	EZJZ1V270EA
R812	033-1011-15	1/16W 100 ohm J	RN116	050-0156-59	1/16W 33 ohm x4	VR1114	001-9213-50	EZJZ1V270EA
R813	033-1011-15	1/16W 100 ohm J	RN117	050-0156-59	1/16W 33 ohm x4	VR1116	001-9213-50	EZJZ1V270EA
R818	033-0000-05	1/16W 0 ohm	RN1301	050-0156-66	1/16W 47 ohm x4	VR1117	001-9213-50	EZJZ1V270EA
R828	033-0000-05	1/16W 0 ohm	RN1302	050-0140-67	1/32W 220 ohm x4J	VR1118	001-9213-50	EZJZ1V270EA
R831	033-1011-15	1/16W 100 ohm J	RN1303	050-0140-67	1/32W 220 ohm x4J	X201	061-3575-70	FA-238
R837	033-1011-15	1/16W 100 ohm J	RN1304	050-0140-67	1/32W 220 ohm x4J			22.5792MHz
R838	033-1031-15	1/16W 10k ohm J	RN1305	050-0140-67	1/32W 220 ohm x4J	X202	061-3609-90	FA-238 20MHz
R839	033-0000-05	1/16W 0 ohm	RN1306	050-0140-67	1/32W 220 ohm x4J	X204	061-9227-90	32.768kHz
R840	032-0221-62	1/16W 8.2k ohm F	RN1307	050-0140-67	1/32W 220 ohm x4J	X501	061-3581-70	FA-238 24.576MHz
R841	033-1031-15	1/16W 10k ohm J	RN201	050-0156-59	1/16W 33 ohm x4	X701	061-3574-90	3.981312MHz
R844	119-0000-05	1/10W 0 ohm JW	RN203	050-0156-59	1/16W 33 ohm x4	ZD1103	001-4305-32	UDZSTE-17 18B
R845	119-0000-05	1/10W 0 ohm JW	RN204	050-0156-59	1/16W 33 ohm x4	ZD1501	001-4305-23	UDZSTE-17 7.5B
R847	032-0221-95	1/16W 2.7k ohm F	RN205	050-0156-59	1/16W 33 ohm x4	ZD1601	001-4342-50	TFZFHTR6.2B
R853	033-1031-15	1/16W 10k ohm J	RN206	050-0156-59	1/16W 33 ohm x4	ZD1602	001-4342-50	TFZFHTR6.2B
R854	033-1031-15	1/16W 10k ohm J	RN207	050-0156-53	1/16W 0 ohm x4	ZD1603	001-4342-50	TFZFHTR6.2B
R855	033-0000-05	1/16W 0 ohm	RN208	050-0156-59	1/16W 33 ohm x4	ZD1604	001-4342-50	TFZFHTR6.2B
R856	032-0221-01	1/16W 47 ohm F	RN209	050-0156-59	1/16W 33 ohm x4	ZD901	001-4305-20	UDZSTE-17 5.6B
R860	033-0000-05	1/16W 0 ohm	RN210	050-0156-59	1/16W 33 ohm x4	ZD902	001-4305-20	UDZSTE-17 5.6B
R861	033-0000-05	1/16W 0 ohm	RN211	050-0156-59	1/16W 33 ohm x4	ZD903	001-4305-20	UDZSTE-17 5.6B
R862	033-0000-05	1/16W 0 ohm	RN213	050-0156-59	1/16W 33 ohm x4	PWB	039-4480-00	PWB(WITHOUT COMPONENTS)
R863	033-1011-15	1/16W 100 ohm J	RN214	050-0156-59	1/16W 33 ohm x4			
R942	033-3301-15	1/16W 33 ohm J	RN216	050-0156-59	1/16W 33 ohm x4			