


EXPLODED VIEW

Block No.M1MM



Parts with the exploded numbers larger than 700 are not supplied.

created date:2016-03-29

No.WA145

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
------	------------	-----------	------------	-------------	-----	-------

EXPLODED VIEW <M1MM>

△	DC1	QAM1623-002	DC CORD		1	K0,K2
△	DC2	QAM1333-001	DC CORD		1	E2,E3
△	DC2	QAM1516-001	DC CORD		1	R0
△	F901	FZB10BT-100	BLADE FUSE		1	
	FC1	E3F-0028-00	FLAT CABLE		1	
	LCD1	B3H-0007-00	LCD		1	
	PA1	A6D-0014-02	PANEL		1	E2,K0,K2,E3
	PA1	A6D-0014-08	PANEL		1	R0
	RC1	QAL1303-004	REMOCON		1	R0,K0,K2
	A	QYSDSF2008ZA	TAP SCREW	M2 x 8mm	4	
	B	GE40377-002A	SPECIAL SCREW		2	
	C	QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	3	
	D	QYSDST2610ZA	TAP SCREW	M2.6 x 10mm	1	
	E	QYSDST2608ZA	TAP SCREW	M2.6 x 8mm	2	
	F	GE40377-005A	SPECIAL SCREW		2	
	G	QYSDSG3006ZA	TAP SCREW	M3 x 6mm	1	E2,K0,K2,E3
	G	QYSPSG3008ZA	TAP SCREW	M3 x 8mm	1	R0
	H	QYSDSF2608ZA	TAP SCREW	M2.6 x 8mm	1	
	J	LV44800-002A	SPECIAL SCREW		2	
	K	QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	1	K0
	203	W0C-0055-10	BT MODULE		1	E2,K0,K2,E3
	203	W0C-0055-20	CIRCUIT MODULE		1	R0
	213	A2C-0006-01	SUB PANEL		1	E2,E3
	213	A2C-0006-02	SUB PANEL		1	R0
	213	A2C-0006-00	SUB PANEL		1	K0,K2
	215	GE35609-001A	LOCK LEVER		1	
	216	GE40514-004A	TORSION SPRING		1	
	217	GE35611-001A	RELEASE LEVER		1	
	218	GE30999-014A	COMP.SPRING		1	
	251	B1A-0011-04	FRONT GLASS		1	E2
	251	B1A-0011-0D	FRONT GLASS		1	R0
	251	B1A-0011-00	FRONT GLASS		1	K0
	251	B1A-0011-0E	FRONT GLASS		1	K2
	251	B1A-0011-0J	FRONT GLASS		1	E3
	252	B1B-0008-03	LENS		1	E2,K0,K2,E3
	252	B1B-0008-0A	LENS		1	R0
	253	B1K-0010-00	LIGHTING BOARD		1	E2,K0,K2,E3
	253	B1K-0010-01	LIGHTING BOARD		1	R0
	254	E2K-0009-00	CONDUCT RUBBER		1	
	255	F0G-0010-00	COVER		1	E2,K0,K2,E3
	255	F0G-0010-01	COVER		1	R0
	256	K2F-0009-00	PUSH KNOB		1	E2,K0,K2,E3
	256	K2F-0009-02	PUSH KNOB		1	R0
	258	K2F-0010-00	PUSH KNOB		1	E2,K0,K2,E3
	258	K2F-0010-02	PUSH KNOB		1	R0
	260	K2K-0098-00	KNOB		1	E2,K0,K2,E3
	260	K2K-0098-01	KNOB		1	R0
	261	GE30999-013A	COMP.SPRING		1	
	263	GE40127-005A	KNOB SPRING		1	
	264	A4G-0008-00	REAR COVER		1	E2,K0,K2,E3
	264	A4G-0008-01	REAR COVER		1	R0
	269	E2K-0015-00	CONDUCT RUBBER		1	
	270	E2K-0016-00	CONDUCT RUBBER		1	
	271	K28-0564-03	KEY TOP		1	E2,K0,K2,E3
	272	K2K-0105-00	KNOB		1	E2,K0,K2,E3
	272	K2K-0101-01	KNOB		1	R0
	353	GE40646-001A	HOOK		2	
	354	GE20342-001A	MOUNTING SLEEVE		1	
	355	B0H-0001-00	ESCUTCHEON		1	E2,K0,K2,E3
	355	B0H-0001-02	ESCUTCHEON		1	R0
	357	QAN0126-001	MICROPHONE		1	
	501	B5A-0167-00	INST.MANUAL	EG GER RUS	1	E2
	501	B5A-0192-00	INST.MANUAL	POR	1	R0
	501	B5A-0166-10	INST.MANUAL	ENG FRE SPA	1	K0
	501	B5A-0229-10	INST.MANUAL	ENG FRE SPA	1	K2
	501	B5A-0432-00	INST.MANUAL	GER ENG FRE ITA SPA RUS	1	E3
				CHI(PEKIN)		
	502	B5A-0167-01	INST.MANUAL	FRE SPA ITA POR DUT	1	E2

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
MAIN PWB ASSY (XJ1-048x-xx) <01>						
	IC161	TDA7718C	ANALOG IC		1	E2,E3
	IC161	TDA7720B-X	IC		1	K0,K2
△	IC301	JCV8034	IC		1	E2,K0,K2,E3
	IC411	MFI337S3959-X	IC		1	E2,K0,K2,E3
	IC555	AK4387ET	ANALOG IC		1	E2,K0,K2,E3
△	IC601	TEF6657HN-X	IC		1	E2,K0,K2,E3
△	IC701	R5S726A0D216FP	IC		1	E2,K0,K2,E3
△	IC821	W3F-0028-00	IC		1	E2,K0,K2
△	IC821	W3F-0029-00	IC		1	E3
	IC831	BU4228F-W	IC		1	E2,K0,K2,E3
	IC841	BR24T02FJ-W-X	IC		1	E2,K0,K2,E3
	IC851	BU1CTD3WG-W	IC		1	E2,K0,K2,E3
	IC861	MP9942GJ	ANALOG IC		1	E2,K0,K2,E3
	IC891	NCP380HSNAJAA-X	IC		1	E2,K0,K2,E3
△	IC901	LV5685PV-H	ANALOG IC		1	E2,K0,K2,E3
	Q220	LSCR523EBFS8	TRANSISTOR		1	E2,K0,K2,E3
	Q250	LTC043TEB-X	DIGI TRANSISTOR		1	E2,E3
	Q260	LTC043TEB-X	DIGI TRANSISTOR		1	E2,K0,K2,E3
	Q270	LTA024EEB-X	DIGI TRANSISTOR		1	E2,K0,K2,E3
	Q271	LSAR523UBFS8	TRANSISTOR		1	E2,K0,K2,E3
	Q272	LTC024EEB-X	DIGI TRANSISTOR		1	E2,K0,K2,E3
	Q273	LTA024EEB-X	DIGI TRANSISTOR		1	E2,K0,K2,E3
	Q320	LTC043TEB-X	DIGI TRANSISTOR		1	K0,K2
	Q330	LTC043TEB-X	DIGI TRANSISTOR		1	K0,K2
	Q340	LTC043TEB-X	DIGI TRANSISTOR		1	K0,K2
	Q350	LTC043TEB-X	DIGI TRANSISTOR		1	K0,K2
	Q470	LTC014EEBFS8	DIGI TRANSISTOR		1	K0
	Q471	LTC043TEB-X	DIGI TRANSISTOR		1	K0
	Q701	LTA014YEB-X	DIGI TRANSISTOR		1	E2,K0,K2,E3
	D100	RSB6.8SM-X	BP Z DIODE		1	E2,K0,K2,E3
	D101	RSB6.8SM-X	BP Z DIODE		1	E2,K0,K2,E3
	D222	DZ2J056M	ZENER DIODE		1	E2,K0,K2,E3
	D223	DZ2J068M	ZENER DIODE		1	E2,K0,K2,E3
	D270	BAW56-TP-X	SI DIODE		1	E2,K0,K2,E3
	D271	BAW56-TP-X	SI DIODE		1	E2,K0,K2,E3
	D273	DA2J101	DIODE		1	E2,K0,K2,E3
	D370	BAW56-TP-X	SI DIODE		1	E2,K0,K2,E3
	D390	MBRX130	SCHOTTKY DIODE		1	E2,K0,K2,E3
	D391	MBRX130	SCHOTTKY DIODE		1	E2,K0,K2,E3
	D400	RB521SM-30-X	SB DIODE		1	E2,K0,K2,E3
	D401	DZ2J051M	ZENER DIODE		1	E2,K0,K2,E3
	D470	DZ2J068M	ZENER DIODE		1	K0
	D471	DZ2J068M	ZENER DIODE		1	K0
	D472	RSB6.8SM-X	BP Z DIODE		1	K0
	D473	RSB6.8SM-X	BP Z DIODE		1	K0
	D474	RSB6.8SM-X	BP Z DIODE		1	K0
	D475	RSB6.8SM-X	BP Z DIODE		1	K0
	D861	DB22306	SCHOTTKY DIODE		1	E2,K0,K2,E3
	D902	SK34A-L-X	SB DIODE		1	E2,K0,K2,E3
	D903	SK34A-L-X	SB DIODE		1	E2,K0,K2,E3
△	D990	1N5401-BPC04	SI DIODE		1	E2,K0,K2,E3
	D1060	RSB6.8SM-X	BP Z DIODE		1	E2,K0,K2,E3
	D1061	RSB6.8SM-X	BP Z DIODE		1	E2,K0,K2,E3
	C100	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C101	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C102	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C103	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C104	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C105	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C161	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
△	C162	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C163	CD04AV1V4R7M	E CAPACITOR	4.7uF 35V M	1	E2,K0,K2,E3
	C164	CD04AV1V4R7M	E CAPACITOR	4.7uF 35V M	1	E2,K0,K2,E3
	C165	CD04AV1C100M	E CAPACITOR	10uF 16V M	1	E2,K0,K2,E3
	C166	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C167	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C168	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,E3
	C169	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,E3
	C170	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	K0,K2
	C171	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C172	CD04AS1C220M	E CAPACITOR	22uF 16V M	1	E2,K0,K2,E3
	C177	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C223	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C224	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C225	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	E2,K0,K2,E3
	C226	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	E2,K0,K2,E3
	C251	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	E2,E3
	C261	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	E2,K0,K2,E3
	C303	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	E2,K0,K2,E3
	C304	QE20982-476Z	E CAPACITOR	47uF	1	E2,K0,K2,E3
	C305	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	E2,K0,K2,E3
	C306	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	E2,K0,K2,E3
	C311	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C313	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	E2,K0,K2,E3
	C314	CK730AV1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C316	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C317	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C318	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C319	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C321	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	K0,K2

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C331	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	K0,K2
	C341	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	K0,K2
	C351	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	K0,K2
	C370	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C390	CK73FBB1H224K	C CAPACITOR	0.22uF 50V K	1	E2,K0,K2,E3
	C391	CK73FBB1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C392	CK73FBB1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C410	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C472	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	K0
	C473	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	K0
	C474	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	K0
	C475	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	K0
	C571	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C572	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	E2,K0,K2,E3
	C573	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C574	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	E2,K0,K2,E3
	C575	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C576	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C588	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	E2,K0,K2,E3
	C589	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	E2,K0,K2,E3
	C598	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	E2,K0,K2,E3
	C599	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	E2,K0,K2,E3
	C601	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	E2,K0,K2,E3
	C602	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	E2,K0,K2,E3
	C603	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C604	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	E2,K0,K2,E3
	C605	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	E2,K0,K2,E3
	C606	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	E2,K0,K2,E3
△	C607	CC73GCH1H010C	C CAPACITOR	1pF 50V C	1	E2,K0,K2,E3
	C608	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	E2,K0,K2,E3
	C609	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
△	C610	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	E2,K0,K2,E3
	C611	CC73GCH1H010C	C CAPACITOR	1pF 50V C	1	E2,K0,K2,E3
	C612	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C614	CC73GCH1H220J	C CAPACITOR	22pF 50V J	1	E2,K0,K2,E3
	C615	CC73GCH1H330J	C CAPACITOR	33pF 50V J	1	E2,K0,K2,E3
	C616	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	E2,K0,K2,E3
	C617	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C618	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C624	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	E2,K0,K2,E3
	C626	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C630	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C700	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C701	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C702	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C703	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C704	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C705	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C706	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C707	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	E2,K0,K2,E3
	C708	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	E2,K0,K2,E3
	C709	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C710	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C711	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C712	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C713	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C716	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C717	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C718	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C721	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	E2,K0,K2,E3
	C722	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	E2,K0,K2,E3
	C723	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C724	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C725	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C726	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C727	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C820	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C821	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C830	CK73GBB1H682K	C CAPACITOR	6800pF 50V K	1	E2,K0,K2,E3
	C831	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C832	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C840	CK73GBB1C473K	C CAPACITOR	0.047uF 16V K	1	E2,K0,K2,E3
	C850	CK73GBB1C474K	C CAPACITOR	0.47uF 16V K	1	E2,K0,K2,E3
	C852	CD04AS0J101M	E CAPACITOR	100uF 6.3V M	1	E2,K0,K2,E3
	C854	CK73GBB1C474K	C CAPACITOR	0.47uF 16V K	1	E2,K0,K2,E3
	C860	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C861	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	E2,K0,K2,E3
	C862	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	E2,K0,K2,E3
	C863	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C864	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C865	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	E2,K0,K2,E3
	C867	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C868	QE20850-157Z	E CAPACITOR	150uF	1	E2,K0,K2,E3
	C869	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	E2,K0,K2,E3
	C870	CC73GCH1H150J	C CAPACITOR	15pF 50V J	1	E2,K0,K2,E3
	C877	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C891	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C892	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C904	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C905	CD04AR1C471M	E CAPACITOR	470uF 16V M	1	E2,K0,K2,E3

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C907	CD04AS0J101M	E CAPACITOR	100uF 6.3V M	1	E2,K0,K2,E3
	C908	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C909	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C911	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	E2,K0,K2,E3
	C912	CK73EXR1A106K	C CAPACITOR	10uF 10V K	1	E2,K0,K2,E3
	C920	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C930	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K0,K2,E3
	C931	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C990	CD04ET1C102M	E CAPACITOR		1	E2,K0,K2,E3
	C1000	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C1002	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1050	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1051	CC73GCH1H050C	C CAPACITOR	5pF 50V C	1	E2,K0,K2,E3
	C1055	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1056	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C1057	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1064	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1069	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1070	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1071	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1072	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C1073	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1074	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1082	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1084	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C1085	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1089	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C1090	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	E2,K0,K2,E3
	C1091	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1094	CC73GCH1H121J	C CAPACITOR	120pF 50V J	1	E2,K0,K2,E3
	C1095	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C1096	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	C1098	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	E2,K0,K2,E3
	R100	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R101	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R102	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R103	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R104	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R105	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R162	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	K0
	R164	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	K0,K2
	R167	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,E3
	R168	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R169	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R170	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R171	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	E2,K0,K2,E3
	R178	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R179	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R221	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R223	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R224	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R225	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R226	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R227	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R229	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R239	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	E2,K0,K2,E3
	R240	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R244	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	E2,K0,K2,E3
	R246	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R250	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	E2,E3
	R251	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	E2,E3
	R252	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	E2,E3
	R253	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	K0,K2
	R260	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	E2,K0,K2,E3
	R261	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	E2,K0,K2,E3
	R262	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	E2,K0,K2,E3
	R270	RK73GB2A104J	MG RESISTOR	100kΩ 1/10W J	1	E2,K0,K2,E3
	R271	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	E2,K0,K2,E3
	R273	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	E2,K0,K2,E3
	R302	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R303	RK73EB2E5R1J	MG RESISTOR	5.1Ω 1/4W J	1	E2,K0,K2,E3
	R304	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R307	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R320	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	K0,K2
	R321	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K0,K2
	R323	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	K0,K2
	R330	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	K0,K2
	R331	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K0,K2
	R333	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	K0,K2
	R340	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	K0,K2
	R341	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K0,K2
	R343	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	K0,K2
	R350	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	K0,K2
	R351	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K0,K2
	R353	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	K0,K2
	R370	RK73GB2A683J	MG RESISTOR	68kΩ 1/10W J	1	E2,K0,K2,E3
	R371	RK73GB2A123J	MG RESISTOR	12kΩ 1/10W J	1	E2,K0,K2,E3
	R372	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	E2,K0,K2,E3
	R381	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,E3
	R390	RK73EB2E472J	MG RESISTOR	4.7kΩ 1/4W J	1	E2,K0,K2,E3
	R400	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R402	RK73GB2A225J	MG RESISTOR	2.2MΩ 1/10W J	1	K0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R403	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K2,E3
	R410	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R411	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R412	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R413	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R414	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R431	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R432	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R470	RK73GB2A104J	MG RESISTOR	100kΩ 1/10W J	1	K0
	R471	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R472	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R473	RK73GB2A4R7J	MG RESISTOR	4.7Ω 1/10W J	1	K0
	R474	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0
	R475	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0
	R476	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K0
	R477	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R478	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R482	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	K0
	R483	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	K0
	R571	RK73GB2A910J	MG RESISTOR	91Ω 1/10W J	1	E2,K0,K2,E3
	R572	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	E2,K0,K2,E3
	R573	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	E2,K0,K2,E3
	R574	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	E2,K0,K2,E3
	R588	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R589	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R598	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R599	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R600	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R601	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R602	RK73GB2A820J	MG RESISTOR	82Ω 1/10W J	1	E2,K0,K2,E3
	R603	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	E2,K0,K2,E3
	R604	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	E2,K0,K2,E3
	R605	RK73GB2A4R7J	MG RESISTOR	4.7Ω 1/10W J	1	E2,K0,K2,E3
	R611	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R612	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R701	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R702	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R703	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R704	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R705	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R707	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R710	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R711	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R712	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R713	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R714	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R715	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R716	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R717	RK73GB2A104J	MG RESISTOR	100kΩ 1/10W J	1	E2,K0,K2,E3
	R719	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	E2,K0,K2,E3
	R720	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	E2,K0,K2,E3
	R721	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R722	RK73GB2A911J	MG RESISTOR	910Ω 1/10W J	1	E2,K0,K2,E3
	R723	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R724	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	E2,K0,K2,E3
	R725	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R726	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	E2,K0,K2,E3
	R727	RK73GB2A153J	MG RESISTOR	15kΩ 1/10W J	1	E2,K0,K2,E3
	R728	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	E2,K0,K2,E3
	R729	RK73GB2A153J	MG RESISTOR	15kΩ 1/10W J	1	E2,K0,K2,E3
	R730	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R732	RK73GB2A393J	MG RESISTOR	39kΩ 1/10W J	1	E2
	R732	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	K2
	R733	RK73GB2A822J	MG RESISTOR	8.2kΩ 1/10W J	1	E2
	R733	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	K0,E3
	R733	RK73GB2A273J	MG RESISTOR	27kΩ 1/10W J	1	K2
	R734	RK73GB2A393J	MG RESISTOR	39kΩ 1/10W J	1	E2,E3
	R735	RK73GB2A822J	MG RESISTOR	8.2kΩ 1/10W J	1	E2,E3
	R735	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	K0,K2
	R739	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R740	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R741	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R742	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R743	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R744	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R745	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R746	RK73GB2A682J	MG RESISTOR	6.8kΩ 1/10W J	1	E2,K0,K2,E3
	R747	RK73GB2A682J	MG RESISTOR	6.8kΩ 1/10W J	1	E2,K0,K2,E3
	R749	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R750	RK73GB2A201J	MG RESISTOR	200Ω 1/10W J	1	E2,K0,K2,E3
	R751	RK73GB2A201J	MG RESISTOR	200Ω 1/10W J	1	E2,K0,K2,E3
	R752	RK73GB2A161J	MG RESISTOR	160Ω 1/10W J	1	E2,K0,K2,E3
	R753	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R754	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R755	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R756	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R757	RK73GB2A123J	MG RESISTOR	12kΩ 1/10W J	1	E2,K0,K2,E3
	R758	RK73GB2A620J	MG RESISTOR	62Ω 1/10W J	1	E2,K0,K2,E3
	R759	RK73GB2A203J	MG RESISTOR	20kΩ 1/10W J	1	E2,K0,K2,E3
	R760	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R765	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R766	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R776	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R777	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R778	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R779	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R781	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R819	RK73GB2A332J	MG RESISTOR	3.3kΩ 1/10W J	1	E2,K0,K2,E3
	R820	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	E2,K0,K2,E3
	R821	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R822	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R830	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R840	RK73GB2A271J	MG RESISTOR	270Ω 1/10W J	1	E2,K0,K2,E3
	R841	RK73GB2A271J	MG RESISTOR	270Ω 1/10W J	1	E2,K0,K2,E3
	R861	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	E2,K0,K2,E3
	R862	RK73EB2E271J	MG RESISTOR	270Ω 1/4W J	1	E2,K0,K2,E3
	R864	RK73GB2A393J	MG RESISTOR	39kΩ 1/10W J	1	E2,K0,K2,E3
	R865	RK73GH2A683D	MG RESISTOR	68kΩ 1/10W D	1	E2,K0,K2,E3
	R867	RK73GH2A393D	MG RESISTOR	39kΩ 1/10W D	1	E2,K0,K2,E3
	R868	RK73GH2A183D	MG RESISTOR	18kΩ 1/10W D	1	E2,K0,K2,E3
	R869	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R890	RK73GH2A203D	MG RESISTOR	20kΩ 1/10W D	1	E2,K0,K2,E3
	R892	RK73EB2E222J	MG RESISTOR	2.2kΩ 1/4W J	1	E2,K0,K2,E3
	R930	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	E2,K0,K2,E3
	R969	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	E2,K0,K2,E3
	R978	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	E2,K0,K2,E3
	R979	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1	E2,K0,K2,E3
	R980	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1	E2,K0,K2,E3
	R1003	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	E2,K0,K2,E3
	R1051	RK73GH2A100D	MG RESISTOR	10Ω 1/10W D	1	E2,K0,K2,E3
	R1060	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1061	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1070	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R1071	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1073	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1074	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1075	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1076	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1077	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1082	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1091	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1170	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1404	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	E2,K0,K2,E3
	R1405	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1406	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1407	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1408	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1414	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1415	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1416	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1417	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1419	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1421	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1425	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1426	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1428	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1429	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E2,K0,K2,E3
	R1430	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1432	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	R1434	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	E2,K0,K2,E3
	L220	LR73Z0AD470M	CHIP INDUCTOR	47uH	1	E2,K0,K2,E3
	L221	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L222	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L223	LR73Z0AD470M	CHIP INDUCTOR	47uH	1	E2,K0,K2,E3
	L591	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	E2,K0,K2,E3
	L600	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	E2,K0,K2,E3
	L601	LK73G0BE4R7K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L602	LK73G0BER47K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L603	NQLM93K-R10X	INDUCTOR	0.1uH K	1	E2,K0,K2,E3
	L604	LK73G0BE1R0K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L605	LK73G0BER22K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L606	LK73G0BER12K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L607	LK73G0BER15K	M.CHIP INDUCTOR		1	E2,K0,K2,E3
	L609	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	E2,K0,K2,E3
	L610	NQR0715-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L611	NQR0715-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L701	LB73G0BK-006	CHIP FERRITE		1	E2,K0,K2,E3
	L709	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L758	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L780	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L820	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L821	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L822	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L823	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L824	NQR0713-001X	FERRITE BEADS		1	E2,K0,K2,E3
	L825	LB73G0CA-002	CHIP FERRITE		1	E2,K0,K2,E3
	L826	LB73G0CK-001	CHIP FERRITE		1	E2,K0,K2,E3
	L827	LB73G0BK-006	CHIP FERRITE		1	E2,K0,K2,E3
	L850	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	E2,K0,K2,E3
	L860	NQLN9EM-100X	INDUCTOR	10uH M	1	E2,K0,K2,E3
	L861	LK73Z0AK4R7M	M.CHIP INDUCTOR	4.7uH	1	E2,K0,K2,E3
	L990	QQR1927-001	CHOKE COIL		1	E2,K0,K2,E3

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	CN228	QGF1030F3-11X	FFC/FPC CONNE	FFC/FPC (1-11)	1	E2,K0,K2,E3
	CN701	QGZ2006J1-20	DETACHABLE CONN	(1-20)	1	E2,K0,K2,E3
	CN990	QNZ0607-001	CAR CONNECTOR		1	E2,K0,K2,E3
△	F321	F53-0513-08	PATTERN FUSE	4A	1	E2,K0,K2,E3
	J220	QNS0307-001	3.5 JACK		1	E2,K0,K2,E3
	J321	QNN0874-001	PIN JACK		1	E2,E3
	J321	QNN0866-001	PIN JACK		1	K0,K2
	J470	QNZ0907-001	CIR CONNECTOR		1	K0
	J600	QNB0356-001	ANT TERMINAL		1	E2,K0,K2,E3
	S830	QSW0648-001Z	TACT SWITCH		1	E2,K0,K2,E3
	VA600	F0K-0014-00	SURGE ABSORBER		1	E2,K0,K2,E3
	X540	NAX1224-001X	CRYSTAL		1	E2,K0,K2,E3
	X600	L7J-0014-00	QUARTZ CRYSTAL		1	E2,K0,K2,E3
	X701	NAX1243-001X	CRYSTAL		1	E2,K0,K2,E3
MAIN PWB ASSY (XJ1-0593-20) <03>						
	IC161	TDA7718C	ANALOG IC		1	R0
△	IC301	JCV8034	IC		1	R0
	IC411	MFI337S395901	MCU IC		1	R0
	IC555	AK4387ET	ANALOG IC		1	R0
△	IC601	TEF6657HN-X	IC		1	R0
△	IC701	R5S726A0D216FP	IC		1	R0
△	IC821	W3F-0028-00	ROM IC		1	R0
	IC831	BU4228F-W	IC		1	R0
	IC841	BR24T02FJ-W-X	IC		1	R0
	IC851	BU1CTD3WG-W	IC		1	R0
	IC861	MP9942GJ	ANALOG IC		1	R0
	IC891	NCP380HSNAJAA-X	IC		1	R0
△	IC901	LV5685PV-H	ANALOG IC		1	R0
	Q220	LSCR523EBFS8	TRANSISTOR		1	R0
	Q250	LTC043TEB-X	DIGI TRANSISTOR		1	R0
	Q260	LTC043TEB-X	DIGI TRANSISTOR		1	R0
	Q270	LTA024EEB-X	DIGI TRANSISTOR		1	R0
	Q271	LSAR523UBFS8	TRANSISTOR		1	R0
	Q272	LTC024EEB-X	DIGI TRANSISTOR		1	R0
	Q273	LTA024EEB-X	DIGI TRANSISTOR		1	R0
	Q320	LTC043TEB-X	DIGI TRANSISTOR		1	R0
	Q330	LTC043TEB-X	DIGI TRANSISTOR		1	R0
	Q701	LTA014YEB-X	DIGI TRANSISTOR		1	R0
	D100	RSB6.8SM-X	BP Z DIODE		1	R0
	D101	RSB6.8SM-X	BP Z DIODE		1	R0
	D222	DZ2J056M	ZENER DIODE		1	R0
	D223	DZ2J068M	ZENER DIODE		1	R0
	D270	BAW56-TP-X	SI DIODE		1	R0
	D271	BAW56-TP-X	SI DIODE		1	R0
	D273	DA2J101	DIODE		1	R0
	D370	BAW56-TP-X	SI DIODE		1	R0
	D390	MBRX130	SCHOTTKY DIODE		1	R0
	D391	MBRX130	SCHOTTKY DIODE		1	R0
	D400	RB521SM-30-X	SB DIODE		1	R0
	D401	DZ2J051M	ZENER DIODE		1	R0
	D861	DB22306	SCHOTTKY DIODE		1	R0
	D902	SK34A-L-X	SB DIODE		1	R0
	D903	SK34A-L-X	SB DIODE		1	R0
△	D990	1N5401-BPC04	SI DIODE		1	R0
	D1060	RSB6.8SM-X	BP Z DIODE		1	R0
	D1061	RSB6.8SM-X	BP Z DIODE		1	R0
	C100	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C101	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C102	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C103	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C104	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C105	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C161	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
△	C162	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C163	CD04AV1V4R7M	E CAPACITOR	4.7uF 35V M	1	R0
	C164	CD04AV1V4R7M	E CAPACITOR	4.7uF 35V M	1	R0
	C165	CD04AV1C100M	E CAPACITOR	10uF 16V M	1	R0
	C166	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C167	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C168	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C169	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C171	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C172	CD04AS1C220M	E CAPACITOR	22uF 16V M	1	R0
	C177	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C223	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C224	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C225	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	R0
	C226	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	R0
	C251	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	R0
	C261	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	R0
	C303	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	R0
	C304	QE20982-476Z	E CAPACITOR	47uF	1	R0
	C305	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	R0
	C306	CC73GCH1H820J	C CAPACITOR	82pF 50V J	1	R0
	C311	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C313	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	R0
	C314	CK730AV1C105K	C CAPACITOR	1uF 16V K	1	R0
	C316	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C317	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C318	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C319	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C321	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	R0
	C331	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	R0
	C370	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C390	CK73FBB1H224K	C CAPACITOR	0.22uF 50V K	1	R0
	C391	CK73FBB1C105K	C CAPACITOR	1uF 16V K	1	R0
	C392	CK73FBB1C105K	C CAPACITOR	1uF 16V K	1	R0
	C410	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C571	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C572	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	R0
	C573	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C574	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	R0
	C575	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C576	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C588	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	R0
	C589	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	R0
	C598	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	R0
	C599	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	R0
	C601	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	R0
	C602	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	R0
	C603	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C604	CK73GBB1H152K	C CAPACITOR	1500pF 50V K	1	R0
	C605	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	R0
△	C606	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	R0
	C607	CC73GCH1H010C	C CAPACITOR	1pF 50V C	1	R0
	C608	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	R0
	C609	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C610	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	R0
△	C611	CC73GCH1H010C	C CAPACITOR	1pF 50V C	1	R0
	C612	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C614	CC73GCH1H220J	C CAPACITOR	22pF 50V J	1	R0
	C615	CC73GCH1H330J	C CAPACITOR	33pF 50V J	1	R0
	C616	CC73GCH1H102J	C CAPACITOR	1000pF 50V J	1	R0
	C617	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C618	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C624	CK73FXR0J106K	C CAPACITOR	10uF 6.3V K	1	R0
	C626	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C630	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C700	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C701	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C702	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C703	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C704	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C705	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C706	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C707	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	R0
	C708	CC73GCH1H090D	C CAPACITOR	9pF 50V D	1	R0
	C709	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C710	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C711	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C712	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C713	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C716	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C717	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C718	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C721	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	R0
	C722	CC73GCH1H120J	C CAPACITOR	12pF 50V J	1	R0
	C723	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C724	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C725	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C726	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C727	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C820	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C821	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C830	CK73GBB1H682K	C CAPACITOR	6800pF 50V K	1	R0
	C831	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C832	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C840	CK73GBB1C473K	C CAPACITOR	0.047uF 16V K	1	R0
	C850	CK73GBB1C474K	C CAPACITOR	0.47uF 16V K	1	R0
	C852	CD04AS0J101M	E CAPACITOR	100uF 6.3V M	1	R0
	C854	CK73GBB1C474K	C CAPACITOR	0.47uF 16V K	1	R0
	C860	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C861	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	R0
	C862	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	R0
	C863	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C864	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C865	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	R0
	C867	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C868	QE20850-157Z	E CAPACITOR	150uF	1	R0
	C869	CK73GBB1C224K	C CAPACITOR	0.22uF 16V K	1	R0
	C870	CC73GCH1H150J	C CAPACITOR	15pF 50V J	1	R0
	C877	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C891	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C892	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C904	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C905	CD04AR1C471M	E CAPACITOR	470uF 16V M	1	R0
	C907	CD04AS0J101M	E CAPACITOR	100uF 6.3V M	1	R0
	C908	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C909	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C911	CK73EBB1C475K	C CAPACITOR	4.7uF 16V K	1	R0
	C912	CK73EXR1A106K	C CAPACITOR	10uF 10V K	1	R0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C920	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C930	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	C931	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C990	CD04ET1C102M	E CAPACITOR	1000uF 16V M	1	R0
	C1000	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C1002	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1010	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1011	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1012	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1013	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1014	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1015	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1016	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1017	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1050	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1051	CC73GCH1H050C	C CAPACITOR	5pF 50V C	1	R0
	C1055	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1056	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C1057	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1064	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1069	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1070	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1071	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1072	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C1073	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1074	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1082	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1084	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C1085	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1089	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C1090	CK73GXR1H104K	C CAPACITOR	0.1uF 50V K	1	R0
	C1091	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1094	CC73GCH1H121J	C CAPACITOR	120pF 50V J	1	R0
	C1095	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C1096	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	C1098	CK73GBB1H103K	C CAPACITOR	0.01uF 50V K	1	R0
	R100	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R101	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R102	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R103	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R104	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R105	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R167	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R168	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R169	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R170	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R171	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	R0
	R178	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R179	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R221	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R223	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R224	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R225	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R226	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R227	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R229	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R239	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R240	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R244	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	R0
	R246	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R250	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	R0
	R251	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R252	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R260	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	R0
	R261	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R262	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R270	RK73GB2A104J	MG RESISTOR	100kΩ 1/10W J	1	R0
	R271	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R273	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R302	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R303	RK73EB2E5R1J	MG RESISTOR	5.1Ω 1/4W J	1	R0
	R304	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R307	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R320	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	R0
	R321	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R323	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R330	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	R0
	R331	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R333	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	R0
	R370	RK73GB2A683J	MG RESISTOR	68kΩ 1/10W J	1	R0
	R371	RK73GB2A123J	MG RESISTOR	12kΩ 1/10W J	1	R0
	R372	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	R0
	R390	RK73EB2E472J	MG RESISTOR	4.7kΩ 1/4W J	1	R0
	R400	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R403	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R410	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R411	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R412	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R413	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R414	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R431	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R432	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R571	RK73GB2A910J	MG RESISTOR	91Ω 1/10W J	1	R0
	R572	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	R0
	R573	RK73GB2A181J	MG RESISTOR	180Ω 1/10W J	1	R0
	R574	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	R0
	R588	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R589	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R598	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R599	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R600	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R601	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R602	RK73GB2A820J	MG RESISTOR	82Ω 1/10W J	1	R0
	R603	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	R0
	R604	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	R0
	R605	RK73GB2A4R7J	MG RESISTOR	4.7Ω 1/10W J	1	R0
	R611	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R612	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R701	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R702	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R703	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R704	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R705	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R707	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R710	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R711	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R712	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R713	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R714	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R715	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R716	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R717	RK73GB2A104J	MG RESISTOR	100kΩ 1/10W J	1	R0
	R719	RK73GB2A162J	MG RESISTOR	1.6kΩ 1/10W J	1	R0
	R720	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	R0
	R721	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R722	RK73GB2A911J	MG RESISTOR	910Ω 1/10W J	1	R0
	R723	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R724	RK73GB2A105J	MG RESISTOR	1MΩ 1/10W J	1	R0
	R725	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R726	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	R0
	R727	RK73GB2A153J	MG RESISTOR	15kΩ 1/10W J	1	R0
	R728	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	R0
	R729	RK73GB2A153J	MG RESISTOR	15kΩ 1/10W J	1	R0
	R730	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R732	RK73GB2A273J	MG RESISTOR	27kΩ 1/10W J	1	R0
	R733	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	R0
	R735	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R739	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R740	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R741	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R742	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R743	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R744	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R745	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R746	RK73GB2A682J	MG RESISTOR	6.8kΩ 1/10W J	1	R0
	R747	RK73GB2A682J	MG RESISTOR	6.8kΩ 1/10W J	1	R0
	R749	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R750	RK73GB2A201J	MG RESISTOR	200Ω 1/10W J	1	R0
	R751	RK73GB2A201J	MG RESISTOR	200Ω 1/10W J	1	R0
	R752	RK73GB2A161J	MG RESISTOR	160Ω 1/10W J	1	R0
	R753	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R754	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R755	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R756	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R757	RK73GB2A123J	MG RESISTOR	12kΩ 1/10W J	1	R0
	R758	RK73GB2A620J	MG RESISTOR	62Ω 1/10W J	1	R0
	R759	RK73GB2A203J	MG RESISTOR	20kΩ 1/10W J	1	R0
	R760	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R765	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R766	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R776	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R777	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R778	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R779	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R781	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R819	RK73GB2A332J	MG RESISTOR	3.3kΩ 1/10W J	1	R0
	R820	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	R0
	R821	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R822	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R830	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R840	RK73GB2A271J	MG RESISTOR	270Ω 1/10W J	1	R0
	R841	RK73GB2A271J	MG RESISTOR	270Ω 1/10W J	1	R0
	R861	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	R0
	R862	RK73EB2E271J	MG RESISTOR	270Ω 1/4W J	1	R0
	R864	RK73GB2A393J	MG RESISTOR	39kΩ 1/10W J	1	R0
	R865	RK73GH2A683D	MG RESISTOR	68kΩ 1/10W D	1	R0
	R867	RK73GH2A393D	MG RESISTOR	39kΩ 1/10W D	1	R0
	R868	RK73GH2A183D	MG RESISTOR	18kΩ 1/10W D	1	R0
	R869	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R890	RK73GH2A203D	MG RESISTOR	20kΩ 1/10W D	1	R0
	R892	RK73EB2E222J	MG RESISTOR	2.2kΩ 1/4W J	1	R0
	R930	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	R0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R969	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	R0
	R978	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1	R0
	R979	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1	R0
	R980	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1	R0
	R1003	RK73GB2A473J	MG RESISTOR	47kΩ 1/10W J	1	R0
	R1051	RK73GH2A100D	MG RESISTOR	10Ω 1/10W D	1	R0
	R1060	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1061	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1070	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R1071	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1073	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1074	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1075	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1076	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1077	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1082	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1091	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1170	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1404	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	R0
	R1405	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1406	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1407	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1408	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1414	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1415	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1416	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1417	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1419	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1421	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1425	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1426	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1428	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1429	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	R1430	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1432	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	R1434	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	R0
	L220	LR73Z0AD470M	CHIP INDUCTOR	47uH	1	R0
	L221	NQR0713-001X	FERRITE BEADS		1	R0
	L222	NQR0713-001X	FERRITE BEADS		1	R0
	L223	LR73Z0AD470M	CHIP INDUCTOR	47uH	1	R0
	L591	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	R0
	L600	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	R0
	L601	LK73G0BE4R7K	M.CHIP INDUCTOR		1	R0
	L602	LK73G0BER47K	M.CHIP INDUCTOR		1	R0
	L603	NQLM93K-R10X	INDUCTOR	0.1uH K	1	R0
	L604	LK73G0BE1R0K	M.CHIP INDUCTOR		1	R0
	L605	LK73G0BER22K	M.CHIP INDUCTOR		1	R0
	L606	LK73G0BER12K	M.CHIP INDUCTOR		1	R0
	L607	LK73G0BER15K	M.CHIP INDUCTOR		1	R0
	L609	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	R0
	L610	NQR0715-001X	FERRITE BEADS		1	R0
	L611	NQR0715-001X	FERRITE BEADS		1	R0
	L701	LB73G0BK-006	CHIP FERRITE		1	R0
	L709	NQR0713-001X	FERRITE BEADS		1	R0
	L758	NQR0713-001X	FERRITE BEADS		1	R0
	L780	NQR0713-001X	FERRITE BEADS		1	R0
	L820	NQR0713-001X	FERRITE BEADS		1	R0
	L821	NQR0713-001X	FERRITE BEADS		1	R0
	L822	NQR0713-001X	FERRITE BEADS		1	R0
	L823	NQR0713-001X	FERRITE BEADS		1	R0
	L824	NQR0713-001X	FERRITE BEADS		1	R0
	L825	LB73G0CA-002	CHIP FERRITE		1	R0
	L826	LB73G0CK-001	CHIP FERRITE		1	R0
	L827	LB73G0BK-006	CHIP FERRITE		1	R0
	L850	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	R0
	L860	NQLN9EM-100X	INDUCTOR	10uH M	1	R0
	L861	LK73Z0AK4R7M	M.CHIP INDUCTOR	4.7uH	1	R0
	L990	QQR1927-001	CHOKE COIL		1	R0
	CN228	QGF1030F3-11X	FFC/FPC CONNE	FFC/FPC (1-11)	1	R0
	CN701	QGZ2006J1-20	DETACHABLE CONN	(1-20)	1	R0
	CN990	QNZ0607-001	CAR CONNECTOR		1	R0
△	F321	F53-0513-08	PATTERN FUSE	4A	1	R0
	J220	QNS0307-001	3.5 JACK		1	R0
	J321	QNN0868-001	PIN JACK		1	R0
	J600	QNB0356-001	ANT TERMINAL		1	R0
	S830	QSW0648-001Z	TACT SWITCH		1	R0
	VA600	F0K-0014-00	SURGE ABSORBER		1	R0
	X540	NAX1224-001X	CRYSTAL		1	R0
	X600	L7J-0014-00	QUARTZ CRYSTAL		1	R0
	X701	NAX1243-001X	CRYSTAL		1	R0
SWITCH PWB ASSY (XJ6-023x-x2) <02>						
	IC1	BU97530KV-M-X	IC		1	E2,K0,K2,E3
	IC90	SIR8630B6T	IR DETECT UNIT		1	K0,K2
	Q1	LSCR523UBFS8	TRANSISTOR		1	E2,K0,K2,E3
	Q51	LSCR523EBFS8	TRANSISTOR		1	E2,K0,K2,E3
	Q52	LSCR523EBFS8	TRANSISTOR		1	E2,K0,K2,E3
	Q53	LSCR523EBFS8	TRANSISTOR		1	E2,K0,K2,E3
	D1	DZ2J056M	ZENER DIODE		1	E2,K0,K2,E3
	D2	MBRX130	SCHOTTKY DIODE		1	E2,K0,K2,E3
	D20	SML-D12V8WT	LED		1	E2,K0,K2,E3
	D21	NESM026DT-W	LED		1	E2,K0,K2,E3

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D22	NESM026DT-W	LED		1	E2,K0,K2,E3
	D23	NESM026DT-W	LED		1	E2,K0,K2,E3
	D24	NESM026DT-W	LED		1	E2,K0,K2,E3
	D40	NESM026DT-W	LED		1	E2,K0,K2,E3
	D51	DZ2J056M	ZENER DIODE		1	E2,K0,K2,E3
	D52	DZ2J056M	ZENER DIODE		1	E2,K0,K2,E3
	D80	DZ2J051M	ZENER DIODE		1	E2,K0,K2,E3
	D81	DZ2J051M	ZENER DIODE		1	E2,K0,K2,E3
	C1	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C5	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C6	CK73EXR1C106K	C CAPACITOR	10uF 16V K	1	E2,K0,K2,E3
	C9	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K0,K2,E3
	C60	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	E2,K0,K2,E3
	C61	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	E2,K0,K2,E3
	C80	CC73GCH1H270J	C CAPACITOR	27pF 50V J	1	E2,K0,K2,E3
	C81	CC73GCH1H270J	C CAPACITOR	27pF 50V J	1	E2,K0,K2,E3
	C82	CK73EXR1C106K	C CAPACITOR	10uF 16V K	1	E2,K0,K2,E3
	C83	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	E2,K0,K2,E3
	C84	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C85	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	E2,K0,K2,E3
	C86	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	C90	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	K0,K2
	R1	RK73EB2E101J	MG RESISTOR	100Ω 1/4W J	1	E2,K0,K2,E3
	R3	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R4	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E2,K0,K2,E3
	R5	RK73FB2B331J	MG RESISTOR	330Ω 1/8W J	1	E2,K0,K2,E3
	R6	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E2,K0,K2,E3
	R22	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R23	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R24	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R26	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R27	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R28	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R30	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R31	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R32	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R34	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R35	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R36	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	E2,K0,K2,E3
	R44	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R45	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R46	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R47	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	E2,K0,K2,E3
	R48	RK73GB2A821J	MG RESISTOR	820Ω 1/10W J	1	E2,K0,K2,E3
	R51	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R52	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R53	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	E2,K0,K2,E3
	R60	RK73FB2B101J	MG RESISTOR	100Ω 1/8W J	1	E2,K0,K2,E3
	R61	RK73FB2B101J	MG RESISTOR	100Ω 1/8W J	1	E2,K0,K2,E3
	R62	RK73FB2B4R7J	MG RESISTOR	4.7Ω 1/8W J	1	E2,K0,K2,E3
	R70	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	E2,K0,K2,E3
	R80	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	E2,K0,K2,E3
	R1007	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	K0,K2
	RA1	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	E2,K0,K2,E3
	RA2	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	E2,K0,K2,E3
	RA3	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	E2,K0,K2,E3
	CN1	QGZ2006K1-20X	DETACHABLE CONN	(1-20)	1	E2,K0,K2,E3
	FL80	NQR0704-001X	CHOKE COIL		1	E2,K0,K2,E3
	J60	QNS0320-001	3.5 JACK		1	E2,K0,K2,E3
	J80	QNZ1076-001	USB CONNECTOR		1	E2,K0,K2,E3
	S20	T9K-0007-00	ROTARY ENCODER		1	E2,K0,K2,E3
SWITCH PWB ASSY (XJ6-0373-21) <04>						
	IC1	BU97530KV-M-X	IC		1	R0
	IC90	SIR8630B6T	IR DETECT UNIT		1	R0
	Q1	LSCR523UBFS8	TRANSISTOR		1	R0
	Q50	LSCR523EBFS8	TRANSISTOR		1	R0
	Q51	LSCR523EBFS8	TRANSISTOR		1	R0
	Q52	LSCR523EBFS8	TRANSISTOR		1	R0
	Q53	LSCR523EBFS8	TRANSISTOR		1	R0
	D1	DZ2J056M	ZENER DIODE		1	R0
	D2	MBRX130	SCHOTTKY DIODE		1	R0
	D20	SML-D12V8WT	LED		1	R0
	D21	NESM026DT-W	LED		1	R0
	D22	NESM026DT-W	LED		1	R0
	D23	NESM026DT-W	LED		1	R0
	D24	NESM026DT-W	LED		1	R0
	D40	NESM026DT-W	LED		1	R0
	D51	DZ2J056M	ZENER DIODE		1	R0
	D52	DZ2J056M	ZENER DIODE		1	R0
	D80	DZ2J051M	ZENER DIODE		1	R0
	D81	DZ2J051M	ZENER DIODE		1	R0
	C1	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0
	C5	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C6	CK73EXR1C106K	C CAPACITOR	10uF 16V K	1	R0
	C9	CK73GXR1C105K	C CAPACITOR	1uF 16V K	1	R0
	C60	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	R0
	C61	CK73GBB1H102K	C CAPACITOR	1000pF 50V K	1	R0
	C80	CC73GCH1H270J	C CAPACITOR	27pF 50V J	1	R0
	C81	CC73GCH1H270J	C CAPACITOR	27pF 50V J	1	R0
	C82	CK73EXR1C106K	C CAPACITOR	10uF 16V K	1	R0
	C83	CK73GBB1H471K	C CAPACITOR	470pF 50V K	1	R0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-303BT	E2	KMM-BT3012U	R0	KMM-BT312U	K0	KMM-BT32U	K2
KMM-L200BT	E3						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C84	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C85	CK73GBB1H472K	C CAPACITOR	4700pF 50V K	1	R0
	C86	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	C90	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	R0
	R1	RK73EB2E101J	MG RESISTOR	100Ω 1/4W J	1	R0
	R3	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R4	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	R0
	R5	RK73FB2B331J	MG RESISTOR	330Ω 1/8W J	1	R0
	R6	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	R0
	R20	RK73GB2A222J	MG RESISTOR	2.2kΩ 1/10W J	1	R0
	R22	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R23	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R24	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R26	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R27	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R28	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R30	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R31	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R32	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R34	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R35	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R36	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	R0
	R44	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R45	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R46	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R47	RK73GB2A122J	MG RESISTOR	1.2kΩ 1/10W J	1	R0
	R48	RK73GB2A821J	MG RESISTOR	820Ω 1/10W J	1	R0
	R50	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R51	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R52	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R53	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	R0
	R60	RK73FB2B101J	MG RESISTOR	100Ω 1/8W J	1	R0
	R61	RK73FB2B101J	MG RESISTOR	100Ω 1/8W J	1	R0
	R62	RK73FB2B4R7J	MG RESISTOR	4.7Ω 1/8W J	1	R0
	R80	RK73GB2A471J	MG RESISTOR	470Ω 1/10W J	1	R0
	R1007	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	R0
	RA1	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	R0
	RA2	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	R0
	RA3	RK74GB1J101J	NET RESISTOR	100Ω 1/16W J	1	R0
	CN1	QGZ2006K1-20X	DETACHABLE CONN	(1-20)	1	R0
	FL80	NQR0704-001X	CHOKE COIL		1	R0
	J60	QNS0320-001	3.5 JACK		1	R0
	J80	E5J-0069-00	USB TERMINAL		1	R0
	S20	T9K-0007-00	ROTARY ENCODER		1	R0