

EXPLODED VIEWS AND PARTS LIST

PACKING (Page 34)

PACKING SECTION PARTS LIST

*: Non spare part

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5
	1	Screw (M5 x 9)	Not used	CBA2384	Not used	Not used
	2	Screw (M5 x 9)	CBA2383	CBA2383	CBA2383	CBA2383
	3	Card Remote Control Unit	Not used	Not used	Not used	Not used
	4	Cord Assy	CDP1697	CDP1837	CDP1697	CDP1697
	5	Panel	Not used	Not used	Not used	Not used
	6	Cover	CEG1356	CEG1359	CEG1356	CEG1356
	7	Protector	QHP3078	QHP3077	QHP3078	QHP3078
	8	Unit Box	QHG4327	QHG4740	QHG4704	QHG4712
	9	Contain Box	QHL4327 (1/6)	QHL4740 (1/4)	QHL4704 (1/6)	QHL4712 (1/6)
	10-1	Owner's Manual	See Contents of Web IM	Not used	See Contents of Web IM	See Contents of Web IM
*	10-2	Warranty Card	CRY1376	QRY3001	CRY1376	CRY1376
	10-3	Quick Start Guide	QRD3607	QRD3865	QRD3814	QRD3814
	10-4	Installation Manual	QRD3619	Not used	QRD3821	QRD3821
	10-5	Owner's Manual	QRB3797	QRD3864	QRB3946	QRB3946
	11	Accessory Assy	QEA3671	*CEC7756	QEA3671	QEA3671
	12	Handle	CND7909	Not used	CND7909	CND7909

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS
	1	Screw (M5 x 9)	Not used	CBA2384	CBA2384	CBA2384
	2	Screw (M5 x 9)	CBA2383	Not used	Not used	Not used
	3	Card Remote Control Unit	Not used	CXE9605	CXE9605	CXE9605
	4	Cord Assy	CDP1697	CDP1697	CDP1697	CDP1837
	5	Panel	Not used	Not used	Not used	Not used
	6	Cover	CEG1356	CEG1356	CEG1356	CEG1356
	7	Protector	QHP3078	QHP3078	QHP3078	QHP3077
	8	Unit Box	QHG4327	QHG4705	QHG4713	QHG4707
	9	Contain Box	QHL4327 (1/6)	QHL4705 (1/6)	QHL4713 (1/6)	QHL4707 (1/6)
	10-1	Owner's Manual	See Contents of Web IM	Not used	Not used	See Contents of Web IM
*	10-2	Warranty Card	CRY1376	CRY1376	CRY1376	Not used
	10-3	Quick Start Guide	QRD3607	Not used	Not used	QRD3815
	10-4	Installation Manual	QRD3619	Not used	Not used	Not used
	10-5	Owner's Manual	QRB3797	QRB3945	QRB3945	Not used
	11	Accessory Assy	QEA3671	CEW3027	CEW3027	*CEC7757
	12	Handle	CND7909	CND7909	CND7909	Not used

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID
	1	Screw (M5 x 9)	Not used	CBA2384	CBA2384	CBA2384
	2	Screw (M5 x 9)	CBA2383	Not used	Not used	Not used
	3	Card Remote Control Unit	Not used	CXE9605	CXE9605	CXE9605
	4	Cord Assy	CDP1697	CDP1837	CDP1837	CDP1837
	5	Panel	Not used	Not used	Not used	CNS9475
	6	Cover	CEG1356	CEG1356	CEG1356	CEG1356
	7	Protector	QHP3078	QHP3077	QHP3078	QHP3077
	8	Unit Box	QHG4327	QHG4709	QHG4711	QHG4710
	9	Contain Box	QHL4327 (1/6)	QHL4709 (1/6)	QHL4711 (1/6)	QHL4710 (1/6)
	10-1	Owner's Manual	See Contents of Web IM	See Contents of Web IM	See Contents of Web IM	See Contents of Web IM
*	10-2	Warranty Card	CRY1376	Not used	Not used	CRY1304
	10-3	Quick Start Guide	QRD3607	QRD3817	QRD3818	QRB3942
	10-4	Installation Manual	QRD3619	Not used	Not used	Not used
	10-5	Owner's Manual	QRB3797	Not used	Not used	Not used
	11	Accessory Assy	QEA3671	*CEC7757	CEW3027	*CEC7757
	12	Handle	CND7909	Not used	CND7909	Not used

EXTERIOR (1) (Page 37)

EXTERIOR (1) SECTION PARTS LIST

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5
A	1	Grille Assy	QXA5587	QXA6465	QXA6381	QXA6386
	2	Grille	QNS4317	QNS4518	QNS4481	QNS4486
	5	Plate	QNM3240	QNM3240	QNM3240	QNM3241
	6	Monitor Key Unit	CWF2635	QWM5451	QWM5451	QWM5452
	12	Inspected TFT LCD Unit	QWX3009	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)
		Non-inspected TFT LCD Unit	QWX3010			
	19	Holder	CND7862	CND7862	CND7862	CND7862
	26	Holder	CND7859	Not used	CND7859	CND7859
	27	Panel	CNU2645	Not used	CNU2645	CNU2645

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS
B	1	Grille Assy	QXA5587	QXA6382	QXA6387	QXA6384
	2	Grille	QNS4317	QNS4482	QNS4487	QNS4484
	5	Plate	QNM3240	QNM3240	QNM3241	QNM3240
	6	Monitor Key Unit	CWF2635	QWM5451	QWM5452	QWM5451
	12	Inspected TFT LCD Unit	QWX3009	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)
		Non-inspected TFT LCD Unit	QWX3010			
	19	Holder	CND7862	CND7862	CND7862	CND7862
	26	Holder	CND7859	CND7859	CND7859	Not used
	27	Panel	CNU2645	CNU2645	CNU2645	Not used

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID
C	1	Grille Assy	QXA5587	QXA6384	QXA6384	QXA6385
	2	Grille	QNS4317	QNS4484	QNS4484	QNS4485
	5	Plate	QNM3240	QNM3240	QNM3240	QNM3240
	6	Monitor Key Unit	CWF2635	QWM5451	QWM5451	QWM5451
	12	Inspected TFT LCD Unit	QWX3009	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)	CWX5024 (TFT LCD)
		Non-inspected TFT LCD Unit	QWX3010			
	19	Holder	CND7862	CND7862	CND7862	CND7863
	26	Holder	CND7859	Not used	CND7859	Not used
	27	Panel	CNU2645	Not used	CNU2645	Not used

EXTERIOR (2) (Page 39)

EXTERIOR (2) SECTION PARTS LIST

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5
	1	Mother Unit	CWF2618	QWM5482	QWM5439	QWM5447
	9	Cord Assy	CDP1697	CDP1837	CDP1697	CDP1697
	10	Heat Conduction Sheet	CNN5528	CNN5729	CNN5729	CNN5729
	11	Fuse (10 A)	YEK5001	CEK1415	YEK5001	YEK5001
	12	Card Remote Control Unit	Not used	Not used	Not used	Not used
	13	Cover	Not used	Not used	Not used	Not used

A

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS
	1	Mother Unit	CWF2618	QWM5440	QWM5448	QWM5442
	9	Cord Assy	CDP1697	CDP1697	CDP1697	CDP1837
	10	Heat Conduction Sheet	CNN5528	CNN5729	CNN5729	CNN5729
	11	Fuse (10 A)	YEK5001	YEK5001	YEK5001	YEK5001
	12	Card Remote Control Unit	Not used	CXE9605	CXE9605	CXE9605
	13	Cover	Not used	CNU3681	CNU3681	CNU3681

B

Mark	No.	Description	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID
	1	Mother Unit	CWF2618	QWM5441	QWM5444	QWM5445
	9	Cord Assy	CDP1697	CDP1837	CDP1837	CDP1837
	10	Heat Conduction Sheet	CNN5528	CNN5729	CNN5729	CNN5729
	11	Fuse (10 A)	YEK5001	YEK5001	YEK5001	YEK5001
	12	Card Remote Control Unit	Not used	CXE9605	CXE9605	CXE9605
	13	Cover	Not used	CNU3681	CNU3681	CNU3681

C

D

E

F

ELECTRICAL PARTS LIST (Page 64)

MOTHER UNIT

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5
IC1011	Flash ROM Unit	*CVQ1156	*CVQ1267	*CVQ1267	CVQ1267
IC2101	OP AMP IC	NJM8065RB1	NJM8065RB1	NJM8065RB1	Not used
Q1601	Bipolar TR	Not used	Not used	Not used	Not used
Q1602	Bipolar TR	Not used	Not used	Not used	Not used
Q1603	Bipolar TR	Not used	Not used	Not used	Not used
Q1604	Bipolar TR	Not used	Not used	Not used	Not used
D1130	Switching Diode	1SS355VM	1SS355VM	1SS355VM	Not used
U901	BT Module	CWX4942	CWX4942	CWX4942	Not used
R756		Not used	Not used	Not used	Not used
R757		RS1/16SS104J	Not used	RS1/16SS104J	RS1/16SS104J
R758		Not used	Not used	Not used	Not used
R759		RS1/16SS104J	Not used	RS1/16SS104J	RS1/16SS104J
R760		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used
R761		Not used	Not used	Not used	RS1/16SS104J
R762		Not used	Not used	Not used	Not used
R763		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	RS1/16SS104J
R901		RS1/16SS511J	RS1/16SS511J	RS1/16SS511J	Not used
R902		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used
R903		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	Not used
R904		RS1/16SS220J	RS1/16SS220J	RS1/16SS220J	Not used
R905		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	Not used
R906		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used
R907		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used
R908		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used
R1071		RS1/16SS221J	RS1/16SS221J	RS1/16SS221J	Not used
R1080		RS1/16SS221J	RS1/16SS221J	RS1/16SS221J	Not used
R1082		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	Not used
R1088		RS1/16SS511J	RS1/16SS511J	RS1/16SS511J	Not used
R1601		Not used	Not used	Not used	Not used
R1602		Not used	Not used	Not used	Not used
R1603		Not used	Not used	Not used	Not used
R1605		Not used	Not used	Not used	Not used
R1606		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS102J
R1607		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS102J
R1706		RS1/10SR9102D	RS1/10SR7502D	RS1/10SR7502D	RS1/10SR7502D
R1707		RS1/10SR1802D	RS1/10SR1302D	RS1/10SR1302D	RS1/10SR1302D
R1712		RS1/16SS1003D	RS1/16SS1803D	RS1/16SS1803D	RS1/16SS1803D
R1713		RS1/16SS9101D	RS1/16SS2002D	RS1/16SS2002D	RS1/16SS2002D
R1717		RS1/16SS302J	RS1/16SS1502D	RS1/16SS1502D	RS1/16SS1502D
R1817		RS1/16SS153J	RS1/16SS273J	RS1/16SS273J	RS1/16SS273J
R1820		RS1/16SS273J	RS1/16SS683J	RS1/16SS683J	RS1/16SS683J
R1821		RS1/16SS474J	RS1/16SS224J	RS1/16SS224J	RS1/16SS224J
R1831		RS1/16SS3R9J	RS1/16SS3R3J	RS1/16SS3R3J	RS1/16SS3R3J
R1832		RS1/16SS270J	RS1/16SS680J	RS1/16SS680J	RS1/16SS680J
R1833		RS1/16SS221J	RS1/16SS180J	RS1/16SS180J	RS1/16SS180J
R1834		RS1/16SS750J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J
R1835		RS1/16SS560J	RS1/16SS430J	RS1/16SS430J	RS1/16SS430J
R1837		RS1/16SS510J	RS1/16SS360J	RS1/16SS360J	RS1/16SS360J
R1839		RS1/16SS151J	RS1/16SS131J	RS1/16SS131J	RS1/16SS131J
R1840		RS1/16SS270J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J
R1841		RS1/16SS131J	RS1/16SS8R2J	RS1/16SS8R2J	RS1/16SS8R2J
R1842		RS1/16SS131J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J
R1843		RS1/16SS151J	RS1/16SS1R0J	RS1/16SS1R0J	RS1/16SS1R0J
R1844		RS1/16SS240J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J

DMH-100BT/XNUC

5		6		7		8	
Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5		
R1845		RS1/16SS330J	RS1/16SS220J	RS1/16SS220J	RS1/16SS220J	A	
R1846		RS1/16SS270J	RS1/16SS300J	RS1/16SS300J	RS1/16SS300J		
R1847		RS1/16SS510J	RS1/16SS270J	RS1/16SS270J	RS1/16SS270J		
R1848		RS1/16SS220J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J		
R1849		RS1/16SS151J	RS1/16SS201J	RS1/16SS201J	RS1/16SS201J		
R1850		RS1/16SS151J	RS1/16SS560J	RS1/16SS560J	RS1/16SS560J		
R1851		RS1/16SS330J	RS1/16SS3R9J	RS1/16SS3R9J	RS1/16SS3R9J		
R1852		RS1/16SS1R0J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J		
R2104		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used		
R2105		RS1/16SS273J	RS1/16SS273J	RS1/16SS273J	Not used		
R2106		RS1/16SS822J	RS1/16SS822J	RS1/16SS822J	Not used	B	
R2107		RS1/16SS824J	RS1/16SS824J	RS1/16SS824J	Not used		
R2108		RS1/16SS563J	RS1/16SS563J	RS1/16SS563J	Not used		
R2109		RS1/16SS622J	RS1/16SS622J	RS1/16SS622J	Not used		
R2111		RS1/16SS472J	RS1/16SS472J	RS1/16SS472J	Not used		
R2118		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used		
R2120		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used		
C901		CKSRYX106M6R3	CKSRYX106M6R3	CKSRYX106M6R3	Not used		
C902		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	Not used		
C903		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	Not used		
C904		CKSRYX475K6R3	CKSRYX475K6R3	CKSRYX475K6R3	Not used	C	
C905		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	Not used		
C2108		CKSSYB104K16	CKSSYB104K16	CKSSYB104K16	Not used		
C2109		CCSSCH101J50	CCSSCH101J50	CCSSCH101J50	Not used		
C2110		CKSRYX225K10	CKSRYX225K10	CKSRYX225K10	Not used		
C2111		CKSSBYX225M10	CKSSBYX225M10	CKSSBYX225M10	Not used		
C2112		CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50	Not used		
C2113		CCSSCH220J50	CCSSCH220J50	CCSSCH220J50	Not used		
C2114		CKSSYX105K10	CKSSYX105K10	CKSSYX105K10	Not used		
C2115		CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50	Not used		
C2116		CKSSYB102K50	CKSSYB102K50	CKSSYB102K50	Not used		

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS		
IC1011	Flash ROM Unit	*CVQ1156	*CVQ1267	CVQ1267	*CVQ1267		
IC2101	OP AMP IC	NJM8065RB1	NJM8065RB1	Not used	NJM8065RB1		
Q1601	Bipolar TR	Not used	Not used	Not used	EMD53		
Q1602	Bipolar TR	Not used	Not used	Not used	EMD53		
Q1603	Bipolar TR	Not used	Not used	Not used	EMD53		
Q1604	Bipolar TR	Not used	Not used	Not used	EMD53		
D1130	Switching Diode	1SS355VM	1SS355VM	Not used	1SS355VM		
U901	BT Module	CWX4942	CWX4942	Not used	CWX4942		
R756		Not used	Not used	Not used	RS1/16SS104J		
R757		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used		
R758		Not used	RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	E	
R759		RS1/16SS104J	Not used	Not used	Not used		
R760		RS1/16SS104J	RS1/16SS104J	Not used	RS1/16SS104J		
R761		Not used	Not used	RS1/16SS104J	Not used		
R762		Not used	Not used	Not used	RS1/16SS104J		
R763		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used		
R901		RS1/16SS511J	RS1/16SS511J	Not used	RS1/16SS511J		
R902		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J		
R903		RS1/16SS103J	RS1/16SS103J	Not used	RS1/16SS103J		
R904		RS1/16SS220J	RS1/16SS220J	Not used	RS1/16SS220J		
R905		RS1/16SS103J	RS1/16SS103J	Not used	RS1/16SS103J	F	
R906		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J		
R907		RS1/16SS104J	RS1/16SS104J	Not used	RS1/16SS104J		

A

B

C

D

E

F

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS
R908		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
R1071		RS1/16SS221J	RS1/16SS221J	Not used	RS1/16SS221J
R1080		RS1/16SS221J	RS1/16SS221J	Not used	RS1/16SS221J
R1082		RS1/16SS103J	RS1/16SS103J	Not used	RS1/16SS103J
R1088		RS1/16SS511J	RS1/16SS511J	Not used	RS1/16SS511J
R1601		Not used	Not used	Not used	RS1/16SS8201D
R1602		Not used	Not used	Not used	RS1/16SS6800D
R1603		Not used	Not used	Not used	RS1/16SS8201D
R1605		Not used	Not used	Not used	RS1/16SS6800D
R1606		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS1001D
R1607		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS1001D
R1706		RS1/10SR9102D	RS1/10SR7502D	RS1/10SR7502D	RS1/10SR7502D
R1707		RS1/10SR1802D	RS1/10SR1302D	RS1/10SR1302D	RS1/10SR1302D
R1712		RS1/16SS1003D	RS1/16SS1803D	RS1/16SS1803D	RS1/16SS1803D
R1713		RS1/16SS9101D	RS1/16SS2002D	RS1/16SS2002D	RS1/16SS2002D
R1717		RS1/16SS302J	RS1/16SS1502D	RS1/16SS1502D	RS1/16SS1502D
R1817		RS1/16SS153J	RS1/16SS273J	RS1/16SS273J	RS1/16SS273J
R1820		RS1/16SS273J	RS1/16SS683J	RS1/16SS683J	RS1/16SS683J
R1821		RS1/16SS474J	RS1/16SS224J	RS1/16SS224J	RS1/16SS224J
R1831		RS1/16SS3R9J	RS1/16SS3R3J	RS1/16SS3R3J	RS1/16SS3R3J
R1832		RS1/16SS270J	RS1/16SS680J	RS1/16SS680J	RS1/16SS680J
R1833		RS1/16SS221J	RS1/16SS180J	RS1/16SS180J	RS1/16SS180J
R1834		RS1/16SS750J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J
R1835		RS1/16SS560J	RS1/16SS430J	RS1/16SS430J	RS1/16SS430J
R1837		RS1/16SS510J	RS1/16SS360J	RS1/16SS360J	RS1/16SS360J
R1839		RS1/16SS151J	RS1/16SS131J	RS1/16SS131J	RS1/16SS131J
R1840		RS1/16SS270J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J
R1841		RS1/16SS131J	RS1/16SS8R2J	RS1/16SS8R2J	RS1/16SS8R2J
R1842		RS1/16SS131J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J
R1843		RS1/16SS151J	RS1/16SS1R0J	RS1/16SS1R0J	RS1/16SS1R0J
R1844		RS1/16SS240J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J
R1845		RS1/16SS330J	RS1/16SS220J	RS1/16SS220J	RS1/16SS220J
R1846		RS1/16SS270J	RS1/16SS300J	RS1/16SS300J	RS1/16SS300J
R1847		RS1/16SS510J	RS1/16SS270J	RS1/16SS270J	RS1/16SS270J
R1848		RS1/16SS220J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J
R1849		RS1/16SS151J	RS1/16SS201J	RS1/16SS201J	RS1/16SS201J
R1850		RS1/16SS151J	RS1/16SS560J	RS1/16SS560J	RS1/16SS560J
R1851		RS1/16SS330J	RS1/16SS3R9J	RS1/16SS3R9J	RS1/16SS3R9J
R1852		RS1/16SS1R0J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J
R2104		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
R2105		RS1/16SS273J	RS1/16SS273J	Not used	RS1/16SS273J
R2106		RS1/16SS822J	RS1/16SS822J	Not used	RS1/16SS822J
R2107		RS1/16SS824J	RS1/16SS824J	Not used	RS1/16SS824J
R2108		RS1/16SS563J	RS1/16SS563J	Not used	RS1/16SS563J
R2109		RS1/16SS622J	RS1/16SS622J	Not used	RS1/16SS622J
R2111		RS1/16SS472J	RS1/16SS472J	Not used	RS1/16SS472J
R2118		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
R2120		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
C901		CKSRYX106M6R3	CKSRYX106M6R3	Not used	CKSRYX106M6R3
C902		CKSSYB104K10	CKSSYB104K10	Not used	CKSSYB104K10
C903		CKSSYB104K10	CKSSYB104K10	Not used	CKSSYB104K10
C904		CKSRYX475K6R3	CKSRYX475K6R3	Not used	CKSRYX475K6R3
C905		CKSSYB104K10	CKSSYB104K10	Not used	CKSSYB104K10
C2108		CKSSYB104K16	CKSSYB104K16	Not used	CKSSYB104K16
C2109		CCSSCH101J50	CCSSCH101J50	Not used	CCSSCH101J50
C2110		CKSRYX225K10	CKSRYX225K10	Not used	CKSRYX225K10

5		6		7		8	
Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS		
C2111		CKSSBYX225M10	CKSSBYX225M10	Not used	CKSSBYX225M10		
C2112		CCSSCH6R0D50	CCSSCH6R0D50	Not used	CCSSCH6R0D50		
C2113		CCSSCH220J50	CCSSCH220J50	Not used	CCSSCH220J50		
C2114		CKSSYX105K10	CKSSYX105K10	Not used	CKSSYX105K10		
C2115		CCSSCH6R0D50	CCSSCH6R0D50	Not used	CCSSCH6R0D50		
C2116		CKSSYB102K50	CKSSYB102K50	Not used	CKSSYB102K50		

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID		
IC1011	Flash ROM Unit	*CVQ1156	*CVQ1267	*CVQ1267	*CVQ1267		
IC2101	OP AMP IC	NJM8065RB1	NJM8065RB1	NJM8065RB1	NJM8065RB1		
Q1601	Bipolar TR	Not used	EMD53	EMD53	EMD53		
Q1602	Bipolar TR	Not used	EMD53	EMD53	EMD53		
Q1603	Bipolar TR	Not used	EMD53	EMD53	EMD53		
Q1604	Bipolar TR	Not used	EMD53	EMD53	EMD53		
D1130	Switching Diode	1SS355VM	1SS355VM	1SS355VM	1SS355VM		
U901	BT Module	CWX4942	CWX4942	CWX4942	CWX4942		
R756		Not used	RS1/16SS104J	Not used	Not used		
R757		RS1/16SS104J	Not used	RS1/16SS104J	RS1/16SS104J		
R758		Not used	Not used	Not used	RS1/16SS104J		
R759		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used		
R760		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	RS1/16SS104J		
R761		Not used	Not used	Not used	Not used		
R762		Not used	Not used	RS1/16SS104J	RS1/16SS104J		
R763		RS1/16SS104J	RS1/16SS104J	Not used	Not used		
R901		RS1/16SS511J	RS1/16SS511J	RS1/16SS511J	RS1/16SS511J		
R902		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J		
R903		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	RS1/16SS103J		
R904		RS1/16SS220J	RS1/16SS220J	RS1/16SS220J	RS1/16SS220J		
R905		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	RS1/16SS103J		
R906		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J		
R907		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	RS1/16SS104J		
R908		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J		
R1071		RS1/16SS221J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J		
R1080		RS1/16SS221J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J		
R1082		RS1/16SS103J	RS1/16SS103J	RS1/16SS103J	RS1/16SS103J		
R1088		RS1/16SS511J	RS1/16SS511J	RS1/16SS511J	RS1/16SS511J		
R1601		Not used	RS1/16SS8201D	RS1/16SS8201D	RS1/16SS8201D		
R1602		Not used	RS1/16SS6800D	RS1/16SS6800D	RS1/16SS6800D		
R1603		Not used	RS1/16SS8201D	RS1/16SS8201D	RS1/16SS8201D		
R1605		Not used	RS1/16SS6800D	RS1/16SS6800D	RS1/16SS6800D		
R1606		RS1/16SS102J	RS1/16SS1001D	RS1/16SS1001D	RS1/16SS1001D		
R1607		RS1/16SS102J	RS1/16SS1001D	RS1/16SS1001D	RS1/16SS1001D		
R1706		RS1/10SR9102D	RS1/10SR7502D	RS1/10SR7502D	RS1/10SR7502D		
R1707		RS1/10SR1802D	RS1/10SR1302D	RS1/10SR1302D	RS1/10SR1302D		
R1712		RS1/16SS1003D	RS1/16SS1803D	RS1/16SS1803D	RS1/16SS1803D		
R1713		RS1/16SS9101D	RS1/16SS2002D	RS1/16SS2002D	RS1/16SS2002D		
R1717		RS1/16SS302J	RS1/16SS1502D	RS1/16SS1502D	RS1/16SS1502D		
R1817		RS1/16SS153J	RS1/16SS273J	RS1/16SS273J	RS1/16SS273J		
R1820		RS1/16SS273J	RS1/16SS683J	RS1/16SS683J	RS1/16SS683J		
R1821		RS1/16SS474J	RS1/16SS224J	RS1/16SS224J	RS1/16SS224J		
R1831		RS1/16SS3R9J	RS1/16SS3R3J	RS1/16SS3R3J	RS1/16SS3R3J		
R1832		RS1/16SS270J	RS1/16SS680J	RS1/16SS680J	RS1/16SS680J		
R1833		RS1/16SS221J	RS1/16SS180J	RS1/16SS180J	RS1/16SS180J		
R1834		RS1/16SS750J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J		
R1835		RS1/16SS560J	RS1/16SS430J	RS1/16SS430J	RS1/16SS430J		
R1837		RS1/16SS510J	RS1/16SS360J	RS1/16SS360J	RS1/16SS360J		

DMH-100BT/XNUC

A

B

C

D

E

F

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID
R1839		RS1/16SS151J	RS1/16SS131J	RS1/16SS131J	RS1/16SS131J
R1840		RS1/16SS270J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J
R1841		RS1/16SS131J	RS1/16SS8R2J	RS1/16SS8R2J	RS1/16SS8R2J
R1842		RS1/16SS131J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J
R1843		RS1/16SS151J	RS1/16SS1R0J	RS1/16SS1R0J	RS1/16SS1R0J
R1844		RS1/16SS240J	RS1/16SS221J	RS1/16SS221J	RS1/16SS221J
R1845		RS1/16SS330J	RS1/16SS220J	RS1/16SS220J	RS1/16SS220J
R1846		RS1/16SS270J	RS1/16SS300J	RS1/16SS300J	RS1/16SS300J
R1847		RS1/16SS510J	RS1/16SS270J	RS1/16SS270J	RS1/16SS270J
R1848		RS1/16SS220J	RS1/16SS330J	RS1/16SS330J	RS1/16SS330J
R1849		RS1/16SS151J	RS1/16SS201J	RS1/16SS201J	RS1/16SS201J
R1850		RS1/16SS151J	RS1/16SS560J	RS1/16SS560J	RS1/16SS560J
R1851		RS1/16SS330J	RS1/16SS3R9J	RS1/16SS3R9J	RS1/16SS3R9J
R1852		RS1/16SS1R0J	RS1/16SS510J	RS1/16SS510J	RS1/16SS510J
R2104		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J
R2105		RS1/16SS273J	RS1/16SS273J	RS1/16SS273J	RS1/16SS273J
R2106		RS1/16SS822J	RS1/16SS822J	RS1/16SS822J	RS1/16SS822J
R2107		RS1/16SS824J	RS1/16SS824J	RS1/16SS824J	RS1/16SS824J
R2108		RS1/16SS563J	RS1/16SS563J	RS1/16SS563J	RS1/16SS563J
R2109		RS1/16SS622J	RS1/16SS622J	RS1/16SS622J	RS1/16SS622J
R2111		RS1/16SS472J	RS1/16SS472J	RS1/16SS472J	RS1/16SS472J
R2118		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J
R2120		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J
C901		CKSRYX106M6R3	CKSRYX106M6R3	CKSRYX106M6R3	CKSRYX106M6R3
C902		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	CKSSYB104K10
C903		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	CKSSYB104K10
C904		CKSRYX475K6R3	CKSRYX475K6R3	CKSRYX475K6R3	CKSRYX475K6R3
C905		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	CKSSYB104K10
C2108		CKSSYB104K16	CKSSYB104K16	CKSSYB104K16	CKSSYB104K16
C2109		CCSSCH101J50	CCSSCH101J50	CCSSCH101J50	CCSSCH101J50
C2110		CKSRYX225K10	CKSRYX225K10	CKSRYX225K10	CKSRYX225K10
C2111		CKSSBYX225M10	CKSSBYX225M10	CKSSBYX225M10	CKSSBYX225M10
C2112		CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50
C2113		CCSSCH220J50	CCSSCH220J50	CCSSCH220J50	CCSSCH220J50
C2114		CKSSYX105K10	CKSSYX105K10	CKSSYX105K10	CKSSYX105K10
C2115		CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50	CCSSCH6R0D50
C2116		CKSSYB102K50	CKSSYB102K50	CKSSYB102K50	CKSSYB102K50

MONITOR KEY UNIT

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-100BT/XNUC	DMH-G220BT/XNEW5	DMH-G120/XNEW5
MC2001	Microphone	CPM1116	CPM1116	CPM1116	Not used
R2018		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used
R2019		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	Not used
R2111		RS1/16SS2702D	RS1/16SS2202D	RS1/16SS2202D	RS1/16SS2202D
C2007		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	Not used

A

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G221BT/XNUR	DMH-G121/XNUR	DMH-G225BT/XNCS
MC2001	Microphone	CPM1116	CPM1116	Not used	CPM1116
R2018		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
R2019		RS1/16SS0R0J	RS1/16SS0R0J	Not used	RS1/16SS0R0J
R2111		RS1/16SS2702D	RS1/16SS2202D	RS1/16SS2202D	RS1/16SS2202D
C2007		CKSSYB104K10	CKSSYB104K10	Not used	CKSSYB104K10

B

Circuit Symbol and No.	Part Name	MVH-G210BT/XNEW5	DMH-G225BT/XNRC	DMH-G225BT/XNRI	DMH-G229BT/XNID
MC2001	Microphone	CPM1116	CPM1116	CPM1116	CPM1116
R2018		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J
R2019		RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J	RS1/16SS0R0J
R2111		RS1/16SS2702D	RS1/16SS2202D	RS1/16SS2202D	RS1/16SS2202D
C2007		CKSSYB104K10	CKSSYB104K10	CKSSYB104K10	CKSSYB104K10

The mounting positions of the additional parts are described in the circuit diagram and PCB diagram of the parent manual.

C

D

E

F