

TK-630H(B)



PACKING

- 6 Warranty card (B46-0409-30)
7 Instruction manual (B62-0069-00)

- 39 Protection bag (H25-0103-04)
10 Ground lead wire (E30-2036-05)
42 Screw set (N99-0365-05)
38 Protection bag (H25-0096-04)
11 Short plug (E31-3228-05)
16 Cover (F07-1336-05)
41 Wire band (J61-0307-05)

- 29 Inner packing case
(H02-0604-03)

- 40 Protection bag
(H25-0724-04)

- 35 Packing fixture
(H12-1410-04)

- 34 Packing fixture
(H12-1399-04)

- 30 Polystyrene plate
(H11-0815-04)

- 31 Polystyrene plate
(H11-0853-04)

- 37 Packing fixture
(H12-1442-04)

- 33 Polystyrene foamed fixture
(H10-2731-01)

- 36 Packing fixture
(H12-1434-04)

- 32 Item carton box
(H52-0203-04)

TK-630H(B)

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TK-630H(B)

FINAL UNIT (X45-3440-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
TK-630H(B)						
1	3B		A01-2020-01	CASE(UPPER)		
2	1A		A01-2025-01	CASE(LOWER)		
3	2B		A10-1320-01	FRAME		
5	3A		B42-3343-04	LABEL(S/NO)		
6	1G		B46-0409-30	WARRANTY CARD		
7	1G		B62-0069-00	INSTRUCTION MANUAL		
8	3A		B72-0300-04	MODEL NAME PLATE	K	
8	3A		B72-0301-04	MODEL NAME PLATE	K2	
8	3A		B72-0302-14	MODEL NAME PLATE	K3	
10	1H		E30-2036-05	GROUND LEAD WIRER		
11	2A, 1H		E31-3228-05	SHORT PLUG		
12	2B		E31-3301-05	CONNECTING WIRE(RA/DO)		
13	2B		E37-0153-05	FLEXIBLE PC BOARD(17P)		
14	2B		E37-0154-05	FLEXIBLE PC BOARD(13P)		
16	1H		F07-1336-05	COVER		
17	1A		F10-1488-02	SHIELDING PLATE(FINAL)		
22	2B		G02-0574-04	LEAF SPRING(AVR)		
23	2B		G02-0709-04	LEAF SPRING(AF.AMP)		
24	3B		G10-0707-14	NON-WOVEN FABRIC		
25	3B		G13-1354-04	CUSHION(IC108)		
26	1A		G53-0716-13	PACKING		
27	3B		G53-0732-03	PACKING		
29	1G		H02-0604-03	INNER PACKING CASE		
30	1H		H11-0815-04	POLYSTYRENE PLATE		
31	1H		H11-0853-04	POLYSTYRENE PLATE		
32	3G		H52-0203-04	ITEM CARTON BOX		
33	2H		H10-2731-01	POLYSTYRENE FOAMED FIXTURE		
34	2G		H12-1399-04	PACKING FIXTURE		
35	2G		H12-1410-04	PACKING FIXTURE		
36	2G		H12-1434-04	PACKING FIXTURE		
37	2H		H12-1442-04	PACKING FIXTURE		
38	1H		H25-0096-04	PROTECTION BAG		
39	1H		H25-0103-04	PROTECTION BAG		
40	1G		H25-0724-04	PROTECTION BAG		
41	1H		J61-0307-05	WIRER BAND		
42	1H		N99-0365-05	SCREW SET		
A	1B, 3B		N35-3008-45	BINDING HEAD MACHINE SCREW		
B	2B, 3B		N87-2606-46	BRAZIER HEAD TAPTITE SCREW		
44	1B		X45-3440-10	FINAL UNIT	K	
44	1B		X45-3440-11	FINAL UNIT	K2	
44	1B		X45-3440-12	FINAL UNIT	K3	
45	2B, 3B		X57-3960-10	TX-RX UNIT	K	
45	2B, 3B		X57-3960-11	TX-RX UNIT	K2	
45	2B, 3B		X57-3960-12	TX-RX UNIT	K3	
FINAL UNIT (X45-3440-XX) -10 : K -11 : K2 -12 : K3						
C2	-4		CK73FB1H472K	CHIP C 4700PF	K	
C5			CK73FB1E104K	CHIP C 0.10UF	K	
C6			CK73FB1H472K	CHIP C 4700PF	K	
C7			CK73FB1E104K	CHIP C 0.10UF	K	

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

FINAL UNIT (X45-3440-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C8			C90-2143-05	ELECTRO 47UF 25WV		
C10			CK73FB1H471K	CHIP C 470PF K	K	
C10			CK73FB1H331K	CHIP C 330PF K	K2	
C10			CC73FSL1H151J	CHIP C 150PF K	K3	
C11			CK45B1H472K	CERAMIC 4700PF K		
C12			CC45SL2H101J	CERAMIC 100PF J	K	
C12			CC45SL2H820J	CERAMIC 82PF J	K2, K3	
C13			CC45SL2H680J	CERAMIC 68PF J	K2, K3	
C14			CK73FB1H472K	CHIP C 4700PF K		
C15			CK73EB1E104K	CHIP C 0.10UF K		
C16			C90-2143-05	ELECTRO 47UF 25WV		
C17			CK73FB1H472K	CHIP C 4700PF K		
C18			CC45SL2H470J	CERAMIC 47PF J	K3	
C18			CC45SL2H680J	CERAMIC 68PF J	K2	
C18			CC45SL2H820J	CERAMIC 82PF J	K	
C19			CC45SL2H271J	CERAMIC 270PF J	K3	
C19			CC45SL2H391J	CERAMIC 390PF J	K2	
C19			CC45SL2H561J	CERAMIC 560PF J	K	
C20 , 21			CK45B1H472K	CERAMIC 4700PF K		
C22 , 23			CM73F2H101J	CHIP C 100PF J	K3	
C22 , 23			CM73F2H181J	CHIP C 180PF J	K	
C24			CM73F2H112J	CHIP C 1100PF J	K	
C24			CM73F2H561J	CHIP C 560PF J	K3	
C24			CM73F2H751J	CHIP C 750PF J	K2	
C25			CM73F2H120J	CHIP C 12PF J	K3	
C25			CM73F2H180J	CHIP C 18PF J	K2	
C25			CM73F2H330J	CHIP C 33PF J	K	
C26			CK73FB1H472K	CHIP C 4700PF K		
C27			CK73EB1E104K	CHIP C 0.10UF K		
C28			CK73FB1H472K	CHIP C 4700PF K		
C29			C90-2143-05	ELECTRO 47UF 25WV		
C30			CK73FB1H472K	CHIP C 4700PF K		
C31			CM73F2H620J	CHIP C 62PF J	K3	
C31			CM73F2H820J	CHIP C 82PF J	K, K2	
C32			CM73F2H040D	CHIP C 4.0PF D	K2	
C32			CM73F2H080D	CHIP C 8.0PF D	K, K3	
C33			CM73F2H101J	CHIP C 100PF J	K3	
C33			CM73F2H121J	CHIP C 120PF J	K2	
C33			CM73F2H151J	CHIP C 150PF J	K	
C34			CM73F2H220J	CHIP C 22PF J	K, K2	
C34			CM73F2H270J	CHIP C 27PF J	K3	
C35			CM73F2H101J	CHIP C 100PF J	K2	
C35			CM73F2H121J	CHIP C 120PF J	K	
C36			CM73F2H390J	CHIP C 39PF J	K2	
C36			CM73F2H470J	CHIP C 47PF J	K3	
C36			CM73F2H510J	CHIP C 51PF J	K	
C37			CM73F2H330J	CHIP C 33PF J	K3	
C37			CM73F2H430J	CHIP C 43PF J	K2	
C37			CM73F2H470J	CHIP C 47PF J	K	
C38			CM73F2H020C	CHIP C 2.0PF C		
C39			CC73FCH1H820J	CHIP C 82PF J		
C40			CM73F2H020C	CHIP C 2.0PF C		
C41			CC73FCH1H680J	CHIP C 68PF J		
C42 -52			CK73FB1H472K	CHIP C 4700PF K		
C53			C90-2020-05	ELECTRO 15UF 25WV		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

FINAL UNIT (X45-3440-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C54			CK73FB1H102K	CHIP C 1000PF K		
C55			C90-2165-05	ELECTRØ 10UF 50WV		
C56			CK73FB1H102K	CHIP C 1000PF K		
C57 ,58			CK73FB1H472K	CHIP C 4700PF K		
C59 ,60			C90-2155-05	ELECTRØ 470UF 25WV		
C61 -64			CK73FB1H472K	CHIP C 4700PF K		
C65			CC73FSL1H101J	CHIP C 100PF J	K2	
C65			CC73FSL1H121J	CHIP C 120PF J	K3	
C65			CC73FSL1H151J	CHIP C 150PF J	K	
C66 ,67			CC73FCH1H330J	CHIP C 33PF J		
C68			CK73FB1H102K	CHIP C 1000PF K		
C69			C90-2146-05	ELECTRØ 100UF 25WV		
C70			CM73F2H820J	CHIP C 82PF J	K3	
C71			CC73FSL1H101J	CHIP C 100PF J	K	
C72 ,73			CM73F2H121J	CHIP C 120PF J	K2, K3	
J2			E04-0167-05	RF COAXIAL CABLE RECEPTACLE		
CN1 ,2			E04-0154-05	RF COAXIAL CABLE RECEPTACLE		
CN3 ,4			E23-0491-15	TERMINAL		
W1			E37-0138-05	CONNECTING WIRE(3P)		
W2			E37-0139-05	CONNECTING WIRE(4P)		
W3			E37-0183-05	FINISHED WIRE		
W4	2A		R92-1061-05	JUMPER REST 0 ØHM		
W5	2A		E37-0160-05	CONNECTING WIRE(2P)		
W6	2A		E37-0161-15	CONNECTING WIRE(15P)		
			G13-0635-04	FORMED PLATE		
			G13-1354-04	FORMED PLATE		
101	2A		G53-0715-03	PACKING		
			J61-0307-05	WIRE BAND		
102	2A		J21-4351-04	MOUNTING HARDWARE		
A2			J31-0531-04	COLLAR		
			L92-0125-05	CØRE		
A1			L34-1376-15	CØIL		
L2			L40-1092-48	SMALL FIXED INDUCTØR(1U)		
L3			L34-0908-05	CØIL		
L4			L34-1039-05	CØIL		
L5			L39-1211-15	CØIL		
L6			L33-0666-05	CHØKE CØIL		
L7			L39-1213-15	CØIL		
L8			L39-1214-25	CØIL	K	
L8			L39-1215-25	CØIL	K3	
L8			L39-1239-05	CØIL	K2	
L9			L33-0625-15	CHØKE CØIL		
L10			L34-1150-05	CØIL	K, K2	
L10			L34-1241-05	CØIL	K3	
L11			L34-1151-05	CØIL	K3	
L11			L34-1241-05	CØIL	K, K2	
L12			L34-1256-05	CØIL	K3	
L12			L34-1259-05	CØIL	K, K2	
L13			L39-0447-05	CØIL		
L14 ,15			L40-2201-48	SMALL FIXED INDUCTØR(22U)		
L16			L40-4792-48	SMALL FIXED INDUCTØR(4.7U)		
L17			L40-5672-48	SMALL FIXED INDUCTØR(56N)	K3	
L17			L40-6872-48	SMALL FIXED INDUCTØR(68N)	K, K2	

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

FINAL UNIT (X45-3440-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
D	1B, 2B		N16-0040-41	WASHER		
E	1B		N09-2077-05	SCREW (M3X8)		
F	1B		N35-3006-46	BINDING HEAD MACHINE SCREW		
G	2A		N87-2606-46	BRAZIER HEAD TAPTITE SCREW		
			N87-3008-46	BRAZIER HEAD TAPTITE SCREW		
			N35-4006-46	BRAZIER HEAD TAPTITE SCREW		
TH1			PTH9M04BC471TS	POSISTOR		
R1 ,3			RK73FB2A271J	CHIP R 270 J 1/10W	K3	
R1 ,3			RK73FB2A151J	CHIP R 150 J 1/10W	K, K2	
R2			RK73FB2A390J	CHIP R 39 J 1/10W	K, K2	
R2			RK73FB2A180J	CHIP R 18 J 1/10W	K3	
R3			RK73FB2A151J	CHIP R 150 J 1/10W		
R4			R92-1261-05	SILID 150 1/2W		
R5			R92-0685-05	CHIP R 22 J 1/2W		
R6			RS14DB3F101J	FL-PROOF RS 100 J 3W		
R7 ,8			RS14DB3F4R7J	FL-PROOF RS 4.7 J 3W		
R9 ,10			RS14DB3A4R7J	FL-PROOF RS 4.7 J 1W		
R11 -14			RS14DB3F221J	FL-PROOF RS 220 J 3W		
R15			RK73FB2A220J	CHIP R 22 J 1/10W	K2	
R15			RK73FB2A270J	CHIP R 27 J 1/10W	K	
R15			RK73FB2A330J	CHIP R 33 J 1/10W	K3	
R16 ,17			RK73FB2A270J	CHIP R 27 J 1/10W		
R18			RK73FB2A220J	CHIP R 22 J 1/10W		
R19			R92-0670-05	CHIP R 0 OHM		
R20			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R21			RK73FB2A223J	CHIP R 22K J 1/10W		
R22			RK73FB2A471J	CHIP R 470 J 1/10W		
R23			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R24			RK73FB2A122J	CHIP R 1.2K J 1/10W		
R25			RK73FB2A101J	CHIP R 100 J 1/10W		
R27			RK73FB2A392J	CHIP R 3.9K J 1/10W		
R28			RK73FB2A122J	CHIP R 1.2K J 1/10W		
R29			RK73FB2A103J	CHIP R 10K J 1/10W		
R31			RK73FB2A271J	CHIP R 270 J 1/10W		
R32			R92-0670-05	CHIP R 0 OHM		
R33			RK73FB2A471J	CHIP R 470 J 1/10W		
R34			RS14DB3A220J	FL-PROOF RS 22 J 1W		
R101			R92-0670-05	CHIP R 0 OHM	K	
R102			R92-0670-05	CHIP R 0 OHM	K2	
R103			R92-0670-05	CHIP R 0 OHM	K3	
VR1			R12-3126-05	TRIM POT. (10K)		
VR2			R12-6423-05	TRIM POT. (10K)		
K1			S76-0409-05	RELAY		
D1			1SS184	DIODE		
D2 ,3			1SS101	DIODE		
D4			1SS184	DIODE		
D5			1SS193	DIODE		
D6			SG-5L(R)			
D7			02CZ10(X,Y)	DIODE		
D8			BRZ-M10DK220	DIODE		
Q1	2B		2SC1971	TRANSISTOR		
Q2	2B		2SC1972	TRANSISTOR		
Q3 ,4			2SC2694	TRANSISTOR		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

FINAL UNIT (X45-3440-XX)

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位 置	New Parts 新	Parts No. 部 品 番 号	Description 部 品 名 / 規 格	Desti- nation 仕 向	Re- marks 備考
Q5 Q6 Q7 Q8 Q9	1B		2SD1406(Y) 2SA1162(Y) 2SC2712(Y) FMW1 FMC2	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q10 Q11			2SD1682(R,S) DTC114EK	TRANSISTOR TRANSISTOR		
			212-0702-05	PLASTIC TUBE		
TX-RX UNIT (X57-3960-XX) -10 : K -11 : K2 -12 : K3						
C101 C102 C103 C104, 105 C106			CK73FB1E104K CE04EW1E470M CK73FB1H102K C92-0007-05 CK73FB1H102K	CHIP C 0.10UF K ELECTRO 47UF 25WV CHIP C 1000PF K CHIP TAN 2.2UF 10WV CHIP C 1000PF K		
C107 C108 C109 C110 C111			CE04EW1E100M CE04EW1E470M CK73FB1H102K C92-0003-05 C90-2032-05	ELECTRO 10UF 25WV ELECTRO 47UF 25WV CHIP C 1000PF K CHIP TAN 0.47UF 25WV ELECTRO 47UF 10WV		
C112 C113 C114 C115 C116			CK73FB1H102K CK73FB1E103K C92-0004-05 CK73FB1E104K CE04EW1C470M	CHIP C 1000PF K CHIP C 0.01UF K ELECTRO 1.0UF 16WV CHIP C 0.10UF K ELECTRO 47UF 16WV		
C117 C118 C119 C120 C121			CK73FB1H102K C92-0008-05 CK73EF1C105Z C92-0007-05 CK73FB1E104K	CHIP C 1000PF K CHIP TAN 3.3UF 16WV CHIP C 1.0UF Z CHIP TAN 2.2UF 10WV CHIP C 0.10UF K		
C122 C123 C124 C125 C126			CE04EW1C470M CK73FB1H102K CK73EF1C105Z CK73FB1E104K CK73FB1H102K	ELECTRO 47UF 16WV CHIP C 1000PF K CHIP C 1.0UF Z CHIP C 0.10UF K CHIP C 1000PF K		
C127, 128 C129 C130 C131 C132, 133			CK73FB1E103K CK73FB1H102K CE04EW1C101M CK73FB1H471K CK73FB1H102K	CHIP C 0.01UF K CHIP C 1000PF K ELECTRO 100UF 16WV CHIP C 470PF K CHIP C 1000PF K		
C134, 135 C136 C137 C138 C140			CC73FCH1H100D CK73FB1E104K CK73FB1E103K CK73FB1E104K CK73FB1H471K	CHIP C 10PF D CHIP C 0.10UF K CHIP C 0.01UF K CHIP C 0.10UF K CHIP C 470PF K		
C141-143 C144, 145 C147-149 C150 C151-154			CK73FB1E103K CK73FB1H102K CK73FB1H102K CC73FSL1H101J CK73FB1H102K	CHIP C 0.01UF K CHIP C 1000PF K CHIP C 1000PF K CHIP C 100PF J CHIP C 1000PF K		
C155-158 C159 C160 C161, 162 C164-166			CC73FSL1H101J CK73FB1H102K CC73FSL1H101J CK73FB1H102K CK73FB1H102K	CHIP C 100PF J CHIP C 1000PF K CHIP C 100PF J CHIP C 1000PF K CHIP C 1000PF K		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位 置	New Parts 新	Parts No. 部 品 番 号	Description 部 品 名 / 規 格	Desti- nation 仕 向	Re- marks 備考
C167, 168 C169-173 C183 C185-193 C195, 196			CC73FSL1H101J CK73FB1H102K CK73FB1H102K CK73FB1H102K CC73FSL1H101J	CHIP C 100PF J CHIP C 1000PF K CHIP C 1000PF K CHIP C 1000PF K CHIP C 100PF J		
C197 C198, 199 C200-206 C207-209 C210			CK73FB1E103K CC73FSL1H101J CK73FB1H102K CC73FSL1H101J CK73FB1H102K	CHIP C 0.01UF K CHIP C 100PF J CHIP C 1000PF K CHIP C 100PF J CHIP C 1000PF K		
C211 C212-216 C218 C219 C301			CC73FSL1H101J CK73FB1H102K C92-0543-05 CC73FCH1H020C CC73FCH1H150J	CHIP C 100PF J CHIP C 1000PF K ELECTRO 3.3UF 10WV CHIP C 2.0PF C CHIP C 15PF J		
C303-306 C307 C308 C309 C310			CK73FB1E103K CC73FCH1H040C CK73FB1E103K CC73FCH1H020C CC73FCH1H040C	CHIP C 0.01UF K CHIP C 4PF C CHIP C 0.01UF K CHIP C 2.0PF C CHIP C 4PF C	K3 K, K2	
C310 C311 C312 C313 C313			CC73FCH1H080D CK73FB1E103K CC73FCH1H020C CC73FCH1H020C CC73FCH1H030C	CHIP C 8PF D CHIP C 0.01UF K CHIP C 2.0PF C CHIP C 2.0PF C CHIP C 3PF C	K3 K2 K	
C313 C314 C315-319 C322 C323			CC73FCH1H080D CC73FCH1H680J CK73FB1E103K CK73FB1E103K CC73FCH1H050C	CHIP C 8PF D CHIP C 68PF J CHIP C 0.01UF K CHIP C 0.01UF K CHIP C 5PF C	K3	
C324 C325, 326 C327 C328 C329, 330			CK73FB1H102K CK73FB1E103K CC73FCH1H560J CC73FCH1H820J CK73FB1E103K	CHIP C 1000PF K CHIP C 0.01UF K CHIP C 56PF J CHIP C 82PF J CHIP C 0.01UF K		
C331 C332 C333, 334 C335 C336			C92-0009-05 CK73FB1E103K CK73FB1E104K CK73FB1H102K CK73FB1E103K	CHIP TAN 4.7UF 10WV CHIP C 0.01UF K CHIP C 0.10UF K CHIP C 1000PF K CHIP C 0.01UF K		
C337, 338 C339, 340 C341, 342 C343 C344			CC73FCH1H470J C92-0009-05 CK73FB1H471K CK73FB1H471K CK73FB1H471K	CHIP C 47PF J CHIP TAN 4.7UF 10WV CHIP C 470PF K CHIP C 470PF K CHIP C 470PF K	K3	
C345 C346 C347 C348 C349			CK73FB1H102K CK73FB1H471K CE04EW1C470M CK73FB1H102K CK73FB1E103K	CHIP C 1000PF K CHIP C 470PF K ELECTRO 47UF 16WV CHIP C 1000PF K CHIP C 0.01UF K		
C350 C351, 352 C353 C354 C355-357			CK73FB1H102K CK73FB1E103K CK73FB1H102K CC73FSL1H101J CK73FB1E103K	CHIP C 1000PF K CHIP C 0.01UF K CHIP C 1000PF K CHIP C 100PF J CHIP C 0.01UF K		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

✕ New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位 置	New Parts 新	Parts No. 部 品 番 号	Description 部 品 名 / 規 格	Desti- nation 仕 向	Re- marks 備考
C359 C360-362 C363 C364 C365			CC73PSL1H101J CK73FB1E103K C90-2032-05 CE04EW1C470M CK73FB1H102K	CHIP C 100PF J CHIP C 0.01UF K ELECTRO 47UF 10WV ELECTRO 47UF 16WV CHIP C 1000PF K		
C366 C367-369 C370, 371 C372 C373			CK73FB1E103K CK73FB1H471K CK73FB1H102K CK73FB1H471K CK73FB1H102K	CHIP C 0.01UF K CHIP C 470PF K CHIP C 1000PF K CHIP C 470PF K CHIP C 1000PF K		
C374 C375-377 C378 C379 C380			CK73FB1E103K CK73FB1H102K CK73FB1E103K CK73FB1E104K CK73FB1E103K	CHIP C 0.01UF K CHIP C 1000PF K CHIP C 0.01UF K CHIP C 0.10UF K CHIP C 0.01UF K		
C381 C501-504 C509 C510 C511			CK73FB1H102K CK73FB1H102K CE04EW1H0R1M CK73FB1E103K C90-2024-05	CHIP C 1000PF K CHIP C 1000PF K ELECTRO 0.1UF 50WV CHIP C 0.01UF K ELECTRO 47UF 6.3WV	K, K2	
C512 C513 C514 C515, 516 C517, 518			CE04EW1C101M CE04LW1C221M C90-2024-05 CE04LW1C221M C092FM1H104K	ELECTRO 100UF 16WV ELECTRO 220UF 16WV ELECTRO 47UF 6.3WV ELECTRO 220UF 16WV MYLAR 0.10UF K		
C519, 520 C521-523 C525			CK73FB1H102K CK73FB1E103K CK73FB1E104K	CHIP C 1000PF K CHIP C 0.01UF K CHIP C 0.1UF K		
CN101 CN102 CN103			E02-2010-05 E02-2015-05 E40-5491-05 E40-5470-05 E40-3269-05	TRANSISTOR SOCKET(IC109) TRANSISTOR SOCKET(IC108) PIN CONNECTOR(17P) PIN CONNECTOR(13P) PIN CONNECTOR(11P)		
CN104 CN105 CN106 CN107 CN108			E40-3243-05 E40-3242-05 E40-3253-05 E40-3251-05 E40-3256-05	PIN CONNECTOR(8P) PIN CONNECTOR(7P) PIN CONNECTOR(9P) PIN CONNECTOR(7P) PIN CONNECTOR(12P)		
CN301 CN302 CN303 CN304 CN305			E04-0154-05 E40-5470-05 E04-0154-05 E40-3239-05 E04-0154-05	RF COAXIAL CABLE RECEPTACLE PIN CONNECTOR(13P) RF COAXIAL CABLE RECEPTACLE PIN CONNECTOR(4P) RF COAXIAL CABLE RECEPTACLE		
CN306 CN501 CN502 W101-104 W105			E40-5492-05 E40-5491-05 E40-3238-05 R92-1061-05 E37-0158-05	PIN CONNECTOR(15P) PIN CONNECTOR(17P) PIN CONNECTOR(3P) JUMPER REST 0 OHM CONNECTING WIRE(11P)		
W107			R92-1061-05	JUMPER REST 0 OHM		
CF301 L301, 302 L301, 302 L303 L304, 305			L72-0342-05 L34-4296-05 L34-4297-05 L40-1001-48 L34-4296-05	CERAMIC FILTER(CFV455F) COIL COIL SMALL FIXED INDUCTOR(10U) COIL	K, K2 K3 K, K2	

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
L304, 305 L306 L307 L308 L309			L34-4297-05 L19-0324-05 L39-0454-05 L34-4216-05 L40-6892-48	COIL TRANSFORMER COIL COIL SMALL FIXED INDUCTOR(6.8U)	K3	
L310 L311 L312 L313 L314			L30-0534-05 L40-2201-48 L30-0534-05 L30-0503-05 L40-3982-48	COIL SMALL FIXED INDUCTOR(22U) IFT IFT SMALL FIXED INDUCTOR(39U)		
L315 L316 L317 L318 L319			L40-5695-48 L40-2211-48 L40-4701-48 L40-3382-48 L40-4701-48	SMALL FIXED INDUCTOR(5.6U) SMALL FIXED INDUCTOR(220U) SMALL FIXED INDUCTOR(47U) SMALL FIXED INDUCTOR(33U) SMALL FIXED INDUCTOR(47U)		
X101 X301 X302 XF301			L77-1374-05 L77-1294-05 L77-1466-15 L71-0257-05	CRYSTAL RESONATOR(12MZ) CRYSTAL RESONATOR(11.155MHZ) CRYSTAL RESONATOR(12.8MHZ) CRYSTAL FILTER(10.7MHZ)		
R101 R102, 103 R104 R105 R106-108			RK73FB2A471J RK73FB2A473J RK73FB2A105J R92-0670-05 RK73FB2A104J	CHIP R 470 J 1/10W CHIP R 47K J 1/10W CHIP R 1.0M J 1/10W CHIP R 0 OHM CHIP R 100K J 1/10W		
R109 R110, 111 R112 R113 R114, 115			RK73FB2A103J RK73FB2A472J RK73FB2A223J RK73FB2A101J RK73FB2A271J	CHIP R 10K J 1/10W CHIP R 4.7K J 1/10W CHIP R 22K J 1/10W CHIP R 100 J 1/10W CHIP R 270 J 1/10W		
R116 R117 R118 R119 R120			RK73FB2A223J RK73FB2A104J RK73FB2A103J RK73FB2A473J RK73FB2A222J	CHIP R 22K J 1/10W CHIP R 100K J 1/10W CHIP R 10K J 1/10W CHIP R 47K J 1/10W CHIP R 2.2K J 1/10W		
R121 R122 R123 R124, 125 R126			RK73FB2A562J RK73FB2A103J RK73FB2A183J RK73FB2A104J RK73FB2A183J	CHIP R 5.6K J 1/10W CHIP R 10K J 1/10W CHIP R 18K J 1/10W CHIP R 100K J 1/10W CHIP R 18K J 1/10W		
R127 R128 R129 R130, 131 R132			RK73FB2A223J RK73FB2A102J RK73FB2A104J RK73FB2A102J RK73FB2A103J	CHIP R 22K J 1/10W CHIP R 1.0K J 1/10W CHIP R 100K J 1/10W CHIP R 1.0K J 1/10W CHIP R 10K J 1/10W		
R133 R134 R135-137 R138 R139-142			RK73FB2A224J RK73FB2A101J RK73FB2A473J RK73FB2A333J RK73FB2A473J	CHIP R 220K J 1/10W CHIP R 100 J 1/10W CHIP R 47K J 1/10W CHIP R 33K J 1/10W CHIP R 47K J 1/10W		
R143, 144 R145-148 R149 R150 R151, 152			RK73FB2A102J RK73FB2A473J RK73FB2A223J R92-0670-05 RK73FB2A682J	CHIP R 1.0K J 1/10W CHIP R 47K J 1/10W CHIP R 22K J 1/10W CHIP R 0 OHM CHIP R 6.8K J 1/10W		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R153			RK73FB2A223J	CHIP R 22K J 1/10W		
R154			RK73FB2A473J	CHIP R 47K J 1/10W		
R155			RK73FB2A104J	CHIP R 100K J 1/10W		
R156			R92-0670-05	CHIP R 0 0HM		
R157			RK73FB2A562J	CHIP R 5.6K J 1/10W		
R159			RK73FB2A473J	CHIP R 47K J 1/10W		
R160			RK73FB2A104J	CHIP R 100K J 1/10W		
R161, 162			RK73FB2A473J	CHIP R 47K J 1/10W		
R165			RK73FB2A222J	CHIP R 2.2K J 1/10W		
R166			RK73FB2A103J	CHIP R 10K J 1/10W		
R167-169			RK73FB2A473J	CHIP R 47K J 1/10W		
R171			RK73FB2A103J	CHIP R 10K J 1/10W		
R172			RK73FB2A101J	CHIP R 100 J 1/10W		
R173			RK73FB2A220J	CHIP R 22 J 1/10W		
R301			RK73FB2A104J	CHIP R 100K J 1/10W		
R302			RK73FB2A680J	CHIP R 68 J 1/10W		
R303			RK73FB2A104J	CHIP R 100K J 1/10W		
R304, 305			RK73FB2A103J	CHIP R 10K J 1/10W		
R306			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R307			RK73FB2A103J	CHIP R 10K J 1/10W		
R308			RK73FB2A101J	CHIP R 100 J 1/10W		
R309			R92-0670-05	CHIP R 0 0HM		
R310, 311			RK73FB2A271J	CHIP R 270 J 1/10W	K, K2	
R310, 311			RK73FB2A561J	CHIP R 560 J 1/10W	K3	
R312, 313			RK73FB2A103J	CHIP R 10K J 1/10W		
R314-317			RK73FB2A100J	CHIP R 10 J 1/10W		
R318			RK73FB2A103J	CHIP R 10K J 1/10W		
R319			RK73FB2A473J	CHIP R 47K J 1/10W		
R320			RK73FB2A101J	CHIP R 100 J 1/10W		
R321			RK73FB2A822J	CHIP R 8.2K J 1/10W		
R322			RK73FB2A222J	CHIP R 2.2K J 1/10W		
R323			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R324			RK73FB2A222J	CHIP R 2.2K J 1/10W		
R325			RK73FB2A103J	CHIP R 10K J 1/10W		
R326			RK73FB2A334J	CHIP R 330K J 1/10W		
R327			RK73FB2A392J	CHIP R 3.9K J 1/10W		
R328			RK73FB2A101J	CHIP R 100 J 1/10W		
R329			RK73FB2A223J	CHIP R 22K J 1/10W		
R330, 331			RK73FB2A332J	CHIP R 3.3K J 1/10W		
R332			RK73FB2A221J	CHIP R 220 J 1/10W		
R333			RK73FB2A273J	CHIP R 27K J 1/10W		
R334, 335			RK73FB2A103J	CHIP R 10K J 1/10W		
R336			RK73FB2A473J	CHIP R 47K J 1/10W		
R337			RK73FB2A394J	CHIP R 390K J 1/10W		
R338-340			RK73FB2A104J	CHIP R 100K J 1/10W		
R341			RK73FB2A332J	CHIP R 3.3K J 1/10W		
R342			RK73FB2A105J	CHIP R 1.0M J 1/10W		
R343			RK73FB2A104J	CHIP R 100K J 1/10W		
R344			RK73FB2A471J	CHIP R 470 J 1/10W		
R345			RK73FB2A560J	CHIP R 56 J 1/10W		
R346			RK73FB2A471J	CHIP R 470 J 1/10W		
R347			RK73FB2A122J	CHIP R 1.2K J 1/10W		
R348			RK73FB2A6R8J	CHIP R 6.8 J 1/10W		
R349			RK73FB2A330J	CHIP R 33 J 1/10W		
R350-352			RK73FB2A102J	CHIP R 1.0K J 1/10W		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R353 R354 R355 R355 R356			RK73FB2A561J RK73FB2A332J RK73FB2A271J RK73FB2A391J RK73FB2A100J	CHIP R 560 J 1/10W CHIP R 3.3K J 1/10W CHIP R 270 J 1/10W CHIP R 390 J 1/10W CHIP R 10 J 1/10W	K, K2 K3	
R357 R358 R359 R360 R361-364			RK73FB2A473J RK73FB2A472J RK73FB2A473J RK73FB2A472J RK73FB2A473J	CHIP R 47K J 1/10W CHIP R 4.7K J 1/10W CHIP R 47K J 1/10W CHIP R 4.7K J 1/10W CHIP R 47K J 1/10W		
R365 R366 R367 R368 R369			RK73FB2A101J RK73FB2A561J RK73FB2A151J RK73FB2A220J RK73FB2A221J	CHIP R 100 J 1/10W CHIP R 560 J 1/10W CHIP R 150 J 1/10W CHIP R 22 J 1/10W CHIP R 220 J 1/10W		
R370 R371, 372 R373 R401 R402			R92-0670-05 RK73FB2A103J RK73FB2A182J R92-0670-05 R92-0670-05	CHIP R 0 0HM CHIP R 10K J 1/10W CHIP R 1.8K J 1/10W CHIP R 0 0HM CHIP R 0 0HM	K K2	
R403 R501 R502 R503 R504			R92-0670-05 RK73FB2A473J RK73FB2A562J RK73FB2A103J RK73FB2A105J	CHIP R 0 0HM CHIP R 47K J 1/10W CHIP R 5.6K J 1/10W CHIP R 10K J 1/10W CHIP R 1.0M J 1/10W	K3	
R505, 506 R507 R508-510 VR101 VR102			RK73FB2A2R2J RK73FB2A102J RS140B3F150J R12-6738-05 R12-6744-05	CHIP R 2.2 J 1/10W CHIP R 1.0K J 1/10W FL-PROOF RS 15 J 3W TRIMMING POT.(4.7K) TRIMMING POT.(47K)		
VR301, 302 VR303			R12-6748-05 R12-6742-05	TRIMMING POT.(220K) TRIMMING POT.(22K)		
K501 K502 S301			S51-1420-05 S76-0401-05 S31-1411-05	RELAY(SP) RELAY(POWER) SLIDE SWITCH(NB ON/OFF)		
D101 D102 D103 D104 D105, 106			02CZ18(X, Y) 1SS181 1SS184 02CZ5.6(X, Y) 1SS184	DIODE DIODE DIODE DIODE DIODE		
D107-110 D111 D112 D301 D302-305			1SS226 1SS184 02CZ15(X, Y) 1SS226 1SV228	DIODE DIODE DIODE DIODE DIODE		
D306 D501, 502 D503 IC101 IC102			1SS268 1SS193 1SS184 TC4013BF L78LR05B-FA	DIODE DIODE DIODE IC(D FLIP-FLOP X2) RESONATOR		
IC103 IC104, 105 IC104, 105 IC106			KCE04 BU4094BF XRU4094BF 78312AGF3343BE	IC IC(SHIFT/STORE REGISTER) IC(SHIFT/STORE REGISTER) IC		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3960-XX)

VCO/PLL UNIT (X58-3850-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
IC107 IC108 IC109 IC110 IC110			TC74HC573AF 27C256QJEMD X24C04PI TC4S11F SC14S11F	IC(LATCH) IC IC IC(2 INPUT NAND GATE) IC(2 INPUT NAND GATE)		
IC301 IC302 IC303 IC304 IC304			MC3371D TC4S66F NJM78L05UA BU4094BF XRU4094BF	IC IC(BILATERAL SWITCH) IC(AVR/+5V) IC(SHIFT/STORE REGISTER) IC(SHIFT/STORE REGISTER)		
IC305 IC501 IC502 Q101-104 Q105			NJM4558E LA4491N UPC78M08H DTA114EK DTC114EK	IC(OP AMP) IC(AF POWER AMP) IC(VOLTAGE REGULATOR/ +8V) DIGITAL TRANSISTOR DIGITAL TRANSISTOR		
Q106 Q107 Q108-112 Q113 Q114, 115			2SC2712(Y) 2SD1757K DTC114EK 2SC2714(Y) DTC114EK	TRANSISTOR TRANSISTOR DIGITAL TRANSISTOR TRANSISTOR DIGITAL TRANSISTOR		
Q116 Q301, 302 Q303-306 Q303-306 Q308, 309			DTD114EK 2SK1577(1) 2SK1577(1) 2SK1577(3) 2SK1577(1)	DIGITAL TRANSISTOR FET FET FET FET	K, K2 K3	
Q310 Q311 Q312 Q313, 314 Q315			2SC2714(Y) DTC114EK 2SK208(Y) 2SC2954 2SB1119(S)	TRANSISTOR DIGITAL TRANSISTOR FET TRANSISTOR TRANSISTOR		
Q316 Q317 Q318, 319 Q320 Q501			DTC114EK 2SB1119(S) DTC114EK 2SK1577(1) DTD114EK	DIGITAL TRANSISTOR TRANSISTOR DIGITAL TRANSISTOR FET DIGITAL TRANSISTOR		
TH101 TH301			157-203-55009 157-102-53003	THERMISTOR(20K) THERMISTOR(1K)		
Z301 Z302 Z302 Z302			X58-3860-10 X58-3850-10 X58-3850-11 X58-3850-12	NB UNIT VCO/PLL UNIT VCO/PLL UNIT VCO/PLL UNIT	K K2 K3	
			212-6010-05	PLASTIC TUBE		
VCO/PLL UNIT (X58-3850-XX) -10 : K -11 : K2 -12 : K3						
C1 C2 , 3 C4 C5 C6			C92-0004-05 CK73FB1E103K CK73FB1H102K CC73FCH1H680J CC73PSL1H101J	ELECTRO 1.0UF 16WV CHIP C 0.01UF K CHIP C 1000PF K CHIP C 68PF J CHIP C 100PF J		
C7 C8 , 9 C10 C11 C12			CC73FCH1H680J CK73FB1H102K CK73FB1H102K CK73FB1E103K CC73PSL1H101J	CHIP C 68PF J CHIP C 1000PF K CHIP C 1000PF K CHIP C 0.01UF K CHIP C 100PF J	K, K2	

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

VCO/PLL UNIT (X58-3850-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C13			CC73FCH1H470J	CHIP C 47PF J		
C14			CK73FB1H102K	CHIP C 1000PF K		
C15, 16			C92-0004-05	ELECTRO 1.0UF 16WV		
C17			CK73FB1H102K	CHIP C 1000PF K		
C18			CK73FB1H471K	CHIP C 470PF K		
C19			C92-0004-05	ELECTRO 1.0UF 16WV		
C20			CK73FB1H102K	CHIP C 1000PF K		
C21			C92-0002-05	CHIP TAN 0.22UF 35WV		
C22			C92-0543-05	CHIP TAN 3.3UF 10WV		
C23			C92-0003-05	CHIP TAN 0.47UF 25WV		
C24			CK73FB1E104K	CHIP C 0.10UF K		
C25			CK73FB1E103K	CHIP C 0.01UF K	K, K2	
C51			CK73FB1E103K	CHIP C 0.01UF K		
C52			CC73FCH1H020C	CHIP C 2.0PF C		
C53			CC73FCH1H020C	CHIP C 2.0PF C	K	
C53			CC73FCH1H040C	CHIP C 4PF C	K3	
C53			CC73FCH1H060D	CHIP C 6PF D	K2	
C54			CC73FCH1H470J	CHIP C 47PF J		
C55			CC73FCH1H220J	CHIP C 22PF J		
C56			CC73FCH1H560J	CHIP C 56PF J	K2, K3	
C56			CC73FCH1H820J	CHIP C 82PF J	K	
C57			CK73FB1E103K	CHIP C 0.01UF K		
C58			C92-0004-05	ELECTRO 1.0UF 16WV		
C59			CK73FB1H102K	CHIP C 1000PF K		
C60			CK73FB1E103K	CHIP C 0.01UF K		
C61			CK73FB1H102K	CHIP C 1000PF K		
C62			CK73FB1E103K	CHIP C 0.01UF K		
C63			CK73FB1H471K	CHIP C 470PF K		
C64			CK73FB1E103K	CHIP C 0.01UF K		
C65			CC73FCH1H070D	CHIP C 7PF D	K3	
C65			CC73FCH1H150J	CHIP C 15PF J	K2	
C65			CC73FCH1H180J	CHIP C 18PF J	K	
C66			CC73FCH1H470J	CHIP C 47PF J		
C67			CC73FCH1H220J	CHIP C 22PF J		
C68			CC73FCH1H560J	CHIP C 56PF J		
C69			CK73FB1E103K	CHIP C 0.01UF K		
C70			CK73FB1H102K	CHIP C 1000PF K		
C71			CK73FB1E103K	CHIP C 0.01UF K		
TC51, 52			C05-0371-05	TRIM CAP 10PF		
CN1			E40-5493-05	PIN CONNECTOR(15P)		
CN51			E40-5494-05	PIN CONNECTOR(7P)		
			F10-1480-03	SHIELDING PLATE		
L1, 2			L40-2282-48	SMALL FIXED INDUCTOR(220N)		
L51			L40-6892-48	SMALL FIXED INDUCTOR(6.8U)		
L52			L34-4290-05	COIL(TX.VCO)	K	
L52			L34-4291-05	COIL(TX.VCO)	K2	
L52			L34-4292-05	COIL(TX.VCO)	K3	
L53			L40-6892-48	SMALL FIXED INDUCTOR(6.8U)		
L54			L34-4293-05	COIL(RX.VCO)	K2	
L54			L34-4294-05	COIL(RX.VCO)	K	
L54			L34-4295-05	COIL(RX.VCO)	K3	
L55			L40-1092-48	SMALL FIXED INDUCTOR(1U)		
R1			RK73FB2A330J	CHIP R 33 J 1/10W		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

VCO/PLL UNIT (X58-3850-XX)

NB UNIT (X58-3860-10)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R2			RK73FB2A122J	CHIP R 1.2K J 1/10W		
R3			RK73FB2A223J	CHIP R 22K J 1/10W		
R4			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R5			R92-0670-05	CHIP R 0 0HM		
R6			RK73FB2A223J	CHIP R 22K J 1/10W		
R8 , 9			RK73FB2A330J	CHIP R 33 J 1/10W		
R10			RK73FB2A333J	CHIP R 33K J 1/10W		
R11			RK73FB2A104J	CHIP R 100K J 1/10W		
R12			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R13			RK73FB2A101J	CHIP R 100 J 1/10W		
R14			RK73FB2A123J	CHIP R 12K J 1/10W		
R15			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R16			RK73FB2A152J	CHIP R 1.5K J 1/10W		
R17			RK73FB2A473J	CHIP R 47K J 1/10W		
R18 , 19			R92-0670-05	CHIP R 0 0HM		
R20 , 21			RK73FB2A221J	CHIP R 220 J 1/10W		
R22			RK73FB2A561J	CHIP R 560 J 1/10W		
R23			RK73FB2A221J	CHIP R 220 J 1/10W		
R24			RK73FB2A103J	CHIP R 10K J 1/10W		
R25 , 26			R92-0670-05	CHIP R 0 0HM		
R51			RK73FB2A330J	CHIP R 33 J 1/10W		
R52 , 53			RK73FB2A103J	CHIP R 10K J 1/10W		
R54			RK73FB2A221J	CHIP R 220 J 1/10W	K2, K3	
R54			RK73FB2A271J	CHIP R 270 J 1/10W	K	
R55			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R56			RK73FB2A273J	CHIP R 27K J 1/10W		
R57			RK73FB2A471J	CHIP R 470 J 1/10W		
R58			RK73FB2A122J	CHIP R 1.2K J 1/10W	K	
R58			RK73FB2A152J	CHIP R 1.5K J 1/10W	K2	
R58			RK73FB2A222J	CHIP R 2.2K J 1/10W	K3	
R59			RK73FB2A104J	CHIP R 100K J 1/10W		
R60			RK73FB2A154J	CHIP R 150K J 1/10W		
R61			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R62			RK73FB2A103J	CHIP R 10K J 1/10W		
R63			RK73FB2A221J	CHIP R 220 J 1/10W	K2, K3	
R63			RK73FB2A271J	CHIP R 270 J 1/10W	K	
R64			RK73FB2A102J	CHIP R 1.0K J 1/10W		
D51			1SV228	DIODE		
D52			1SV164	DIODE		
D53			1SV228	DIODE		
IC1			MB1504PF	IC		
Q1			2SC2714(Y)	TRANSISTOR		
Q2			2SA1162(Y)	TRANSISTOR		
Q3			DTC143EK	DIGITAL TRANSISTOR		
Q4			2SA1312(GR)	TRANSISTOR		
Q5			2SC3324(G)	TRANSISTOR		
Q51			2SK508NV(K52)	PET		
Q52			DTC114EK	DIGITAL TRANSISTOR		
Q53			2SK508NV(K52)	PET		
Q54 , 55			DTC114EK	DIGITAL TRANSISTOR		
Q56			2SC2714(Y)	TRANSISTOR		
NB UNIT (X58-3860-10)						
C1			CK73FB1E103K	CHIP C 0.01UF K		
C2 , 3			C92-0543-05	CHIP TAN 3.3UF 10WV		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

NB UNIT (X58-3860-10)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C4			CC73FCH1H680J	CHIP C 68PF J		
C5			CK73FB1E104K	CHIP C 0.10UF K		
C6 ,7			CK73FB1E103K	CHIP C 0.01UF K		
C8			CC73FCH1H220J	CHIP C 22PF J		
C9			CC73FCH1H470J	CHIP C 47PF J		
C10			CK73FB1E103K	CHIP C 0.01UF K		
C11			CK73FB1E104K	CHIP C 0.10UF K		
C12			CC73FCH1H220J	CHIP C 22PF J		
C13 ,14			CK73FB1H102K	CHIP C 1000PF K		
C15 ,16			CK73FB1E103K	CHIP C 0.01UF K		
C17			C92-0543-05	CHIP TAN 3.3UF 10WV		
C18			CK73FB1E104K	CHIP C 0.10UF K		
C19			CK73FB1H102K	CHIP C 1000PF K		
C20			CC73FCH1H820J	CHIP C 82PF J		
C21			CC73PSL1H221J	CHIP C 220PF J		
C22 -24			CK73FB1E103K	CHIP C 0.01UF K		
C25			CC73PSL1H221J	CHIP C 220PF J		
C51			CC73FCH1H390J	CHIP C 39PF J		
C52			CC73PSL1H101J	CHIP C 100PF J		
C53			CC73PSL1H331J	CHIP C 330PF J		
C54 ,55			CC73PSL1H221J	CHIP C 220PF J		
C56			CC73PSL1H331J	CHIP C 330PF J		
C57			CC73PSL1H181J	CHIP C 180PF J		
C58 ,59			CC73PSL1H271J	CHIP C 270PF J		
C60			CC73PSL1H331J	CHIP C 330PF J		
C61			CC73PSL1H181J	CHIP C 180PF J		
C62 ,63			CC73PSL1H221J	CHIP C 220PF J		
C64			CC73PSL1H331J	CHIP C 330PF J		
C65			CC73PSL1H101J	CHIP C 100PF J		
C66			CC73FCH1H390J	CHIP C 39PF J		
CN51,52			B40-0411-05	PIN CONNECTOR(4P)		
			F11-1122-24	SHIELDING CASE		
L1			L40-1001-48	SMALL FIXED INDUCTOR(10U)		
L2			L40-5695-48	SMALL FIXED INDUCTOR(5.6U)		
L3			L40-1011-48	SMALL FIXED INDUCTOR(100U)		
L4			L40-5695-48	SMALL FIXED INDUCTOR(5.6U)		
L51			L40-2782-48	SMALL FIXED INDUCTOR(27U)		
L52			L40-6882-48	SMALL FIXED INDUCTOR(68U)		
L53			L40-1092-48	SMALL FIXED INDUCTOR(1U)		
L54 -57			L40-1292-48	SMALL FIXED INDUCTOR(1.2U)		
L58			L40-1092-48	SMALL FIXED INDUCTOR(1U)		
L59			L40-6882-48	SMALL FIXED INDUCTOR(68U)		
L60			L40-2782-48	SMALL FIXED INDUCTOR(27U)		
R1			R92-0670-05	CHIP R 0 OHM		
R2			RK73FB2A333J	CHIP R 33K J 1/10W		
R3			RK73FB2A104J	CHIP R 100K J 1/10W		
R4			RK73FB2A103J	CHIP R 10K J 1/10W		
R5			RK73FB2A104J	CHIP R 100K J 1/10W		
R6			RK73FB2A471J	CHIP R 470 J 1/10W		
R7			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R8			RK73FB2A101J	CHIP R 100 J 1/10W		
R9			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R10			RK73FB2A330J	CHIP R 33 J 1/10W		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

NB UNIT (X58-3860-10)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R11			RK73FB2A273J	CHIP R 27K J 1/10W		
R12 , 13			RK73FB2A562J	CHIP R 5.6K J 1/10W		
R14			RK73FB2A563J	CHIP R 56K J 1/10W		
R15			RK73FB2A104J	CHIP R 100K J 1/10W		
R16			RK73FB2A684J	CHIP R 680K J 1/10W		
R17			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R18			RK73FB2A223J	CHIP R 22K J 1/10W		
R19			RK73FB2A103J	CHIP R 10K J 1/10W		
R20			RK73FB2A151J	CHIP R 150 J 1/10W		
R21			RK73FB2A104J	CHIP R 100K J 1/10W		
R22			RK73FB2A334J	CHIP R 330K J 1/10W		
R23			RK73FB2A684J	CHIP R 680K J 1/10W		
R24			RK73FB2A222J	CHIP R 2.2K J 1/10W		
R25			RK73FB2A103J	CHIP R 10K J 1/10W		
R26			RK73FB2A223J	CHIP R 22K J 1/10W		
R27			RK73FB2A101J	CHIP R 100 J 1/10W		
R28			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R29			RK73FB2A103J	CHIP R 10K J 1/10W		
R30 , 31			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R32			RK73FB2A101J	CHIP R 100 J 1/10W		
D2			1SS184	DIODE		
IC1			MC1350D	IC		
Q1			3SK131(M)	FET		
Q2			2SA1162(Y)	TRANSISTOR		
Q3 -6			2SC2712(Y)	TRANSISTOR		
Q7			2SA1162(Y)	TRANSISTOR		

L:Scandinavia

K:USA

P:Canada

Y:PX(Far East, Hawaii)

T:England

E:Europe

Y:AAFES(Europe)

X:Australia

M:Other Areas

⚠ indicates safety critical components.