

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
EXPLODED VIEW <M1MM>						
	AUB1	CB-XJ6153K00N	AUDIO PWB	XJ6-153K-00	1	K0,K1
	AUB1	CB-XJ6153K01N	AUDIO PWB	XJ6-153K-01	1	K2
	AUB1	CB-XJ6153M01N	AUDIO PWB	XJ6-153M-01	1	A1,M1
	AUB1	CB-XJ6153E01N	AUDIO PWB	XJ6-153E-01	1	E1
	AUB1	CB-XJ6153X01N	AUDIO PWB	XJ6-153X-01	1	X1
	DEB1	CB-XJ8092K07N	DETACH PWB	XJ8-092K-00	1	
	DGB1	CB-XJA080K00N	DIGITAL IO PWB	XJA-080K-00	1	K0
	DGB1	CB-XJA080K02N	DIGITAL IO PWB	XJA-080K-02	1	K2
	DGB1	CB-XJA080K01N	DIGITAL IO PWB	XJA-080K-01	1	K1
	DGB1	CB-XJA080M01N	DIGITAL IO PWB	XJA-080M-01	1	A1,M1
	DGB1	CB-XJA080E01N	DIGITAL IO PWB	XJA-080E-01	1	E1
	DGB1	CB-XJA080X01N	DIGITAL IO PWB	XJA-080X-01	1	X1
	GYB1	CB-XJ5009J00N	GYRO PWB	XJ5-009J-00	1	
	PNB1	CB-XJ8092K03N	PANEL PWB	XJ8-092K-00	1	
	SDB1	CB-XJ8092K08N	SD PWB	XJ8-092K-00	1	K0
	SWB1	CB-XJ8092K05N	SW PWB	XJ8-092K-00	1	
	FC1	E3G-0174-00	FFC WIRE		1	
	FC2	EF0AM051004AC	FFC WIRE		1	
	FC3	E3G-0175-00	FFC WIRE		1	
	FC4	EF0AA051503AC	FFC WIRE		1	K0
	FPC1	E3J-0061-00	FPC		1	
	FPC2	E3J-0060-00	FPC		1	
	DC1	E3A-0578-00	DC CORD		1	K0,K2,K1,A1,M1,X1
	DC2	E3A-0579-00	DC CORD		1	E1
△	F1	FZB10AU-150	BLADE FUSE		1	
	LCD1	B3H-0140-00	LCD ASSY		1	
	PA1	A6C-0143-00	PANEL ASSY		1	K0
	PA1	A6C-0143-02	PANEL ASSY		1	K2
	PA1	A6C-0143-01	PANEL ASSY		1	K1
	PA1	A6C-0143-04	PANEL ASSY		1	A1,M1
	PA1	A6C-0143-03	PANEL ASSY		1	E1,X1
	RC1	A7A-0028-00	REMOTE CTL(IR)		1	A1,M1,X1
	A	QYSDST2606MA	TAP SCREW	M2.6 x 6.0mm	11	
	B	QYNYS2600ZA	NUT	M2.6	2	
	C	QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	79	K0
	C	QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	77	K2,K1,X1
	C	QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	76	A1,M1
	C	QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	78	E1
	D	LV45522-001A	SPECIAL SCREW		2	
	E	NOZ-0150-00	TAPTITE SCREW		10	
	F	QYSDSG3006ZA	TAP SCREW	M3.0 x 6.0mm	2	
	G	QYSDST2005ZA	TAP SCREW	M2.0 x 5.0mm	6	
	H	NOZ-0355-00	STEPPED SCREW		4	
	J	VKZ4777-012	SCREW		26	
	K	N09-6909-05	STEPPED SCREW		2	
	L	N32-4012-43	F.HEAD M.SCREW		4	
	M	QYSPSG3008ZA	TAP SCREW	M3.0 x 8.0mm	3	
	N	QYSDST2614ZA	TAP SCREW	M2.6 x 14.0mm	2	
	P	NOZ-0367-01	SPECIAL SCREW		4	
	Q	N90-5008-48	TP HEAD M.SCREW		4	
	R	QYSDSF2608ZA	TAP SCREW	M2.6 x 8.0mm	1	
	S	QYSDST3006MA	TAP SCREW	M3.0 x 6.0mm	1	
	T	QYSDST2610ZA	TAP SCREW	M2.6 x 10.0mm	2	
	213	F0C-0071-00	COOL SHEET		1	
	222	F0G-0408-00	COVER		2	
	223	J2B-0590-00	BRACKET		1	
	224	J2B-0591-00	BRACKET		1	
	225	E3A-0732-00	USB CORD		1	K0,K2,K1,X1
	225	E3A-0733-00	USB CORD		1	A1,M1,E1
	227	F0K-0264-00	FAN		1	
	233	F0G-0403-00	COVER		1	
	235	A2C-0099-00	SUB PANEL		1	K0
	235	A2C-0099-02	SUB PANEL		1	K2,K1
	235	A2C-0099-05	SUB PANEL		1	A1,M1
	235	A2C-0099-03	SUB PANEL		1	E1,X1
	237	F0G-0282-00	J.COVER(USB)		1	
	238	F0G-0410-00	COVER		1	
	240	F0G-0402-00	HINGE COVER		1	
	241	F0G-0404-00	COVER		1	
	242	F0G-0421-00	COVER		1	
	243	G1G-0123-00	SHEET		1	
	244	F2K-0012-00	INS.COVER		5	
	245	J5A-0009-00	HINGE		1	
	246	F0G-0407-00	COVER		1	
	247	F0G-0405-00	COVER		1	
	248	G1B-0444-00	CUSHION		1	
	249	E3A-0708-00	CORD W.PINJACK		1	
	249	E3A-0613-00	CORD WITH PLUG		1	M1,X1
	251	B1K-0177-00	LIGHTING BOARD		1	
	253	B1K-0178-10	LIGHTING BOARD		1	
	254	T6A-0099-00	PLASTIC LENS		1	
	255	B1K-0176-00	LIGHTING BOARD		1	
	256	B1K-0175-00	LIGHTING BOARD		1	
	257	G1D-0371-07	CONDUCT CUSHION		3	
	258	J2B-0595-00	BRACKET		1	
	259	J2K-0270-00	GUIDE		1	
	260	J2K-0271-00	GUIDE		1	
	261	A4G-0123-00	REAR COVER		1	
	262	A2B-0188-00	DRESSING PANEL		1	
	263	K2K-0553-00	KNOB ASSY		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	264	B0K-0126-00	CAP		1	
	265	GE40127-009A	KNOB SPRING		1	
	352	E3A-0364-00	USB CORD	BLACK	1	
	353	T9A-0070-00	ANTENNA ASSY		1	
	356	E3A-0613-00	CORD WITH PLUG		1	A1
	357	T9B-0066-00	MICROPHONE		1	
	358	QYSSSP5008ZA	SCREW	M5.0 x 8.0mm	6	K0,K2,K1,A1,M1,X1
	359	QYSTSP5008ZA	SCREW	M5.0 x 8.0mm	6	K0,K2,K1,A1,M1,X1
	361	F0G-0409-00	COVER		2	
	362	F0G-0406-00	COVER		1	
	364	J2B-0592-00	BRACKET		1	
	365	J2B-0596-00	BRACKET		1	
	366	QYSDST3006MA	TAP SCREW	M3.0 x 6.0mm	2	
	367	NOZ-0367-01	SPECIAL SCREW		6	
	368	E3A-0067-00	ANTENNA CABLE		1	X1
	501	B5A-3356-00	INST.MANUAL		1	A1,M1,X1
	501	B5A-3356-01	INST.MANUAL		1	M1
	502	B5A-3356-02	INST.MANUAL		1	A1
	710	-----	TOP PLATE	NO SERVICE PART	1	K0,K1
	710	-----	TOP PLATE	NO SERVICE PART	1	K2,A1,M1,E1,X1
	715	-----	HEAT SINK	NO SERVICE PART	1	
	716	-----	BRACKET	NO SERVICE PART	1	
	717	-----	S.CHASSIS ASSY	NO SERVICE PART	1	
	719	-----	SIDE PLATE	NO SERVICE PART	1	
	720	-----	SIDE PLATE	NO SERVICE PART	1	
	721	-----	REAR PANEL	NO SERVICE PART	1	K0,K2,K1
	721	-----	REAR PANEL	NO SERVICE PART	1	A1,M1
	721	-----	REAR PANEL	NO SERVICE PART	1	E1
	721	-----	REAR PANEL	NO SERVICE PART	1	X1
	726	-----	BRACKET	NO SERVICE PART	1	
	729	-----	CHASS.CALK.ASSY	NO SERVICE PART	1	
	730	-----	SLIDER	NO SERVICE PART	1	
	731	-----	BRACKET	NO SERVICE PART	1	
	732	-----	SLIDE BASE	NO SERVICE PART	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
GYRO PWB ASSY (XJ5-009J-00) <XJ5>						
	C2	CK73HXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C3	CK73HXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	R2	RK73EB2E101J	MG RESISTOR	100Ω 1/4W J	1	
	R3	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R4	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R5	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R6	RK73EB2E101J	MG RESISTOR	100Ω 1/4W J	1	
	R7	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R8	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R10	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	
	CN1	EC710AM-0510A	FFC FPC CONNE		1	
	SN1	-----	SENSOR	NO SERVICE PART	1	
AUDIO PWB ASSY (XJ6-153x-0x) <XJ6>						
	IC1	LV5680NPVC-H	MOS IC		1	
	IC31	NJU7108F3	MOS IC		1	
	IC41	XC6223B331P-G	ANALOG IC		1	
	IC101	JCV8031	ANALOG IC		1	
	IC115	TC7SH17FUJC	MOS IC		1	K2
	IC201	TDA7715LV	ANALOG IC		1	
	IC202	NJM8080RB1	ANALOG IC		1	
	IC203	NJM8080RB1	ANALOG IC		1	
	IC251	NJM8080RB1	ANALOG IC		1	K0,K2,K1,X1
	IC252	NJM8080RB1	ANALOG IC		1	K0,K2,K1,X1
	IC261	NJM2794RB2	BIPOLAR IC		1	K0,K2,K1,X1
	IC290	TC74HCT4053FT	MOS IC		1	K0,K2,K1,X1
	IC302	SI47901A2GE1A	MOS IC		1	
	IC303	W3F-0573-00	ROM IC		1	
	IC304	SN74AUP3G17CU	MOS IC		1	
	IC305	SN74AUP2G17CK	MOS IC		1	K0,K2,K1
	IC306	TCA9517DGK	MOS IC		1	
	IC307	SN74AUP2G17CK	MOS IC		1	K0,K2,K1
	IC351	MM3703F18HE	ANALOG IC		1	
	IC352	MM3703F33HE	ANALOG IC		1	
	IC511	TC7SET32FUJC	MOS IC		1	K0,K2,K1,E1
	IC512	TC7SH17FUJC	MOS IC		1	K0,K2,K1,E1
	IC601	NJW1240V	MOS IC		1	
	IC851	NJM2903CRB1	MOS IC		1	
	IC852	TC7SH126FUJC	MOS IC		1	
	IC1101	NJM2746V	ANALOG IC		1	K0,K1,A1,M1,E1,X1
	IC1102	NJM2746V	ANALOG IC		1	K0,K1,A1,M1,E1,X1
	IC2001	NJU7108F3	MOS IC		1	
	IC2301	-----	MCU IC	NO SERVICE PART	1	
	IC2302	XC6120N282N-G	MOS IC		1	
	IC2303	NJU7108F3	MOS IC		1	
	IC2304	TC7SH08FUJC	MOS IC		1	
	IC2501	AK7738VQ	MOS IC		1	
	IC2502	AK4388AET	ANALOG IC		1	
	IC2503	AK4388AET	ANALOG IC		1	
	IC2507	XC6209B502P-G	MOS IC		1	
	IC2508	MM3411A33NE	ANALOG IC		1	
	IC2601	NJM8080RB1	ANALOG IC		1	
	IC2602	NJM2871BF05	ANALOG IC		1	
	Q11	2SB1689	TRANSISTOR		1	
	Q12	KRC407E-P	DIGI TRANSISTOR		1	
	Q51	KTC4075EP/Y/	TRANSISTOR		1	
	Q60	KTA2014EP/Y/	TRANSISTOR		1	
	Q61	KTC4075EP/Y/	TRANSISTOR		1	
	Q62	KTA2014EP/Y/	TRANSISTOR		1	
	Q63	KTC4075EP/Y/	TRANSISTOR		1	
	Q80	KRA307E-P	TRANSISTOR		1	
	Q81	KTA2014EP/Y/	TRANSISTOR		1	
	Q82	KTC4075EP/Y/	TRANSISTOR		1	
	Q90	KRC403E-P	DIGI TRANSISTOR		1	
	Q151	KRC407E-P	DIGI TRANSISTOR		1	
	Q152	KRA306E-P	TRANSISTOR		1	
	Q155	KRC407E-P	DIGI TRANSISTOR		1	
	Q156	KRA306E-P	TRANSISTOR		1	
	Q161	KRC410E-P	DIGI TRANSISTOR		1	
	Q162	KRC410E-P	DIGI TRANSISTOR		1	
	Q163	KRC410E-P	DIGI TRANSISTOR		1	
	Q164	KRC410E-P	DIGI TRANSISTOR		1	
	Q165	KRC410E-P	DIGI TRANSISTOR		1	
	Q166	KRC410E-P	DIGI TRANSISTOR		1	
	Q191	KRA306E-P	TRANSISTOR		1	
	Q193	KRC410E-P	DIGI TRANSISTOR		1	
	Q194	KRC410E-P	DIGI TRANSISTOR		1	
	Q2004	KRC404E-P	DIGI TRANSISTOR		1	
	Q2301	2SB1689	TRANSISTOR		1	
	Q2302	KRC407E-P	DIGI TRANSISTOR		1	
	Q2303	KTA2014EP/Y/	TRANSISTOR		1	
	Q2304	KRA307E-P	TRANSISTOR		1	
	Q2305	KTC4075EP/Y/	TRANSISTOR		1	
	Q2306	KRC407E-P	DIGI TRANSISTOR		1	
	Q2307	KTC4075EP/Y/	TRANSISTOR		1	
	Q2308	KRC407E-P	DIGI TRANSISTOR		1	
	Q2309	KRC407E-P	DIGI TRANSISTOR		1	
	Q2310	KTA2014EP/Y/	TRANSISTOR		1	
	Q2311	RE1L002SN	FET		1	
	Q2312	KRC407E-P	DIGI TRANSISTOR		1	
	Q2313	RE1L002SN	FET		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	Q2314	KRC407E-P	DIGI TRANSISTOR		1	
	Q2401	RE1C002ZP	FET		1	
	Q2402	RE1L002SN	FET		1	
	Q2501	KRC407E-P	DIGI TRANSISTOR		1	
	Q2502	KRC407E-P	DIGI TRANSISTOR		1	
	D1	D4F60-53	DIODE		1	
	D11	RB161MM-20	SCHOTTKY DIODE		1	
	D32	BZT52B16LSHF	ZENER DIODE		1	
	D41	GS1J-LTP	DIODE		1	
	D42	GS1J-LTP	DIODE		1	K0,K2,K1,A1,M1,X1
	D43	GS1J-LTP	DIODE		1	
	D44	GS1J-LTP	DIODE		1	K0,K2,K1,A1,M1,X1
	D55	BZT52B6V2LSHF	ZENER DIODE		1	
	D60	1SS355-HF	DIODE		1	
	D61	1SS355-HF	DIODE		1	
	D71	DAP202UM	DIODE		1	
	D80	1SS355-HF	DIODE		1	
	D90	1SS355-HF	DIODE		1	
	D101	DAP202UM	DIODE		1	
	D151	DAP202UM	DIODE		1	
	D155	DAP202UM	DIODE		1	
	D191	DAP202UM	DIODE		1	
	D202	1SS355-HF	DIODE		1	
	D203	DAP202UM	DIODE		1	
	D204	DAP202UM	DIODE		1	
	D205	DAP202UM	DIODE		1	
	D270	1SS355-HF	DIODE		1	K0,K2,K1,X1
	D271	BZT52B4V7LSHF	ZENER DIODE		1	K0,K2,K1,X1
	D2005	BZT52B8V2LSHF	ZENER DIODE		1	
	D2006	BZT52B10LSHF	ZENER DIODE		1	
	D2007	BZT52B16LSHF	ZENER DIODE		1	
	D2301	1SS355-HF	DIODE		1	
	D2401	1SS355-HF	DIODE		1	
	D2402	1SS355-HF	DIODE		1	
	D2409	1SS355-HF	DIODE		1	
	D2502	DAN217WM	DIODE		1	
	D2601	BZT52B11LSHF	ZENER DIODE		1	
	D2602	BZT52B11LSHF	ZENER DIODE		1	
	D2603	1SS355-HF	DIODE		1	
	C1	CD04EW1C332M2	E CAPACITOR	3300uF 16V M	1	K0,K1,A1,M1,E1,X1
	C1	CD04AZ1C332M2	E CAPACITOR	3300uF 16V M	1	K2
	C2	CK730MF2W104K	C CAPACITOR	0.1uF 450V K	1	A1,M1,E1
	C11	CE32CB1V101M	E CAPACITOR	100uF 35V M	1	
	C12	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C13	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C14	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C15	CE32CB1A101M	E CAPACITOR	100uF 10V M	1	
	C16	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C18	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C19	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C20	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C21	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C22	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C23	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C24	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C25	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C26	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C27	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C28	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C31	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C32	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C41	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C42	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C51	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C52	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C60	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C71	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C80	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C90	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C100	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C101	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C102	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C103	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C104	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C105	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C106	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C109	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C110	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C111	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C112	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C113	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C114	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C115	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	K2
	C121	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C122	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C123	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C124	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C125	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C126	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C127	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C128	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C131	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C132	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C133	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C134	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C135	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C136	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C137	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C138	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C145	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C146	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C151	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C152	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C153	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C154	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C155	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C156	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C171	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C172	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C173	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C174	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C175	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C176	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C177	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C191	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C192	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C195	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C196	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C197	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C201	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C202	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C203	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C204	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K2
	C205	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C206	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C208	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C211	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C212	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C215	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C216	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C219	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C220	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C227	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C228	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C234	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C235	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C236	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C237	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C238	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C241	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C243	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C244	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C251	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1,X1
	C252	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1,X1
	C253	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	K0,K2,K1,X1
	C254	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	K0,K2,K1,X1
	C255	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	K0,K2,K1,X1
	C256	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	K0,K2,K1,X1
	C260	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	K0,K2,K1,X1
	C271	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1,X1
	C272	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1,X1
	C273	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1,X1
	C274	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1,X1
	C275	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C276	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C277	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C278	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0,K2,K1,X1
	C279	CK73JXR1C103K	C CAPACITOR	0.01uF 16V K	1	K0,K2,K1,X1
	C283	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C284	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C285	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C287	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1,X1
	C288	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1,X1
	C289	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1,X1
	C290	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C291	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C292	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K0,K2,K1,X1
	C293	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1,X1
	C294	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	K0,K2,K1,X1
	C302	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	K0,K2,K1,X1
	C309	CC73JCH1H030C	C CAPACITOR	3pF 50V C	1	
	C310	CC73JCH1H070D	C CAPACITOR	7pF 50V D	1	
	C311	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C312	CC73JCH1H330J	C CAPACITOR	33pF 50V J	1	
	C313	CC73JCH1H010C	C CAPACITOR	1pF 50V C	1	
	C314	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C316	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C317	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C319	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C320	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C321	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C324	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C325	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C326	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C327	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C328	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C329	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C330	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C331	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C332	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C333	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C335	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C337	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	K0,K2,K1
	C338	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	K0,K2,K1
	C351	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C352	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C353	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C354	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C356	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C357	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C358	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C359	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C360	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C361	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C501	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1
	C502	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0,K2,K1
	C503	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0,K2,K1
	C511	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	K0,K2,K1,E1
	C512	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	K0,K2,K1,E1
	C601	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C602	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C603	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C604	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C605	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C606	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C610	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C611	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C612	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C613	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C614	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C616	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C618	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C619	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C711	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	K2
	C712	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	K2
	C713	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C714	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C715	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C716	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C721	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C722	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C793	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C794	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C851	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C852	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C854	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C855	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C1204	CB73QAD1C106M	F CAPACITOR	10uF 16V M	1	K0,K1,A1,M1,E1,X1
	C1711	CB73QAD1C106M	F CAPACITOR	10uF 16V M	1	K0,K1,A1,M1,E1,X1
	C1712	CB73QAD1C106M	F CAPACITOR	10uF 16V M	1	K0,K1,A1,M1,E1,X1
	C2006	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2186	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2301	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C2302	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C2303	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C2304	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2305	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2306	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2307	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2309	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C2310	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C2312	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2313	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2314	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2315	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2316	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2317	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2318	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2319	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2321	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2322	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2323	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2324	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2325	CE32CC0J331M	E CAPACITOR	330uF 6.3V M	1	
	C2331	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2332	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2333	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2401	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2501	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2502	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2503	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2504	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C2505	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2506	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2507	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2508	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C2509	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C2510	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C2512	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2513	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2514	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2515	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2516	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2517	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2527	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2528	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2529	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2530	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2531	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2532	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2533	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2534	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C2535	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2536	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2537	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2538	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2539	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2540	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2541	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2542	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2543	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2544	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2545	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2549	CC73JCH1H120J	C CAPACITOR	12pF 50V J	1	
	C2550	CC73JCH1H120J	C CAPACITOR	12pF 50V J	1	
	C2551	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C2552	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2553	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2554	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C2556	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2561	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2562	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2563	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2564	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2565	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2566	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2567	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2568	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C2571	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C2572	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2602	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2603	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C2605	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2606	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2607	CC73JCH1H220J	C CAPACITOR	22pF 50V J	1	
	C2609	CC73JCH1H220J	C CAPACITOR	22pF 50V J	1	
	C2611	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C2613	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C2615	CK73JXR1A683K	C CAPACITOR	0.068uF 10V K	1	
	C2616	CK73JXR1A683K	C CAPACITOR	0.068uF 10V K	1	
	C2617	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C2621	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2622	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2623	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C2624	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C2625	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	R13	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R15	RK73HH1J273D	MG RESISTOR	27kΩ 1/16W D	1	
	R17	RK73HH1J472D	MG RESISTOR	4.7kΩ 1/16W D	1	
	R18	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R19	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R30	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R31	RK73EB2E622J	MG RESISTOR	6.2kΩ 1/4W J	1	
	R32	RK73EB2E622J	MG RESISTOR	6.2kΩ 1/4W J	1	
	R33	RK73HH1J113D	MG RESISTOR	11kΩ 1/16W D	1	
	R34	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R35	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R36	RK73HH1J474D	MG RESISTOR	470kΩ 1/16W D	1	
	R37	RK73EB2E153J	MG RESISTOR	15kΩ 1/4W J	1	
	R38	RK73GH2A333D	MG RESISTOR	33kΩ 1/10W D	1	
	R39	RK73HB1J273J	MG RESISTOR	27kΩ 1/16W J	1	
	R40	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1
	R41	RK73FB2B472J	MG RESISTOR	4.7kΩ 1/8W J	1	
	R42	RK73FB2B472J	MG RESISTOR	4.7kΩ 1/8W J	1	
	R50	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R51	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	
	R52	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	
	R53	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	
	R54	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R55	RK73GB2A152J	MG RESISTOR	1.5kΩ 1/10W J	1	
	R60	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R61	RK73GB2A111J	MG RESISTOR	110Ω 1/10W J	1	
	R62	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	

E1
K0,K2,K1,A1,M1,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R63	RK73HB1J243J	MG RESISTOR	24kΩ 1/16W J	1	
	R64	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R65	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R66	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R67	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R68	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R69	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R70	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R72	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R73	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	
	R74	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R80	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R81	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R82	RK73FB2B103J	MG RESISTOR	10kΩ 1/8W J	1	
	R83	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R84	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R90	RK73GB2A272J	MG RESISTOR	2.7kΩ 1/10W J	1	
	R91	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R100	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R101	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R101	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R102	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R102	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R103	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R103	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R104	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R104	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R115	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K2
	R116	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K1,A1,M1,E1,X1
	R140	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R142	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R143	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R144	RK73HB1J432J	MG RESISTOR	4.3kΩ 1/16W J	1	K0,K1,A1,M1,E1,X1
	R144	RK73HB1J751J	MG RESISTOR	750Ω 1/16W J	1	K2
	R145	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R146	RK73HB1J1R0J	MG RESISTOR	1.0Ω 1/16W J	1	K0,K1,A1,M1,E1,X1
	R146	RK73HB1J3R0J	MG RESISTOR	3.0Ω 1/16W J	1	K2
	R151	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R152	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R153	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R154	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R155	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R156	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R159	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R161	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R162	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R163	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R164	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R165	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R166	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R171	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R172	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R173	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R174	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R175	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R176	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R191	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R192	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R193	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R194	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R195	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R196	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R201	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R202	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R204	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R205	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R206	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R211	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R212	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R213	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R214	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R215	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R216	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R217	RK73HH1J392D	MG RESISTOR	3.9kΩ 1/16W D	1	
	R218	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R219	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R220	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R251	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R252	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R253	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	K0,K2,K1,X1
	R254	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	K0,K2,K1,X1
	R255	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,X1
	R256	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,X1
	R257	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,X1
	R258	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,X1
	R260	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	K0,K2,K1,X1
	R261	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	K0,K2,K1,X1
	R272	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	K0,K2,K1,X1
	R273	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	K0,K2,K1,X1
	R283	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R284	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R285	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R287	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R288	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R289	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R290	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R291	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R292	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R293	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	K0,K2,K1,X1
	R294	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R295	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R296	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R297	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R303	RK73HH1J510D	MG RESISTOR	51Ω 1/16W D	1	
	R304	RK73HB1J121J	MG RESISTOR	120Ω 1/16W J	1	
	R309	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R310	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R311	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R312	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R313	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R314	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R315	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R316	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R317	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R318	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R320	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R321	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R322	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R323	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R324	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R326	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R328	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R335	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R336	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R337	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K2,K1
	R338	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K2,K1
	R341	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R343	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K2,K1
	R345	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K2,K1
	R351	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R353	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R354	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R357	RK73HB1J562J	MG RESISTOR	5.6kΩ 1/16W J	1	
	R358	RK73HB1J562J	MG RESISTOR	5.6kΩ 1/16W J	1	
	R359	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R360	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R361	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R367	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R368	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R369	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R370	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	K0,K2,K1
	R370	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	A1,M1,E1,X1
	R371	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	K0,K2,K1
	R371	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	A1,M1,E1,X1
	R372	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	K0,K2,K1
	R372	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	A1,M1,E1,X1
	R373	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	K0,K2,K1
	R373	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	A1,M1,E1,X1
	R500	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0,K2,K1
	R501	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0,K2,K1
	R502	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0,K2,K1
	R503	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0,K2,K1
	R511	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0,K2,K1,E1
	R512	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0,K2,K1,E1
	R513	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0,K2,K1,E1
	R514	RK73HB1J2R2J	MG RESISTOR	2.2Ω 1/16W J	1	K0,K2,K1,E1
	R515	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,E1
	R516	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,E1
	R517	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0,K2,K1,E1
	R581	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0,K2,K1,X1
	R582	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0,K2,K1,X1
	R611	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R612	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R614	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R615	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R616	RK73HB1J684J	MG RESISTOR	680kΩ 1/16W J	1	
	R798	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R851	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
	R852	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
	R855	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R856	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R857	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R859	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R861	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R863	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R864	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R1101	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R1101	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R1102	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R1102	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R1103	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R1103	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R1104	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R1104	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R1111	RK73HB1J120J	MG RESISTOR	12Ω 1/16W J	1	K2
	R1112	RK73HB1J120J	MG RESISTOR	12Ω 1/16W J	1	K2
	R1113	RK73HB1J120J	MG RESISTOR	12Ω 1/16W J	1	K2
	R1114	RK73HB1J120J	MG RESISTOR	12Ω 1/16W J	1	K2
	R1146	RK73HH1J160D	MG RESISTOR	16Ω 1/16W D	1	K0,K1,A1,M1,E1,X1
	R1146	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K2
	R2008	RK73HH1J223D	MG RESISTOR	22kΩ 1/16W D	1	
	R2009	RK73HH1J184D	MG RESISTOR	180kΩ 1/16W D	1	
	R2010	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R2011	RK73HH1J392D	MG RESISTOR	3.9kΩ 1/16W D	1	
	R2012	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R2013	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R2014	RK73HH1J753D	MG RESISTOR	75kΩ 1/16W D	1	
	R2015	RK73HH1J561D	MG RESISTOR	560Ω 1/16W D	1	
	R2301	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2302	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2303	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2304	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2307	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2310	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R2311	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2312	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2313	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2314	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2316	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2317	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R2318	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2319	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2320	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2321	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2322	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2323	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2324	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2325	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2326	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2327	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2328	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2329	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2331	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2332	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2333	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2334	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2335	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2336	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2337	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2338	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2339	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2340	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2341	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2342	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2343	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2344	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2345	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2346	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2347	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2348	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2349	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2350	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2351	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R2352	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R2355	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2356	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2357	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2359	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2361	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2362	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2363	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2364	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2365	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2366	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2367	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2368	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2369	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2370	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2371	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2372	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2373	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2374	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2375	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R2376	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R2377	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R2378	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2379	RK73HB1J124J	MG RESISTOR	120kΩ 1/16W J	1	
	R2380	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R2381	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2382	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2383	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R2389	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2391	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R2392	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2393	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2394	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2395	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2396	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2397	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2398	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2400	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2401	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2402	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2403	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2404	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2405	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2406	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2407	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2408	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2409	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R2501	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2503	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2504	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2506	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2507	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2511	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2512	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2513	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2514	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2518	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2519	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2521	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2522	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2524	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2545	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2546	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2547	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2548	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2549	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2550	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R2551	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R2552	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2553	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2554	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2555	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2556	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2557	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2558	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2559	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2560	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2561	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2562	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2563	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2564	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2565	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2566	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2567	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2568	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	
	R2569	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2570	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2572	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2574	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2575	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2576	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R2577	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2578	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R2579	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R2581	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2587	RK73HB1J392J	MG RESISTOR	3.9kΩ 1/16W J	1	
	R2588	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2589	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2590	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2591	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2592	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2593	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2594	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2595	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R2596	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2609	RK73HB1J203J	MG RESISTOR	20kΩ 1/16W J	1	
	R2610	RK73HB1J203J	MG RESISTOR	20kΩ 1/16W J	1	
	R2612	RK73HB1J304J	MG RESISTOR	300kΩ 1/16W J	1	
	R2614	RK73HB1J304J	MG RESISTOR	300kΩ 1/16W J	1	
	R2616	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2617	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2618	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R2620	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R2622	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R2624	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	
	R2625	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	L1	L3D-0053-00	CHOKE COIL		1	K0,K2,K1,X1
	L1	L3D-0062-00	CHOKE COIL		1	A1,M1,E1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	L301	LK73G0BE1R0K	M.CHIP INDUCTOR		1	
	L302	LK73G0BE1R0K	M.CHIP INDUCTOR		1	
	L303	LK73G0BER33K	M.CHIP INDUCTOR		1	
	L304	LK73G0BER18K	M.CHIP INDUCTOR		1	
	L305	LK73G0BE68NK	M.CHIP INDUCTOR		1	
	L306	LK73G0BE1R5K	M.CHIP INDUCTOR		1	
	L601	LK73G0AQ1R0K	M.CHIP INDUCTOR		1	
	L2301	LB73G0FK-001	CHIP FERRITE		1	
	CN101	EB770AX-05E0A	B TO B CONNE		1	
	CN2301	EA720AT-1008A	W TO B CONNE		1	
	CN2303	EC710AM-0510A	FFC FPC CONNE		1	
△	F6	F53-0513-08	PATTERN FUSE	4A	1	
△	F7	F53-0513-08	PATTERN FUSE	4A	1	
△	F171	F53-0513-08	PATTERN FUSE	4A	1	
△	F191	F53-0513-08	PATTERN FUSE	4A	1	
△	F500	FZA10BZ-2R5	FUSE (CC)		1	E1
△	F581	F53-0513-08	PATTERN FUSE	4A	1	
	J1	E5J-0022-00	R.RECEPTACLE		1	
	J151	E6D-0025-00	PIN JACK		1	K0,K2,K1,E1
	J151	E6D-0027-00	PIN JACK		1	A1,M1,X1
	J191	E1B-0041-00	3.5D PHONE JACK		1	
	J501	E5G-0029-00	CYL.RECEPTACLE		1	K0,K2,K1
	J501	E5G-0030-00	CYL.RECEPTACLE		1	E1
	J581	E1B-0041-00	3.5D PHONE JACK		1	K0,K2,K1,X1
	J2601	E1B-0041-00	3.5D PHONE JACK		1	
	VA52	SDV1005E18//2	VARIATOR		1	
	VA55	SDV1005E18//2	VARIATOR		1	
	VA60	SDV1005E18//2	VARIATOR		1	
	VA72	SDV1005E18//2	VARIATOR		1	
	VA74	SDV1005E18//2	VARIATOR		1	
	VA75	SDV1005E18//2	VARIATOR		1	
	VA171	SDV1005A14//0	VARIATOR		1	
	VA172	SDV1005A14//0	VARIATOR		1	
	VA173	SDV1005A14//0	VARIATOR		1	
	VA174	SDV1005A14//0	VARIATOR		1	
	VA175	SDV1005A14//0	VARIATOR		1	
	VA176	SDV1005A14//0	VARIATOR		1	
	VA177	SDV1005A14//0	VARIATOR		1	
	VA195	SDV1005A14//0	VARIATOR		1	
	VA196	SDV1005A14//0	VARIATOR		1	
	VA197	SDV1005A14//0	VARIATOR		1	
	VA301	F0K-0010-00	SURGE ABSORBER		1	
	VA302	F0K-0014-00	SURGE ABSORBER		1	
	VA501	SDV1005A14//0	VARIATOR		1	K0,K2,K1
	VA502	SDV1005A14//0	VARIATOR		1	K0,K2,K1
	VA503	SDV1005A14//0	VARIATOR		1	K0,K2,K1
	VA511	SDV1005E18//2	VARIATOR		1	K0,K2,K1,E1
	VA512	SDV1005E18//2	VARIATOR		1	K0,K2,K1,E1
	VA513	SDV1005E18//2	VARIATOR		1	K0,K2,K1,E1
	VA581	SDV1005A14//0	VARIATOR		1	K0,K2,K1,X1
	VA582	SDV1005A14//0	VARIATOR		1	K0,K2,K1,X1
	VA583	SDV1005A14//0	VARIATOR		1	K0,K2,K1,X1
	VA851	SDV1005E18//2	VARIATOR		1	
	W301	E3A-0039-10	ANTENNA CABLE		1	
	X301	L7J-0194-00	QUARTZ CRYSTAL		1	
	X2301	L7J-0099-00	QUARTZ CRYSTAL		1	
	X2501	L7J-0026-00	QUARTZ CRYSTAL		1	
VIDEO PWB ASSY (XJ8-092K-0x) <XJ8>						
	IC1	PICA38603-NV	IR DETECT UNIT		1	
	IC100	MM3703F33HE	ANALOG IC		1	
	IC300	W3F-0572-00	MCU IC		1	
	IC301	IC-PST8428U	MOS IC		1	
	IC302	TC7SH32FUJC	MOS IC		1	
	IC303	TC7SH17FUJC	MOS IC		1	
	IC500	NJW4131R-B	ANALOG IC		1	
	IC600	-----	MOS IC	NO SERVICE PART	1	
	IC601	XC6223B331P-G	ANALOG IC		1	
	IC700	OZ537SILN-B21	ANALOG IC		1	
	Q30	LSCR523UBFS8	TRANSISTOR		1	
	Q31	LSCR523UBFS8	TRANSISTOR		1	
	Q32	LSCR523UBFS8	TRANSISTOR		1	
	Q50	LSCR523UBFS8	TRANSISTOR		1	
	Q51	LSCR523UBFS8	TRANSISTOR		1	
	Q52	LSCR523UBFS8	TRANSISTOR		1	
	Q300	KRC407E-P	DIGI TRANSISTOR		1	
	Q301	KRC407E-P	DIGI TRANSISTOR		1	
	D1	NSSM124F	LED		1	
	D2	NSSM124F	LED		1	
	D4	NSSM124F	LED		1	
	D5	NSSM124F	LED		1	
	D6	NSSM124F	LED		1	
	D7	NSSM124F	LED		1	
	D300	RB531SM-30	DIODE		1	
	D500	RB160MM-30	SCHOTTKY DIODE		1	
	D701	RB056LAM-40	SCHOTTKY DIODE		1	
	D3001	EDZCVFH6.8B	ZENER DIODE		1	
	D3002	EDZCVFH6.8B	ZENER DIODE		1	
	D4000	TPD4E05U06DQA	DIODE		1	
	D4001	TPD4E05U06DQA	DIODE		1	
	D4002	TPD4E05U06DQA	DIODE		1	
	C1	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C2	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C100	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C101	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C102	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C103	CK73HXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C104	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C105	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C200	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C201	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C202	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C203	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C204	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C205	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C300	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C301	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C302	CK73HXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C303	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C305	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C306	CK73HXR1A474K	C CAPACITOR	0.47uF 10V K	1	
	C307	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C308	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C309	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C310	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C317	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C318	CK73FXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C319	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C320	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C400	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C401	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C402	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C403	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C409	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C410	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C411	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C412	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C413	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C414	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C415	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C416	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C501	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C502	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C504	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C505	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C506	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C507	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C508	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C509	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C510	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C511	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C512	CK73FXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C513	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C514	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C515	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C516	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C517	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C518	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C600	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C601	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C602	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C603	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C604	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C605	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C606	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C610	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C611	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C612	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C613	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C614	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C615	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C616	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C617	CK73JXR1C103K	C CAPACITOR	0.01uF 16V K	1	
	C618	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C619	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C620	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C621	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C622	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C623	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C624	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C631	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C632	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C633	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C634	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C635	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C636	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C637	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C638	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C639	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C640	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C641	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C642	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C643	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C644	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C645	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C646	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C647	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C648	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C649	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C650	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C651	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C652	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C700	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C701	CK73GXR1H105K	C CAPACITOR	1uF 50V K	1	
	C702	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C703	CK73GXR1H105K	C CAPACITOR	1uF 50V K	1	
	C704	CK73HXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C705	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C707	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C708	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C709	CS77DBY1E101M	TA E CAPACITOR	100uF 25V M	1	
	C711	CE32EL1V220M	E CAPACITOR	22uF 35V M	1	
	C712	CE32EL1V220M	E CAPACITOR	22uF 35V M	1	
	C713	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C714	CB73LAE1V106M	FILM CAPACITOR	10uF 35V M	1	
	C904	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C905	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C3003	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C3004	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C3005	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C3006	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C3007	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C3008	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C4000	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C4001	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C4002	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C4003	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C4004	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C4005	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C4006	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C4007	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C5001	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	K0
	C5002	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	K0
	C5003	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	K0
	C5004	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	K0
	R1	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R11	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R12	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R15	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R17	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R18	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R30	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R31	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R32	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R33	RK73FB2B471J	MG RESISTOR	470Ω 1/8W J	1	
	R34	RK73FB2B221J	MG RESISTOR	220Ω 1/8W J	1	
	R35	RK73FB2B221J	MG RESISTOR	220Ω 1/8W J	1	
	R36	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R37	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R38	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R39	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R40	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R41	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R42	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R43	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R44	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R50	RK73EB2E681J	MG RESISTOR	680Ω 1/4W J	1	
	R51	RK73FB2B561J	MG RESISTOR	560Ω 1/8W J	1	
	R52	RK73FB2B561J	MG RESISTOR	560Ω 1/8W J	1	
	R53	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R54	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R55	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R56	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R57	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R58	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R107	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R108	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R109	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R200	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R203	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R204	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R206	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R207	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R209	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R211	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R213	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R214	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R215	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R216	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R217	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R230	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R301	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R302	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R303	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R304	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R310	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R311	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R312	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R313	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R314	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R315	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R316	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R318	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R319	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R320	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R322	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R324	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R325	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R327	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R328	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R329	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R330	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R331	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R332	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R333	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R334	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R335	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R336	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R337	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R338	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R340	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R347	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R348	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R349	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R350	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R351	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R352	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R353	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R354	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R355	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R356	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R358	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R402	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R403	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R404	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R405	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R406	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
	R407	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
	R410	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R411	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R412	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R413	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R414	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R416	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R500	RK73EB2E472J	MG RESISTOR	4.7kΩ 1/4W J	1	
	R501	RK73HH1J473D	MG RESISTOR	47kΩ 1/16W D	1	
	R502	RK73HB1J273J	MG RESISTOR	27kΩ 1/16W J	1	
	R503	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R504	RK73HH1J681D	MG RESISTOR	680Ω 1/16W D	1	
	R506	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R507	RK73HH1J224D	MG RESISTOR	220kΩ 1/16W D	1	
	R600	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R601	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R602	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R603	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R604	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R605	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R606	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R607	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R608	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R609	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R610	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R611	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R612	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R613	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R614	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R615	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R616	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R617	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R618	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R619	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R620	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R621	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R622	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R623	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R624	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R625	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R626	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R627	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R628	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R629	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R630	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R631	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R632	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R633	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R634	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R635	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R636	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R637	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R638	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R642	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R643	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R644	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R645	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R646	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R648	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R649	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R650	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R652	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R656	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R657	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R658	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R662	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R665	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R666	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R667	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R700	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R701	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R703	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R704	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R706	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R707	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R708	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	
	R711	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R712	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R715	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R716	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R717	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R719	RK73HB1J273J	MG RESISTOR	27kΩ 1/16W J	1	
	R4004	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R4005	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4006	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4007	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4008	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4009	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4010	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4011	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4012	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4013	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R4014	RK73HH1J220D	MG RESISTOR	22Ω 1/16W D	1	
	R5001	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R5002	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R5003	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R5004	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0
	R5005	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R5006	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	L200	LB73E0FU-004	CHIP FERRITE		1	
	L300	LR73Z0AD100K	CHIP INDUCTOR		1	
	L400	LB73G0EA-002	CHIP FERRITE		1	
	L500	LR79Z0BH470M	CHIP INDUCTOR		1	
	L600	LR73Z0AD100K	CHIP INDUCTOR		1	
	L601	LR73Z0AD100K	CHIP INDUCTOR		1	
	L602	LR73Z0AD100K	CHIP INDUCTOR		1	
	L610	LB73G0DY-003	CHIP FERRITE		1	
	L611	LB73G0DY-003	CHIP FERRITE		1	
	L612	LB73G0DY-003	CHIP FERRITE		1	
	L613	LB73G0DY-003	CHIP FERRITE		1	
	L614	LB73G0DY-003	CHIP FERRITE		1	
	L615	LB73G0DY-003	CHIP FERRITE		1	
	L616	LB73G0DY-003	CHIP FERRITE		1	
	L617	LB73G0DY-003	CHIP FERRITE		1	
	L618	LB73G0DY-003	CHIP FERRITE		1	
	L619	LB73G0DY-003	CHIP FERRITE		1	
	L620	LB73G0DY-003	CHIP FERRITE		1	
	L621	LB73G0DY-003	CHIP FERRITE		1	
	L622	LB73G0DY-003	CHIP FERRITE		1	
	L623	LB73G0DY-003	CHIP FERRITE		1	
	L624	LB73G0DY-003	CHIP FERRITE		1	
	L625	LB73G0DY-003	CHIP FERRITE		1	
	L626	LB73G0DY-003	CHIP FERRITE		1	
	L627	LB73G0DY-003	CHIP FERRITE		1	
	L628	LB73G0DY-003	CHIP FERRITE		1	
	L629	LB73G0DY-003	CHIP FERRITE		1	
	L630	LB73G0DY-003	CHIP FERRITE		1	
	L631	LB73G0DY-003	CHIP FERRITE		1	
	L700	LR79Z0MZ100M	CHIP INDUCTOR		1	
	L701	LR79Z0MZ100M	CHIP INDUCTOR		1	
	CN1	EC720AA-0518A	FFC FPC CONNE		1	
	CN100	EC720BK-0564B	FFC FPC CONNE		1	
	CN200	EC720BK-0540B	FFC FPC CONNE		1	
	CN302	EC720AT-0510A	FFC FPC CONNE		1	
	CN400	EC720AA-0518A	FFC FPC CONNE		1	
	CN600	EC720CF-0570A	FFC FPC CONNE		1	
	CN601	EC720AA-0508A	FFC FPC CONNE		1	
	CN3001	EB770BT-0560C	B TO B CONNE		1	
	CN3002	EC720BK-0564B	FFC FPC CONNE		1	
	CN4000	EB740BT-0560A	B TO B CONNE		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	CN4001	EC720BK-0564B	FFC FPC CONNE		1	
	CN5001	EC720AA-0515A	FFC FPC CONNE		1	K0
	J5001	E2K-0065-00	SD CARD CONNE		1	K0
	S1	S7A-0001-00	TACTILE PUSH SW		1	
	S2	S7A-0001-00	TACTILE PUSH SW		1	
	S4	S7A-0001-00	TACTILE PUSH SW		1	
	S5	S7A-0001-00	TACTILE PUSH SW		1	
	S6	T9K-0031-00	ROTARY ENCODER		1	
	S3001	S6D-0001-00	LEVER SWITCH		1	
	VA100	SDV1005E18//0	VARIATOR		1	
	VA101	SDV1005E18//0	VARIATOR		1	
	VA102	SDV1005E18//0	VARIATOR		1	
	VA103	SDV1005E18//0	VARIATOR		1	
	VA104	SDV1005E18//0	VARIATOR		1	
	VA107	SDV1005E18//0	VARIATOR		1	
	VA108	SDV1005E18//0	VARIATOR		1	
	VA109	SDV1005E18//0	VARIATOR		1	
	VA110	SDV1005E18//0	VARIATOR		1	
	VA111	SDV1005E18//0	VARIATOR		1	
	VA112	SDV1005E18//0	VARIATOR		1	
	VA113	SDV1005E18//0	VARIATOR		1	
	VA114	SDV1005E18//0	VARIATOR		1	
	VA115	SDV1005H26//0	VARIATOR		1	
	VA116	SDV1005H26//0	VARIATOR		1	
	VA117	SDV1005E18//0	VARIATOR		1	
	VA118	SDV1005E18//0	VARIATOR		1	
	VA400	SDV1005E18//0	VARIATOR		1	
	VA403	SDV1005E18//0	VARIATOR		1	
	VA404	SDV1005E18//0	VARIATOR		1	
	VA405	SDV1005E18//0	VARIATOR		1	
	VA406	SDV1005E18//0	VARIATOR		1	
	VA408	SDV1005E18//0	VARIATOR		1	
	VA409	SDV1005E18//0	VARIATOR		1	
	VA4000	SDV1005H26//0	VARIATOR		1	
	VA4001	SDV1005H26//0	VARIATOR		1	
	VA4002	SDV1005H26//0	VARIATOR		1	
	VA4003	SDV1005H26//0	VARIATOR		1	
	VA4004	SDV1005H26//0	VARIATOR		1	
	VA4005	SDV1005H26//0	VARIATOR		1	
	VA4006	SDV1005H26//0	VARIATOR		1	
	VA4007	SDV1005H26//0	VARIATOR		1	
	VA4008	SDV1005H26//0	VARIATOR		1	
	VA4009	SDV1005H26//0	VARIATOR		1	
	VA4010	SDV1005H26//0	VARIATOR		1	
	VA4011	SDV1005H26//0	VARIATOR		1	
	VA4012	SDV1005H26//0	VARIATOR		1	
	VA4013	SDV1005H26//0	VARIATOR		1	
	VA4014	SDV1005H26//0	VARIATOR		1	
	VA4015	SDV1005H26//0	VARIATOR		1	
	VA4016	SDV1005H26//0	VARIATOR		1	
	VA4017	SDV1005H26//0	VARIATOR		1	
	VA4018	SDV1005H26//0	VARIATOR		1	
	VA4019	SDV1005H26//0	VARIATOR		1	
	VA4020	SDV1005H26//0	VARIATOR		1	
	VA4021	SDV1005H26//0	VARIATOR		1	
	VA4022	SDV1005H26//0	VARIATOR		1	
DIGITAL IO PWB ASSY (XJA-080x-0x) <XJA>						
	IC21	ML86251LAZ07F	MOS IC	BGA	1	
	IC22	TC7SH08FUJC	MOS IC		1	
	IC81	NJU7108F3	MOS IC		1	
	IC111	XC6209B502P-G	MOS IC		1	
	IC112	NJW1341VC3	MOS IC		1	
	IC151	AK8818VQ	MOS IC		1	
	IC231	TPS2543RTE	MOS IC		1	
	IC251	MM3411A18NE	ANALOG IC		1	
	IC252	RP108J081B-AE	MOS IC		1	
	IC301	TCC3171G-0XX	MPU IC	BGA	1	E1,X1
	IC302	MM3411A12NE	ANALOG IC		1	
	IC303	TPS7B7701QWPQ	ANALOG IC		1	E1,X1
	IC401	IT68013FN/BX	MOS IC		1	E1,X1
	IC402	XC6223B121P-G	ANALOG IC		1	
	IC451	TS3DV642A0RUA	MOS IC		1	
	IC501	XC6223B121P-G	ANALOG IC		1	
	IC502	TP2825-KA	MOS IC		1	
	IC701	TC7SET08FUJC	MOS IC		1	
	IC721	TC7SH08FUJC	MOS IC		1	
	IC722	TC7SZ125FUJC	MOS IC		1	
	IC723	TC7SET08FUJC	MOS IC		1	
	IC781	TC7SZ125FUJC	MOS IC		1	K0,K2,K1,X1
	IC782	TC7SZ125FUJC	MOS IC		1	K0,K2,K1,X1
	IC831	AK4387ET7	ANALOG IC		1	
	IC853	NJG1143UA2	MOS IC		1	
	IC854	UBX-M8030-KT	MOS IC		1	
	IC855	NJM2903CRB1	MOS IC		1	
	IC856	NJM2903CRB1	MOS IC		1	
	IC857	MM3608A33NH	ANALOG IC		1	
	IC858	MM3411A33NE	ANALOG IC		1	
	IC901	NJM8080RB1	ANALOG IC		1	
	IC902	NJM8080RB1	ANALOG IC		1	
	IC1001	TCC8034-0AX-I	MPU IC		1	
	IC1060	TC7WZ34FUJC	MOS IC		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	IC1151	TC7SH08FUJC	MOS IC		1	
	IC1152	RA8900CEUB	ANALOG IC		1	
	IC1153	TC7WZ34FUJC	MOS IC		1	
	IC1154	TC7WZ34FUJC	MOS IC		1	
	IC1601	K4F6E3S4HMGHC	DRAM IC		1	
	IC1701	-----	PROGRAMMED IC	NO SERVICE PART	1	K0
	IC1701	-----	PROGRAMMED IC	NO SERVICE PART	1	K2,K1
	IC1701	-----	PROGRAMMED IC	NO SERVICE PART	1	A1,M1,E1,X1
	IC1751	-----	ROM IC	NO SERVICE PART	1	
	IC1801	MFI343S00177	MCU IC		1	
	IC2001	LM53635MQRNLQ	ANALOG IC		1	
	IC2101	DA9063-35HO-A	MCU IC		1	
	IC2151	XCL219B183F-G	ANALOG IC		1	
	IC2301	MP9843GL	MOS IC		1	
	IC2401	MP9843GL	MOS IC		1	
	IC2501	MP9843GL	MOS IC		1	
	IC2502	INA199B3DCK	ANALOG IC		1	
	IC2701	XC6223B331P-G	ANALOG IC		1	K0
	IC2702	XC6223B151P-G	ANALOG IC		1	
	IC2703	TPS1H100AQWPQ	ANALOG IC		1	
	Q1	KRC407E-P	DIGI TRANSISTOR		1	
	Q21	KTC4075EP/Y/	TRANSISTOR		1	
	Q81	KTA2014EP/Y/	TRANSISTOR		1	
	Q111	RE1L002SN	FET		1	
	Q112	RE1L002SN	FET		1	
	Q113	KRA307E-P	TRANSISTOR		1	
	Q114	KRC407E-P	DIGI TRANSISTOR		1	
	Q401	RE1L002SN	FET		1	
	Q741	KRC407E-P	DIGI TRANSISTOR		1	A1,M1,E1,X1
	Q742	RE1C002ZP	FET		1	A1,M1,E1,X1
	Q743	RE1C002ZP	FET		1	A1,M1,E1,X1
	Q801	SSM3J372RF	FET		1	
	Q1151	RE1L002SN	FET		1	
	Q1153	KRC407E-P	DIGI TRANSISTOR		1	
	Q1202	KRA307E-P	TRANSISTOR		1	
	Q1203	LTC043ZEBFS8	DIGI TRANSISTOR		1	
	Q1801	KRC407E-P	DIGI TRANSISTOR		1	
	Q1802	KRC407E-P	DIGI TRANSISTOR		1	
	Q1803	KRC407E-P	DIGI TRANSISTOR		1	
	Q1804	KTA2014EP/Y/	TRANSISTOR		1	
	Q1805	KTC4075EP/Y/	TRANSISTOR		1	
	Q2101	KRC407E-P	DIGI TRANSISTOR		1	
	Q2102	RE1L002SN	FET		1	
	Q2103	RE1L002SN	FET		1	
	Q2501	LSCR523EBFS8	TRANSISTOR		1	
	Q2502	LSAR523EBFS8	TRANSISTOR		1	
	Q2503	KRC407E-P	DIGI TRANSISTOR		1	
	Q2504	KRC407E-P	DIGI TRANSISTOR		1	
	D302	1SS355-HF	DIODE		1	E1,X1
	D401	1SS355-HF	DIODE		1	
	D501	BZT52B5V6LSHF	ZENER DIODE		1	
	D502	BZT52B5V6LSHF	ZENER DIODE		1	
	D721	1SS355-HF	DIODE		1	
	D722	BZT52B5V6LSHF	ZENER DIODE		1	
	D723	BZT52B5V6LSHF	ZENER DIODE		1	
	D741	DAN202UM	DIODE		1	A1,M1,E1,X1
	D781	1SS355-HF	DIODE		1	K0,K2,K1,X1
	D782	BZT52B5V6LSHF	ZENER DIODE		1	K0,K2,K1,X1
	D783	BZT52B5V6LSHF	ZENER DIODE		1	K0,K2,K1,X1
	D803	1SS355-HF	DIODE		1	
	D804	1SS355-HF	DIODE		1	
	D2001	1SS355-HF	DIODE		1	
	D2002	1SS355-HF	DIODE		1	
	D2003	RB085BM-40	SCHOTTKY DIODE		1	
	C1	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C6	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C21	CC73JCH1H120J	C CAPACITOR	12pF 50V J	1	
	C22	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C23	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C24	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C25	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C26	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C27	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1	
	C28	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C29	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C31	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C32	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C33	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C34	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C35	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C36	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C37	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C38	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C39	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C40	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C41	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C42	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C43	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C44	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C45	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C46	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C47	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C48	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C49	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C50	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C51	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C52	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C53	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C55	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C57	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C58	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C59	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C61	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C62	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C63	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C64	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C66	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C67	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C68	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C69	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C70	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C71	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C72	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C74	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C76	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C77	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C81	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C82	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C83	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C91	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C111	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C112	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	
	C113	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C117	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	
	C121	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C122	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C123	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C124	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C125	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C126	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C127	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C128	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C129	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C131	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C132	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C134	CE32BJ1C470M	E CAPACITOR	47uF 16V M	1	
	C136	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C137	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C151	CK73EXR1C226K	C CAPACITOR	22uF 16V K	1	
	C152	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C153	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C154	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C155	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C156	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C158	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C159	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C160	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C231	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C232	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C251	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C252	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	
	C253	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C254	CC73HCH1H0R5C	C CAPACITOR	0.5pF 50V C	1	
	C255	CC73HCH1H100D	C CAPACITOR	10pF 50V D	1	
	C257	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C258	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C259	CC73HCH1H100D	C CAPACITOR	10pF 50V D	1	
	C260	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C261	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C262	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C263	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C264	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C265	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C266	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C267	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C268	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C269	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C270	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C271	CC73HCH1H100D	C CAPACITOR	10pF 50V D	1	
	C272	CC73HCH1H040C	C CAPACITOR	4pF 50V C	1	
	C273	CC73HCH1H060D	C CAPACITOR	6pF 50V D	1	
	C274	CC73HCH1H010C	C CAPACITOR	1pF 50V C	1	
	C276	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C277	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C278	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C279	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C280	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	
	C281	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C282	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	
	C301	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C305	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C306	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1
	C307	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,X1
	C308	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C309	CC73JCH1H070D	C CAPACITOR	7pF 50V D	1	E1,X1
	C310	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	E1,X1
	C311	CC73JCH1H070D	C CAPACITOR	7pF 50V D	1	E1,X1
	C312	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C314	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C315	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C318	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	E1,X1
	C320	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	E1,X1
	C321	CC73JCH1H090D	C CAPACITOR	9pF 50V D	1	E1,X1
	C322	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	E1,X1
	C323	CC73JCH1H030C	C CAPACITOR	3pF 50V C	1	E1,X1
	C324	CC73JCH1H680J	C CAPACITOR	68pF 50V J	1	E1,X1
	C335	CC73JCH1H680J	C CAPACITOR	68pF 50V J	1	E1,X1
	C336	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,X1
	C337	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	E1,X1
	C338	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1
	C339	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	E1,X1
	C340	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1
	C401	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C402	CC73JCH1H070C	C CAPACITOR	7pF 50V C	1	
	C403	CC73JCH1H070C	C CAPACITOR	7pF 50V C	1	
	C404	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	
	C405	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C406	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C407	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C408	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C409	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C410	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C411	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C412	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C414	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C415	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C416	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C417	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C418	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C419	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C420	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C421	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C422	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C423	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C424	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C425	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C426	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C427	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C428	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C431	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C433	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C434	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C435	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C436	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C437	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C438	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C451	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C452	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C501	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C502	CC73JCH1H070C	C CAPACITOR	7pF 50V C	1	
	C503	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C504	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C505	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C506	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C507	CC73JCH1H070C	C CAPACITOR	7pF 50V C	1	
	C508	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C509	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C510	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C511	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C512	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C513	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C514	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C515	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C516	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C517	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C518	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C519	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C520	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C521	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C522	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C523	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C524	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C525	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C528	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C529	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C701	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C702	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C703	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C704	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C721	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C722	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C723	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C743	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	A1,M1,E1,X1
	C781	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0,K2,K1,X1
	C782	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	K0,K2,K1,X1
	C783	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0,K2,K1,X1
	C831	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C832	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C833	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C834	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C835	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C836	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C837	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C838	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C860	CC73JCH1H120J	C CAPACITOR	12pF 50V J	1	
	C861	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C862	CC73JCH1H020C	C CAPACITOR	2pF 50V C	1	
	C863	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1	
	C864	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C865	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	
	C866	CC730CC1H1R8B	C CAPACITOR	1.8pF 50V B	1	
	C867	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C868	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C869	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C870	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C871	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C872	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C873	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C874	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C875	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C878	CC73JCH1H060C	C CAPACITOR	6pF 50V C	1	
	C879	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C880	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C881	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C882	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C883	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C884	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C886	CC73HCH1H010C	C CAPACITOR	1pF 50V C	1	
	C901	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C902	CC73JCH1H181J	C CAPACITOR	180pF 50V J	1	
	C903	CC73JCH1H181J	C CAPACITOR	180pF 50V J	1	
	C904	CC73JCH1H181J	C CAPACITOR	180pF 50V J	1	
	C905	CC73JCH1H181J	C CAPACITOR	180pF 50V J	1	
	C906	CC73JCH1E331J	C CAPACITOR	330pF 25V J	1	
	C907	CC73JCH1E331J	C CAPACITOR	330pF 25V J	1	
	C908	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C909	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C910	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C911	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C912	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C913	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C914	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C915	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C916	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C1001	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C1060	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1151	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1152	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1153	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1154	CC73JCH1H080C	C CAPACITOR	8pF 50V C	1	
	C1155	CC73JCH1H080C	C CAPACITOR	8pF 50V C	1	
	C1157	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1158	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1159	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1303	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C1401	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C1402	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C1403	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C1404	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C1405	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1406	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C1407	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1408	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1409	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C1410	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1411	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1412	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1413	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1414	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1415	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1416	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1417	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1418	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1419	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1420	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1421	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1422	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1423	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1424	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1425	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1426	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1427	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1428	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C1519	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1520	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1521	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1522	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1523	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1524	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1525	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1526	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1527	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1528	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1529	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1530	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1531	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1532	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1533	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1534	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1535	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1536	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1537	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1538	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1601	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C1602	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C1603	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C1604	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1605	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1606	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1607	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1608	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1609	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1610	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1611	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1612	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1613	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1614	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1615	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1616	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1617	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1618	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1619	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1620	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1621	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1622	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1623	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1624	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1625	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1626	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1627	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1628	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1629	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1630	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1631	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1632	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1633	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1634	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1635	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1636	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1637	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1638	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1639	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1640	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1641	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1642	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1643	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1644	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1645	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1646	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1647	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1648	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1649	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1650	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1651	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1652	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1653	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1654	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1655	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1656	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1657	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1658	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C1701	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1702	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1703	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1704	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1705	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1706	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1707	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C1751	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C1801	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2001	CD040CP1C222M	E CAPACITOR	2200uF 16V M	1	
	C2002	CD73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C2003	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2004	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C2005	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C2006	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2007	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2008	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2009	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C2010	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2011	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2103	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2104	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2105	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2106	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C2107	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C2108	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2109	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2110	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C2111	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2112	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C2113	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2114	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C2115	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C2116	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2120	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2121	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2122	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2123	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2124	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2125	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2126	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2127	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2128	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2129	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2130	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2131	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C2132	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2133	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2134	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2135	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2136	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2137	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2138	CK73EXR0J476M	C CAPACITOR	47uF 6.3V M	1	
	C2139	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C2151	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C2152	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C2218	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2219	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2220	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2301	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2302	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2304	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2305	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2306	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C2308	CC73JCH1H680J	C CAPACITOR	68pF 50V J	1	
	C2309	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2310	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2311	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2312	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2313	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2314	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2401	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2402	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2404	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2405	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2406	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C2407	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2408	CC73JCH1H470J	C CAPACITOR	47pF 50V J	1	
	C2409	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2410	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2411	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2412	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2413	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2418	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2419	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2420	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1	
	C2501	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2502	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	C2503	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2504	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2506	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C2507	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2508	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C2509	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2510	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2511	CK73JXR1C104K	C CAPACITOR	0.1uF 16V K	1	
	C2512	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2513	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C2514	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2515	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C2516	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C2701	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	KO
	C2702	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	KO
	C2704	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C2705	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	
	C2707	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2708	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2709	CK73EXR1H475K	C CAPACITOR	4.7uF 50V K	1	
	R4	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R5	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R6	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R7	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R8	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R9	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R10	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R11	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R12	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R13	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R14	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R15	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R16	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R17	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R19	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R21	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R22	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R23	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R24	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R25	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R26	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R27	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R28	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R29	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R30	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R31	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R32	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R33	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R34	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R35	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R36	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R37	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R39	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R40	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R41	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R42	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R44	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R46	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R49	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R57	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R63	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R70	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R71	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R72	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R73	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R81	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R82	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R83	RK73HH1J474D	MG RESISTOR	470kΩ 1/16W D	1	
	R84	RK73HH1J474D	MG RESISTOR	470kΩ 1/16W D	1	
	R85	RK73HH1J394D	MG RESISTOR	390kΩ 1/16W D	1	
	R86	RK73HH1J823D	MG RESISTOR	82kΩ 1/16W D	1	
	R87	RK73HH1J394D	MG RESISTOR	390kΩ 1/16W D	1	
	R88	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R113	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R114	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R115	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R120	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R122	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R123	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R124	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R125	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R126	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R129	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R151	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R155	RK73HH1J391D	MG RESISTOR	390Ω 1/16W D	1	
	R157	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R158	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R159	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R160	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R161	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R231	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R232	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R234	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R235	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R237	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R252	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R254	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R255	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R256	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R257	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R258	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R259	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R260	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R261	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R262	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R263	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R266	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R267	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R268	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R270	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R271	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R273	RK73HH1J330D	MG RESISTOR	33Ω 1/16W D	1	
	R274	RK73HH1J331D	MG RESISTOR	330Ω 1/16W D	1	
	R275	RK73HH1J820D	MG RESISTOR	82Ω 1/16W D	1	
	R276	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R277	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R278	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R280	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R281	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R282	RK73HH1J562D	MG RESISTOR	5.6kΩ 1/16W D	1	
	R283	RK73HH1J162D	MG RESISTOR	1.6kΩ 1/16W D	1	
	R304	RK73GB2A102J	MG RESISTOR	1kΩ 1/10W J	1	E1,X1
	R305	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	E1,X1
	R306	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	E1,X1
	R307	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	E1,X1
	R308	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	E1,X1
	R309	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	E1,X1
	R310	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	E1,X1
	R312	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R313	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1
	R314	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R317	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R318	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R321	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R322	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R323	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R324	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1
	R327	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R328	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	E1,X1
	R329	RK73HH1J561D	MG RESISTOR	560Ω 1/16W D	1	E1,X1
	R335	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	E1,X1
	R337	RK73HH1J472D	MG RESISTOR	4.7kΩ 1/16W D	1	E1,X1
	R338	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	E1,X1
	R339	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1
	R340	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R341	RK73HH1J392D	MG RESISTOR	3.9kΩ 1/16W D	1	E1,X1
	R378	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R379	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R384	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R385	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R401	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R403	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R404	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R405	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R406	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R407	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R408	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R409	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R411	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R412	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R413	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R414	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R415	RK73HB1J225J	MG RESISTOR	2.2MΩ 1/16W J	1	
	R416	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R417	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R418	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R419	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R420	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R421	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R422	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R423	RK73GB2A390J	MG RESISTOR	39Ω 1/10W J	1	
	R425	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R426	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	
	R427	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R428	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R429	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R430	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R431	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R432	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R433	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R434	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R435	RK73HB1J270J	MG RESISTOR	27Ω 1/16W J	1	
	R451	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R452	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R453	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R501	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R502	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R503	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R504	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R505	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R508	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R509	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R510	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R511	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R512	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R513	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R514	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R515	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R516	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R517	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R518	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R601	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R602	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R703	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R704	RK73HB1J750J	MG RESISTOR	75Ω 1/16W J	1	
	R721	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R722	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R723	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	
	R724	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R725	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R726	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R741	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R742	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R743	RK73GH2A472D	MG RESISTOR	4.7kΩ 1/10W D	1	
	R744	RK73GH2A472D	MG RESISTOR	4.7kΩ 1/10W D	1	
	R745	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	A1,M1,E1,X1
	R746	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R747	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R748	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	A1,M1,E1,X1
	R749	RK73GB2A470J	MG RESISTOR	47Ω 1/10W J	1	A1,M1,E1,X1
	R750	RK73EB2E511J	MG RESISTOR	510Ω 1/4W J	1	A1,M1,E1,X1
	R751	RK73GB2A470J	MG RESISTOR	47Ω 1/10W J	1	A1,M1,E1,X1
	R752	RK73EB2E511J	MG RESISTOR	510Ω 1/4W J	1	A1,M1,E1,X1
	R753	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	A1,M1,E1,X1
	R754	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	A1,M1,E1,X1
	R781	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	K0,K2,K1,X1
	R782	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K2,K1,X1
	R783	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0,K2,K1,X1
	R784	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K2,K1,X1
	R786	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0,K2,K1,X1
	R831	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R832	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R833	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R834	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R836	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R837	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R838	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R839	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R840	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R841	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R842	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R843	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R844	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R853	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R854	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R855	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R856	RK73HB1J750J	MG RESISTOR	75Ω 1/16W J	1	
	R857	RK73PB2H300J	MG RESISTOR	30Ω 1/2W J	1	
	R858	RK73PB2H300J	MG RESISTOR	30Ω 1/2W J	1	
	R859	RK73PB2H300J	MG RESISTOR	30Ω 1/2W J	1	
	R860	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R861	RK73HB1J151J	MG RESISTOR	150Ω 1/16W J	1	
	R862	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R863	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R864	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R865	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R866	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R867	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R868	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R869	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R901	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R902	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R904	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R905	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R906	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R907	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R908	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R909	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R910	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R911	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R912	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R913	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R914	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R915	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R916	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R917	RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
	R918	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R919	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R920	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R922	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R923	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	
	R1001	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1002	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1003	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1004	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1005	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1006	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1007	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R1008	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1009	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1011	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1020	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R1021	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1022	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1023	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1024	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1025	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1026	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1027	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1028	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1029	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1030	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1031	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1032	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1033	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R1034	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R1055	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1056	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1057	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1058	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1059	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R1060	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R1061	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1063	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1064	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1065	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1066	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1071	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1072	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1074	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1076	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1077	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1078	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1088	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K2,K1
	R1089	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K2,K1
	R1090	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K2,K1
	R1091	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K2,K1
	R1092	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1093	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1094	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1095	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1096	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1097	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1098	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1099	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1100	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1101	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1112	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1113	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R1114	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1115	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	K0
	R1116	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	K0
	R1117	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R1118	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	K0
	R1119	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	K0
	R1120	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	K0
	R1121	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R1122	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1123	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	K0
	R1124	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	K0
	R1125	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	K0
	R1126	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	K0
	R1127	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	K0
	R1128	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	K0
	R1131	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	A1,M1,E1,X1
	R1132	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	A1,M1,E1,X1
	R1133	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	A1,M1,E1,X1
	R1134	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	A1,M1,E1,X1
	R1151	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R1152	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R1153	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R1154	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R1159	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1160	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1161	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1163	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1164	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1165	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R1166	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1167	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1168	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1169	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1170	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1171	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1172	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1173	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1174	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1175	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1176	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1177	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R1178	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1179	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1180	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1181	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1182	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1183	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1184	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1185	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1186	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1187	RK73HB1J474J	MG RESISTOR	470kΩ 1/16W J	1	
	R1188	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1191	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1192	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1193	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1194	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R1195	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1196	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1197	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1198	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1203	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1204	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1205	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R1206	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R1208	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R1209	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R1218	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1219	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1220	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1221	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1225	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1227	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1231	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1232	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1233	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1234	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1251	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1252	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1253	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1264	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R1265	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R1266	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R1267	RK73HH1J822D	MG RESISTOR	8.2kΩ 1/16W D	1	
	R1268	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1272	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1273	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1274	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1276	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1279	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1281	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1283	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1285	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1287	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1289	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1300	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1309	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1310	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R1311	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1312	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1313	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1314	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1315	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1316	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1317	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1318	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1319	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1320	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1321	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1322	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1323	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1324	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1325	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1326	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1327	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1603	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R1604	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R1605	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1607	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1609	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1611	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1614	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R1615	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1701	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1702	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1703	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1704	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1705	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1706	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1707	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1708	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R1709	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R1710	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1711	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1714	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1715	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1716	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R1717	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1718	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1719	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1720	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1721	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1722	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1723	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1724	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1725	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1751	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1752	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1753	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1754	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1755	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1756	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1757	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1758	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R1759	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1762	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1763	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1801	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1803	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1804	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1805	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1806	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1807	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R1809	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R1810	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1811	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1812	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1851	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1852	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1853	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1854	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1855	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1856	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R1857	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1858	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1859	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1860	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1861	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1862	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1863	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R1864	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1865	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1866	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1867	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1869	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R1871	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1872	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1874	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1875	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1876	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R1877	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R1878	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R2001	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R2002	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R2004	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R2005	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2006	RK73HB1J3R3J	MG RESISTOR	3.3Ω 1/16W J	1	
	R2007	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2102	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R2103	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2104	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2106	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R2109	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2111	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2119	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2120	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R2121	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2122	RZ73F0BS150J	RESISTOR	15Ω J	1	
	R2123	RZ73F0BS330J	RESISTOR	33Ω J	1	
	R2124	RZ73F0BS150J	RESISTOR	15Ω J	1	
	R2125	RZ73F0BS330J	RESISTOR	33Ω J	1	
	R2127	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2129	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R2130	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R2151	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2152	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2153	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2218	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R2301	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2302	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2303	RK73HH1J471D	MG RESISTOR	470Ω 1/16W D	1	
	R2304	RK73HH1J363D	MG RESISTOR	36kΩ 1/16W D	1	
	R2306	RK73HH1J182D	MG RESISTOR	1.8kΩ 1/16W D	1	
	R2307	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R2308	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2309	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2310	RK73HH1J623D	MG RESISTOR	62kΩ 1/16W D	1	
	R2313	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R2314	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R2315	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R2401	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2402	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2403	RK73HH1J471D	MG RESISTOR	470Ω 1/16W D	1	
	R2404	RK73HH1J363D	MG RESISTOR	36kΩ 1/16W D	1	
	R2406	RK73HH1J182D	MG RESISTOR	1.8kΩ 1/16W D	1	
	R2407	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R2408	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2409	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2410	RK73HH1J623D	MG RESISTOR	62kΩ 1/16W D	1	
	R2413	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2418	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R2501	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R2502	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R2503	RK73HH1J471D	MG RESISTOR	470Ω 1/16W D	1	
	R2504	RK73HH1J363D	MG RESISTOR	36kΩ 1/16W D	1	
	R2506	RK73HH1J511D	MG RESISTOR	510Ω 1/16W D	1	
	R2507	RK73HH1J113D	MG RESISTOR	11kΩ 1/16W D	1	
	R2508	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R2509	RK73HH1J623D	MG RESISTOR	62kΩ 1/16W D	1	
	R2512	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2513	RK73EB2E151J	MG RESISTOR	150Ω 1/4W J	1	
	R2514	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2515	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R2516	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R2517	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R2518	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R2519	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R2520	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R2521	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R2522	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R2523	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R2524	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R2525	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R2702	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	K0
	R2703	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R2704	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	K0
	R2705	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R2712	RK73HH1J911D	MG RESISTOR	910Ω 1/16W D	1	
	RA501	RK74GB1J301J	MG RESISTOR	300Ω 1/16W J	1	
	RA502	RK74GB1J301J	MG RESISTOR	300Ω 1/16W J	1	
	RA853	RK74GB1J301J	MG RESISTOR	300Ω 1/16W J	1	
	RA854	RK74GB1J301J	MG RESISTOR	300Ω 1/16W J	1	
	L2	L3D-0039-00	CHOKE COIL		1	
	L3	L3D-0039-00	CHOKE COIL		1	
	L4	L3D-0039-00	CHOKE COIL		1	
	L5	L3D-0039-00	CHOKE COIL		1	
	L6	L3D-0039-00	CHOKE COIL		1	
	L21	LB73G0ED-004	CHIP FERRITE		1	
	L22	LB73G0ED-004	CHIP FERRITE		1	
	L23	LB73G0ED-004	CHIP FERRITE		1	
	L24	LB73G0ED-004	CHIP FERRITE		1	
	L25	LB73G0ED-004	CHIP FERRITE		1	
	L111	LR73Z0AC100K	CHIP INDUCTOR		1	
	L251	LK73H0AM2N2S	M.CHIP INDUCTOR		1	
	L252	LB73G0ED-004	CHIP FERRITE		1	
	L253	LB73G0ED-004	CHIP FERRITE		1	
	L254	LB73G0ED-004	CHIP FERRITE		1	
	L255	LK73H0AM2N2S	M.CHIP INDUCTOR		1	
	L256	LB73G0ED-004	CHIP FERRITE		1	
	L301	LK73G0ASR22J	M.CHIP INDUCTOR		1	E1,X1
	L302	LK73G0ASR22J	M.CHIP INDUCTOR		1	E1,X1
	L303	LB73G0EB-001	CHIP FERRITE		1	E1,X1
	L304	LB73G0EB-001	CHIP FERRITE		1	E1,X1
	L305	LK73G0ASR15J	M.CHIP INDUCTOR		1	E1,X1
	L307	LK73G0ASR10J	M.CHIP INDUCTOR		1	E1,X1
	L308	LK73G0ASR10J	M.CHIP INDUCTOR		1	E1,X1
	L309	LK73G0ASR22J	M.CHIP INDUCTOR		1	E1,X1
	L310	LK73G0ASR22J	M.CHIP INDUCTOR		1	E1,X1
	L311	LK73G0AS10NJ	M.CHIP INDUCTOR		1	E1,X1
	L401	LB73G0ED-004	CHIP FERRITE		1	
	L402	LB73G0ED-004	CHIP FERRITE		1	
	L501	LB73G0ED-004	CHIP FERRITE		1	
	L502	LB73G0ED-004	CHIP FERRITE		1	
	L503	LB73G0ED-004	CHIP FERRITE		1	
	L504	LB73G0ED-004	CHIP FERRITE		1	
	L505	LB73G0ED-004	CHIP FERRITE		1	
	L506	LB73G0ED-004	CHIP FERRITE		1	
	L801	LF73H0AB9N1B	F.C. INDUCTOR		1	
	L802	LR79H0HU27NJ	CHIP INDUCTOR		1	
	L803	LB73H0DZ-001	CHIP FERRITE		1	
	L804	LR79H0HU7N5G	CHIP INDUCTOR		1	
	L805	LB73H0DZ-001	CHIP FERRITE		1	
	L2001	LR79Z0PX2R0N	CHIP INDUCTOR		1	
	L2101	LR77Z0AK1R0M	CHIP INDUCTOR		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNR1007XR	K0	DMX1037S	K2	DMX1057XR	K1	DMX9720XS	A1
DMX9720XS	M1	DMX9720XDS	E1	DMX9720XDS	X1		

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	L2102	LR77Z0AK1R0M	CHIP INDUCTOR		1	
	L2103	LR77Z0AK1R0M	CHIP INDUCTOR		1	
	L2104	LR77Z0AK1R0M	CHIP INDUCTOR		1	
	L2105	LR77Z0AK1R0M	CHIP INDUCTOR		1	
	L2106	LR77Z0AK1R0M	CHIP INDUCTOR		1	
	L2301	LR79Z0PB2R2M	CHIP INDUCTOR		1	
	L2401	LR79Z0PB2R2M	CHIP INDUCTOR		1	
	L2501	LR79Z0PB2R2M	CHIP INDUCTOR		1	
	L2702	LB73G0ED-004	CHIP FERRITE		1	
	A251	W0C-0340-00	RF MODULE		1	
	AT251	T9A-0052-00	CHIP ANTENNA		1	
	AT252	T9A-0052-00	CHIP ANTENNA		1	
	CN1	EC720BK-0564B	FFC FPC CONNE		1	
	CN231	EA710AP-2009A	W TO B CONNE		1	
	CN601	EB760AX-05E0D	B TO B CONNE		1	
	CN701	EA710AT-1004A	W TO B CONNE		1	
	CN721	EA120CE-2503A	W TO B CONNE		1	
	CN781	EA120CK-2004A	W TO B CONNE		1	K0,K2,K1,X1
	CN851	EA710AP-2007A	W TO B CONNE		1	
	CN1111	EC710AM-0515A	FFC FPC CONNE		1	K0
	CN1851	EC720AT-0516A	FFC FPC CONNE		1	
△	F1	FZA10BF-R50	FUSE (CC)		1	
△	F92	F53-0513-08	PATTERN FUSE	4A	1	
△	F721	F53-0513-08	PATTERN FUSE	4A	1	
△	F741	F53-0513-08	PATTERN FUSE	4A	1	
△	F781	F53-0513-08	PATTERN FUSE	4A	1	
△	F782	F53-0513-08	PATTERN FUSE	4A	1	
△	F851	F53-0513-08	PATTERN FUSE	4A	1	
△	F901	F53-0513-08	PATTERN FUSE	4A	1	
	J301	E0E-0033-00	C.RECEPTACLE-SM		1	E1,X1
	J401	E5J-0146-00	HDMI TERMINAL		1	
	J741	E1B-0041-00	3.5D PHONE JACK		1	A1,M1,E1,X1
	J801	E5J-0023-00	R.RECEPTACLE		1	
	J901	E1B-0041-00	3.5D PHONE JACK		1	
	SF801	L7K-0074-00	SAW FILTER		1	
	VA233	SDV1005H26//0	VARIATOR		1	
	VA234	SDV1005H26//0	VARIATOR		1	
	VA301	SDV1005H26//0	VARIATOR		1	E1,X1
	VA302	F0K-0014-00	SURGE ABSORBER		1	E1,X1
	VA401	AVRL101A1R1NB	VARIATOR		1	
	VA402	AVRL101A1R1NB	VARIATOR		1	
	VA403	AVRL101A1R1NB	VARIATOR		1	
	VA405	F0K-0176-00	SURGE ABSORBER		1	
	VA406	F0K-0176-00	SURGE ABSORBER		1	
	VA407	AVRL101A1R1NB	VARIATOR		1	
	VA408	EZJP0270EA	VARIATOR		1	
	VA721	SDV1005A14//0	VARIATOR		1	
	VA722	SDV1005A14//0	VARIATOR		1	
	VA741	SDV1005E18//2	VARIATOR		1	A1,M1,E1,X1
	VA742	SDV1005E18//2	VARIATOR		1	A1,M1,E1,X1
	VA743	SDV1005E18//2	VARIATOR		1	A1,M1,E1,X1
	VA781	SDV1005A14//0	VARIATOR		1	K0,K2,K1,X1
	VA782	SDV1005A14//0	VARIATOR		1	K0,K2,K1,X1
	VA802	F0K-0029-00	SURGE ABSORBER		1	
	VA851	SDV1005E18//1	VARIATOR		1	
	VA852	SDV1005E18//1	VARIATOR		1	
	VA853	SDV1005E18//1	VARIATOR		1	
	VA854	SDV1005E18//1	VARIATOR		1	
	VA855	SDV1005E18//1	VARIATOR		1	
	VA856	SDV1005E18//1	VARIATOR		1	
	VA901	SDV1005A14//0	VARIATOR		1	
	VA902	SDV1005A14//0	VARIATOR		1	
	VA903	SDV1005A14//0	VARIATOR		1	
	X21	L7J-0146-00	QUARTZ CRYSTAL		1	
	X251	L7H-0052-00	SPXO		1	
	X301	L7J-0176-00	QUARTZ CRYSTAL		1	E1,X1
	X401	L7J-0052-00	QUARTZ CRYSTAL		1	
	X501	L7J-0052-00	QUARTZ CRYSTAL		1	
	X801	L7H-0098-00	TCXO		1	
	X802	L7J-0095-00	QUARTZ CRYSTAL		1	
	X1151	L7J-0197-00	QUARTZ CRYSTAL		1	