

1234

EXPLODED VIEWS AND PARTS LIST

PACKING (Page 46)

PACKING SECTION PARTS LIST

*: Non spare part

Mark	No.	Description	MVH-2300NEX/ XNUC	MVH-AV251BT/ XNUC	SPH-DA240BT/ XNUR	DMH-Z5150BT/ XNCS
A	1	Cord Assy	CDP1665	CDP1665	CDP1670	CDP1665
	4	Screw	CBA2383	CBA2383	CBA2383	Not used
	6	Handle	Not used	Not used	CND6289	Not used
	7	Cover	CEG1359	CEG1359	CEG1356	CEG1356
	8	Unit Box	CHG9472	QHG4458	QHG4459	QHG4456
B	9	Contain Box	CHL9472 (1/4)	QHL4458 (1/6)	QHL4459 (1/6)	QHL4456 (1/6)
	10	Protector	CHP4863	CHP4863	CHP4864	CHP4863
	11	Card Remote Control Unit	CXE5116	Not used	Not used	CXE5116
	16-1	Owner's Manual	See Contents of Web IM (3)	See Contents of Web IM (3)	QRD3632	QRD3630
	16-2	Quick Start Guide	CRD5016	QRD3640	Not used	Not used
	16-3	Installation Manual	CRD5017	QRD3635	Not used	Not used
	16-6	Warranty Card	QRY3001	QRY3001	CRY1376	Not used
C	17	Panel	Not used	Not used	Not used	CNS9475

Owner's Manual, Quick Start Guide, Installation Manual

Part No.	Language
QRD3630	English, Spanish (Espanol), Portuguese (B)
QRD3632	Russian
QRD3635	English, French, Spanish (Espanol)
QRD3640	English, French, Spanish (Espanol)

(3) CONTENTS OF Web IM

Part No.	Language
*QRI3113	English
*QRI3114	French
*QRI3115	Spanish (Espanol)

Above operation manuals are supplied in PDF files by the WEB.
Regarding the availability of paper manual, contact Pioneer Service representative in your region.

EXTERIOR (1) (Page 49)

EXTERIOR (1) SECTION PARTS LIST

Mark	No.	Description	MVH-2300NEX/ XNUC	MVH-AV251BT/ XNUC	SPH-DA240BT/ XNUR	DMH-Z5150BT/ XNCS
*	4	Holder	CND7759	CND7759	CND7758	CND7758
	20	Grille Assy	CXF1484	QXA5855	QXA5856	QXA5853
	23	Grille	CNU4014	QNS4372	QNS4373	QNS4371
	26	Service Unit (Monitor)	CXY1226	CXY1226	CXY1227	CXY1227
	28	Holder	Not used	Not used	CND7102	Not used
	29	Panel	Not used	Not used	CNU2645	Not used
	40	Gasket	CNN5583	CNN5583	Not used	Not used

EXTERIOR (2) (Page 51)

EXTERIOR (2) SECTION PARTS LIST

Mark	No.	Description	MVH-2300NEX/ XNUC	MVH-AV251BT/ XNUC	SPH-DA240BT/ XNUR	DMH-Z5150BT/ XNCS
	2	Cord Assy	CDP1665	CDP1665	CDP1670	CDP1665
	4	Card Remote Control Unit	CXE5116	Not used	Not used	CXE5116
	5	Battery Cover	CNU1624	Not used	Not used	CNU1624
	13	FFC	CDD1220	CDD1220	CDD1219	CDD1219
	14	Holder	CND7750	CND7750	CND7748	CND7748
	16	Service Unit (Mother I/F)	CXY1217	QXX3282	QXX3283	QXX3280
	23	Holder	CND7760	CND7760	Not used	Not used
	24	Service Unit (I-Data)	CXY1237	QXX3286	Not used	Not used
	25	Screw	BSZ26P060FTC	BSZ26P060FTC	Not used	Not used
	26	FFC	CDD1222	CDD1222	Not used	Not used

ELECTRICAL PARTS LIST (Page 91)

SERVICE UNIT (MOTHER I/F)

	Circuit Symbol and No.	Part Name	MVH-2300NEX/ XNUC	MVH-AV251BT/ XNUC	SPH-DA240BT/ XNUR	DMH-Z5150BT/ XNCS
A	IC1301	Flash ROM Unit	CVQ1121	CVQ1192	CVQ1193	CVQ1193
	IC1321	Flash Memory IC	W25Q64FVSSIG	W25Q64JVSSIQ	W25Q16JVSSIQ	W25Q16JVSSIQ
	IC4131	Buffer Logic IC	TC7SH126FUS1	TC7SH126FUS1	Not used	Not used
	IC4132	AND Logic IC	MC74VHC1GT08DFG	MC74VHC1GT08DFG	Not used	Not used
	IC4171	AND Logic IC	MC74VHC1GT08DFG	MC74VHC1GT08DFG	Not used	Not used
	IC4172	AND Logic IC	MC74VHC1GT08DFG	MC74VHC1GT08DFG	Not used	Not used
	Q602	Resistor Built-IN TR	Not used	Not used	Not used	RN4982S1
	Q603	Resistor Built-IN TR	Not used	Not used	Not used	RN4982S1
B	Q604	Resistor Built-IN TR	Not used	Not used	Not used	RN4982S1
	Q605	Resistor Built-IN TR	Not used	Not used	Not used	RN4982S1
	D9	Rectifier Diode	DA2J101	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)
	D12	Rectifier Diode	DA2J101	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)
	D13	Rectifier Diode	DA2J101	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)	1SS355VM (Switching Diode)
	D4171	Rectifier Diode	DA2J101	DA2J101	Not used	Not used
C	△ P301	Poly Switch	FSMD110-24R	FSMD110-24R	FSMD020-R	FSMD020-R
	CN2251	FFC/FPC Connector	Not used	Not used	CKS6710	CKS6710
	CN2252	FFC/FPC Connector	CKS6703	CKS6703	Not used	Not used
	CN4001	FFC/FPC Connector	Not used	Not used	CKS6645	CKS6645
	CN4002	FFC/FPC Connector	CKS6646	CKS6646	Not used	Not used
	CN4171	FFC/FPC Connector	CKS6634	CKS6634	Not used	Not used
	JA4131	Connector	CKS6495	CKS6495	Not used	Not used
D	R651		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS1001D
	R652		Not used	Not used	Not used	RS1/16SS6800D
	R676		Not used	Not used	Not used	RS1/16SS104J
	R677		RS1/16SS104J	RS1/16SS104J	RS1/16SS104J	Not used
	R678		RS1/16SS104J	RS1/16SS104J	Not used	Not used
	R679		Not used	Not used	RS1/16SS104J	RS1/16SS104J
	R706		Not used	Not used	Not used	RS1/16SS6800D
	R709		Not used	Not used	Not used	RS1/16SS8201D
	R710		Not used	Not used	Not used	RS1/16SS8201D
E	R711		RS1/16SS102J	RS1/16SS102J	RS1/16SS102J	RS1/16SS1001D
	R807		RS1/16SS473J	RS1/16SS473J	Not used	Not used
	R808		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
	R809		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
	R812		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
	R815		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
	R831		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
	R836		RS1/16SS473J	RS1/16SS473J	Not used	Not used
	R1523		Not used	Not used	RS1/16SS0R0J	RS1/16SS0R0J
F	R1524		Not used	Not used	RS1/16SS104J	RS1/16SS104J

Circuit Symbol and No.	Part Name	MVH-2300NEX/ XNUC	MVH-AV251BT/ XNUC	SPH-DA240BT/ XNUR	DMH-Z5150BT/ XNCS
R1527		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R1528		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R1535		Not used	Not used	RS1/16SS0R0J	RS1/16SS0R0J
R1536		Not used	Not used	RS1/16SS0R0J	RS1/16SS0R0J
R1537		Not used	Not used	RS1/16SS0R0J	RS1/16SS0R0J
R1541		Not used	Not used	RS1/16SS0R0J	RS1/16SS0R0J
R2251		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R2252		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R2503		RS1/16SS684J	Not used	Not used	Not used
R2504		RS1/16SS1802D	RS1/16SS2002D	RS1/16SS2002D	RS1/16SS2002D
R2509		Not used	RS1/16SS103J	RS1/16SS103J	RS1/16SS103J
R4142		RS1/16SS471J	RS1/16SS471J	Not used	Not used
R4143		RS1/16SS223J	RS1/16SS223J	Not used	Not used
R4144		RS1/16SS223J	RS1/16SS223J	Not used	Not used
R4145		RS1/16SS181J	RS1/16SS181J	Not used	Not used
R4146		RS1/16SS181J	RS1/16SS181J	Not used	Not used
R4147		RS1/10SR822J	RS1/10SR822J	Not used	Not used
R4148		RS1/10SR471J	RS1/10SR471J	Not used	Not used
R4149		RS1/16SS104J	RS1/16SS104J	Not used	Not used
R4151		RS1/16SS471J	RS1/16SS471J	Not used	Not used
R4152		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R4153		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R4172		RS1/16SS101J	RS1/16SS101J	Not used	Not used
R4174		RS1/16SS103J	RS1/16SS103J	Not used	Not used
R4176		RS1/16SS104J	RS1/16SS104J	Not used	Not used
R4177		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R4178		RS1/16SS102J	RS1/16SS102J	Not used	Not used
R4179		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
R4180		RS1/16SS0R0J	RS1/16SS0R0J	Not used	Not used
C1506		Not used	Not used	CKSSYB104K10	CKSSYB104K10
C1518		Not used	Not used	CKSRYB105K10	CKSRYB105K10
C1520		Not used	Not used	CKSRYB105K10	CKSRYB105K10
C1522		Not used	Not used	CKSRYB105K10	CKSRYB105K10
C1531		Not used	Not used	CKSSYB104K10	CKSSYB104K10
C2504		Not used	CKSSYX105K10	CKSSYX105K10	CKSSYX105K10
C4135		CKSSYB104K10	CKSSYB104K10	Not used	Not used
C4136		CKSSYB104K10	CKSSYB104K10	Not used	Not used
C4137		CKSRYX104K50	CKSRYX104K50	Not used	Not used
C4172		CKSSYB104K10	CKSSYB104K10	Not used	Not used
C4174		CKSSYB104K10	CKSSYB104K10	Not used	Not used
C9002		CKSRYB105K10	CKSRYB105K10	Not used	Not used
C9003		CKSRYB105K10	CKSRYB105K10	Not used	Not used
C9018		CKSRYB105K10	CKSRYB105K10	Not used	Not used
C9019		CKSRYB105K10	CKSRYB105K10	Not used	Not used

