


EXPLODED VIEW

Block No.M1MM



No.WA492

Parts with the exploded numbers larger than 700 are not supplied.

created date:2022-06-16

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
EXPLODED VIEW <M1MM>						
MAB1		CB-XJ1352M01N	MAIN PWB	XJ1-352M-01	1	M1
MAB1		CB-XJ1352E01N	MAIN PWB	XJ1-352E-01	1	E1
MAB1		CB-XJ1352K00N	MAIN PWB	XJ1-352K-00	1	K0
MAB1		CB-XJ1352K01N	MAIN PWB	XJ1-352K-01	1	K1
MAB1		CB-XJ1352E03N	MAIN PWB	XJ1-352E-03	1	E3
MAB1		CB-XJ1352K02N	MAIN PWB	XJ1-352K-02	1	K2
MAB1		CB-XJ1352E02N	MAIN PWB	XJ1-352E-02	1	E2
MAB1		CB-XJ1352M02N	MAIN PWB	XJ1-352M-02	1	M2
MAB1		CB-XJ1352A01N	MAIN PWB	XJ1-352A-01	1	A1
MAB1		CB-XJ1352H01N	MAIN PWB	XJ1-352H-01	1	H1
MAB1		CB-XJ1352K03N	MAIN PWB	XJ1-352K-03	1	K3
MAB1		CB-XJ1352X01N	MAIN PWB	XJ1-352X-01	1	X1
DC1		E3A-0324-00	DC CORD		1	M1,K0,K1,K2,M2,A1,H1,K3
DC2		E3A-0320-00	DC CORD		1	E1,E3,E2,X1
F901		FZB10BT-100	BLADE FUSE		1	
LCD1		B3H-0034-00	LCD		1	M1,E1,K0,K1
LCD1		B3H-0102-00	LCD		1	E3,K2,E2,M2,A1,H1
LCD1		B3H-0107-00	LCD		1	K3,X1
PA1		A6D-0162-0N	PANEL ASSY		1	M1
PA1		A6D-0162-0L	PANEL ASSY		1	E1
PA1		A6D-0162-0F	PANEL ASSY		1	K0
PA1		A6D-0162-0G	PANEL ASSY		1	K1
PA1		A6D-0162-0K	PANEL ASSY		1	E3
PA1		A6D-0162-0E	PANEL ASSY		1	K2
PA1		A6D-0162-0J	PANEL ASSY		1	E2
PA1		A6D-0162-0M	PANEL ASSY		1	M2,A1,H1
PA1		A6D-0162-0D	PANEL ASSY		1	K3
PA1		A6D-0162-0W	PANEL ASSY		1	X1
B		LV41200-004A	SPECIAL SCREW		3	
C		QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	2	M1,E1,K0,K1,E3,K2,E2,M2,A1,H1,X1,K3
C		QYSDST2606ZA	TAP SCREW	M2.6 x 6.0mm	5	
E		QYSDSF2008ZA	TAP SCREW	M2.0 x 8.0mm	3	
F		QYSDST2612ZA	TAP SCREW	M2.6 x 12.0mm	2	
G		QYSPSG3008ZA	TAP SCREW	M3.0 x 8.0mm	1	
H		QYSDSF2608ZA	TAP SCREW	M2.6 x 8.0mm	1	
J		QYSDST2608ZA	TAP SCREW	M2.6 x 8.0mm	1	
213		A2C-0063-02	SUB PANEL		1	
215		D1A-0023-00	LEVER		1	
216		G0A-0027-00	EXTEN.SPRING		1	
217		D1A-0022-00	LEVER		1	
221		E3A-0423-10	CORD W.CON.		1	K3
222		E3A-0442-10	CORD W.CON.		1	K3
260		K2K-0388-00	KNOB		1	
261		GE30999-013A	COMP. SPRING		1	
262		K2K-0101-02	KNOB		1	M1,E1,K0,K1
262		K2K-0165-00	KNOB BASE		1	E3,K2,E2,M2,A1,H1,K3,X1
263		GE40127-005A	KNOB SPRING		1	
264		E2K-0069-00	CONDUCT RUBBER		1	
266		A4G-0093-01	REAR COVER		1	
271		QNZ1117-001	RUBBER CONNE		1	M1,E1,K0,K1
271		E2K-0029-00	CONDUCT RUBBER		1	E3,K2,E2,M2,A1,H1,K3,X1
351		GE40531-001A	SCREW SET		1	M1,K2,M2,A1,H1,K3
353		QYSPSF2008ZA	TAP SCREW	M2.0 x 8.0mm	1	M1,K0,K1,K2,M2,A1,H1,K3
355		GE40646-001A	HOOK		2	
357		B0H-0013-06	ESCUTCHEON		1	M1,E1,E3,E2,M2,A1,H1
357		B0H-0014-04	ESCUTCHEON		1	K0,K1,K2
357		B0H-0013-07	ESCUTCHEON		1	K3,X1
358		GE20342-001A	MOUNTING SLEEVE		1	
359		GE40521-001A	CARRYING CASE		1	M1,M2,A1,H1
360		T9B-0073-00	MICROPHONE		1	
501		B5A-3850-00	INST.MANUAL		1	M1,M2
501		B5A-3879-00	INST.MANUAL		1	A1
501		B5A-4091-00	INST.MANUAL		1	H1
501		B5A-4090-00	INST.MANUAL		1	X1
702		-----	SWITCH PWB	NO SERVICE PART	1	M1
702		-----	SWITCH PWB	NO SERVICE PART	1	E1
702		-----	SWITCH PWB	NO SERVICE PART	1	K0,K1
702		-----	SWITCH PWB	NO SERVICE PART	1	E3,K3,X1
702		-----	SWITCH PWB	NO SERVICE PART	1	K2,E2,M2,A1,H1
711		-----	TOP COVER	NO SERVICE PART	1	
712		-----	BOTTOM PLATE	NO SERVICE PART	1	
718		-----	HEAT SINK	NO SERVICE PART	1	
719		-----	COOL SHEET	NO SERVICE PART	1	
720		-----	COOLING RUBBER	NO SERVICE PART	1	
751		-----	PANEL	NO SERVICE PART	1	M1,E1
751		-----	PANEL	NO SERVICE PART	1	K0,K1
751		-----	PANEL	NO SERVICE PART	1	E3,E2,M2,A1,H1
751		-----	PANEL	NO SERVICE PART	1	K2
751		-----	PANEL	NO SERVICE PART	1	K3,X1
752		-----	FRONT GLASS	NO SERVICE PART	1	M1
752		-----	FRONT GLASS	NO SERVICE PART	1	E1
752		-----	FRONT GLASS	NO SERVICE PART	1	K0
752		-----	FRONT GLASS	NO SERVICE PART	1	K1
752		-----	FRONT GLASS	NO SERVICE PART	1	E3
752		-----	FRONT GLASS	NO SERVICE PART	1	K2

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	752	-----	FRONT GLASS	NO SERVICE PART	1	E2
	752	-----	FRONT GLASS	NO SERVICE PART	1	M2,A1,H1
	752	-----	FRONT GLASS	NO SERVICE PART	1	K3
	752	-----	FRONT GLASS	NO SERVICE PART	1	X1
	753	-----	COVER	NO SERVICE PART	1	
	755	-----	KNOB ASSY	NO SERVICE PART	1	
	756	-----	PUSH KNOB	NO SERVICE PART	1	
	757	-----	PUSH KNOB	NO SERVICE PART	1	
	758	-----	LIGHTING BOARD	NO SERVICE PART	1	
	759	-----	TAP SCREW	NO SERVICE PART	1	
	765	-----	LIGHTING BOARD	NO SERVICE PART	1	
	767	-----	LCD CASE	NO SERVICE PART	1	M1,E1,K0,K1
	767	-----	LCD CASE	NO SERVICE PART	1	E3,K2,E2,M2,A1,H1,K3,X1
	768	-----	OPTI.DIFFUSER	NO SERVICE PART	1	M1,E1,K0,K1
	768	-----	OPTI.DIFFUSER	NO SERVICE PART	1	E3,K2,E2,M2,A1,H1
	768	-----	OPTI.DIFFUSER	NO SERVICE PART	1	K3,X1
	769	-----	LIGHTING BOARD	NO SERVICE PART	1	M1,E1,K0,K1
	769	-----	LIGHTING BOARD	NO SERVICE PART	1	E3,K2,E2,M2,A1,H1,K3,X1
	770	-----	REF.SHEET	NO SERVICE PART	1	M1,E1,K0,K1
	770	-----	REF.SHEET	NO SERVICE PART	1	E3,K2,E2,M2,A1,H1,K3,X1
	802	-----	SUB-INST.MANUAL	NO SERVICE PART	1	H1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
MAIN PWB ASSY (XJ1-352x-0x) <XJ1>						
	IC161	BD37069FV-M	ANALOG IC		1	
	IC164	NJM11100F1	ANALOG IC		1	M2,A1,H1
	IC165	NJW4190R-A	ANALOG IC		1	E2,K3,X1
	IC220	NJM4565V-ZB	ANALOG IC		1	
	IC301	JCV8034	ANALOG IC		1	
	IC411	MF1343S00177	MCU IC		1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	IC470	TC7SH08FUJC	MOS IC		1	K3
	IC481	SN65HVD3082ED	MOS IC		1	K3
	IC482	TC7SH08FUJC	MOS IC		1	K3
	IC540	MP9943AGQ	ANALOG IC		1	
	IC601	TEF6657AHN205	ANALOG IC		1	
	IC701	STA1080HOA3	MPU IC		1	
	IC702	TC7SH08FUJC	MOS IC		1	
	IC821	W3F-0635-00	ROM IC		1	M1,E1
	IC821	W3F-0636-00	ROM IC		1	K0,K1
	IC821	W3F-0637-00	ROM IC		1	E3,K2,E2,M2,A1,H1,K3,X1
	IC822	W25Q16JVSSIM	ROM IC		1	
	IC831	IC-PST8428U	MOS IC		1	
	IC841	IC-PST8428U	MOS IC		1	
	IC890	TPS25221DBV	MOS IC		1	
	IC901	BD49105RFS-M	ANALOG IC		1	
	IC1901	M12L1218A6TIS	DRAM IC		1	M1,E1
	IC1901	M12L2511A6TIT	DRAM IC		1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	Q220	LSCR523UBFS8	TRANSISTOR		1	
	Q250	2SD2114K/VW/	TRANSISTOR		1	
	Q260	2SD2114K/VW/	TRANSISTOR		1	M1,E1,K0,K1
	Q270	LTA014EEBFS8	DIGI TRANSISTOR		1	
	Q271	LSAR523UBFS8	TRANSISTOR		1	
	Q272	LTC024EEBFS8	DIGI TRANSISTOR		1	
	Q273	LTA014EEBFS8	DIGI TRANSISTOR		1	
	Q274	LTC024EEBFS8	DIGI TRANSISTOR		1	
	Q320	2SD2114K/VW/	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q330	2SD2114K/VW/	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q340	2SD2114K/VW/	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q350	2SD2114K/VW/	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q470	LTC014EEBFS8	DIGI TRANSISTOR		1	K3
	Q471	LTC043TEBFS8	DIGI TRANSISTOR		1	K3
	Q480	LSCR523UBFS8	TRANSISTOR		1	K3
	Q481	LSCR523UBFS8	TRANSISTOR		1	K3
	Q482	LSCR523UBFS8	TRANSISTOR		1	K3
	Q483	LSAR523UBFS8	TRANSISTOR		1	K3
	Q484	RQ5L015SP	FET		1	K3
	Q485	LTC043ZUBFS8	DIGI TRANSISTOR		1	K3
	Q486	LTC043ZUBFS8	DIGI TRANSISTOR		1	K3
	Q890	LTC043EUBFS8	DIGI TRANSISTOR		1	
	Q903	KRC407E-P	DIGI TRANSISTOR		1	
	Q904	RE1C002ZP	FET		1	
	Q920	LTA044EEBFS8	DIGI TRANSISTOR		1	
	D220	UDZV6.8B	ZENER DIODE		1	
	D221	UDZV6.8B	ZENER DIODE		1	
	D222	UDZV5.6B	ZENER DIODE		1	
	D271	BAW56-TP	DIODE ARRAY		1	
	D273	1SS355-HF	DIODE		1	
	D370	BAW56-TP	DIODE ARRAY		1	
	D390	SM5818PL	SCHOTTKY DIODE		1	
	D391	MBR0530	DIODE		1	
	D400	RB521SM-40	DIODE		1	
	D401	UDZV5.1B	ZENER DIODE		1	
	D480	UDZV6.2B	ZENER DIODE		1	K3
	D481	UDZV6.2B	ZENER DIODE		1	K3
	D482	UDZV5.1B	ZENER DIODE		1	K3
	D540	SMD24PL	SCHOTTKY DIODE		1	
	D902	SK34A-L	SCHOTTKY DIODE		1	
	D903	SK34A-L	SCHOTTKY DIODE		1	
	D906	SK34A-L	SCHOTTKY DIODE		1	
	D907	SK34A-L	SCHOTTKY DIODE		1	
	D991	GN3XB	DIODE		1	
	C101	CK73JXR1H332K	C CAPACITOR	3300pF 50V K	1	
	C102	CK73JXR1H332K	C CAPACITOR	3300pF 50V K	1	
	C103	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C104	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C105	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C106	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C161	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C162	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C163	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C164	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C165	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C166	CE32BJ1V4R7M	E CAPACITOR	4.7uF 35V M	1	
	C167	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C168	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C169	CE32BY1C470M	E CAPACITOR	47uF 16V M	1	
	C170	CE32CL1C100M	E CAPACITOR	10uF 16V M	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1
Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local	
	C171	CE32BM1E470M	E CAPACITOR	47uF 25V M	1	E2,K3,X1	
	C171	CE32CL1E330M	E CAPACITOR	33uF 25V M	1	M2,A1,H1	
	C181	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K3,X1	
	C183	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E2,K3,X1	
	C187	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	E2,K3,X1	
	C188	CK73GXR1E105K	C CAPACITOR	1uF 25V K	1	E2,K3,X1	
	C189	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	M2,A1,H1	
	C190	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	M2,A1,H1	
	C191	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	M2,A1,H1	
	C192	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	M2,A1,H1	
	C193	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C222	CK73JXR1C333K	C CAPACITOR	0.033uF 16V K	1		
	C223	CK73JXR1C333K	C CAPACITOR	0.033uF 16V K	1		
	C224	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C225	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C226	CC73JCH1H220J	C CAPACITOR	22pF 50V J	1		
	C227	CK73JXR1H151K	C CAPACITOR	150pF 50V K	1		
	C228	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C229	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C230	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C231	CK73JXR1H151K	C CAPACITOR	150pF 50V K	1		
	C234	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C235	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C236	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1		
	C238	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C252	CK730DK1E106K	C CAPACITOR	10uF 25V K	1		
	C262	CK730DK1E106K	C CAPACITOR	10uF 25V K	1	M1,E1,K0,K1	
	C273	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C304	CE32CL1E330M	E CAPACITOR	33uF 25V M	1		
	C311	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1		
	C312	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C313	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C316	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C317	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C318	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C319	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C322	CK730DK1E106K	C CAPACITOR	10uF 25V K	1	E3,K2,E2,M2,A1,H1,K3,X1	
	C332	CK730DK1E106K	C CAPACITOR	10uF 25V K	1	E3,K2,E2,M2,A1,H1,K3,X1	
	C333	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C334	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C335	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C336	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1		
	C342	CK730DK1E106K	C CAPACITOR	10uF 25V K	1	E3,K2,E2,M2,A1,H1,K3,X1	
	C352	CK730DK1E106K	C CAPACITOR	10uF 25V K	1	E3,K2,E2,M2,A1,H1,K3,X1	
	C362	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C370	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1		
	C391	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1		
	C410	CK73JXR0J224K	C CAPACITOR	0.22uF 6.3V K	1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1	
	C470	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C472	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	K3	
	C473	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	K3	
	C474	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	K3	
	C475	CK73GXR1C225K	C CAPACITOR	2.2uF 16V K	1	K3	
	C480	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K3	
	C481	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	K3	
	C482	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	K3	
	C483	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	K3	
	C484	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	K3	
	C485	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K3	
	C486	CK73JXR1H682K	C CAPACITOR	6800pF 50V K	1	K3	
	C540	CE32CC1A151M	E CAPACITOR	150uF 10V M	1		
	C541	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1		
	C543	CK73JXR1E223K	C CAPACITOR	0.022uF 25V K	1		
	C544	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C545	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1		
	C547	CK73JXR0J474K	C CAPACITOR	0.47uF 6.3V K	1		
	C548	CK73JXR0J474K	C CAPACITOR	0.47uF 6.3V K	1		
	C549	CK73JXR0J474K	C CAPACITOR	0.47uF 6.3V K	1		
	C550	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1		
	C601	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1		
	C602	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1		
	C603	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1		
	C604	CK73JXR1H152K	C CAPACITOR	1500pF 50V K	1		
	C605	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1		
	C606	CC73JCH1H090D	C CAPACITOR	9pF 50V D	1		
	C607	CC73JCH1H010C	C CAPACITOR	1pF 50V C	1		
	C608	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1		
	C609	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1		
	C610	CC73JCH1H120J	C CAPACITOR	12pF 50V J	1		
	C611	CC73JCH1H010C	C CAPACITOR	1pF 50V C	1		
	C612	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C614	CC73JCH1H220J	C CAPACITOR	22pF 50V J	1		
	C615	CC73JCH1H330J	C CAPACITOR	33pF 50V J	1		
	C616	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1		
	C617	CK73JXR0J224K	C CAPACITOR	0.22uF 6.3V K	1		
	C618	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C619	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1		

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1
Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local	
	C620	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C622	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C623	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C625	CK73JXR1H221K	C CAPACITOR	220pF 50V K	1		
	C680	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C702	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C703	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C704	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1		
	C705	CC73JCH1H180J	C CAPACITOR	18pF 50V J	1		
	C706	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C707	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C708	CK73JXR1C473K	C CAPACITOR	0.047uF 16V K	1		
	C709	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C710	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1		
	C711	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C713	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C714	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C715	CK73JXR1C472K	C CAPACITOR	4700pF 16V K	1		
	C716	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C719	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C720	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1		
	C721	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C722	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1		
	C723	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1		
	C724	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C725	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C726	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C727	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C728	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C729	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1		
	C730	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C731	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1		
	C733	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1		
	C735	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1		
	C736	CC73JCH1H080D	C CAPACITOR	8pF 50V D	1		
	C737	CC73JCH1H080D	C CAPACITOR	8pF 50V D	1		
	C738	CK73JXR1A472K	C CAPACITOR	4700pF 10V K	1		
	C740	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C741	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1		
	C742	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C744	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1		
	C745	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C746	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1		
	C747	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1		
	C749	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C750	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1		
	C751	CE32B20J101M	E CAPACITOR	100uF 6.3V M	1		
	C754	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C756	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C820	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C821	CK73JXR0J224K	C CAPACITOR	0.22uF 6.3V K	1		
	C822	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C824	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1		
	C825	CK73JXR0J224K	C CAPACITOR	0.22uF 6.3V K	1		
	C830	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C831	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C832	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1		
	C841	CK73HXR1A334K	C CAPACITOR	0.33uF 10V K	1		
	C842	CK73JXR0J224K	C CAPACITOR	0.22uF 6.3V K	1		
	C843	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C890	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1		
	C893	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1		
	C894	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1		
	C895	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C902	CC73JCH1E391J	C CAPACITOR	390pF 25V J	1		
	C903	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C904	CC73JCH1E271J	C CAPACITOR	270pF 25V J	1		
	C905	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C906	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C907	CE32CC1A151M	E CAPACITOR	150uF 10V M	1		
	C911	CK73GXR1E105K	C CAPACITOR	1uF 25V K	1		
	C912	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1		
	C913	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1		
	C914	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C915	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C916	CE32BY1C221M	E CAPACITOR	220uF 16V M	1		
	C917	CK73GXR1E105K	C CAPACITOR	1uF 25V K	1		
	C919	CD04ET1C222M1	E CAPACITOR	2200uF 16V M	1		
	C932	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C946	CK73GXR1E105K	C CAPACITOR	1uF 25V K	1		
	C947	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C950	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1		
	C952	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1		
	C954	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1		
	C990	CD04ET1C222M1	E CAPACITOR	2200uF 16V M	1		
	C1001	CC73JCH1H221J	C CAPACITOR	220pF 50V J	1		
	C1010	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C1011	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C1012	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		
	C1013	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1		

K0,K1,E3,K2,E2,M2,A1
,H1,K3,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C1014	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C1015	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C1016	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C1017	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C1020	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C1021	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C1301	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C1302	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C1303	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C1304	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C1305	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C1901	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1902	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1903	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1904	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1905	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C1906	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C1907	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C1908	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1909	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C1910	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C2010	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C2040	CC73JCH1H100D	C CAPACITOR	10pF 50V D	1	
	C2041	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C2042	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C2044	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C2060	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C2085	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K3
	C9000	CK73JXR1C224K	C CAPACITOR	0.22uF 16V K	1	
	C9001	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9002	CK73JXR1A103K	C CAPACITOR	0.01uF 10V K	1	
	C9003	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C9004	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9006	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C9007	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9008	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9014	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9018	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9019	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9022	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9023	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9024	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C9025	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9027	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9033	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C9034	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9035	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C9037	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C9038	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C9039	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C9040	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	
	C9041	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9045	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9046	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9049	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C9050	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C9051	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C9055	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C9056	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C9057	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	
	C9058	CK73JXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C9059	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9060	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9061	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9062	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C9064	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C9065	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9066	CK73JXR1C472K	C CAPACITOR	4700pF 16V K	1	
	C9068	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C9070	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9076	CC73JCH1H150J	C CAPACITOR	15pF 50V J	1	
	C9077	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9078	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C9082	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C9083	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C9086	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C9087	CK73JXR1C473K	C CAPACITOR	0.047uF 16V K	1	
	C9090	CC73JCH1E471J	C CAPACITOR	470pF 25V J	1	
	C9094	CK73JXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	
	C9095	CK73JXR1H103K	C CAPACITOR	0.01uF 50V K	1	K3
	C9117	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C9118	CC73JCH1H101J	C CAPACITOR	100pF 50V J	1	
	C9119	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	
	C9122	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9206	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9207	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9208	CK73JXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C9210	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	M1,E1,E3,E2,M2
	C9211	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	M1,E1
	C9212	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	E3,E2,M2
	C9213	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	E3,E2,M2
	C9214	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	E3,E2,M2

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1
Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local	
	C9215	CK73JXR1H222K	C CAPACITOR	2200pF 50V K	1	E3,E2,M2	
	C9217	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1		
	C9218	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1		
	C9219	CC73JCH1H050C	C CAPACITOR	5pF 50V C	1		
	VA720	CK73HXR1A105K	C CAPACITOR 2		1		
	L700	RK73HB1J000J	MG RESISTOR		1		
	L706	RK73HB1J000J	MG RESISTOR		1	K3	
	L707	RK73HB1J000J	MG RESISTOR		1	K3	
	L708	RK73HB1J000J	MG RESISTOR		1		
	L709	RK73HB1J000J	MG RESISTOR		1		
	L811	RK73HB1J000J	MG RESISTOR		1		
	L822	RK73HB1J000J	MG RESISTOR		1		
	L824	RK73HB1J220J	MG RESISTOR		1		
	L825	RK73HB1J220J	MG RESISTOR		1		
	L826	RK73HB1J220J	MG RESISTOR		1		
	L827	RK73HB1J220J	MG RESISTOR		1		
	L828	RK73HB1J220J	MG RESISTOR		1		
	L829	RK73HB1J000J	MG RESISTOR		1		
	L2000	RK73HB1J101J	MG RESISTOR		1		
	L2001	RK73HB1J101J	MG RESISTOR		1		
	L2003	RK73HB1J000J	MG RESISTOR		1	K3	
	L2004	RK73HB1J000J	MG RESISTOR		1	K3	
	L9002	RK73GB2A000J	MG RESISTOR		1		
	R100	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1		
	R101	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R103	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1		
	R104	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1		
	R112	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R113	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R114	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R115	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K3	
	R116	RK73GB2A4R7J	MG RESISTOR	4.7Ω 1/10W J	1	K3	
	R117	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K3	
	R145	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R146	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R147	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R148	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R149	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R150	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		
	R160	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	M2,A1,H1	
	R161	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E2,M2,A1,H1,K3,X1	
	R162	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R173	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R175	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	M1,E1,K0,K1,E3,K2,E2,K3,X1	
	R176	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E2,K3,X1	
	R177	RK73HB1J562J	MG RESISTOR	5.6kΩ 1/16W J	1	E2,K3,X1	
	R178	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	E2,K3,X1	
	R179	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	E2,K3,X1	
	R180	RK73HH1J153D	MG RESISTOR	15kΩ 1/16W D	1	E2,K3,X1	
	R181	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E2,K3,X1	
	R182	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	M2,A1,H1	
	R183	RK73HH1J132D	MG RESISTOR	1.3kΩ 1/16W D	1	M2,A1,H1	
	R188	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	M1,E1,K0,K1,E3,K2,M2,A1,H1	
	R220	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R221	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R222	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R223	RK73HB1J822J	MG RESISTOR	8.2kΩ 1/16W J	1		
	R224	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R225	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1		
	R226	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1		
	R227	RK73HB1J124J	MG RESISTOR	120kΩ 1/16W J	1		
	R229	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1		
	R230	RK73HB1J124J	MG RESISTOR	120kΩ 1/16W J	1		
	R231	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R232	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R233	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1		
	R234	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1		
	R236	RK73HB1J512J	MG RESISTOR	5.1kΩ 1/16W J	1		
	R237	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1		
	R238	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R250	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1		
	R251	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1		
	R252	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1		
	R253	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1	
	R254	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1		
	R260	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	M1,E1,K0,K1	
	R261	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	M1,E1,K0,K1	
	R262	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	M1,E1,K0,K1	
	R264	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	M1,E1,K0,K1	
	R270	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1		
	R271	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1		
	R272	RK73HB1J303J	MG RESISTOR	30kΩ 1/16W J	1		
	R273	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1		
	R302	RK73HB1J432J	MG RESISTOR	4.3kΩ 1/16W J	1		
	R303	RK73HB1J160J	MG RESISTOR	16Ω 1/16W J	1		
	R304	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1		
	R305	RK73HB1J1R0J	MG RESISTOR	1.0Ω 1/16W J	1		
	R316	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1		

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R317	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R318	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R319	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R320	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R321	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R322	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R323	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R330	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R331	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R332	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R333	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R340	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R341	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R342	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R343	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R350	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R351	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R352	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R353	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3,X1
	R370	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	
	R371	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R372	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R390	RK73EB2E472J	MG RESISTOR	4.7kΩ 1/4W J	1	
	R400	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R410	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	R411	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	R413	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	R414	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	R471	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K3
	R472	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K3
	R473	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	K3
	R474	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	K3
	R475	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K3
	R476	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	K3
	R477	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	K3
	R480	RK73HB1J334J	MG RESISTOR	330kΩ 1/16W J	1	K3
	R481	RK73EB2E3R3J	MG RESISTOR	3.3Ω 1/4W J	1	K3
	R482	RK73EB2E3R3J	MG RESISTOR	3.3Ω 1/4W J	1	K3
	R483	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	K3
	R484	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K3
	R485	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	K3
	R486	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K3
	R487	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	K3
	R488	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	K3
	R489	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	K3
	R490	RK73HB1J183J	MG RESISTOR	18kΩ 1/16W J	1	K3
	R491	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K3
	R492	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	K3
	R493	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K3
	R494	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	K3
	R495	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K3
	R496	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K3
	R498	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	K3
	R541	RK73HB1J512J	MG RESISTOR	5.1kΩ 1/16W J	1	
	R542	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R543	RK73HB1J200J	MG RESISTOR	20Ω 1/16W J	1	
	R544	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	
	R545	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	
	R546	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R548	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R601	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R602	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R603	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R604	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R605	RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
	R611	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R682	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R683	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R684	RK73HB1J392J	MG RESISTOR	3.9kΩ 1/16W J	1	
	R685	RK73HB1J392J	MG RESISTOR	3.9kΩ 1/16W J	1	
	R688	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R690	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R691	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R702	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R703	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R704	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R705	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R706	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	
	R709	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R710	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R711	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R712	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R713	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R714	RK73HB1J274J	MG RESISTOR	270kΩ 1/16W J	1	
	R718	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R720	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	K3
	R730	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R738	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R739	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R740	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R741	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R742	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R743	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R746	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R755	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R756	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R760	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R761	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R766	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R768	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	M1,M2,A1,H1,X1
	R768	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	E1,E3,E2
	R769	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	M1,M2,A1,H1,X1
	R769	RK73HB1J822J	MG RESISTOR	8.2kΩ 1/16W J	1	E1,E3,E2
	R769	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0,K1,K2,K3
	R770	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	K1,E3,A1,K3
	R770	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	H1
	R770	RK73HB1J273J	MG RESISTOR	27kΩ 1/16W J	1	X1
	R771	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	M1,E1,K0,K2,E2,M2
	R771	RK73HB1J822J	MG RESISTOR	8.2kΩ 1/16W J	1	K1,E3,A1,K3
	R771	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	H1
	R771	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	X1
	R772	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R777	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R778	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R782	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R785	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R788	RK73HH1J823D	MG RESISTOR	82kΩ 1/16W D	1	
	R789	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R796	RK73HH1J302D	MG RESISTOR	3kΩ 1/16W D	1	
	R797	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R798	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R799	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R800	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R801	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R802	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,K0,K1,E3,K3,X1
	R803	RK73HB1J225J	MG RESISTOR	2.2MΩ 1/16W J	1	M1,K2,E2,M2,A1,H1
	R805	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R806	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R808	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R809	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R820	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R823	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R824	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R827	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R828	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R829	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R830	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R831	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R844	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R845	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R846	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R848	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R861	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	
	R862	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R870	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R889	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R890	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R891	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R892	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R893	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R903	RK73HH1J394D	MG RESISTOR	390kΩ 1/16W D	1	M1,E1,K0,K1,E3,K2
	R903	RK73HH1J334D	MG RESISTOR	330kΩ 1/16W D	1	E2,K3,X1
	R903	RK73HH1J474D	MG RESISTOR	470kΩ 1/16W D	1	M2,A1,H1
	R904	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	M1,E1,K0,K1,E3,K2
	R904	RK73HH1J473D	MG RESISTOR	47kΩ 1/16W D	1	E2,K3,X1
	R904	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	M2,A1,H1
	R905	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R908	RK73HH1J154D	MG RESISTOR	150kΩ 1/16W D	1	
	R909	RK73HH1J473D	MG RESISTOR	47kΩ 1/16W D	1	
	R910	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R911	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	
	R912	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R913	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R917	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1
Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local	
	R923	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R924	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R925	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R926	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R927	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R928	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R929	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R933	RK73HH1J684D	MG RESISTOR	680kΩ 1/16W D	1		
	R934	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1		
	R939	RK73HH1J433D	MG RESISTOR	43kΩ 1/16W D	1		
	R940	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1		
	R946	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1		
	R950	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R951	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1		
	R952	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R954	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1		
	R955	RK73EB2E184J	MG RESISTOR	180kΩ 1/4W J	1		
	R980	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1		
	R981	RK73EB2E682J	MG RESISTOR	6.8kΩ 1/4W J	1		
	R982	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1		
	R984	RK73EB2E473J	MG RESISTOR	47kΩ 1/4W J	1		
	R1070	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1		
	R1300	RK73HB1J562J	MG RESISTOR	5.6kΩ 1/16W J	1		
	R1301	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R1302	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R1303	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R1900	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1901	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1902	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1903	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1904	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1905	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1906	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1907	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1908	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1909	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1910	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1911	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1912	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1913	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1914	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1915	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1920	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R1921	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1		
	R1932	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R1964	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1965	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1966	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1967	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1968	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1969	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1970	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1971	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1977	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1978	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1979	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1980	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1981	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1982	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1983	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1984	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1985	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1986	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1987	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1988	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1989	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R1992	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1		
	R2003	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2004	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2010	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R2011	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R2012	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2013	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R2016	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R2017	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R2018	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R2019	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2021	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2023	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1		
	R2030	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	M1,E1,K0,K1,E3,K2,E2,M2,A1,H1,X1	
	R2033	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1		
	R2034	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1		
	R9011	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1		
	R9012	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1		
	R9015	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R9021	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1		
	R9023	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1		
	R9201	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1		
	L540	LK73Z0CA4R7M	M.CHIP INDUCTOR		1	M1,E1,K0,K1,E3,K2,E2,M2,A1,K3,H1,X1	
	L540	LK73Z0CQ4R7M	M.CHIP INDUCTOR		1		

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	L541	LR7920JM100M	CHIP INDUCTOR		1	
	L600	LR7320AD4R7M	CHIP INDUCTOR		1	
	L601	LK73G0BE4R7K	M.CHIP INDUCTOR		1	
	L602	LK73G0BER47K	M.CHIP INDUCTOR		1	
	L603	LK73G0BER10K	M.CHIP INDUCTOR		1	
	L604	LK73G0BE1R0K	M.CHIP INDUCTOR		1	
	L605	LK73G0BER22K	M.CHIP INDUCTOR		1	
	L606	LK73G0BER12K	M.CHIP INDUCTOR		1	
	L607	LK73G0BER15K	M.CHIP INDUCTOR		1	
	L701	LB73H0FS-006	CHIP FERRITE		1	
	L790	RK73HB1J100J	MG RESISTOR		1	M1,E1
	L790	LK73H0BX2N2B	M.CHIP INDUCTOR		1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	L792	RK73HB1J100J	MG RESISTOR		1	M1,E1
	L792	LK73H0BX2N2B	M.CHIP INDUCTOR		1	K0,K1,E3,K2,E2,M2,A1,H1,K3,X1
	L821	LB73G0ED-002	CHIP FERRITE		1	
	L830	LB73G0ED-002	CHIP FERRITE		1	
	L831	LB73H0FS-006	CHIP FERRITE		1	
	L901	LR7920JM330M	CHIP INDUCTOR		1	
	L903	LK7320CQ4R7M	M.CHIP INDUCTOR		1	
	L990	L3D-0043-00	CHOKE COIL		1	
	L2002	RK73HB1J151J	MG RESISTOR		1	K3
	L2005	LR7320AD4R7M	CHIP INDUCTOR		1	
	L2006	RK73HH1J470D	MG RESISTOR		1	
	L9000	LR7320AD1R0M	CHIP INDUCTOR		1	
	L9001	LB73G0ED-002	CHIP FERRITE		1	
	A1303	W0C-0414-00	CIRCUIT MODULE		1	
	CN220	EA710AP-2002A	W TO B CONNE		1	K3
	CN481	EA710AP-2006A	W TO B CONNE		1	K3
	CN701	E5J-0216-00	R.RECEPTACLE		1	
	CN990	E5J-0139-00	R.RECEPTACLE		1	
△	F321	F53-0513-08	PATTERN FUSE		1	
△	F322	F53-0513-08	PATTERN FUSE		1	
△	F540	FZA10BH-2R5	FUSE (CC)		1	
	J220	E1B-0013-00	3.5D PHONE JACK		1	M1,E1,K0,K1,E3,K2,E2,M2,A1,H1,X1
	J321	E6D-0014-10	PIN JACK		1	M1,E1,K0,K1
	J321	E6D-0016-10	PIN JACK		1	E3,K2,E2,M2,A1,H1,K3,X1
	J470	E5G-0029-00	CYL.RECEPTACLE		1	K3
	J601	E6J-0017-00	JACK OTHERS		1	
	S830	S7A-0031-00	TACTILE PUSH SW		1	
	VA471	F0K-0420-00	SURGE ABSORBER		1	K3
	VA472	F0K-0420-00	SURGE ABSORBER		1	K3
	VA473	F0K-0420-00	SURGE ABSORBER		1	K3
	VA474	F0K-0420-00	SURGE ABSORBER		1	K3
	VA475	F0K-0420-00	SURGE ABSORBER		1	K3
	VA476	F0K-0420-00	SURGE ABSORBER		1	K3
	VA480	F0K-0420-00	SURGE ABSORBER		1	K3
	VA601	F0K-0265-00	SURGE ABSORBER		1	
	VA701	F0K-0420-00	SURGE ABSORBER		1	
	VA702	F0K-0420-00	SURGE ABSORBER		1	
	VA703	F0K-0420-00	SURGE ABSORBER		1	
	VA704	F0K-0420-00	SURGE ABSORBER		1	
	VA705	F0K-0420-00	SURGE ABSORBER		1	
	VA706	F0K-0420-00	SURGE ABSORBER		1	
	VA707	F0K-0420-00	SURGE ABSORBER		1	
	VA709	F0K-0420-00	SURGE ABSORBER		1	
	VA710	F0K-0420-00	SURGE ABSORBER		1	
	VA711	F0K-0420-00	SURGE ABSORBER		1	
	VA714	F0K-0420-00	SURGE ABSORBER		1	
	VA716	F0K-0420-00	SURGE ABSORBER		1	
	VA717	F0K-0420-00	SURGE ABSORBER		1	
	VA718	F0K-0420-00	SURGE ABSORBER		1	
	VA901	SDV1005E18//0	VARIISTOR		1	
	X600	L7J-0014-00	QUARTZ CRYSTAL		1	
	X701	L7J-0138-00	QUARTZ CRYSTAL		1	
	X702	L7J-0123-00	QUARTZ CRYSTAL		1	
SWITCH PWB ASSY (XJ6-161x-0x) <XJ6>						
	IC1	BU97520AKV-M	MOS IC		1	M1,E1,K0,K1
	IC90	SIRD630B6T	IR DETECT UNIT		1	M1
	Q1	LSCR523UBFS8	TRANSISTOR		1	M1,E1,K0,K1
	Q51	LSCR523EBFS8	TRANSISTOR		1	M1,E1,K0,K1
	Q52	LSCR523UBFS8	TRANSISTOR		1	M1,E1,K0,K1
	Q90	LTA014EEBFS8	DIGI TRANSISTOR		1	M1
	Q91	LTC014EEBFS8	DIGI TRANSISTOR		1	M1
	D1	UDZV5.6B	ZENER DIODE		1	M1,E1,K0,K1
	D2	SM5818PL	SCHOTTKY DIODE		1	M1,E1,K0,K1
	D20	QSMH-C199	LED		1	M1,E1,K0,K1
	D21	LRT67F-U1AA11	LED		1	M1,E1
	D21	QSMTUBB5ZT3Y2	LED		1	K0,K1
	D22	LRT67F-U1AA11	LED		1	M1,E1
	D22	QSMTUBB5ZT3Y2	LED		1	K0,K1
	D23	LRT67F-U1AA11	LED		1	M1,E1
	D23	QSMTUBB5ZT3Y2	LED		1	K0,K1
	D25	QSMH-C199	LED		1	M1,E1
	D25	QSMR-C13SBCMN	LED		1	K0,K1
	D26	QSMH-C199	LED		1	M1,E1
	D26	QSMR-C13SBCMN	LED		1	K0,K1
	D46	NHSW157B	LED		1	M1,E1,K0,K1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D48	NHSW157B	LED		1	M1,E1,K0,K1
	C1	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	M1,E1,K0,K1
	C4	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	M1,E1,K0,K1
	C5	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	M1,E1,K0,K1
	C6	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	M1,E1,K0,K1
	C7	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	M1,E1,K0,K1
	C60	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	M1,E1,K0,K1
	C61	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	M1,E1,K0,K1
	C80	CC73JCH1H270J	C CAPACITOR	27pF 50V J	1	M1,E1
	C80	CC73JCH1H070D	C CAPACITOR	7pF 50V D	1	K0,K1
	C81	CC73JCH1H270J	C CAPACITOR	27pF 50V J	1	M1,E1
	C81	CC73JCH1H070D	C CAPACITOR	7pF 50V D	1	K0,K1
	C82	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	M1,E1,K0,K1
	C83	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	M1,E1,K0,K1
	C84	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	M1,E1,K0,K1
	C85	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	M1,E1,K0,K1
	C86	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	M1,E1,K0,K1
	C91	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	M1
	R1	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R3	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	M1,E1,K0,K1
	R5	RK73EB2E331J	MG RESISTOR	330Ω 1/4W J	1	M1,E1,K0,K1
	R6	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	M1,E1,K0,K1
	R21	RK73GB2A152J	MG RESISTOR	1.5kΩ 1/10W J	1	M1,E1,K0,K1
	R22	RK73EB2E821J	MG RESISTOR	820Ω 1/4W J	1	M1,E1
	R22	RK73EB2E681J	MG RESISTOR	680Ω 1/4W J	1	K0,K1
	R23	RK73EB2E471J	MG RESISTOR	470Ω 1/4W J	1	M1,E1
	R23	RK73EB2E391J	MG RESISTOR	390Ω 1/4W J	1	K0,K1
	R24	RK73FB2B122J	MG RESISTOR	1.2kΩ 1/8W J	1	M1,E1,K0,K1
	R25	RK73FB2B102J	MG RESISTOR	1kΩ 1/8W J	1	M1,E1
	R25	RK73FB2B911J	MG RESISTOR	910Ω 1/8W J	1	K0,K1
	R27	RK73FB2B331J	MG RESISTOR	330Ω 1/8W J	1	M1,E1,K0,K1
	R40	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R41	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R42	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R43	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R44	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R45	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R46	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R47	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R48	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R49	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R50	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R51	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R52	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	M1,E1,K0,K1
	R53	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	M1,E1,K0,K1
	R60	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R61	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	M1,E1,K0,K1
	R62	RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	M1,E1,K0,K1
	R80	RK73EB2E221J	MG RESISTOR	220Ω 1/4W J	1	M1,E1,K0,K1
	CN2	E5K-0007-00	R.PLUG		1	M1,E1,K0,K1
	FL80	L3D-0063-00	CHOKE COIL		1	M1,E1
	FL80	L7K-0038-00	FILTER		1	K0,K1
	J60	E1B-0037-00	3.5D PHONE JACK		1	M1,E1,K0,K1
	J80	E5J-0069-00	USB TERMINAL		1	M1,E1,K0,K1
	S20	T9K-0007-00	ROTARY ENCODER		1	M1,E1,K0,K1
	VA80	F0K-0420-00	SURGE ABSORBER		1	M1,E1
	VA81	F0K-0420-00	SURGE ABSORBER		1	M1,E1
	VA82	F0K-0420-00	SURGE ABSORBER		1	M1,E1,K0,K1
SWITCH PWB ASSY (XJ6-162x-02) <XJ6>						
	IC1	BU97550KV-M	MOS IC		1	E3,K2,E2,M2,A1,H1,K3,X1
	IC3	AS431AN-G1	ANALOG IC		1	E3,K2,E2,M2,A1,H1,K3,X1
	IC90	SIRD630B6T	IR DETECT UNIT		1	K2,E2,M2,A1
	IC90	LRT15CTM4	IR DETECT UNIT		1	H1
	Q50	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q51	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q52	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q53	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q54	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q55	LSCR523EBFS8	TRANSISTOR		1	E3,K2,E2,M2,A1,H1,K3,X1
	Q90	LTA014EEBFS8	DIGI TRANSISTOR		1	K2,E2,M2,A1,H1
	Q91	LTC014EEBFS8	DIGI TRANSISTOR		1	K2,E2,M2,A1,H1
	D2	SM5818PL	SCHOTTKY DIODE		1	E3,K2,E2,M2,A1,H1,K3,X1
	D3	SM5818PL	SCHOTTKY DIODE		1	E3,K2,E2,M2,A1,H1,K3,X1
	D20	QSMH-C199	LED		1	E3,K2,E2,M2,A1,H1,K3,X1
	D21	ASMTYTD9ZDA02	LED		1	E3,K2,E2,M2,A1,H1,K3,X1
	D22	ASMTYTD9ZDA02	LED		1	E3,K2,E2,M2,A1,H1,K3,X1
	D23	ASMTYTD9ZDA02	LED		1	E3,K2,E2,M2,A1,H1,K3,X1
	D24	ASMTYTD9ZDA02	LED		1	E3,K2,E2,M2,A1,H1,K3,X1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D49	ASMTYTD9ZDA02	LED		1	,X1 E3,K2,E2,M2,A1,H1,K3 ,X1
	C1	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C5	CK73GXR1A475K	C CAPACITOR	4.7uF 10V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C6	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C7	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C60	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C61	CK73JXR1H102K	C CAPACITOR	1000pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C80	CC73JCH1H090D	C CAPACITOR	9pF 50V D	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C81	CC73JCH1H090D	C CAPACITOR	9pF 50V D	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C82	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C83	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C84	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C85	CK73JXR1H471K	C CAPACITOR	470pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C86	CK73JXR1H472K	C CAPACITOR	4700pF 50V K	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	C91	CK73HXR1A105K	C CAPACITOR	1uF 10V K	1	K2,E2,M2,A1,H1
	R1	RK73HH1J473D	MG RESISTOR	47kΩ 1/16W D	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R2	RK73HH1J473D	MG RESISTOR	47kΩ 1/16W D	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R3	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R4	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R6	RK73EB2E151J	MG RESISTOR	150Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R8	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R10	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R14	RK73HB1J124J	MG RESISTOR	120kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R21	RK73EB2E391J	MG RESISTOR	390Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R22	RK73EB2E471J	MG RESISTOR	470Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R23	RK73EB2E331J	MG RESISTOR	330Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R25	RK73FB2B561J	MG RESISTOR	560Ω 1/8W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R26	RK73FB2B681J	MG RESISTOR	680Ω 1/8W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R27	RK73FB2B471J	MG RESISTOR	470Ω 1/8W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R33	RK73EB2E511J	MG RESISTOR	510Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R34	RK73EB2E821J	MG RESISTOR	820Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R35	RK73EB2E561J	MG RESISTOR	560Ω 1/4W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R40	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R41	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R42	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R43	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R44	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R45	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R46	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R47	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R48	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R49	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R50	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R51	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R52	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R53	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3 ,X1
	R54	RK73HB1J682J	MG RESISTOR	6.8kΩ 1/16W J	1	E3,K2,E2,M2,A1,H1,K3

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
KMM-BT208	M1	KMM-BT209	E1	KMM-BT232U	K0	KMM-BT270U	K1
KMM-BT309	E3	KMM-BT332	K2	KMM-BT358	E2	KMM-BT408	M2
KMM-BT408	A1	KMM-BT408	H1	KMR-M332BT	K3	KMR-M408BT	X1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R55	RK73HB1J682J	MG RESISTOR	6.8k Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R56	RK73HB1J682J	MG RESISTOR	6.8k Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R57	RK73HB1J682J	MG RESISTOR	6.8k Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R60	RK73HB1J101J	MG RESISTOR	100 Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R61	RK73HB1J101J	MG RESISTOR	100 Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R62	RK73HB1J4R7J	MG RESISTOR	4.7 Ω 1/16W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	R80	RK73EB2E221J	MG RESISTOR	220 Ω 1/4W J	1	,X1 E3,K2,E2,M2,A1,H1,K3
	CN2	E5K-0007-00	R.PLUG		1	,X1 E3,K2,E2,M2,A1,H1,K3
	FL80	L7K-0038-00	FILTER		1	,X1 E3,K2,E2,M2,A1,H1,K3
	J60	E1B-0037-00	3.5D PHONE JACK		1	,X1 E3,K2,E2,M2,A1,H1,K3
	J80	E5J-0069-00	USB TERMINAL		1	,X1 E3,K2,E2,M2,A1,H1,K3
	S20	T9K-0007-00	ROTARY ENCODER		1	,X1 E3,K2,E2,M2,A1,H1,K3
	VA82	F0K-0420-00	SURGE ABSORBER		1	,X1 E3,K2,E2,M2,A1,H1,K3