
clarion

Clarion Co., Ltd.
50 Kamitoda, Toda-shi, Saitama 335-8511 Japan
Service Dept.: 5-66 Azuma , Kitamoto-shi, Saitama 364-0007 Japan
Tel: +81-48-541-2335 / 2432 FAX: +81-48-541-2703

Published by Service Dept.
298-6244-00 Mar.2005
Printed in Japan

Service Manual



NISSAN MOTOR Genuine
AM/FM Radio CD Player

Model PP-2449V-H

(Genuine No. 28185 EA021)
(ID No. CY14B)

ORIGINAL SERVICE MANUAL

This additional service manual is designed to be used together with Original model.

Original model	Manual No.
PP-2449V-B	298-6104-01

DIFFERENCE FROM ORIGINAL MODEL

1. Exploded view/parts list
   Main section
   CD mechanism section
2. The parts of equalizer in circuit diagram of Main PWB section

NOTES

* We cannot supply PWB with component parts in principle. When a circuit on PWB has failure, please repair it by component parts base. Parts which are not mentioned in service manual are not supplied.
* Specifications and design are subject to change without notice for further improvement.

COMPONENT

1. Main unit ---------- 1

DIFFERENCE EXPLODED VIEW / PARTS LIST

Main section

(Refer to page 5 of the original service manual.)

The following parts are difference parts.

NO.	PART NO.	DESCRIPTION	Q'TY
1	940-7962-94	ESCUTCHEON-ASSY	1
18	286-6126-74	SETPLATE	1
20	379-1333-30	INDICATOR(LCD)	1
26	017-0433-95	PILOTLAMP(14V40mA)	5
27	017-0447-86	PILOTLAMP(8V105mA)	2

CD mechanism section 929-0220-86

(Refer to page 7 of the original service manual.)

The following parts are difference parts.

NO.	PART NO.	DESCRIPTION	Q'TY
1	966-0595-26	DRIVE PLATE ASSY	1
14	966-1722-20	SH-RACK ASSY	1
18	621-1716-20	RACK	1
23	621-1731-20	IDLE CASE	1
39	621-1726-20	ROLLER SLEEVE	2
45	621-1729-20	SH-BASE	1

DIFFERENCE ELECTRICAL PARTS LIST

Main PWB(B1) section

(Refer to page 8,9 of the original service manual.)

The following parts are difference parts.

REF No.	PART No.	DESCRIPTION
C117	043-0277-51	0.022uF
C501	----------	Not used
C503	----------	Not used
C507	----------	Not used
C510	----------	Not used
C511	----------	Not used
C514	----------	Not used
C517	178-6822-78	6800pF
C518	178-4722-78	4700pF
C519	178-1232-78	0.012uF
C520	178-5622-78	5600pF
C525	178-1232-78	0.012uF
C526	178-5622-78	5600pF
C527	178-6822-78	6800pF
C528	178-4722-78	4700pF
C529	178-1242-78	0.12uF
C530	178-1242-78	0.12uF
C531	178-1042-78	0.1uF
C532	178-1042-78	0.1uF
C533	178-5632-78	0.056uF
C534	178-5632-78	0.056uF
C535	178-8232-78	0.082uF
C536	178-8232-78	0.082uF
C545	178-4732-78	0.047uF
C546	178-4732-78	0.047uF
C547	178-1242-78	0.12uF
C548	178-1242-78	0.12uF
C551	043-0309-92	10V 0.68uF
C552	043-0309-92	10V 0.68uF
C553	178-1042-78	0.1uF
C554	178-1042-78	0.1uF
C555	178-6832-78	0.068uF
C556	178-6832-78	0.068uF
C557	178-1042-78	0.1uF
C558	178-6832-78	0.068uF
C563	178-1042-78	0.1uF
C564	178-6832-78	0.068uF
C570	178-2242-78	0.22uF
C571	178-2242-78	0.22uF
R211	----------	Not used
R213 (Added part)	119-1031-15	1/10W 10k ohm
R509	----------	Not used
R511	----------	Not used
R517	----------	Not used
R518	----------	Not used
R519	----------	Not used
R520	----------	Not used
R534 (Added part)	119-4721-15	1/10W 4.7k ohm
R535	119-2721-15	1/10W 2.7k ohm
R536	----------	Not used
R545	119-2721-15	1/10W 2.7k ohm
R546	----------	Not used
R548 (Added part)	119-4721-15	1/10W 4.7k ohm
R549	119-8211-15	1/10W 820 ohm
R550	119-8211-15	1/10W 820 ohm
R551	119-3321-15	1/10W 3.3k ohm
R552	119-3321-15	1/10W 3.3k ohm
R569	119-2721-15	1/10W 2.7k ohm
R570	119-2721-15	1/10W 2.7k ohm
R571	119-8211-15	1/10W 820 ohm
R572	119-8211-15	1/10W 820 ohm
R573	119-6831-15	1/10W 68k ohm
R574	119-6831-15	1/10W 68k ohm
R575	119-4721-15	1/10W 4.7k ohm
R586	119-4721-15	1/10W 4.7k ohm
R588	119-6831-15	1/10W 68k ohm
R589	119-6831-15	1/10W 68k ohm
R597	119-1831-15	1/10W 18k ohm
R598	119-1831-15	1/10W 18k ohm

Switch PWB(B2) section

(Refer to page 9 of the original service manual.)

The following part is the difference part.

REF No.	PART No.	DESCRIPTION
LCD1	379-1333-30	LCD
PL901	017-0447-86	8V105mA
PL902	017-0447-86	8V105mA
PL903	017-0433-95	14V40mA
PL904	017-0433-95	14V40mA
PL905	017-0433-95	14V40mA
PL906	017-0433-95	14V40mA
PL907	017-0433-95	14V40mA